



제2021 - 2149913 호

안 전 인 증 서

(사업장명) 극동호이스트(주)

(소 재 지) (15423)경기도 안산시 단원구 해봉로 119, 607B, 4L(성곡동630-2)

위 사업장에서 제조하는 아래의 품목이 산업안전보건법 제84조 및 시행규칙 제110조제1항에 따른 안전인증 심사 결과 안전·보건기준에 적합하므로 안전인증표시의 사용을 인증합니다.

_____ 품 목 _____

호이스트 (국내품)

_____ 형식,모델(용량,등급)/인증번호 _____

KDC10-D (10Ton) / 21-AE2AC-00005

_____ 인 증 기 준 _____

고용노동부 고시 제2020 - 41호 (위험기계·기구 안전인증 고시)




_____ 인 증 조 건 _____

(15423)경기도 안산시 단원구 해봉로 119, 607B, 4L(성곡동630-2)에서 생산된 동일 형식 제품에
한함

설치장소 : 옥외

2021년 01월 19일

한국산업안전보건공단 이사장





심사결과 통지서

신청인	사업장명	극동호이스트(주)	사업장관리번호	134-81-013350
	사업자등록번호	134-81-01335	대표자 성명	최성찬
	소재지	(15423) 경기도 안산시 단원구 해봉로 119		
안전인증대상 기계·기구명		호이스트 [동일형식인정 - “별첨(5모델)” 참조]		
형 식 (규 격)	KDC10-D	용 량 (등 급)	10 Ton	

산업안전보건법 제 84조 및 같은 법 시행규칙 제110조에 따라 실시한

- ☐ 예비심사
- ☒ 서면심사
 - ☐ 기술능력 및 생산체계 심사
 - ☐ 개별 제품심사
 - ☐ 개별 제품심사(제작중)
 - ☐ 형식별 제품심사

결과가 [V] 적 합
 [] 부적합

합을 통지합니다.

2020년 06월 05일

인증심사원

이승태

이 승 태 (서명 또는 인)

한국산업안전보건공단 이사장



서 면 심 사 서 류

형식 번호 : KDC10-D

극 동 호 이 스톱 (주)



주소 : 경기도 안산시 단원구 해봉로 119 (성곡동)

TEL : 031) 491 - 5311

FAX : 031) 363 - 3952

동 일 형 식 일 랑 표

사업장명		극동호이스트㈜		개정일자 및 번호		인증번호	비 고
형식 및 모델		동일 형식 인정범위 및 내역					
형식	모델	권상속도(m/min)	회행속도(m/min)	양정(m)	회행방식		
KDC10-D	KDC10-L9-D	MAIN : 4.5 m/min CREEP : 0.45 m/min	고속 : 15 m/min (INVERTER : 2~15 m/min) 저속 : 10 m/min (INVERTER : 2~10 m/min)	9	모터 구동식		회행 인버터 포함
	KDC10-L12-D			12			
	KDC10-L18-D			18			
	KDC10-L24-D			24			
	KDC10-L30-D			30			



제 2012-BJ-0009 호



안 전 인 증 서

정호엔지니어링

경기도 광명시 노동사동 440-5

위 사업장에서 제조하는 아래의 품목이 산업안전보건법 제34조 및 같은 법 시행규칙 제58조의4제4항에 따른 안전인증 심사 결과 안전·보건기준에 적합하므로 안전인증표시의 사용을 인증합니다.

품 목

양중기용 과부하방지장치

형식·모델/용량·등급/인증번호

형식·모델

JDL-100

용량·등급

J-2

인증번호

12-AV2BJ-0009

인 증 기 준

방호장치 의무안전인증 고시(고용노동부고시 제2010-36호)

인 증 조 건

아래 주소에서 생산되는 제품에 한함.



정호엔지니어링, 경기도 광명시 노동사동 440-5

2012년 06월 11일

한국산업안전보건공단 이사장



형식번호	KDC10-D
모델명	KDC10-L9-D



NO	DESCRIPTION	MATERIAL	QTY	SIZE	REMARK
1	LOAD LIMITER	-	1	-	
2	PUSH BUTTON S/W	-	1	-	
3	SAFETY LATCH	SS275	1	-	
4	UPPER LIMIT S/W	SS275	1	-	
5	T/S RAIL	-	-	15KG/M	



극동호이스트
제한하중
10000kg

VIEW A

SPECIFICATION	
HOISTING LOAD	10000 KG
TESTING LOAD	12500 KG
LIFT	9 M
RATING	30 MIN
HOISTING	SPEED 4.5 / 0.45 M/MIN MOTOR 9/1.1 KW x 8P
TRAVEL -SING	HIGH SPEED 15 M/MIN MOTOR 0.75KW x 4 P
LOW	SPEED 10 M/MIN MOTOR 0.5KW x 6 P
WIRE ROPE	(6x37) ϕ 16 x 4FALLS
POWER SOURCE	AC3 ϕ x220V(380,440,480,480V)x60Hz
COLOR	10 B 3/5
WEIGHT	1145 KG



형식번호	KDC10-D
모델명	KDC10-L12-D



극동호이스트
제한하중
10000Kg
모델명: KDC10-L12-D

VIEW A




SPECIFICATION	
HOISTING LOAD	10000 KG
TESTING LOAD	12500 KG
LIFT	12 M
RATING	30 MIN
HOISTING	SPEED 4.5 / 0.45 M/MIN MOTOR 9 / 1.1 KW x 8P
TRAVER-SING	HIGH SPEED 15 M/MIN MOTOR 0.75KW x 4 P
	LOW SPEED 10 M/MIN MOTOR 0.5KW x 6 P
WIRE ROPE	(6x37) $\phi 16$ x 4FALLS
POWER SOURCE	AC3 ϕ x220V(380,440,460,480V)x60Hz
COLOR	10 B 3/5
WEIGHT	1265 KG

NO	DESCRIPTION	MATERIAL	QTY	SIZE	REMARK
1	LOAD LIMITER	-	1	-	-
2	PUSH BUTTON S/W	-	1	-	-
3	SAFETY LATCH	SS275	1	-	-
4	UPPER LIMIT S/W	SS275	1	-	-
5	T/S RAIL	-	-	15KG/M	-

MANUFACTURER	극동호이스트 주식회사 KUDONG HOIST CO., LTD.			
TITLE	ASSEMBLY DRAWING KDC10-L12-D			
SCALE	DWG. NO.	KDC10D1200	SHT. NO.	REV.
N/S				

형식번호	KDC10-D
모델명	KDC10-L18-D




극동호이스트
제한하중
10000kg
모델명: KDC10-L18-D

VIEW A




SPECIFICATION	
HOISTING LOAD	10000 KG
TESTING LOAD	12500 KG
LIFT	18 M
RATING	30 MIN
HOISTING	SPEED 4.5 / 0.45 M/MIN MOTOR 9/1.1 KW x 8P
TRAVER -SING	HIGH SPEED 15 M/MIN MOTOR 0.75KW x 4 P
	LOW SPEED 10 M/MIN MOTOR 0.5KW x 6 P
WIRE ROPE	(6x37) Ø16 x 4FALLS
POWER SOURCE	AC3Øx220V(380,440,460,480V)x60HZ
COLOR	10 B 3/5
WEIGHT	1410 KG




NO	DESCRIPTION	MATERIAL	QTY	SIZE	REMARK
1	LOAD LIMITER	-	1	-	
2	PUSH BUTTON SW	-	1	-	
3	SAFETY LATCH	SS275	1	-	
4	UPPER LIMIT SW	SS275	1	-	
5	T/S RAIL	-	-	15KG/M	

MANUFACTURER	극동호이스트 주식회사 KIDONG HOIST CO., LTD.			
TITLE	ASSEMBLY DRAWING KDC10-L18-D			
SCALE	DWG. NO.	KDC10D1800	SHT. NO.	REV.
N/S				

형식번호	KDC10-D
모델명	KDC10-L24-D



8		9		10	
NO	DESCRIPTION	MATERIAL	QTY	SIZE	REMARK
1	LOAD LIMITER	-	1	-	
2	PUSH BUTTON S/W	-	1	-	
3	SAFETY LATCH	SS275	1	-	
4	UPPER LIMIT S/W	SS275	1	-	
5	T/S RAIL	-	-	15XGM	



제 한하중
10000kg



VIEW A

SPECIFICATION			
HOISTING LOAD	10000	KG	
TESTING LOAD	12500	KG	
LIFT	24	M	
RATING	30	MIN	
HOISTING	SPEED	4.5 / 0.45	M/MIN
	MOTOR	9/1.1	KW x 8P
TRAVER -SING	HIGH	15	M/MIN
	MOTOR	0.75KW x 4	P
	SPEED	10	M/MIN
LOW	MOTOR	0.5KW x 6	P
WIRE ROPE	(6x37) ϕ 16 x 4FALSS		
POWER SOURCE	AC3 ϕ x220V(380,440,460,480V)x60Hz		
COLOR	10 B 3/5		
WEIGHT	1560 KG		

	A	21 APR 2020	REPAWING	K.H HEN	-	-	-	-	-
REV	DATE	DESCRIPTION			DRAWN	CHECK	APPROV.		
PROJECT									
CLIENT									
MANUFACTURER									
 극동호이스트 주식회사 KUNGDOONG HOIST CO., LTD.									
TITLE									
ASSEMBLY DRAWING KDCTO-124-D									
SCALE	DWG. NO.			SHT. NO.			REV.		
N/S	KDCTODD2400								



형식번호	KDC10-D
모델명	KDC10-L30-D



NO	DESCRIPTION	MATERIAL	QTY	SIZE	REMARK
1	LOAD LIMITER	-	1	-	
2	PUSH BUTTON S/W	-	1	-	
3	SAFETY LATCH	SS275	1	-	
4	UPPER LIMIT S/W	SS275	1	-	
5	T/S RAIL	-	-	15KG/M	

극동호이스트
제한하중
10000kg
모델명: KDC10-L30-D

VIEW A



SPECIFICATION	
HOISTING LOAD	10000 KG
TESTING LOAD	12500 KG
LIFT	30 M
RATING	30 MIN
HOISTING	SPEED 4.5 / 0.45 M/MIN MOTOR 9/1.1 KW x 8P
TRAVER-SING	SPEED 15 M/MIN (2 UNITS) MOTOR 0.75KW x 4 P
LOW	SPEED 10 M/MIN (2 UNITS) MOTOR 0.5KW x 6 P
WIRE ROPE	(6x37) Ø16 x 4FALLS
POWER SOURCE	AC3Øx220V(380,440,460,480V)x60HZ
COLOR	10 B 3/5
WEIGHT	1720 KG

MANUFACTURER	KD 극동호이스트 주식회사 KIDONG HOIST CO., LTD.
TITLE	ASSEMBLY DRAWING KDC10-L30-D
SCALE	DWG. NO. KDC10D3000
N/S	SHT. NO. REV.
REV	DATE DESCRIPTION DRAWN CHECK APPRVD
PROJECT	
CLIENT	

1	2	3	4	5	6	7	8	9	10
A	B	C	D	E	F	G	H	I	

NO	DESCRIPTION	MT'L	REMARKS
1	PANEL CASE	SPC	1.6t
2	PANEL COVER	SPC	1.6t
3	HINGE	PUR'	
4	CLAMP	PUR'	
5	SPONGE	PUR'	

NOTE

1. PROTECTION DEGREE :

A. INDOOR TYPE : DUST PROOF

B. OUT DOOR TYPE : SPLASH PROOF

2. FINAL PAINTING COLOR (MUNSELL NO.)

A. IN SIDE : 10B 3/5

B. OUT SIDE : 10B 3/5

3. PAINTING THICKNESS : ABOVE 40 um

4. APPLICATION VOLTAGE : 220V, 380V, 440V, 460V, 480V

5. 제어용 전선 : 1.5sq KIV, HIV

6. 외함 개방 구조는 다음과 같다.

1) 외함 개방시 충전 부분이 차단되도록 한다.

2) 외함 개방 후 충전되어있는 부분은 IP2X 이상의 직접 접촉 방호가 되어있을것.

SELECTION	HOIST CAPACITY	DESCRIPTION	IN DOOR			OUT DOOR			REMARK
			A	B	L	A	B	L	
	10 TON	CREEP	450	200	710	450	200	710	
		T/S	230	150	350	230	150	350	

NO	DESCRIPTION	SPECIFICATION	QTY	REMARK
1	CHASSIS PLATE		1	아연 도금
2	CABLE DUCT	-	1	
3	MAGNET CONTACT	DMC65	1	M1, MAIN MAG.
4	MAGNET CONTACT	MC-100a	2	HOISTING
5	MAGNET CONTACT	DMC22b	2	CREEP
6	SILICON RECTIFIER	SR-60	1	HOISTING
7	SILICON RECTIFIER	SR-30	1	CREEP
8	E.O.C.R	SS-60	1	HOISTING
9	E.O.C.R	SS-30	1	CREEP
10	MCCB100	125AF/75AT	1	LS-2
11	UPPER LIMIT	AC 600V/3A	1	LS-1
12	LIMIT LEVER	SS275	1	
13	FUSE (F11,F12)	3 A	2	
14	FUSE (F13)	5 A	1	
15	TRANSFORMER	220V/110,120V, 200VA	1	
16	TERMINAL BLOCK	60A,25A		
17	TERMINAL BLOCK	15A		
18	EARTH TERMINAL	5x25x50	1	

NOTE

1. 전선의 색상은 다음과 같다.

1) 흑색 : 교류 및 직류 전원선으로 5) 형색 : 직류 제어선으로

2) 적색 : 교류 제어회로

3) 주황색 : 외부 전원에서 공급되는 인동장치 제어회로

4) 녹색 또는 녹색과 황색 혼용 : 접지선

2. CABLE MATERIAL : KIV OR EQUIVALENT

MIN SIZE : 1.5sq


3. 제어용 전선 : 1.5mm KIV,HIV

4. 제작시 다소 변경될수있음.

5. 외함 개방구조는 다음과 같을것.

1) 외함 개방시 충전부분이 차단되도록 할것.

2) 외함 개방후 충전되어있는 부분은 IP2X 이상의 직접 접촉 방호가 되어있을것.



NOTE

1. UPPER LIMIT LS-1의 접점 허용 전류 용량. : AC 600V, 3A

2. UPPER LIMIT LS-2의 접점 허용 전류 용량. : NFB 103AF

3. EARTH TERMINAL RESISTANCE : 0.018 Ω

4. POWER SOURCE : AC. 3φ 220V 60HZ



CUSTOMER

CABLE CONNECTION DIAGRAM

KDC10-D

KD

극동호이스트 주식회사

KUKDONG HOIST CO., LTD.

DWG. NO.

KDC10D-BA20

ORDER NO.

SHT. NO.

SCALE

DESIGN

9

8

7

6

5

4

3

2

1


DATE


REDRAWING

27 APR 2020


REV


10

[illegible]



SPECIFICATION SYMBOLS	HOISTING POWER	HOISTING MOTOR	CREEP MOTOR	DC MAG. BRAKE	NO FUSE BREAKER	TRANSFORMER	FUSE	MAIN MAGNET	MAGNET CONTACTOR	UPPER LIMIT	ELECTRIC OVER CURRENT RELAY	SILICON RECTIFIER	LOAD LIMITER	CABLE
	HOIST	IM 10	IM 11	DB10, 11	LS-II & MCCB100	TR 1	F11, F12	M1	M101, M102	LS-I, LS-II	EOCR100	RF100	LOAD LIMITER	C20-01
SELECTION MAKER	10TON AC3PH 220V 60Hz	9KWx8P	1.1KWx8P	DC 100V	ABS103c/75AT	220/110V/20V/200VA	3A 5A	DMC65	MC-100a	AC 600V 3A	SS-60	SR-60	JDL-100	VCT 16sqx4c
		KUK DONG			LS	SHINHAN	-	DONG-A	LS	DONG-A	KUK DONG	ASECO	JUNGHO	DONGIL
TITLE														
CABLE CONNECTION DIAGRAM														
KDC10-D														
REDRAWING	DWG. NO.													
	KDC10D-E21													
DATE	KUKDONG HOIST CO., LTD.													
REV	KUKDONG HOIST CO., LTD.													






NO	DESCRIPTION	SPECIFICATION	Q'TY	REMARK
1	CHASSIS PLATE		1	아 연 도 플
2	CABLE DUCT	-	1	
3	MAGNET CONTACT	DMC40b	1	M1, MAIN MAG.
4	MAGNET CONTACT	DMC65	2	HOISTING
5	MAGNET CONTACT	DMC22b	2	CREEP
6	SILICON RECTIFIER	SR-60	1	HOISTING
7	SILICON RECTIFIER	SR-30	1	CREEP
8	E.O.C.R	SS-30	1	HOISTING
9	E.O.C.R	SS-05	1	CREEP
10	MCCB100	50AF/50AT	1	LS-2
11	UPPER LIMIT	AC 600V/3A	1	LS-1
12	LIMIT LEVER	SS275	1	
13	FUSE (F11,F12)	2 A	2	
14	FUSE (F13)	5 A	1	
15	TRANSFORMER	380V/110,120V, 200VA	1	
16	TERMINAL BLOCK	60A,25A		
17	TERMINAL BLOCK	15A		
18	EARTH TERMINAL	5x25x50	1	


1. 전자의 생산은 다음과 같다.

- 1) 흑색 : 고무 및 외부 전원선
 - 2) 적색 : 고무제어외도
 - 3) 주황색 : 외부 전원에서 공급되는 인동장치 제어외도
 - 4) 녹색 또는 녹색과 황색 혼용 : 접지선
2. CABLE MATERIAL : [KIV OR EQUIVALENT
MIN SIZE : 1.5sq
3. 제어용 전선 : 1.5mm KIV,HIV
4. 제어시 다소 변경될수있음.
5. 외함 개방구조는 다음과 같을것.
- 1) 외함 개방시 충전부분이 차단되도록 할것.
 - 2) 외함 개방후 충전되어있는 부분은 IP2X 이상의 차단 접속 방호가 되도록




1. UPPER LIMIT LS-1의 전정 허용 전류 용량 : AC 600V, 3A
2. UPPER LIMIT LS-2의 전정 허용 전류 용량 : NFB 53AF
3. EARTH TERMINAL RESISTANCE : 0.018 Ω
4. POWER SOURCE : AC. 3 ϕ 380V 60HZ

[illegible]

1	2	3	4	5	6	7	8	9	10			
A	B	C	D	E	F	G	H					
		TITLE		CABLE CONNECTION DIAGRAM		CUSTOMER		DESIGN	SCALE	SHT. NO.	ORDER NO.	
				KDC10-D		크동호이스트 주식회사 KUKDONG HOIST CO., LTD.						
REV	DATE	DESCRIPTION	DRAWN	CHECK	APPRVD					DWG. NO.	KDC10D-BA31	
27 APR 2020		REDRAWING	K.H.Han	-	-							
1	2	3	4	5	6	7	8	9	10			


NO	DESCRIPTION	SPEC	Q'TY	REMARK
1	CHASSIS PLATE	-	1	아 연 도 금
2	CABLE DUCT	-	1	
3	MAGNET CONTACTOR	DMC22b	2	TRaversing
4	E.O.C.R	SS-05	1	TRaversing
5	SILICON RECTIFIER	SR-30	1	TRaversing
6	TERMINAL BLOCK	25A , 15A	1	TRaversing





HOISTING MOTION

POWER CIRCUIT



SPECIFICATION SYMBOLS	HOISTING POWER	HOISTING MOTOR	HOISTING MOTOR	NO FUSE BREAKER	TRANSFORMER	FUSE	MAGNET CONTACTOR	UPPER LIMIT	ELECTRIC OVER CURRENT RELAY	SILICON RECTIFIER	LOAD LIMITER	CABLE
DESCRIPTION	HOIST	IM 10	IM 11	LS-II & MCCB100	TR 1	F11, F12	M101, M102	LS-I, LS-II	EOCR100	RF100	RF110	C20-01
SELECTION MAKER	10TON AC3PH 220V 60Hz	9KWx8P	1.1KWx8P	ABS103c/75AT	220/110V/120V/200VA	3A	MC-100g	AC 600V 3A	SS-60	SR-60	JDL-100	VCT 16sqx4c

REV	DATE	DESCRIPTION	DRAWN	CHECK	APPROVD	TITLE	CUSTOMER	DESIGN	SCALE	SHT. NO.	ORDER NO.	DWG. NO.
1	27.APR.2020	REDRAWING	K.H.Han	-	-	KUKDONG HOIST CO., LTD.	KUKDONG	ASECO	JUNGHU	DONGIL	KDC10D-E22	



REV	
A	

NO	DESCRIPTION	SPECIFICATION	Q'TY	REMARK
1	CHASSIS PLATE		1	아 연 도 금
2	CABLE DUCT	-	1	
3	MAGNET CONTACT	DMC40b	1	M1, MAIN MAG.
4	MAGNET CONTACT	DMC48b	2	HOISTING
5	MAGNET CONTACT	DMC22b	2	CREEP
6	SILICON RECTIFIER	SR-60	1	HOISTING
7	SILICON RECTIFIER	SR-30	1	CREEP
8	E.O.C.R	SS-30	1	HOISTING
9	E.O.C.R	SS-05	1	CREEP
10	MCCB100	50AF/40AT	1	LS-2
11	UPPER LIMIT	AC 600V/3A	1	LS-1
12	LIMIT LEVER	SS275	1	
13	FUSE (F11,F12)	2 A	2	
14	FUSE (F13)	5 A	1	
15	TRANSFORMER	440V/110V,120V, 200VA	1	
16	TERMINAL BLOCK	60A,25A		
17	TERMINAL BLOCK	15A		
18	EARTH TERMINAL	51x25x50	1	

NOTE

1. 전선의 색상은 다음과 같다.

1) 흑색 : 교류 및 직류 전원선으로 5) 정색 : 직류 제어선으로

2) 적색 : 교류제어회로

3) 주황색 : 외부 전원에서 공급되는 연동장치 제어회로

4) 녹색 또는 녹색과 황색 혼용 : 접지선

2. CABLE MATERIAL : KIV OR EQUIVALENT
MIN SIZE : 1.5sq


3. 제어용 전선 : 1.5mm KIV,HIV

4. 제자시 다소 변경될수있음.

5. 외함 개방구조는 다음과 같을것.

1) 외함 개방시 충전부분이 차단되도록 할것.

2) 외함 개방후 충전되어있는 부분은 IP2X 이상의 직접 접촉 방호가 되어있을것.



NOTE

1. UPPER LIMIT LS-1의 접점 허용 전류 용량 : AC 600V, 3A

2. UPPER LIMIT LS-2의 접점 허용 전류 용량 : NFB 53AF

3. EARTH TERMINAL RESISTANCE : 0.018 Ω

4. POWER SOURCE : AC 3φ 440V 60HZ



CUSTOMER

TITLE

CABLE CONNECTION DIAGRAM

KDC10-D

크동호이스트 주식회사
KUKDONG HOIST CO., LTD.

DWG. NO. KDC10D-BA40

ORDER NO.

SCALE

DESIGN

SHT. NO.

27 APR 2020
DATE



REDRAWING
DESCRIPTION


K.H.Han
DRAWN

-
CHECK


-
APPRVD


NO	DESCRIPTION	SPEC	Q'TY	REMARK
1	CHASSIS PLATE	-	1	아 연 도 금
2	CABLE DUCT	-	1	
3	MAGNET CONTACTOR	DMC22b	2	TRAVERSING
4	E.O.C.R	SS-05	1	TRAVERSING
5	SILICON RECTIFIER	SR-30	1	TRAVERSING
6	TERMINAL BLOCK	25A , 15A	1	TRAVERSING

[illegible]




SPECIFICATION SYMBOLS	HOISTING POWER	HOISTING MOTOR	CREEP MOTOR	DC MAG. BRAKE	NO FUSE BREAKER	TRANSFORMER	FUSE	MAIN MAGNET	MAGNET CONTACTOR	UPPER LIMIT	ELECTRIC OVER CURRENT RELAY	SILICON RECTIFIER	LOAD LIMITER	CABLE	
	HOIST	IM 10	IM 11	DB10, 11	LS-II & MCCB100	TR 1	F11,F12	M1	M101,M102	LS-I, LS-II	EOCR100	RF100	LOAD LIMITER	C20-01	
SELECTION	10TON AC3PH 440V 60Hz	9KWx8P	1.1KWx8P	DC 100V	ABS53c/40AT	440V/110V/120V/200VA	2A	DMC40b	DMC48b	AC 600V 3A	SS-30	SR-60	JDL-100	VCT 6.0sqx4c	
	SELECTION MAKER	KUK DONG													
						LS	SHINHAN	DONG-A	DONG-A	KUK DONG	ASECO		JUNGHO	DONGIL	
					TITLE										ORDER NO.
					CABLE CONNECTION DIAGRAM										
					KDC10-D										
R-2020	REDRAWING	K.H.Han	-	-	KDC10D-E41										
DATE	DESCRIPTION	DRAWN	CHECK	APPROVD	DWG. NO.										
					크동호이스트 주식회사 KUKDONG HOIST CO., LTD.										
															







극동호이스트 주식회사
KUKDONG HOIST CO., LTD.




1. UPPER LIMIT LS-1의 전압 허용 전류 용량 : AC 600V, 3A
2. UPPER LIMIT LS-2의 전압 허용 전류 용량 : NFB 53AF
3. EARTH TERMINAL RESISTANCE : 0.018 Ω
4. POWER SOURCE : AC 3ø 460V 60HZ

[illegible]


[illegible]







1	2
3	4
5	6
7	8
9	10
11	12
13	14
15	16
17	18
19	20
21	22
23	24
25	26
27	28
29	30
31	32
33	34
35	36
37	38
39	40
41	42
43	44
45	46
47	48
49	50
51	52
53	54
55	56
57	58
59	60
61	62
63	64
65	66
67	68
69	70
71	72
73	74
75	76
77	78
79	80
81	82
83	84
85	86
87	88
89	90
91	92
93	94
95	96
97	98
99	100
101	102
103	104
105	106
107	108
109	110
111	112
113	114
115	116
117	118
119	120
121	122
123	124
125	126
127	128
129	130
131	132
133	134
135	136
137	138
139	140
141	142
143	144
145	146
147	148
149	150
151	152
153	154
155	156
157	158
159	160
161	162
163	164
165	166
167	168
169	170
171	172
173	174
175	176
177	178
179	180
181	182
183	184
185	186
187	188
189	190
191	192
193	194
195	196
197	198
199	200
201	202
203	204
205	206
207	208
209	210
211	212
213	214
215	216
217	218
219	220
221	222
223	224
225	226
227	228
229	230
231	232
233	234
235	236
237	238
239	240
241	242
243	244
245	246
247	248
249	250
251	252
253	254
255	256
257	258
259	260
261	262
263	264
265	266
267	268
269	270
271	272
273	274
275	276
277	278
279	280
281	282
283	284
285	286
287	288
289	290
291	292
293	294
295	296
297	298
299	300
301	302
303	304
305	306
307	308
309	310
311	312
313	314
315	316
317	318
319	320
321	322
323	324
325	326
327	328
329	330
331	332
333	334
335	336



NO	DESCRIPTION	SPECIFICATION	Q'TY	REMARK
1	CHASSIS PLATE		1	아 연 도 금
2	CABLE DUCT	-	1	
3	MAGNET CONTACT	DMC40b	1	M1, MAIN MAG.
4	MAGNET CONTACT	DMC48b	2	HOISTING
5	MAGNET CONTACT	DMC22b	2	CREEP
6	SILICON RECTIFIER	SR-60	1	HOISTING
7	SILICON RECTIFIER	SR-30	1	CREEP
8	E.O.C.R	SS-30	1	HOISTING
9	E.O.C.R	SS-05	1	CREEP
10	MCCB100	50AF/40AT	1	LS-2
11	UPPER LIMIT	AC 600V/3A	1	LS-1
12	LIMIT LEVER	SS275	1	
13	FUSE (F11,F12)	2 A	2	
14	FUSE (F13)	5 A	1	
15	TRANSFORMER	480V/110V,120V, 200VA	1	
16	TERMINAL BLOCK	60A,25A		
17	TERMINAL BLOCK	15A		
18	EARTH TERMINAL	5t×25×50	1	

NOTE

1. 전선의 색상은 다음과 같다.

1) 흑색 : 교류 및 직류 전원선으로 5) 정색 : 직류 제어선으로

2) 적색 : 교류제어회로

3) 주광색 : 외부 전원에서 공급되는 연동장치 제어회로

4) 녹색 또는 녹색과 황색 혼용 : 접지선

2. CABLE MATERIAL : KIV OR EQUIVALENT

MIN SIZE : 1.5sq


3. 제어용 전선 : 1.5mm KIV,HIV

4. 제작시 다소 변경될수있음.

5. 외함 개방구조는 다음과 같을것.

1) 외함 개방시 중전부분이 차단되도록 할것.

2) 외함 개방후 충전되어있는 부분은 IP2X 이상의 직접 접촉 방호가 되어있을것.



NOTE

1. UPPER LIMIT LS-1의 접점 허용 전류 용량.: AC 600V, 3A

2. UPPER LIMIT LS-2의 접점 허용 전류 용량.: NFB 53AF

3. EARTH TERMINAL RESISTANCE : 0.018 Ω

4. POWER SOURCE : AC. 3φ 480V 60HZ



CUSTOMER

CABLE CONNECTION DIAGRAM

TITLE

KDC10-D

REV

DATE

DESCRIPTION

DRAWN

CHECK

APPRVD

DESIGN

SCALE

SHT. NO.

ORDER NO.


DWG. NO.


KDC10D-BA60


KUKDONG HOIST CO., LTD.


KD


KUKDONG HOIST CO., LTD.


[illegible]



[illegible]









SPECIFICATION SYMBOLS	UPPER LIMIT	PENDANT P.B. S/W	LOAD LIMITER	LIMIT SWITCH
DESCRIPTION	LS-1	E.S.B	LOAD LIMITER	LS-301,302
	AC 600V 3A	250V 3A	JDL-100	KG - L001
	AC 600V 3A	250V 3A	JDL-100	KG - L001
MAKER	KUNHUNG	KG-AUTO	JUNG-HO	KG-AUTO

CUSTOMER		TITLE	
KUDONG HOIST CO., LTD.		CONTROL CIRCUIT DIAGRAM	
KDC10D-E002		KDC10-D	
REV	DATE	DESCRIPTION	APPRVD
1	27 APR.2020	REDRAWING	K.H.Han
2			
3			
4			
5			
6			
7			
8			
9			
10			




NO.	DESCRIPTION	MTL		WEIGHT(Kg)		QTY		REMARKS.
		PUR	SS400	TOTAL	SUB	TOTAL	SUB	
1	T/S BOX	PUR				1		
2	4 1/2"	SS400				1		
3	MC2B	PUR				1		
4	MC	PUR				1		
5	RF	PUR				1		
6	RELAY & SOCKET	PUR				1		
7	TR	PUR				1		
8	INVERTER	PUR				1		
9	TERMINAL BLOCK	PUR				1		
10	DUCT	PUR				1		
11	EARTH BUS BAR	PUR				1		

[illegible]



KD
극동호이스트 주식회사
KUKDONG HOIST CO., LTD.



구분	조각번호	표시등
색상		
좌측	비상	비상
우측	비정상	비정상
녹색	정상	정상
청색	의무	의무
흰색, 회색, 흑색	지정된의미없음	기타


* MATERIAL : POLYCARBONATE(PLASTIC)

* BODY COLOR : YELLOW, BLACK

* IP : 55 이상

NO	SYMBOL	TYPE	SPEC.	COLOR
1	E.B.S	PUSH LOCK TURN RESET TYPE	250VAC x 6A	RED
2	SPARE			
3	상	1PUSH BUTTON 1STEP (2STEP)		BLACK
4	하	1PUSH BUTTON 1STEP (2STEP)		
5	동(전)	1PUSH BUTTON 1STEP (2STEP)		
6	서(후)	1PUSH BUTTON 1STEP (2STEP)		
7	보조 와이어	ø 2.0		

REV	DATE	DESCRIPTION	DRAWN	CHECK	APPRVD	TITLE	CUSTOMER	DESIGN	SCALE	SHT NO.	ORDER NO.
05-AUG-2016	05-AUG-2016	REDRAWING	K.H.Han	-	-	PENDANT PUSH BUTTON SWITCH LAY OUT	극동호이스트 주식회사 KUKDONG HOIST CO., LTD.				



구분	색상	조작버튼	표시등
적색	비상	비상	비상
황색	비정상	비정상	비정상
녹색	정상	정상	정상
청색	임무	임무	임무
흰색, 회색-흑색	지정된의미없음		기타

* MATERIAL : POLYCARBONATE(PLASTIC)

* BODY COLOR : YELLOW, BLACK

* IP : 55 이상

NO	SYMBOL	TYPE	SPEC.	COLOR
1	E.B.S	PUSH LOCK TURN RESET TYPE	250VAC x 6A	RED
2	SPARE			
3	상	1PUSH BUTTON 1STEP (2STEP)		BLACK
4	하	1PUSH BUTTON 1STEP (2STEP)		
5	동 (좌)	1PUSH BUTTON 1STEP (2STEP)		
6	서 (우)	1PUSH BUTTON 1STEP (2STEP)		
7	남 (전)	1PUSH BUTTON 1STEP (2STEP)		
8	북 (후)	1PUSH BUTTON 1STEP (2STEP)		
9	보조 WIRE	ø 2.0		

REV		DATE		DESCRIPTION		DRAWN		CHECK		APPRVD		TITLE		CUSTOMER		DESIGN		SCALE		SHT. NO.		ORDER NO.	
05 AUG 2016		REDRAWING				K.H.Han						PENDANT PUSH BUTTON SWITCH LAY OUT		크동호이스트 주식회사 KUKDONG HOIST CO., LTD.									
1		2		3		4		5		6		7		8		9		10					

IV. 참고자료



LOAD LIMITER 권고 SETTING치

* POWER SOURCE : AC 3Φ 220V 60Hz

극동하이스트(주)

HOIST	MOTOR 용량	LOAD LIMITER 권고 SETTING치			LOAD CURRENT		C.T MODEL	연결단자 NO	C.T 용량	REMARK
		LOAD CURRENT	ADJ START TIME	SHOCK TIME	100%	110%				
C1 TON	2.4KW x 4P	110%	1 SEC	1 SEC	10.0 A	11.0 A	CT-2	K-K1, L-L1	5 V.A	
	0.4KW x 4P	110%	1 SEC	1 SEC	2.7 A	3.0 A	CT-1	K-K1, L-L1	5 V.A	
C2 TON	3.7KW x 4P	110%	1 SEC	1 SEC	16.0 A	17.6 A	CT-2	K-K1, L-L1	5 V.A	
	0.4KW x 4P	110%	1 SEC	1 SEC	2.7 A	3.0 A	CT-1	K-K1, L-L1	5 V.A	
C2.8 TON	5.0KW x 4P	110%	1 SEC	1 SEC	22.8 A	25.1 A	CT-2	K-K1, L-L1	5 V.A	
	1.5KW x 4P	110%	1 SEC	1 SEC	7.3 A	8.0 A	CT-1	K-K1, L-L1	5 V.A	
C3 TON	5.5KW x 4P	110%	1 SEC	1 SEC	22.8 A	25.1 A	CT-2	K-K1, L-L1	5 V.A	
	1.5KW x 4P	110%	1 SEC	1 SEC	7.3 A	8.0 A	CT-1	K-K1, L-L1	5 V.A	
C5 TON	5.5KW x 6P	110%	1 SEC	1 SEC	28.2 A	31.0 A	CT-2	K-K1, L-L1	5 V.A	
	1.0KW x 6P	110%	1 SEC	1 SEC	6.7 A	7.4 A	CT-1	K-K1, L-L1	5 V.A	
C7.5 TON	5.5KW x 6P	110%	1 SEC	1 SEC	28.2 A	31.0 A	CT-2	K-K1, L-L1	5 V.A	
	1.0KW x 6P	110%	1 SEC	1 SEC	6.7 A	7.4 A	CT-1	K-K1, L-L1	5 V.A	
C10 TON	9.0KW x 8P	110%	1 SEC	1 SEC	45.0 A	49.5 A	CT-2	K-K1, L-L1	5 V.A	
	1.1KW x 8P	110%	1 SEC	1 SEC	8.0 A	8.8 A	CT-2	K-K1, L-L1	5 V.A	

NOTE

1. 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

LOAD LIMITER 권고 SETTING치

* POWER SOURCE : AC 3Φ 380V 60Hz

극동호이스트(주)

HOIST	MOTOR 용량	LOAD LIMITER 권고 SETTING치			LOAD CURRENT		C.T MODEL	연결단자 NO	C.T 용량	REMARK
		LOAD CURRENT	ADJ START TIME	SHOCK TIME	100%	110%				
C1 TON	2.4KW x 4P	110%	1 SEC	1 SEC	5.8 A	6.4 A	CT-2	K-K1, L-L1	5 V.A	
	0.4KW x 4P	110%	1 SEC	1 SEC	1.6 A	1.8 A	CT-1	K-K1, L-L1	5 V.A	
C2 TON	3.7KW x 4P	110%	1 SEC	1 SEC	9.3 A	10.2 A	CT-2	K-K1, L-L1	5 V.A	
	0.4KW x 4P	110%	1 SEC	1 SEC	1.6 A	1.8 A	CT-1	K-K1, L-L1	5 V.A	
C2.8 TON	5.0KW x 4P	110%	1 SEC	1 SEC	12.2 A	13.4 A	CT-2	K-K1, L-L1	5 V.A	
	1.5KW x 4P	110%	1 SEC	1 SEC	4.2 A	4.6 A	CT-1	K-K1, L-L1	5 V.A	
C3 TON	5.5KW x 4P	110%	1 SEC	1 SEC	12.2 A	13.4 A	CT-2	K-K1, L-L1	5 V.A	
	1.5KW x 4P	110%	1 SEC	1 SEC	4.2 A	4.6 A	CT-1	K-K1, L-L1	5 V.A	
C5 TON	5.5KW x 6P	110%	1 SEC	1 SEC	16.3 A	17.9 A	CT-2	K-K1, L-L1	5 V.A	
	1.0KW x 6P	110%	1 SEC	1 SEC	3.9 A	4.3 A	CT-1	K-K1, L-L1	5 V.A	
C7.5 TON	5.5KW x 6P	110%	1 SEC	1 SEC	16.3 A	17.9 A	CT-2	K-K1, L-L1	5 V.A	
	1.0KW x 6P	110%	1 SEC	1 SEC	3.9 A	4.3 A	CT-1	K-K1, L-L1	5 V.A	
C10 TON	9.0KW x 8P	110%	1 SEC	1 SEC	26.0 A	28.6 A	CT-2	K-K1, L-L1	5 V.A	
	1.1KW x 8P	110%	1 SEC	1 SEC	4.6 A	5.1 A	CT-2	K-K1, L-L1	5 V.A	

NOTE

1. 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

LOAD LIMITER 권고 SETTING치

* POWER SOURCE : AC 3Φ 440V 60Hz

극동하이스트(주)

HOIST	MOTOR 용량	LOAD LIMITER 권고 SETTING치			LOAD CURRENT		C.T MODEL	연결단자 NO	C.T 용량	REMARK
		LOAD CURRENT	ADJ START TIME	SHOCK TIME	100%	110%				
C1 TON	2.4KW x 4P	110%	1 SEC	1 SEC	5.0 A	5.5 A	CT-2	K-K1, L-L1	5 V.A	
	0.4KW x 4P	110%	1 SEC	1 SEC	1.4 A	1.5 A	CT-1	K-K1, L-L1	5 V.A	
C2 TON	3.7KW x 4P	110%	1 SEC	1 SEC	8.0 A	8.8 A	CT-2	K-K1, L-L1	5 V.A	
	0.4KW x 4P	110%	1 SEC	1 SEC	1.4 A	1.5 A	CT-1	K-K1, L-L1	5 V.A	
C2.8 TON	5.0KW x 4P	110%	1 SEC	1 SEC	10.5 A	11.6 A	CT-2	K-K1, L-L1	5 V.A	
	1.5KW x 4P	110%	1 SEC	1 SEC	3.7 A	4.1 A	CT-1	K-K1, L-L1	5 V.A	
C3 TON	5.5KW x 4P	110%	1 SEC	1 SEC	10.5 A	11.6 A	CT-2	K-K1, L-L1	5 V.A	
	1.5KW x 4P	110%	1 SEC	1 SEC	3.7 A	4.1 A	CT-1	K-K1, L-L1	5 V.A	
C5 TON	5.5KW x 6P	110%	1 SEC	1 SEC	14.1 A	15.5 A	CT-2	K-K1, L-L1	5 V.A	
	1.0KW x 6P	110%	1 SEC	1 SEC	3.3 A	3.6 A	CT-1	K-K1, L-L1	5 V.A	
C7.5 TON	5.5KW x 6P	110%	1 SEC	1 SEC	14.1 A	15.5 A	CT-2	K-K1, L-L1	5 V.A	
	1.0KW x 6P	110%	1 SEC	1 SEC	3.3 A	3.6 A	CT-1	K-K1, L-L1	5 V.A	
C10 TON	9.0KW x 8P	110%	1 SEC	1 SEC	22.5 A	24.8 A	CT-2	K-K1, L-L1	5 V.A	
	1.1KW x 8P	110%	1 SEC	1 SEC	4.0 A	4.4 A	CT-1	K-K1, L-L1	5 V.A	

NOTE

1. 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

LOAD LIMITER 권고 SETTING치

* POWER SOURCE : AC 3Φ 460V 60Hz

극동호이스트(주)

HOIST	MOTOR 용량	LOAD LIMITER 권고 SETTING치			LOAD CURRENT		C.T MODEL	연결단자 NO	C.T 용량	REMARK
		LOAD CURRENT	ADJ START TIME	SHOCK TIME	100%	110%				
C1 TON	2.4KW x 4P	110%	1 SEC	1 SEC	4.8 A	5.3 A	CT-2	K-K1, L-L1	5 V.A	
	0.4KW x 4P	110%	1 SEC	1 SEC	1.4 A	1.5 A	CT-1	K-K1, L-L1	5 V.A	
C2 TON	3.7KW x 4P	110%	1 SEC	1 SEC	7.7 A	8.5 A	CT-2	K-K1, L-L1	5 V.A	
	0.4KW x 4P	110%	1 SEC	1 SEC	1.4 A	1.5 A	CT-1	K-K1, L-L1	5 V.A	
C2.8 TON	5.0KW x 4P	110%	1 SEC	1 SEC	10.0 A	11.0 A	CT-2	K-K1, L-L1	5 V.A	
	1.5KW x 4P	110%	1 SEC	1 SEC	3.5 A	3.9 A	CT-1	K-K1, L-L1	5 V.A	
C3 TON	5.5KW x 4P	110%	1 SEC	1 SEC	10.0 A	11.0 A	CT-2	K-K1, L-L1	5 V.A	
	1.5KW x 4P	110%	1 SEC	1 SEC	3.5 A	3.9 A	CT-1	K-K1, L-L1	5 V.A	
C5 TON	5.5KW x 6P	110%	1 SEC	1 SEC	13.5 A	14.9 A	CT-2	K-K1, L-L1	5 V.A	
	1.0KW x 6P	110%	1 SEC	1 SEC	3.2 A	3.5 A	CT-1	K-K1, L-L1	5 V.A	
C7.5 TON	5.5KW x 6P	110%	1 SEC	1 SEC	13.5 A	14.9 A	CT-2	K-K1, L-L1	5 V.A	
	1.0KW x 6P	110%	1 SEC	1 SEC	3.2 A	3.5 A	CT-1	K-K1, L-L1	5 V.A	
C10 TON	9.0KW x 8P	110%	1 SEC	1 SEC	21.5 A	23.7 A	CT-2	K-K1, L-L1	5 V.A	
	1.1KW x 8P	110%	1 SEC	1 SEC	3.7 A	4.1 A	CT-1	K-K1, L-L1	5 V.A	

NOTE

1. 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

LOAD LIMITER 권고 SETTING치

* POWER SOURCE : AC 3Φ 480V 60Hz

극동하이스트(주)

HOIST	MOTOR 용량	LOAD LIMITER 권고 SETTING치			LOAD CURRENT		C.T MODEL	연결단자 NO	C.T 용량	REMARK
		LOAD CURRENT	ADJ START TIME	SHOCK TIME	100%	110%				
C1 TON	2.4KW x 4P	110%	1 SEC	1 SEC	4.6 A	5.1 A	CT-2	K-K1, L-L1	5 V.A	
	0.4KW x 4P	110%	1 SEC	1 SEC	1.4 A	1.5 A	CT-1	K-K1, L-L1	5 V.A	
C2 TON	3.7KW x 4P	110%	1 SEC	1 SEC	7.3 A	8.0 A	CT-2	K-K1, L-L1	5 V.A	
	0.4KW x 4P	110%	1 SEC	1 SEC	1.4 A	1.5 A	CT-1	K-K1, L-L1	5 V.A	
C2.8 TON	5.0KW x 4P	110%	1 SEC	1 SEC	9.6 A	10.6 A	CT-2	K-K1, L-L1	5 V.A	
	1.5KW x 4P	110%	1 SEC	1 SEC	3.4 A	3.7 A	CT-1	K-K1, L-L1	5 V.A	
C3 TON	5.5KW x 4P	110%	1 SEC	1 SEC	9.6 A	10.6 A	CT-2	K-K1, L-L1	5 V.A	
	1.5KW x 4P	110%	1 SEC	1 SEC	3.4 A	3.7 A	CT-1	K-K1, L-L1	5 V.A	
C5 TON	5.5KW x 6P	110%	1 SEC	1 SEC	12.9 A	14.2 A	CT-2	K-K1, L-L1	5 V.A	
	1.0KW x 6P	110%	1 SEC	1 SEC	3.1 A	3.4 A	CT-1	K-K1, L-L1	5 V.A	
C7.5 TON	5.5KW x 6P	110%	1 SEC	1 SEC	12.9 A	14.2 A	CT-2	K-K1, L-L1	5 V.A	
	1.0KW x 6P	110%	1 SEC	1 SEC	3.1 A	3.4 A	CT-1	K-K1, L-L1	5 V.A	
C10 TON	9.0KW x 8P	110%	1 SEC	1 SEC	20.6 A	22.7 A	CT-2	K-K1, L-L1	5 V.A	
	1.1KW x 8P	110%	1 SEC	1 SEC	3.6 A	4.0 A	CT-1	K-K1, L-L1	5 V.A	

NOTE

1. 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

E.O.C.R 권고 SETTING치

* POWER SOURCE : AC 3Φ 220V 60Hz

극동호이스트(주)

HOIST	MOTOR 용량	MOTOR 정격 전류	DRIVE TYPE	E.O.C.R TYPE	권고 SETTING 치			REMARK
					DELAY TIME	OPERATION TIME	CURRENT	
C1 TON	2.4KW x 4P	10.0 A	1 DRAVE	SS-30	3 SEC	1 SEC	11.0 A	
	0.4KW x 4P	2.7 A	1 DRAVE	SS-05	3 SEC	1 SEC	3.0 A	
C2 TON	3.7KW x 4P	16.0 A	1 DRAVE	SS-30	3 SEC	1 SEC	17.6 A	
	0.4KW x 4P	2.7 A	1 DRAVE	SS-05	3 SEC	1 SEC	3.0 A	
C2.8 TON	5.0KW x 4P	22.8 A	1 DRAVE	SS-30	3 SEC	1 SEC	25.1 A	
	1.5KW x 4P	7.3 A	1 DRAVE	SS-30	3 SEC	1 SEC	8.0 A	
C3 TON	5.5KW x 4P	22.8 A	1 DRAVE	SS-30	3 SEC	1 SEC	25.1 A	
	1.5KW x 4P	7.3 A	1 DRAVE	SS-30	3 SEC	1 SEC	8.0 A	
C5 TON	5.5KW x 6P	28.2 A	1 DRAVE	SS-30	3 SEC	1 SEC	31.0 A	
	1.0KW x 6P	6.7 A	1 DRAVE	SS-30	3 SEC	1 SEC	7.4 A	
C7.5 TON	5.5KW x 6P	28.2 A	1 DRAVE	SS-30	3 SEC	1 SEC	31.0 A	
	1.0KW x 6P	6.7 A	1 DRAVE	SS-30	3 SEC	1 SEC	7.4 A	
C10 TON	9.0KW x 8P	45.0 A	1 DRAVE	SS-60	3 SEC	1 SEC	49.5 A	
	1.1KW x 8P	8.0 A	1 DRAVE	SS-30	3 SEC	1 SEC	8.8 A	

NOTE

1. 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

E.O.C.R 권고 SETTING치

* POWER SOURCE : AC 3Φ 380V 60Hz

극동하이스트(주)

HOIST	MOTOR 용량	MOTOR 정격 전류	DRIVE TYPE	E.O.C.R TYPE	권고 SETTING 치			REMARK
					DELAY TIME	OPERATION TIME	CURRENT	
C1 TON	2.4KW x 4P	5.8 A	1 DRAVE	SS-30	3 SEC	1 SEC	6.4 A	
	0.4KW x 4P	1.6 A	1 DRAVE	SS-05	3 SEC	1 SEC	1.8 A	
C2 TON	3.7KW x 4P	9.3 A	1 DRAVE	SS-30	3 SEC	1 SEC	10.2 A	
	0.4KW x 4P	1.6 A	1 DRAVE	SS-05	3 SEC	1 SEC	1.8 A	
C2.8 TON	5.0KW x 4P	12.2 A	1 DRAVE	SS-30	3 SEC	1 SEC	13.4 A	
	1.5KW x 4P	4.2 A	1 DRAVE	SS-05	3 SEC	1 SEC	4.6 A	
C3 TON	5.5KW x 4P	12.2 A	1 DRAVE	SS-30	3 SEC	1 SEC	13.4 A	
	1.5KW x 4P	4.2 A	1 DRAVE	SS-05	3 SEC	1 SEC	4.6 A	
C5 TON	5.5KW x 6P	16.3 A	1 DRAVE	SS-30	3 SEC	1 SEC	17.9 A	
	1.0KW x 6P	3.9 A	1 DRAVE	SS-05	3 SEC	1 SEC	4.3 A	
C7.5 TON	5.5KW x 6P	16.3 A	1 DRAVE	SS-30	3 SEC	1 SEC	17.9 A	
	1.0KW x 6P	3.9 A	1 DRAVE	SS-05	3 SEC	1 SEC	4.3 A	
C10 TON	9.0KW x 8P	26.0 A	1 DRAVE	SS-30	3 SEC	1 SEC	28.6 A	
	1.1KW x 8P	4.6 A	1 DRAVE	SS-05	3 SEC	1 SEC	5.1 A	

NOTE

1. 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

E.O.C.R 권고 SETTING치

* POWER SOURCE : AC 3Φ 440V 60Hz

극동하이스트(주)

HOIST	MOTOR 용량	MOTOR 정격 전류	DRIVE TYPE	E.O.C.R TYPE	권고 SETTING 치			REMARK
					DELAY TIME	OPERATION TIME	CURRENT	
C1 TON	2.4KW x 4P	5.0 A	1 DRAVE	SS-30	3 SEC	1 SEC	5.5 A	
	0.4KW x 4P	1.4 A	1 DRAVE	SS-05	3 SEC	1 SEC	1.5 A	
C2 TON	3.7KW x 4P	8.0 A	1 DRAVE	SS-30	3 SEC	1 SEC	8.8 A	
	0.4KW x 4P	1.4 A	1 DRAVE	SS-05	3 SEC	1 SEC	1.5 A	
C2.8 TON	5.0KW x 4P	10.5 A	1 DRAVE	SS-30	3 SEC	1 SEC	11.6 A	
	1.5KW x 4P	3.7 A	1 DRAVE	SS-05	3 SEC	1 SEC	4.1 A	
C3 TON	5.5KW x 4P	10.5 A	1 DRAVE	SS-30	3 SEC	1 SEC	11.6 A	
	1.5KW x 4P	3.7 A	1 DRAVE	SS-05	3 SEC	1 SEC	4.1 A	
C5 TON	5.5KW x 6P	14.1 A	1 DRAVE	SS-30	3 SEC	1 SEC	15.5 A	
	1.0KW x 6P	3.3 A	1 DRAVE	SS-05	3 SEC	1 SEC	3.6 A	
C7.5 TON	5.5KW x 6P	14.1 A	1 DRAVE	SS-30	3 SEC	1 SEC	15.5 A	
	1.0KW x 6P	3.3 A	1 DRAVE	SS-05	3 SEC	1 SEC	3.6 A	
C10 TON	9.0KW x 8P	22.5 A	1 DRAVE	SS-30	3 SEC	1 SEC	24.8 A	
	1.1KW x 8P	4.0 A	1 DRAVE	SS-05	3 SEC	1 SEC	4.4 A	

NOTE

1. 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

E.O.C.R 권고 SETTING치

* POWER SOURCE : AC 3Φ 460V 60Hz

극동호이스트(주)

HOIST	MOTOR 용량	MOTOR 정격 전류	DRIVE TYPE	E.O.C.R TYPE	권고 SETTING 치			REMARK
					DELAY TIME	OPERATION TIME	CURRENT	
C1 TON	2.4KW x 4P	4.8 A	1 DRAVE	SS-30	3 SEC	1 SEC	5.3 A	
	0.4KW x 4P	1.4 A	1 DRAVE	SS-05	3 SEC	1 SEC	1.5 A	
C2 TON	3.7KW x 4P	7.7 A	1 DRAVE	SS-30	3 SEC	1 SEC	8.5 A	
	0.4KW x 4P	1.4 A	1 DRAVE	SS-05	3 SEC	1 SEC	1.5 A	
C2.8 TON	5.0KW x 4P	10.0 A	1 DRAVE	SS-30	3 SEC	1 SEC	11.0 A	
	1.5KW x 4P	3.5 A	1 DRAVE	SS-05	3 SEC	1 SEC	3.9 A	
C3 TON	5.5KW x 4P	10.0 A	1 DRAVE	SS-30	3 SEC	1 SEC	11.0 A	
	1.5KW x 4P	3.5 A	1 DRAVE	SS-05	3 SEC	1 SEC	3.9 A	
C5 TON	5.5KW x 6P	13.5 A	1 DRAVE	SS-30	3 SEC	1 SEC	14.9 A	
	1.0KW x 6P	3.2 A	1 DRAVE	SS-05	3 SEC	1 SEC	3.5 A	
C7.5 TON	5.5KW x 6P	13.5 A	1 DRAVE	SS-30	3 SEC	1 SEC	14.9 A	
	1.0KW x 6P	3.2 A	1 DRAVE	SS-05	3 SEC	1 SEC	3.5 A	
C10 TON	9.0KW x 8P	21.5 A	1 DRAVE	SS-30	3 SEC	1 SEC	23.7 A	
	1.1KW x 8P	3.7 A	1 DRAVE	SS-05	3 SEC	1 SEC	4.1 A	

NOTE

1. 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

E.O.C.R 권고 SETTING치

* POWER SOURCE : AC 3Φ 480V 60Hz

극동하이스트(주)

HOIST	MOTOR 용량	MOTOR 정격 전류	DRIVE TYPE	E.O.C.R TYPE	권고 SETTING 치			REMARK
					DELAY TIME	OPERATION TIME	CURRENT	
C1 TON	2.4KW x 4P	4.6 A	1 DRAVE	SS-30	3 SEC	1 SEC	5.1 A	
	0.4KW x 4P	1.4 A	1 DRAVE	SS-05	3 SEC	1 SEC	1.5 A	
C2 TON	3.7KW x 4P	7.3 A	1 DRAVE	SS-30	3 SEC	1 SEC	8.0 A	
	0.4KW x 4P	1.4 A	1 DRAVE	SS-05	3 SEC	1 SEC	1.5 A	
C2.8 TON	5.0KW x 4P	9.6 A	1 DRAVE	SS-30	3 SEC	1 SEC	10.6 A	
	1.5KW x 4P	3.4 A	1 DRAVE	SS-05	3 SEC	1 SEC	3.7 A	
C3 TON	5.5KW x 4P	9.6 A	1 DRAVE	SS-30	3 SEC	1 SEC	10.6 A	
	1.5KW x 4P	3.4 A	1 DRAVE	SS-05	3 SEC	1 SEC	3.7 A	
C5 TON	5.5KW x 6P	12.9 A	1 DRAVE	SS-30	3 SEC	1 SEC	14.2 A	
	1.0KW x 6P	3.1 A	1 DRAVE	SS-05	3 SEC	1 SEC	3.4 A	
C7.5 TON	5.5KW x 6P	12.9 A	1 DRAVE	SS-30	3 SEC	1 SEC	14.2 A	
	1.0KW x 6P	3.1 A	1 DRAVE	SS-05	3 SEC	1 SEC	3.4 A	
C10 TON	9.0KW x 8P	20.6 A	1 DRAVE	SS-30	3 SEC	1 SEC	22.7 A	
	1.1KW x 8P	3.6 A	1 DRAVE	SS-05	3 SEC	1 SEC	4.0 A	

NOTE

1. 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

E.O.C.R 권고 SETTING 치

* POWER SOURCE : AC3Φ 220V 60Hz

극동호이스트 (주)

MOTOR 용량	MOTOR 정격 전류	DRIVE TYPE	E.O.C.R TYPE	권고 SETTING 치			REMARK
				DELAY TIME	OPERATION TIME	CURRENT	
0.2KW x 6P	2.1 A	1 DRIVE	SS - 05	3 SEC	1 SEC	2.3 A	
		2DRIVE	SS - 05	3 SEC	1 SEC	4.6 A	
0.4KW x 4P	2.7 A	1 DRIVE	SS - 05	3 SEC	1 SEC	3.0 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	5.9 A	
0.5KW x 6P	3.4 A	1 DRIVE	SS - 05	3 SEC	1 SEC	3.7 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	7.5 A	
0.75KW x 4P	4.1 A	1 DRIVE	SS - 05	3 SEC	1 SEC	4.5 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	9.0 A	
1.0KW x 6P	6.8 A	1 DRIVE	SS - 30	3 SEC	1 SEC	7.5 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	15.0 A	
1.5KW x 4P	7.4 A	1 DRIVE	SS - 30	3 SEC	1 SEC	8.1 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	16.3 A	
1.5KW x 6P	7.6 A	1 DRIVE	SS - 30	3 SEC	1 SEC	8.4 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	16.7 A	
2.2KW x 4P	10.0 A	1 DRIVE	SS - 30	3 SEC	1 SEC	11.0 A	
		2 DRIVE	SS - 30	3 SEC	1 SEC	22.0 A	
0.8/0.4KW x 4/8P	4.8 A	1 DRIVE	SS - 30	3 SEC	1 SEC	5.3 A	
		2 DRIVE	SS - 05	3 SEC	1 SEC	4.7 A	
2.2KW x 6P	12.0 A	1 DRIVE	SS - 30	3 SEC	1 SEC	10.6 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	9.4 A	
3.7KW x 4P	16.0 A	1 DRIVE	SS - 30	3 SEC	1 SEC	13.2 A	
		2DRIVE	SS - 60	3 SEC	1 SEC	26.4 A	

NOTE

1, 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

E.O.C.R 권고 SETTING 치

극동호이스트 (주)

* POWER SOURCE : AC3Φ 380V 60Hz

MOTOR 용량	MOTOR 정격 전류	DRIVE TYPE	E.O.C.R TYPE	권고 SETTING 치			REMARK
				DELAY TIME	OPERATION TIME	CURRENT	
0.2KW x 6P	1.6 A	1 DRIVE	SS - 05	3 SEC	1 SEC	1.8 A	
		2DRIVE	SS - 05	3 SEC	1 SEC	3.5 A	
0.4KW x 4P	1.8 A	1 DRIVE	SS - 05	3 SEC	1 SEC	2.0 A	
		2DRIVE	SS - 05	3 SEC	1 SEC	4.0 A	
0.5KW x 6P	2.0 A	1 DRIVE	SS - 05	3 SEC	1 SEC	2.2 A	
		2DRIVE	SS - 05	3 SEC	1 SEC	4.4 A	
0.75KW x 4P	2.4 A	1 DRIVE	SS - 05	3 SEC	1 SEC	2.6 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	5.3 A	
1.0KW x 6P	3.9 A	1 DRIVE	SS - 05	3 SEC	1 SEC	4.3 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	8.6 A	
1.5KW x 4P	4.3 A	1 DRIVE	SS - 05	3 SEC	1 SEC	4.7 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	9.5 A	
1.5KW x 6P	4.4 A	1 DRIVE	SS - 05	3 SEC	1 SEC	4.8 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	9.7 A	
2.2KW x 4P	5.8 A	1 DRIVE	SS - 30	3 SEC	1 SEC	6.4 A	
		2 DRIVE	SS - 30	3 SEC	1 SEC	12.8 A	
0.8/0.4KW x 4/8P	2.8 A	1 DRIVE	SS - 05	3 SEC	1 SEC	3.1 A	
			SS - 05	3 SEC	1 SEC	2.9 A	
	2.6 A	2 DRIVE	SS - 30	3 SEC	1 SEC	6.1 A	
			SS - 30	3 SEC	1 SEC	5.8 A	
2.2KW x 6P	7.0 A	1 DRIVE	SS - 30	3 SEC	1 SEC	7.7 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	15.4 A	
3.7KW x 4P	9.3 A	1 DRIVE	SS - 30	3 SEC	1 SEC	10.2 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	20.5 A	

NOTE

1, 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

E.O.C.R 권고 SETTING 치

* POWER SOURCE : AC3Φ 440V 60Hz

극동하이스트 (주)

MOTOR 용량	MOTOR 정격 전류	DRIVE TYPE	E.O.C.R TYPE	권고 SETTING 치			REMARK
				DELAY TIME	OPERATION TIME	CURRENT	
0.2KW x 6P	1.2 A	1 DRIVE	SS - 05	3 SEC	1 SEC	1.3 A	
		2DRIVE	SS - 05	3 SEC	1 SEC	2.6 A	
0.4KW x 4P	1.4 A	1 DRIVE	SS - 05	3 SEC	1 SEC	1.5 A	
		2DRIVE	SS - 05	3 SEC	1 SEC	3.1 A	
0.5KW x 6P	1.7 A	1 DRIVE	SS - 05	3 SEC	1 SEC	1.9 A	
		2DRIVE	SS - 05	3 SEC	1 SEC	3.7 A	
0.75KW x 4P	2.0 A	1 DRIVE	SS - 05	3 SEC	1 SEC	2.2 A	
		2DRIVE	SS - 05	3 SEC	1 SEC	4.4 A	
1.0KW x 6P	2.8 A	1 DRIVE	SS - 05	3 SEC	1 SEC	3.1 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	6.2 A	
1.5KW x 4P	3.7 A	1 DRIVE	SS - 05	3 SEC	1 SEC	4.1 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	8.1 A	
1.5KW x 6P	3.8 A	1 DRIVE	SS - 05	3 SEC	1 SEC	4.2 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	8.4 A	
2.2KW x 4P	5.0 A	1 DRIVE	SS - 30	3 SEC	1 SEC	5.5 A	
		2 DRIVE	SS - 30	3 SEC	1 SEC	11.0 A	
0.8/0.4KW x 4/8P	2.4 A	1 DRIVE	SS - 05	3 SEC	1 SEC	2.6 A	
		2 DRIVE	SS - 05	3 SEC	1 SEC	2.5 A	
2.2KW x 6P	5.8 A	1 DRIVE	SS - 30	3 SEC	1 SEC	5.3 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	6.4 A	
3.7KW x 4P	8.0 A	1 DRIVE	SS - 30	3 SEC	1 SEC	12.8 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	8.8 A	
				3 SEC	1 SEC	17.6 A	

NOTE

1, 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

E.O.C.R 권고 SETTING 치

* POWER SOURCE : AC3Φ 460V 60Hz

극동호이스트 (주)

MOTOR 용량	MOTOR 정격 전류	DRIVE TYPE	E.O.C.R TYPE	권고 SETTING 치			REMARK
				DELAY TIME	OPERATION TIME	CURRENT	
0.2KW x 6P	1.2 A	1 DRIVE	SS - 05	3 SEC	1 SEC	1.3 A	
		2DRIVE	SS - 05	3 SEC	1 SEC	2.6 A	
0.4KW x 4P	1.4 A	1 DRIVE	SS - 05	3 SEC	1 SEC	1.5 A	
		2DRIVE	SS - 05	3 SEC	1 SEC	3.1 A	
0.5KW x 6P	1.7 A	1 DRIVE	SS - 05	3 SEC	1 SEC	1.9 A	
		2DRIVE	SS - 05	3 SEC	1 SEC	3.7 A	
0.75KW x 4P	2.0 A	1 DRIVE	SS - 05	3 SEC	1 SEC	2.2 A	
		2DRIVE	SS - 05	3 SEC	1 SEC	4.4 A	
1.0KW x 6P	2.8 A	1 DRIVE	SS - 05	3 SEC	1 SEC	3.1 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	6.2 A	
1.5KW x 4P	3.7 A	1 DRIVE	SS - 05	3 SEC	1 SEC	4.1 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	8.1 A	
1.5KW x 6P	3.8 A	1 DRIVE	SS - 05	3 SEC	1 SEC	4.2 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	8.4 A	
2.2KW x 4P	5.0 A	1 DRIVE	SS - 30	3 SEC	1 SEC	5.5 A	
		2 DRIVE	SS - 30	3 SEC	1 SEC	11.0 A	
0.8/0.4KW x 4/8P	2.4 A	1 DRIVE	SS - 05	3 SEC	1 SEC	2.6 A	
		2 DRIVE	SS - 05	3 SEC	1 SEC	2.5 A	
2.2KW x 6P	5.8 A	1 DRIVE	SS - 30	3 SEC	1 SEC	5.3 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	5.0 A	
3.7KW x 4P	8.0 A	1 DRIVE	SS - 30	3 SEC	1 SEC	12.8 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	8.8 A	
				3 SEC	1 SEC	17.6 A	

NOTE

1, 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

E.O.C.R 권고 SETTING 치

* POWER SOURCE : AC3Φ 480V 60Hz

극동하이스트 (주)

MOTOR 용량	MOTOR 정격 전류	DRIVE TYPE	E.O.C.R TYPE	권고 SETTING 치			REMARK
				DELAY TIME	OPERATION TIME	CURRENT	
0.2KW x 6P	1.2 A	1 DRIVE	SS - 05	3 SEC	1 SEC	1.3 A	
		2DRIVE	SS - 05	3 SEC	1 SEC	2.6 A	
0.4KW x 4P	1.4 A	1 DRIVE	SS - 05	3 SEC	1 SEC	1.5 A	
		2DRIVE	SS - 05	3 SEC	1 SEC	3.1 A	
0.5KW x 6P	1.6 A	1 DRIVE	SS - 05	3 SEC	1 SEC	1.8 A	
		2DRIVE	SS - 05	3 SEC	1 SEC	3.5 A	
0.75KW x 4P	1.9 A	1 DRIVE	SS - 05	3 SEC	1 SEC	2.1 A	
		2DRIVE	SS - 05	3 SEC	1 SEC	4.2 A	
1.0KW x 6P	2.8 A	1 DRIVE	SS - 05	3 SEC	1 SEC	3.1 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	6.2 A	
1.5KW x 4P	3.7 A	1 DRIVE	SS - 05	3 SEC	1 SEC	4.1 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	8.1 A	
1.5KW x 6P	3.8 A	1 DRIVE	SS - 05	3 SEC	1 SEC	4.2 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	8.4 A	
2.2KW x 4P	5.0 A	1 DRIVE	SS - 30	3 SEC	1 SEC	5.5 A	
		2 DRIVE	SS - 30	3 SEC	1 SEC	11.0 A	
0.8/0.4KW x 4/8P	2.4 A	1 DRIVE	SS - 05	3 SEC	1 SEC	2.6 A	
		2 DRIVE	SS - 05	3 SEC	1 SEC	2.5 A	
2.2KW x 6P	5.8 A	1 DRIVE	SS - 30	3 SEC	1 SEC	5.3 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	5.0 A	
3.7KW x 4P	8.0 A	1 DRIVE	SS - 30	3 SEC	1 SEC	6.4 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	12.8 A	
		1 DRIVE	SS - 30	3 SEC	1 SEC	8.8 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	17.6 A	

NOTE

1, 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

SALES OFFICE : 7th floor, 145, Teheran-ro, Gangnam-gu, Seoul, Korea

TEL : 82-2-3420-3500, FAX : 82-2-3420-3600, E-mail : sales@dsrcorp.com, http://www.dsrcorp.com

MILL TEST CERTIFICATE / CERTIFICATE OF INSPECTION

Certificate No : 201810-Do637-1

Reel/Coil No : 1 - 2

Purchaser : -

Date : 2018. 10. 10

P.O No : -

L/C No. : -

Invoice No : Do637-160

1. TYPE / GRADE

Construction : 6X37+FC

Diameter : 16 MM

Length : 1,000 MTRS X 2 R/L

Specification : KS D 3514

Coating : BRIGHT

Grade : 1,770

Lay : RHRL

Lubrication : A-2

2. ROPE TEST RESULTS

Items	Normal or Specified	Actual
Diameter	16 MM	16.4 MM
Breaking Strength	145.0 KN	149 KN
Lay Length	- MM	107 MM
Preforming	Good	Good

3. WIRE TEST RESULTS

Items	Normal or Specified	Actual
Diameter	0.72 MM	0.73 MM
Tensile Strength	1,770 N/MM2	1,833 N/MM2
Break Force	720 N	767 N
Torsion	27	40
Weight of Coating	- G/M2	- G/M2

We hereby certify that the above results are true and correct in every detail.

CHEMICAL ANALYSIS OF WIRE ROD

Charge No	Chemical Composition (%)				
	C	Si	Mn	P	S
SF 97502	0.71	0.20	0.47	0.009	0.007

Approval or Inspection Possibility

WIRE ROPE

Suncheon Factory : 15, Sandan 1-gil, Seo-myeon, Suncheon-si Jeonnam-do, Korea.
Yulchon Factory : 80-21, Yulchonsandan 1-ro, Haeryong-myeon, Suncheon-si, Jeonnam-do, Korea



WIRE

Suncheon 2 Factory : 38, Sandan 4-gil, Seo-myeon, Suncheon-si Jeonnam-do, Korea

Quality Management Dept



JIS G 3521
(KSKR 08020)
JIS G 3522
(KSKR 08021)



KS D 3510
(NIB1728)

Handwritten signature

Chief Inspector

THREE PHASE INDUCTION MOTOR DATA SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	HOISTING
2. MANUFACTURE	극동 호이스트 (주)
3. FRAME NUMBER	160 L
4. RATED POWER	9.0 KW x 8 P
5. RATED VOLTAGE AND FREQUENCY	220 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TEMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	825 RPM
11. FULL LOAD CURRENT	45.0 A
12. STARTING CURRENT AT RATED VOLTAGE	213 A
13. MINIMUM STARTING VOLTAGE	198 V
14. EFFICIENCY AT 100% RATED LOAD	79.5 %
15. POWER FACTOR AT 100% RATED LOAD	66.4 %
16. STARTING TORQUE	15.9 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6309zz OPL : 6308zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPERATURE	40 °C
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

THREE PHASE INDUCTION MOTOR DATA SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	HOISTING
2. MANUFACTURE	극동 호이스트 (주)
3. FRAME NUMBER	160 L
4. RATED POWER	9.0 KW x 8 P
5. RATED VOLTAGE AND FREQUENCY	380 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TEMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	825 RPM
11. FULL LOAD CURRENT	26.0 A
12. STARTING CURRENT AT RATED VOLTAGE	122.9 A
13. MINIMUM STARTING VOLTAGE	342 V
14. EFFICIENCY AT 100% RATED LOAD	79.5 %
15. POWER FACTOR AT 100% RATED LOAD	66.4 %
16. STARTING TORQUE	15.9 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6309zz OPL : 6308zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPERATURE	40 °C
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

THREE PHASE INDUCTION MOTOR DATA SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	HOISTING
2. MANUFACTURE	극동 호이스트 (주)
3. FRAME NUMBER	160 L
4. RATED POWER	9.0 KW x 8 P
5. RATED VOLTAGE AND FREQUENCY	440 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TEMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	825 RPM
11. FULL LOAD CURRENT	22.5 A
12. STARTING CURRENT AT RATED VOLTAGE	106.0 A
13. MINIMUM STARTING VOLTAGE	396 V
14. EFFICIENCY AT 100% RATED LOAD	79.5 %
15. POWER FACTOR AT 100% RATED LOAD	66.4 %
16. STARTING TORQUE	15.9 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6309zz OPL : 6308zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPERATURE	40 °C
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

THREE PHASE INDUCTION MOTOR DATA SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	HOISTING
2. MANUFACTURE	극동 호이스트 (주)
3. FRAME NUMBER	160 L
4. RATED POWER	9.0 KW x 8 P
5. RATED VOLTAGE AND FREQUENCY	460 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TEMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	825 RPM
11. FULL LOAD CURRENT	21.5 A
12. STARTING CURRENT AT RATED VOLTAGE	102.2 A
13. MINIMUM STARTING VOLTAGE	414 V
14. EFFICIENCY AT 100% RATED LOAD	79.5 %
15. POWER FACTOR AT 100% RATED LOAD	66.4 %
16. STARTING TORQUE	15.9 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6309zz OPL : 6308zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPERATURE	40 °C
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

THREE PHASE INDUCTION MOTOR DATA SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	HOISTING
2. MANUFACTURE	극동 호이스트 (주)
3. FRAME NUMBER	160 L
4. RATED POWER	9.0 KW x 8 P
5. RATED VOLTAGE AND FREQUENCY	480 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1 . 0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TEMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	825 RPM
11. FULL LOAD CURRENT	20.6 A
12. STARTING CURRENT AT RATED VOLTAGE	97.97 A
13. MINIMUM STARTING VOLTAGE	432 V
14. EFFICIENCY AT 100% RATED LOAD	79.5 %
15. POWER FACTOR AT 100% RATED LOAD	66.4 %
16. STARTING TORQUE	15.9 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6309zz OPL : 6308zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPERATURE	40 °C
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

THREE PHASE INDUCTION MOTOR DATA SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	HOISTING
2. MANUFACTURE	극동 호이스트 (주)
3. FRAME NUMBER	112 S
4. RATED POWER	1.1 KW x 8 P
5. RATED VOLTAGE AND FREQUENCY	220 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1 . 0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TEMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	830 RPM
11. FULL LOAD CURRENT	7.95 A
12. LOCKED ROTOR CURRENT	41.1 A
13. MINIMUM STARTING VOLTAGE	198 V
14. EFFICIENCY AT 100% RATED LOAD	71.0 %
15. POWER FACTOR AT 100% RATED LOAD	51.5 %
16. STARTING TORQUE	2.85 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6208zz OPL : 6206zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPERATURE	40 °C
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

THREE PHASE INDUCTION MOTOR DATA SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	HOISTING
2. MANUFACTURE	극동 호이스트 (주)
3. FRAME NUMBER	112 S
4. RATED POWER	1.1 KW x 8 P
5. RATED VOLTAGE AND FREQUENCY	380 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TEMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	830 RPM
11. FULL LOAD CURRENT	4.57 A
12. LOCKED ROTOR CURRENT	23.8 A
13. MINIMUM STARTING VOLTAGE	342 V
14. EFFICIENCY AT 100% RATED LOAD	71.0 %
15. POWER FACTOR AT 100% RATED LOAD	51.5 %
16. STARTING TORQUE	2.85 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6208zz OPL : 6206zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPERATURE	40 °C
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

THREE PHASE INDUCTION MOTOR DATA SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	HOISTING
2. MANUFACTURE	극동 호이스트 (주)
3. FRAME NUMBER	112 S
4. RATED POWER	1.1 KW x 8 P
5. RATED VOLTAGE AND FREQUENCY	440 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TEMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	830 RPM
11. FULL LOAD CURRENT	3.95 A
12. LOCKED ROTOR CURRENT	20.55 A
13. MINIMUM STARTING VOLTAGE	396 V
14. EFFICIENCY AT 100% RATED LOAD	71.0 %
15. POWER FACTOR AT 100% RATED LOAD	51.5 %
16. STARTING TORQUE	2.85 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6208zz OPL : 6006zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPERATURE	40 °C
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

THREE PHASE INDUCTION MOTOR DATA SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	HOISTING
2. MANUFACTURE	극동 호이스트 (주)
3. FRAME NUMBER	112 S
4. RATED POWER	1.1 KW x 8 P
5. RATED VOLTAGE AND FREQUENCY	460 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TEMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	830 RPM
11. FULL LOAD CURRENT	3.7 A
12. LOCKED ROTOR CURRENT	18.73 A
13. MINIMUM STARTING VOLTAGE	414 V
14. EFFICIENCY AT 100% RATED LOAD	71.0 %
15. POWER FACTOR AT 100% RATED LOAD	51.5 %
16. STARTING TORQUE	2.85 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6208zz OPL : 6006zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPERATURE	40 °C
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

THREE PHASE INDUCTION MOTOR DATA SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	HOISTING
2. MANUFACTURE	극동 호이스트 (주)
3. FRAME NUMBER	112 S
4. RATED POWER	1.1 KW x 8 P
5. RATED VOLTAGE AND FREQUENCY	480 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1 . 0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TEMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	830 RPM
11. FULL LOAD CURRENT	3.6 A
12. LOCKED ROTOR CURRENT	18.53 A
13. MINIMUM STARTING VOLTAGE	432 V
14. EFFICIENCY AT 100% RATED LOAD	71.0 %
15. POWER FACTOR AT 100% RATED LOAD	51.5 %
16. STARTING TORQUE	2.85 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6208zz OPL : 6006zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPERATURE	40 °C
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

THREE PHASE INDUCTION MOTOR DATA SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	TRAVERSING
2. MANUFACTURE	극동 호이스트 (주)
3. FRAME NUMBER	90 S
4. RATED POWER	0.75 KW x 4 P
5. RATED VOLTAGE AND FREQUENCY	220 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1 . 0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TEMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	1760 RPM
11. FULL LOAD CURRENT	4.1 A
12. STARTING CURRENT AT RATED VOLTAGE	22.1 A
13. MINIMUM STARTING VOLTAGE	198 V
14. EFFICIENCY AT 100% RATED LOAD	66.0 %
15. POWER FACTOR AT 100% RATED LOAD	73.5 %
16. STARTING TORQUE	1.02 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6205zz OPL : 6204zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPERATURE	40 °C
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

THREE PHASE INDUCTION MOTOR DATA SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	TRAVERSING
2. MANUFACTURE	극동 호이스트 (주)
3. FRAME NUMBER	90 S
4. RATED POWER	0.75 KW x 4 P
5. RATED VOLTAGE AND FREQUENCY	380 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1 . 0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TEMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	1760 RPM
11. FULL LOAD CURRENT	2.4 A
12. STARTING CURRENT AT RATED VOLTAGE	13.5 A
13. MINIMUM STARTING VOLTAGE	342 V
14. EFFICIENCY AT 100% RATED LOAD	67.0 %
15. POWER FACTOR AT 100% RATED LOAD	69.5 %
16. STARTING TORQUE	0.85 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6205zz OPL : 6204zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPERATURE	40 °C
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

THREE PHASE INDUCTION MOTOR DATA SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	TRAVERSING
2. MANUFACTURE	극동 호이스트 (주)
3. FRAME NUMBER	90 S
4. RATED POWER	0.75 KW x 4 P
5. RATED VOLTAGE AND FREQUENCY	440 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1 . 0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TEMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	1760 RPM
11. FULL LOAD CURRENT	2.0 A
12. STARTING CURRENT AT RATED VOLTAGE	11.1 A
13. MINIMUM STARTING VOLTAGE	396 V
14. EFFICIENCY AT 100% RATED LOAD	67.0 %
15. POWER FACTOR AT 100% RATED LOAD	73.5 %
16. STARTING TORQUE	1.02 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6205zz OPL : 6204zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPERATURE	40 °C
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

THREE PHASE INDUCTION MOTOR DATA SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	TRAVERSING
2. MANUFACTURE	극동 호이스트 (주)
3. FRAME NUMBER	90 S
4. RATED POWER	0.75 KW x 4 P
5. RATED VOLTAGE AND FREQUENCY	460 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATTING	1 . 0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TEMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	1760 RPM
11. FULL LOAD CURRENT	2.0 A
12. STARTING CURRENT AT RATED VOLTAGE	10.6 A
13. MINIMUM STARTING VOLTAGE	414 V
14. EFFICIENCY AT 100% RATED LOAD	66.0 %
15. POWER FACTOR AT 100% RATED LOAD	73.5 %
16. STARTING TORQUE	1.02 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6205zz OPL : 6204zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPERATURE	40 °C
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

THREE PHASE INDUCTION MOTOR DATA SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	TRAVERSING
2. MANUFACTURE	극동 호이스트 (주)
3. FRAME NUMBER	90 S
4. RATED POWER	0.75 KW x 4 P
5. RATED VOLTAGE AND FREQUENCY	480 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATTING	1 . 0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TEMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	1760 RPM
11. FULL LOAD CURRENT	1.9 A
12. STARTING CURRENT AT RATED VOLTAGE	10.2 A
13. MINIMUM STARTING VOLTAGE	432 V
14. EFFICIENCY AT 100% RATED LOAD	66.0 %
15. POWER FACTOR AT 100% RATED LOAD	73.5 %
16. STARTING TORQUE	1.02 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6205zz OPL : 6204zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPERATURE	40 °C
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

THREE PHASE INDUCTION MOTOR DATA SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	TRAVERSING
2. MANUFACTURE	극동 호이스트 (주)
3. FRAME NUMBER	90 S
4. RATED POWER	0.5 KW x 6 P
5. RATED VOLTAGE AND FREQUENCY	220 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1 . 0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TEMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	1160 RPM
11. FULL LOAD CURRENT	3.4 A
12. STARTING CURRENT AT RATED VOLTAGE	16.4 A
13. MINIMUM STARTING VOLTAGE	198 V
14. EFFICIENCY AT 100% RATED LOAD	64.0 %
15. POWER FACTOR AT 100% RATED LOAD	59.5 %
16. STARTING TORQUE	0.80 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6205zz OPL : 6204zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPERATURE	40 °C
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

THREE PHASE INDUCTION MOTOR DATA SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	TRAVERSING
2. MANUFACTURE	극동 호이스트 (주)
3. FRAME NUMBER	90 S
4. RATED POWER	0.5 KW x 6 P
5. RATED VOLTAGE AND FREQUENCY	380 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TEMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	1160 RPM
11. FULL LOAD CURRENT	2.0 A
12. STARTING CURRENT AT RATED VOLTAGE	9.5 A
13. MINIMUM STARTING VOLTAGE	342 V
14. EFFICIENCY AT 100% RATED LOAD	64.0 %
15. POWER FACTOR AT 100% RATED LOAD	59.5 %
16. STARTING TORQUE	0.80 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6205zz OPL : 6204zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPERATURE	40 °C
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

THREE PHASE INDUCTION MOTOR DATA SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	TRAVERSING
2. MANUFACTURE	극동 호이스트 (주)
3. FRAME NUMBER	90 S
4. RATED POWER	0.5 KW x 6 P
5. RATED VOLTAGE AND FREQUENCY	440 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1 . 0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TEMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	1160 RPM
11. FULL LOAD CURRENT	1.7 A
12. STARTING CURRENT AT RATED VOLTAGE	8.2 A
13. MINIMUM STARTING VOLTAGE	396 V
14. EFFICIENCY AT 100% RATED LOAD	64.0 %
15. POWER FACTOR AT 100% RATED LOAD	59.5 %
16. STARTING TORQUE	0.80 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6205zz OPL : 6204zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPERATURE	40 °C
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

THREE PHASE INDUCTION MOTOR DATA SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	TRAVERSING
2. MANUFACTURE	극동 호이스트 (주)
3. FRAME NUMBER	90 S
4. RATED POWER	0.5 KW x 6 P
5. RATED VOLTAGE AND FREQUENCY	460 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1 . 0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TEMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	1160 RPM
11. FULL LOAD CURRENT	1.7 A
12. STARTING CURRENT AT RATED VOLTAGE	7.9 A
13. MINIMUM STARTING VOLTAGE	414 V
14. EFFICIENCY AT 100% RATED LOAD	64.0 %
15. POWER FACTOR AT 100% RATED LOAD	59.5 %
16. STARTING TORQUE	0.80 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6205zz OPL : 6204zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPERATURE	40 °C
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

THREE PHASE INDUCTION MOTOR DATA SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	TRAVERSING
2. MANUFACTURE	극동 호이스트 (주)
3. FRAME NUMBER	90 S
4. RATED POWER	0.5 KW x 6 P
5. RATED VOLTAGE AND FREQUENCY	480 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1 . 0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TEMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	1160 RPM
11. FULL LOAD CURRENT	1.6 A
12. STARTING CURRENT AT RATED VOLTAGE	7.5 A
13. MINIMUM STARTING VOLTAGE	432 V
14. EFFICIENCY AT 100% RATED LOAD	64.0 %
15. POWER FACTOR AT 100% RATED LOAD	59.5 %
16. STARTING TORQUE	0.80 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6205zz OPL : 6204zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPERATURE	40 °C
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E