



제 2014 - 25798 호

안 전 인 증 서

(사업장명)

극동호이스트(주)

(소재지) (425-833)경기도 안산시 성곡동630-2 반월공단 B-607-14

위 사업장에서 제조하는 아래의 품목이 산업안전보건법 제34조 및 같은 법 시행규칙 제58조의4제4항에 따른 안전인증 심사 결과 안전·보건기준에 적합하므로 안전인증표시의 사용을 인증합니다.

_____ 품 목 _____
호이스트


_____ 형식,모델(용량,등급)/인증번호 _____
KDC1-DL (1Ton) /14-AQ2AC-02274

_____ 인 증 기 준 _____
고용노동부 고시 제2012 - 33호 (위험기계,기구 의무안전인증 고시)

_____ 인 증 조 건 _____
인증유효기간 :

2014년 07월 11일

한국산업안전보건공단이사장





심사결과 통지서

신청인	사업장명	극동호이스트(주)	사업장관리번호	134-81-013350
	사업자등록번호	134-81-01335	대표자 성명	최성찬
	소재지	(425 - 833) 경기도 안산시 성곡동630-2 반월공단 B-607-14		
안전인증대상 기계·기구명				
호이스트				
형 식 (규 격)	KDC1-DL		용 량 (등 급)	1 Ton

산업안전보건법 제 34조 및 같은 법 시행규칙 제58조의4에 따라 실시한

☐ 예비심사

☒ 서면심사

☐ 기술능력 및 생산체계 심사

☐ 개별 제품심사

☐ 개별 제품심사(제작중)

☐ 형식별 제품심사

결과가 ☒ 적 합
☐ 부적합

함을 통지합니다.

2014년 07월 07일

인증심사원

강성두 변명수

(서명 또는 인)

한국산업안전보건공단 경기서부지사장



서 면 심 사 서 류

형식 번호 : KDC1 - DL

극 동 호 이 스트 (주)

工場 : 경기도 안산시 단원구 해봉로 119 (성곡동)

電話 : 031) 491 - 5311

FAX : 031) 494 - 5315

산업재해예방
안전보건공단

KOREA OCCUPATIONAL SAFETY & HEALTH AGENCY

동일형식일람표

사업장명	구동호이스트	개정일자 및 번호	2014년 06월 25일	인증번호	
형식 및 모델	모델	동일 형식 인정범위 및 내역			비 고
형식	모델	권상속도(m/min)	회행속도(m/min)	양정(m)	회행방식
KDC1-DL	KDC1-L6-DL	고속: 12M/MIN CREEP: 1.2M/MIN	고속:24M/MIN 저속:16M/MIN	6	모터구동식
	KDC1-L9-DL			9	
				-	



산업재해예방
안전보건공단

KOREA OCCUPATIONAL SAFETY & HEALTH AGENCY


5) 방호장치의 성능검사 합격증 사본



산업재해예방

안전보건공단

KOREA OCCUPATIONAL SAFETY & HEALTH AGENCY



제 2012-BJ-0009 호



안 전 인 증 서

정호엔지니어링

경기도 광명시 노동사동 440-5

위 사업장에서 제조하는 아래의 품목이 산업안전보건법 제34조 및 같은 법 시행규칙 제58조의4항에 따른 안전인증 심사 결과 안전·보건기준에 적합하므로 안전인증표시의 사용을 인증합니다.

품 목

양중기용 과부하방지장치

형식·모델/용량·등급/인증번호

형식·모델

JDL-100

용량·등급

J-2

인증번호

12-AV2BJ-0009

인 증 기 준

방호장치 의무안전인증 고시(고용노동부고시 제2010-36호)

인 증 조 건

아래 주소에서 생산되는 제품에 한함.

정호엔지니어링, 경기도 광명시 노동사동 440-5




한국산업안전보건공단 이사장

1-안전인증서.jpg 123 KB

산업재해예방

안전보건공단

KOREA OCCUPATIONAL SAFETY & HEALTH AGENCY



유드 저장 삭제


II. 도 면




산업재해예방

안전보건공단


KOREA OCCUPATIONAL SAFETY & HEALTH AGENCY



1) 기 계







SPECIFICATION			
RATED LOAD	1000	KG	
TESTING LOAD	1250	KG	
LIFT	9	M	
RATING	30	MIN	
HOISTING	SPEED	12/1.2	M/MIN
	MOTOR	2.4/0.4	KW x 4 P
TRAVERSING	SPEED	24	M/MIN
	MOTOR	0.75	KW x 4 P
	SPEED	16	M/MIN
	MOTOR	0.5	KW x 6 P
WIRE ROPE	(6x19) ϕ 6 x 4 FALLS		
POWER SOURCE	AC3 ϕ 220V(380,440,460,480)V 60Hz		
COLOR	10 B 3/5		
WEIGHT	425	KG	

4	UPPER LIMIT S/W	SS400	1				
3	SAFETY LATCH	SS400	1				
2	EMERGENCY S/W	—	1				
1	LOAD LIMITER	—	1				
No.	DESCRIPTION	M ³ L	SUB QTY	TOTAL	SUB WEIGHT(kg)	TOTAL	REMARKS.
PROJECT	DATE DIM mm						
TITLE	KDC 1 DL (9M)		SCALE		PROJECTION		
	ARRANGEMENT DRAWING FOR HOIST		A3/15		3rd		
DRAWN	DESIGNED	CHECKED	APPROVED	REF.		DRAWING	
 KDK 동호이스트 주식회사 KUK DONG HOIST CO., LTD.			SHEET No.		DWG No.		
					KDC1DL900		

VIEW A




2) 전 기



산업재해예방

안전보건공단

KOREA OCCUPATIONAL SAFETY & HEALTH AGENCY



DESCRIPTION	SYMBOLS	DESCRIPTION	SYMBOLS	SYMBOLS		DESCRIPTION	SYMBOLS		DESCRIPTION	SYMBOLS	
				MAKE	BREAK		MAKE	BREAK			
3 PHASE SQUIRREL CAGE ROTOR INDUCTION MOTOR		NO FUSE BREAKER 2 PHASE				MAGNETIC & RELAY CONTACTOR			PUSHBUTTON SWITCH 1 BUTTON 2 STEP TYPE		
3 PHASE SQUIRREL CAGE ROTOR INDUCTION MOTOR		NO FUSE BREAKER 3 PHASE				ON DELAY TIME CONTACTOR			TOGGLE SWITCH OR SELECTOR SWITCH		
DC MAG BRAKE		EARTH LEAKAGE BREAKER 2 PHASE				OFF DELAY TIME CONTACTOR					
THRUSTOR BRAKE		EARTH LEAKAGE BREAKER 3 PHASE				EOCR OR THERMAL RELAY CONTACTOR					
C-DC MAG. BRAKE		TRANSFORMER				THERMOSTAT					
SC BRAKE		CURRENT TRANSFORMER				LIMIT SWITCH					
RECIPER		POTENTIAL TRANSFORMER				PUSHBUTTON SWITCH					
LOAD LIMIT ELECTRICAL		FUSE				EMERGENCY PUSHBUTTON SWITCH					
ELE CURRENT		FUSE WITH CONTACTOR				KEY SWITCH					
		TH. RESISTANCE UNIT				FOOT SWITCH					

A														
A														
A														
A														
WK														
									</					

DESCRIPTION	SYMBOLS	DESCRIPTION	SYMBOLS	DESCRIPTION	SYMBOLS
WIRE INTERNAL TO ENCLOSURE	—	CONTROLLER OR REMOTE CONTROLLER CONTACTOR		SOLENOID COIL	
WIRE (EXTERNAL TO ENCLOSURE)	----	UPPER LIMIT SWITCH (LS-#)		RESISTOR	
WIRE NOT CONNECTED	+	THERMAL RELAY		VARIABLE RESISTOR	
WIRE CONNECTED	+	PILOT(SIGNAL) LAMP		SLIP RING	
TERMINAL	⊙	ROTARY LAMP		CABLE REEL	
GROUNDED (EARTH)	⊥	WARNING SIREN		SPACE HEATER	
PLUG RECEPTACLE	⋈	BUZZER		SURGE ABSORBER	
MAGNETIC CONTROLLER COIL	⊙	ANALOG METER		LOAD CELL	
AUX. RELAY	⊙	VOLT METER		BALLAST WITH RECEPTACLE	
TIMER	⊙	FLUORESCENT LAMP		FAN	

[illegible]

ELECTRICAL SPECIFICATION

POWER SOURCE : AC 3Φ 220V, 380V, 440V, 460V, 480V 60Hz
 CONTROL SOURCE : AC 1Φ 110V(120V) 60Hz

SUBJECT	MOTOR OUTPUT	220V		380V		440V	460V	480V	440, 460, 480V	BRAKE	REMARK
		STATOR CURRENT	1st CABLE SIZE	STATOR CURRENT	1st CABLE SIZE	STATOR CURRENT	STATOR CURRENT	STATOR CURRENT	1st CABLE SIZE		
M.L. HOIST	2.4KW x 4P 30 MIN	10.0 A	4.0 sq	2.8 A	4.0 sq	5.0 A	4.8 A	4.6 A	4.0 sq	DC MAG. BRAKE	
	0.4KW x 4P 30 MIN	2.7 A	4.0 sq	1.6 A	4.0 sq	1.4 A	1.3 A	1.2 A	4.0 sq	DC MAG. BRAKE	
CRABE HOIST	0.75KW x 4P 30 MIN	4.1 A	4.0 sq	2.4 A	4.0 sq	2.0 A	2.0 A	1.9 A	4.0 sq	DC MAG. BRAKE	1 DRIVE
	0.5KW x 6P 30 MIN	3.4 A	4.0 sq	2.0 A	4.0 sq	1.7 A	1.7 A	1.6 A	4.0 sq	DC MAG. BRAKE	1 DRIVE
CONTROL CIRCUIT		2 A	2.5 sq	2 A	2.5 sq	2 A	2 A	2 A	2.5 sq		
LIGHTING & ACC'Y CIRCUIT											
SUB TOT (PEAK LOAD)	HIGH	16.1 A	4.0 sq	7.2 A	4.0 sq	9.0 A	8.8 A	8.5 A	4.0 sq	I(A)=M/H + T/S + ASS'Y	
	LOW	15.1 A	4.0 sq	6.8 A	4.0 sq	8.7 A	8.5 A	8.2 A	4.0 sq	I(A)=M/H + T/S + ASS'Y	
SUB TOT (NORMAL LOAD)											

*. 위 계산는 HIGH(MAX.)일때와 LOW(MIN.)일때만 계산한것임.
 *. 위 계산은 LIFT 6.9M에 적용

NO	DESCRIPTION	CABLE SIZE
1	MAIN EARTH LINE	USER SCOPE
2	POWER SOURCE	USER SCOPE
3	TROLLEY BAR	USER SCOPE
4	POWER SOURCE WITH EARTH	USER SCOPE
5	HOIST POWER SOURCE WITH EARTH	VCIF 4.0SQ x 1C
6	HOISTING MOTOR WITH EARTH	VCIF 4.0SQ x 1C
7	CREEP MOTOR WITH EARTH	VCIF 4.0SQ x 1C
8	TRAVERSING MOTOR WITH EARTH	VCIF 4.0SQ x 1C

* CV CABLE 4C중 1C는 EARTH로 사용함.

- NOTE -

1. 전동기 외함, 제어반의 프레임 등은 접지하여 그 접지 저항은

400V 미만 : 100옴 이하일것.(3중 접지)
400V 이상 : 10옴을 이하일것.(특 3중접지)

2.MAIN S/W BOX는 3중 접지 요.

동전위접지

1. 전기장비와 기계의 노출된 모든 도전부는 보호전위접지에 연결되어야 하며 적절한 접지연속성 기능이 유지되어야함.

2. 보호전위접지에는 개폐기, 과전류보호장치가 부착되지 않아야 한다.

시험대상 전선의 최소 유효단면적	최고전압강하(V)
1.0	3.3
1.5	2.6
2.5	1.6
4.0	1.4
>6.0	1.0

----- USER SCOPE
----- KUKDONG SCOPE

산입제해예방
안전보건공단
KOSHA

100C1-EC001

KOREA OCCUPATIONAL SAFETY & HEALTH AGENCY

DRAWING	DESIGN	CHECKED	APPROVED	SCALE	DATE	ORDER NO.
				NONE		

CUSTOMER	DRAWING TITLE	REVISIONS	CHK.	APP.	DATE
	EARTH DETAILS DRAWING				

DWG. NO. KDCI-EC001

■ 보호본딩회로의 연속성 확인

시험전선의 최소유호 단면적(mm²)	최고 전압 강하(V)
1.0	3.3
1.5	2.6
2.5	1.9
4.0	1.4
>6.0	1.0

① 보호본딩회로의 연속성의 검증은 PELV전원(50/60Hz)에서 최소 10A 이상의 전류를 10초 이상의 인가에 의한다.

시험은 PE단자와 보호본딩회로의 여러지점 사이에서 이루어진다.

② PE단자와 시험 지점 사이에서 측정된 전압은(표 참조) 값을 초과해서는 아니된다.

■ 절연저항 시험

전원선과 보호본딩선 사이를 직류 500V로 측정된 절연저항 값은 1MΩ 이상이어야 한다.

■ 압 시험

① 압에서 작동되도록 설계된 전기장치의 회로를 제외한 모든 회로와 보호본딩회로의 전선 사이에 1초 이상 속되는 다음의 시험 전압에 견딜수 있어야 한다.

- 장치의 정격전압의 두배 또는 1,000V 중 큰값의 전압

② 이 시험을 견딜수 없도록 설계된 부품은 시험이 진행되기 전에 차단하여야 한다.

KDC1DL-E234

KDC1DL-E234

The drawing consists of two views of a mechanical assembly. The top view shows a circular component with a central shaft and a rectangular housing. The side view shows the assembly mounted on a base with two support legs. Callout numbers 1, 2, and 3 are present.

- 1: Points to the central shaft or a component on the shaft.
- 2: Points to a component on the shaft, possibly a pulley or a coupling.
- 3: Points to the base or support legs of the assembly.

3 PHASE INDUCTION MOTOR			
KW	P	TYPE	TENV
VOLTS	V	RATING	min
AMP.S	A	AMP. TEMP	40°C
HEARTS		INS.CLASS	F
R.P.M		BEARING	
ROTOR	C	BEARING	
SERIAL.		DATE	

KUKDONG HOIST CO.,LTD

KUKD	3 PHASE INDUCTION MOTOR			
	KW	PI TYPE	TENV	
	VOLTS	VIRATING	min	
	AMP S	A	TEMP	40C
	HEARTS	INS. CLASS		F
	R.P.M	BEARING		
	ROTOR	BEARING		
	C	DATE		
	SERIAL			
KUKDONG HOIST CO.,LTD				

[illegible]

1	2	3	4	5	6	7	8	9
---	---	---	---	---	---	---	---	---

극동호이스트

제한하중

1000K

380

580

170

1

2

IN DOOR

OUT DOOR

SPONGE

SPONGE

20

20

25

NOTE

1.PROTECTION DEGREE ;
A. INDOOR TYPE : DUST PROOF
B. OUT DOOR TYPE : SPLASH PROOF
2.FINAL PAINTING COLOR (MUNSELL NO.)
A. IN SIDE : 10B 3/5
B. OUT SIDE : 10B 3/5
3.PAINTING THICKNESS : ABOVE 40 μ
4.APPLICATION VOLTAGE : 220V,380V,440V,460V,480V
5. BOX INSIDE CONTROL CABLE : 2.5sq KIV. HIV
6. 외함 기밀 구조는 다음과 같다.
1) 외함 기밀시 충전부분이 차단되도록 한다.
2) 외함 기밀 후 충전되어있는 부분은 IP2X 이상의
적합 접촉 방호가 되어있을것.

DL 1TON

PROJECT

QTY

SHEET NO

DRAWN

CHK

APP

극동호이스트 주식회사
KUK DONG HOIST CO., LTD.

HOIST CONTROL BOX
LAY OUT DRAWING

KDC1EB001

극동호이스트

제한하중

1000K

380

580

170

1

2

IN DOOR

OUT DOOR

SPONGE

SPONGE

20

20

25

NOTE

1.PROTECTION DEGREE ;
A. INDOOR TYPE : DUST PROOF
B. OUT DOOR TYPE : SPLASH PROOF
2.FINAL PAINTING COLOR (MUNSELL NO.)
A. IN SIDE : 10B 3/5
B. OUT SIDE : 10B 3/5
3.PAINTING THICKNESS : ABOVE 40 μ
4.APPLICATION VOLTAGE : 220V,380V,440V,460V,480V
5. BOX INSIDE CONTROL CABLE : 2.5sq KIV. HIV
6. 외함 기밀 구조는 다음과 같다.
1) 외함 기밀시 충전부분이 차단되도록 한다.
2) 외함 기밀 후 충전되어있는 부분은 IP2X 이상의
적합 접촉 방호가 되어있을것.

DL 1TON

PROJECT

QTY

SHEET NO

DRAWN

CHK

APP

극동호이스트 주식회사
KUK DONG HOIST CO., LTD.

HOIST CONTROL BOX
LAY OUT DRAWING


KDC1EB001

안전보건공단

Korea Occupational Safety & Health Agency

192.168.11.174 / 2014-07-10 09:35:55

1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
POWER CIRCUIT																			
TRAVELLING POWER SUPPLY SYSTEM																			
ADR'S NO.																			A1



- 1. --- MARKED OWNER SCOPE
- 2. EARTH : 제 3종접지 공사(400V 미만전압 : 100 OHM 이하)
제 3종접지 공사(400V 이상전압 : 10 OHM 이하)

1. 전선의 색상은 다음과 같다.
- 1) 흑색 : 전원선
 - 2) 적색 : 교류제어선
 - 3) 청색 : 교류제어선
 - 4) 녹색 또는 녹색과 황색 혼용 : 접지
 - 5) 흰색 : 중립
3. 조작 버튼의 색상은 다음과 같다.
- 1) 적색 : 비상
 - 2) 황색 : 비정상
 - 3) 청색 : 외부
2. 표시등의 색상은 다음과 같다.
- 1) 적색 : 비상
 - 2) 황색 : 비정상
 - 3) 녹색 : 정상
 - 4) 청색 : 외부
 - 5) 흰색 : 중립

SELECTION	VOLTAGE	1	1	1	1	1	1	1	1
	220V	1A	2A	33AF/20AT					
	380V	1A	2A	33AF/10AT					
	480V	1A	2A	33AF/10AT					
	50V	1A	2A	33AF/10AT					
	480V	1A	2A	33AF/10AT					

산업재해예방
안전보건공단
KOREA OCCUPATIONAL SAFETY & HEALTH AGENCY

△																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																				
---	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--

KDC
극동호이스트 주식회사
KUK DONG HOIST CO., LTD.

1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
																			ADR'S NO.

NO	SYMBOL	DESCRIPTION	SPECIFICATION	Q'TY	REMARK
1	MCCB100	NO FUSE BREAKER	33AF/20AT	1	HOISTING
2	M101,102	MAG. CONTACTOR	DMC22C	2	HOISTING
3	M111,112	MAG. CONTACTOR	DMC22C	2	CREEP HOIST
4	M301,302	MAG. CONTACTOR	DMC22C	2	TRAVERSING
5	EOCR100	ELECTRONIC OVER CURRENT RELAY	SS-30	1	HOISTING
6	EOCR110	ELECTRONIC OVER CURRENT RELAY	SS-05	1	CREEP HOIST
7	EOCR300	ELECTRONIC OVER CURRENT RELAY	SS-05	1	TRAVERSING
8	RF100	SILICON RECTIFIER	SR-30	1	HOISTING
9	RF110	SILICON RECTIFIER	SR-30	1	CREEP HOIST
10	RF300	SILICON RECTIFIER	SR-30	1	TRAVERSING
11	TR1	TRANSFORMER	220V/110V,120V 60VA	1	
12	F11,12,(13)	FUSE	1A, (2A)	2(1)	
13		TERMINAL BLOCK	35A,15A	1	
14		EARTH TERMINAL	3tx20x50	1	

NOTE

- 전선의 색상은 다음과 같다.
1) 흑색 : 교류 및 직류전원선
2) 적색 : 교류제어선
3) 파랑색 : 외부전원에서 공급되는 운동장치 제어회로
4) 녹색 또는 노색과 황색 혼용 : 접지선
- CABLE MATERIAL : KIV OR EQUIVALENT
MIN SIZE : 2.5sq
- 제어용 전선 : 2.5mm KIV,HIV
- 제어시 다소 변경 될수있음.
- 외함 개방구조는 다음과 같음.
1) 외함 개방시 용전부분이 차단되도록 함.
2) 외함 개방후 용전되어있는 부분은 IP2X 이상의 위험 접촉 보호가 되어있음.

NOTE

- UPPER LIMIT S-1,LS-2의 전동 작동 전류 용량 AC 600V,75A
- POWER SOURCE : AC 3 ϕ 220V 60Hz
- EARTH TERMINAL RESISTANCE 0.018 Ω

380

580

사

안전보건공단

KOSHA

KDC01BA21

HOIST CONTROL BOX

ARRANGEMENT DRAWING

REVISIONS

CHK.

APP.

CUSTOMER

DRAWING TITLE

KUK DONG HOIST CO., LTD.

DRAWING

DESIGN

CHECKED

APPROVED


SCALE

DATE

ORDER NO.

DWG. NO


KDC01BA21




SPECIFICATION SYMBOLS		HOISTING POWER		HOISTING MOTOR		DC MAG. BRAKE		NO FUSE BREAKER		TRANSFORMER		FUSE		MAGNET CONTACTOR		UPPER LIMIT		ELECTRIC OVER CURRENT RELAY		SILICON RECTIFIER		LOAD LIMITER		CABLE	
DESCRIPTION		HOIST		IM 11		DB10		MCCB100		TR 1		F11,F12 F13		M101,M102 M111,M112		LS-I, LS-II		EOCR100		RF100		LOAD LIMITER		C20-01	
		1TON AC3PH 220V 60Hz		2.2kW/4P		DC 100V		DBE-33AF /20A		220V/100V/120V/60VA		1A 2A		DOC-22P DOC-22P		AC 600V 75A		SS-30		SR-30		JDL-100		VFCT 4.0sqx4c	
SELECTION MAKER				KUKDONG				DEARYUK		SHINHAN		-		DEARYUK		KUK DONG		ASAN		JUNGHO		DONGIL			
						CUSTOMER								DRAWING		CHECKED		APPROVED		SCALE		DATE		ORDER NO.	
						DRAWING TITLE		CREEP HOISTING POWER & CONTROL												NONE					
DATE		REVISIONS		CHK. APP.										CIRCUIT DIAGRAM				DWG. NO						KDC01E22	
																국동호이스트 주식회사									
																KUK DONG HOIST CO., LTD.									



1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
POWER CIRCUIT										CREEP HOIST MOTION									
HOISTING MOTION										CREEP HOIST MOTION									
C20-01										B1									



SPECIFICATION SYMBOLS		HOISTING POWER		HOISTING MOTOR		DC MAG. BRAKE		NO. FUSE BREAKER		TRANSFORMER		FUSE		MAGNET CONTACTOR		UPPER LIMIT		ELECTRIC OVER CURRENT RELAY		SILICON RECTIFIER		LOAD LIMITER		CABLE	
DESCRIPTION		HOIST		IM 11		DB10		MCCB100		TR 1		F11, F12 F13		M101, M102 M111, M112		LS-I, LS-II		EOCR100		RF100		RF110		C20-01	
		1TON AC 3PH 380V 60Hz		2.4KW 4P 0.4KWx4P		AC 100V		DBE-33AF/10A		380V/110V, 120V, 130V, 140V, 150V, 160V		1A 2A		DOC-22P DOC-22P		AC 600V 75A		SS-30		SS-05		SR-30		JDL-100 VFCT 4.0sqx4c	
SELECTION MAKER				KUKDONG				DEARYUK		SHINHAN		-		DEARYUK		KUKDONG				ASAN		JUNGHO		DONGIL	
						CUSTOMER																			
						DRAWING TITLE		CREEP HOISTING POWER CONTROL CIRCUIT																	
						CHK. APP.		DIAGRAM																	
REVISIONS								DWG. NO																	
DATE								KDC01E32																	

[illegible]

192, 168, 11, 174 / 2014-07-10 09:38:55


KDC01E43-DL

[illegible]

KDC01E53-DL

1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
																			ADR'S NO.

380



NOTE

1. UPPER LIMIT LS-1LS-2의 설정·회전·전류 용량 : AC-60A, 75A
2. POWER SOURCE : AC 3φ/480V 60Hz
3. EARTH TERMINAL RESISTANCE 0.018Ω

NO	SYMBOL	DESCRIPTION	SPECIFICATION	Q'TY	REMARK
1	MCCB100	NO FUSE BREAKER	33AF/10AT	1	HOISTING
2	M101,102	MAG. CONTACTOR	DMC22C	2	HOISTING
3	M111,112	MAG. CONTACTOR	DMC22C	2	CREEP HOIST
4	M301,302	MAG. CONTACTOR	DMC22C	2	TRAVERSING
5	EOCR100	ELECTRONIC OVER CURRENT RELAY	SS-30	1	HOISTING
6	EOCR110	ELECTRONIC OVER CURRENT RELAY	SS-05	1	CREEP HOIST
7	EOCR300	ELECTRONIC OVER CURRENT RELAY	SS-05	1	TRAVERSING
8	RF100	SILICON RECTIFIER	SR-30	1	HOISTING
9	RF110	SILICON RECTIFIER	SR-30	1	CREEP HOIST
10	RF300	SILICON RECTIFIER	SR-30	1	TRAVERSING
11	TR1	TRANSFORMER	480V/110V, 120V 60VA	1	
12	F11,12,(13)	FUSE	1A, (2A)	2(1)	
13		TERMINAL BLOCK	35A, 15A	1	
14		EARTH TERMINAL	3tx20x50	1	

NOTE



1. 전선의 색상은 다음과 같다.
1) 흑색 : 전선선
2) 적색 : 고압제어선
3) 파랑색 : 외부 전선에서 공급되는 전동장치 제어회로
4) 녹색 또는 노색과 노랑 혼용 : 접지선
2. CABLE MATERIAL : KIV OR EQUIVALENT
MIN SIZE : 2.5sq
3. 제어용 전선 : 2.5mm KIV,HIV
4. 제어시 다소 변경 필요함.
5. 외함 개방후 용접부본이 차단되도록 함.
- 1) 외함 개방후 용접부본이 차단되도록 함.
- 2) 외함 개방후 용접부본이 차단되도록 함.

DRAWING	DESIGN	CHECKED	APPROVED	SCALE	DATE	ORDER NO.
				NONE		
국동호이스트 주식회사 KUK DONG HOIST CO., LTD.						KDC01BA61
HOIST CONTROL BOX						
ARRANGEMENT DRAWING						
CUSTOMER						
DRAWING TITLE						
REVISIONS	CHK.	APP.				
MK	DATE					



안전보건공단
Korea Occupational Safety & Health Agency


192.168.11.174 / 2014-07-10 09:38:55




NO.	DESCRIPTION	MTL	SUB QTY	TOTAL QTY	SUB WEIGHT(Kg)	TOTAL WEIGHT(Kg)	REMARKS.
2	국판	SS400	1				
1	T/S BOX	PUR	1				
10	EARTH BUS BAR	PUR	1				
9	DUCT	PUR	1				
8	TERMINAL BLOCK	PUR	1				
7	INVERTER	PUR	1				
6	TR	PUR	1				
5	RELAY & SCOKET	PUR	1				
4	RF	PUR	1				
3	MC	PUR	1				
2	MCCB	PUR	1				

PROJECT	DATE	DIM
		mm
TITLE	SCALE	PROJECTION
T/S CONTROL PANEL(INVERTER)	A3/3	3rd
DRAWN	DESIGNED	CHECKED
APPROVED	REF. DRAWING	
KID		
국동호이스트 주식회사 KUK DONG HOIST CO., LTD.		
SHEET No.		DWG No.
		KD1E1001

[illegible]


[illegible]



*|P : 55 이상

NO	SYMBOL	TYPE	SPEC.	COLOR
1	E.B.S	PUSH LOCK TURN RESET TYPE	250VAC x 6A	RED
2	SPARE			
3	상	PUSH BUTTON(2STEP)		BLACK
4	하	PUSH BUTTON(2STEP)		
5	동(전)	PUSH BUTTON		
6	서(후)	PUSH BUTTON		
7	보조 와이어	ø 2.0		


	A		CUSTOMER	DRAWING TITLE	PENDANT PUSH BUTTON SWITCH LAY OUT	DWG. NO.	APPROVED	SCALE	DATE
	A								
	A								
MK	DATE	REVISIONS	CHK.	APP.		KUK DONG HOIST CO., LTD. 			



- * MATERIAL : POLYCARBONATE(PLASTIC)
* BODY COLOR : YELLOW, BLACK
* IP : 55 이상

NO	SYMBOL	TYPE	SPEC.	COLOR
1	E.B.S	PUSH LOCK TURN RESET TYPE	250VAC x 6A	RED
2	SPARE			
3	상	PUSH BUTTON(2STEP)		BLACK
4	하	PUSH BUTTON(2STEP)		
5	동(전)	PUSH BUTTON(2STEP)		
6	서(후)	PUSH BUTTON(2STEP)		
7	보조 와이어	ø 2.0		

☒		CUSTOMER	DRAWING TITLE	PENDANT PUSH BUTTON SWITCH LAY OUT	DWG. NO.	DATE
☒						
☒						
☒						
MK	DATE	REVISIONS	CHK.	APP.	KUK DONG HOIST CO., LTD.	



색상	구분	조작버튼	표시등
적색	비상	비상	비상
황색	비정상	비정상	비정상
녹색	정상	정상	정상
청색	의무	의무	의무
흰색, 회색 - 흑색	지정된의미없음		기타

* MATERIAL : POLYCARBONATE (PLASTIC)
 * BODY COLOR : YELLOW, BLACK
 * IP : 55 이상


NO	SYMBOL	TYPE	SPEC.	COLOR
1	E.B.S	PUSH LOCK TURN RESET TYPE	250VAC x 6A	RED
2	SPARE			
3	상	PUSH BUTTON (2STEP)		
4	하	PUSH BUTTON (2STEP)		
5	동 (좌)	PUSH BUTTON		
6	서 (우)	PUSH BUTTON		
7	남 (전)	PUSH BUTTON		
8	북 (후)	PUSH BUTTON		
9	보조 WIRE	φ 2.0		BLACK

A																
A																
A																
MK	DATE	REVISIONS	CHK.	APP.	CUSTOMER	DRAWING TITLE		PENDANT PUSH BUTTON SWITCH		DRAWING	DESIGN	CHECKED	APPROVED	SCALE	DATE	
										LAY OUT						
										KUK DONG HOIST CO., LTD.					DWG. NO	

안전보건공단

안전보건공단

KOREA OCCUPATIONAL SAFETY & HEALTH AGENCY



색상	구분	조작버튼	표시등
적색		비상	비상
황색		비정상	비정상
녹색		정상	정상
청색		의무	의무
흰색, 회색 - 흑색 지정된의미없음			기타


- * MATERIAL : POLYCARBOBATE(PLASTIC)
- * BODY COLOR : YELLOW, BLACK
- * IP : 55 이상

NO	SYMBOL	TYPE	SPEC.	COLOR
1	E.B.S	PUSH LOCK TURN RESET TYPE	250VAC x 6A	RED
2	SPARE			
3	상	PUSH BUTTON(2STEP)		BLACK
4	하	PUSH BUTTON(2STEP)		
5	동 (좌)	PUSH BUTTON(2STEP)		
6	서 (우)	PUSH BUTTON(2STEP)		
7	남 (전)	PUSH BUTTON		
8	북 (후)	PUSH BUTTON		
9	보조 WIRE	φ 2.0		

△	CUSTOMER	DRAWING	TITLE	CHK.	APP.	REVISIONS	DATE	DRAWING	DESIGN	CHECKED	APPROVED	SCALE	DATE
								PENDANT PUSH BUTTON SWITCH LAY OUT					
△													
△													
MK													

IV. 참 고 도 서

- 1 LOAD LIMITER 권고 SETTING 치
- 2 E.O.C.R 권고 SETTING치
- 3 MOTOR DATA SHEET
- 4 WIRE ROPE 성적서
- 5 SUB VENDOR LIST
- 6 HOIST 취급설명서
- 7 과부하 방지장치 취급설명서
- 8 INVERTER 취급설명서



LOAD LIMITER 권고 SETTING치

* POWER SOURCE : AC 3Φ 220V 60Hz

국동호이스트(주)

POST	MOTOR 용량	LOAD LIMITER 권고 SETTING치			LOAD CURRENT		C.T MODEL	연결단자 NO	C.T 용량	REMARK
		LOAD CURRENT	ADJ START TIME	SHOCK TIME	100%	110%				
C1 ON	2.4KW x 4P	110%	1 SEC	1 SEC	10 A	11.2 A	CT-2	K-K1, L-L1	5 V.A	
	0.4KW x 4P	110%	1 SEC	1 SEC	2.7 A	3.1 A	CT-1	K-K1, L-L1	5 V.A	
C2 2TON	3.7KW x 4P	110%	1 SEC	1 SEC	16.0 A	17.4 A	CT-2	K-K1, L-L1	5 V.A	
	0.4KW x 4P	110%	1 SEC	1 SEC	2.7 A	3.1 A	CT-1	K-K1, L-L1	5 V.A	
C2.5 TON	5.0KW x 4P	110%	1 SEC	1 SEC	22.8 A	24.2 A	CT-2	K-K1, L-L1	5 V.A	
	1.5KW x 4P	110%	1 SEC	1 SEC	7.3 A	8.3 A	CT-1	K-K1, L-L1	5 V.A	
C3 3TON	5.5KW x 4P	110%	1 SEC	1 SEC	22.8 A	24.3 A	CT-2	K-K1, L-L1	5 V.A	
	1.5KW x 4P	110%	1 SEC	1 SEC	7.3 A	8.3 A	CT-1	K-K1, L-L1	5 V.A	
C3.5 TON	5.5KW x 6P	110%	1 SEC	1 SEC	28.2 A	30.1 A	CT-2	K-K1, L-L1	5 V.A	
	1.0KW x 6P	110%	1 SEC	1 SEC	6.7 A	8.1 A	CT-1	K-K1, L-L1	5 V.A	
C7.5 T	5.5KW x 6P	110%	1 SEC	1 SEC	28.2 A	30.1 A	CT-2	K-K1, L-L1	5 V.A	
	1.0KW x 6P	110%	1 SEC	1 SEC	6.7 A	8.1 A	CT-1	K-K1, L-L1	5 V.A	
C	W x P x P 110%	110%	1 SEC	1 SEC	45.0 A	49.1 A	CT-2	K-K1, L-L1	5 V.A	
	1.1KW x P	110%	1 SEC	1 SEC	8.0 A	9.6 A	CT-2	K-K1, L-L1	5 V.A	

NOTE

1. 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능하다.

LOAD LIMITER 권고 SETTING치

* POWER SOURCE : AC 3 ϕ 380V 60Hz

극동하이스트(주)

HUIST C.T. TON	MOTOR 용량	LOAD LIMITER 권고 SETTING치			LOAD CURRENT		연결단자 NO	C.T MODEL	C.T 용량	REMARK
		LOAD CURRENT	ADJ START TIME	SHOCK TIME	100%	110%				
C1.5 TON	2.4KW x 4P	110%	1 SEC	1 SEC	5.8 A	6.3 A	K-K1, L-L1	CT-2	5 V.A	
	0.4KW x 4P	110%	1 SEC	1 SEC	1.6 A	2.1 A	K-K1, L-L1	CT-1	5 V.A	
	3.7KW x 4P	110%	1 SEC	1 SEC	9.3 A	11.3 A	K-K1, L-L1	CT-2	5 V.A	
C2.5 TON	0.4KW x 4P	110%	1 SEC	1 SEC	1.6 A	2.1 A	K-K1, L-L1	CT-1	5 V.A	
	5.0KW x 4P	110%	1 SEC	1 SEC	12.2 A	13.6 A	K-K1, L-L1	CT-2	5 V.A	
	1.5KW x 4P	110%	1 SEC	1 SEC	4.2 A	5.4 A	K-K1, L-L1	CT-1	5 V.A	
C3.5 TON	5.5KW x 4P	110%	1 SEC	1 SEC	12.2 A	13.6 A	K-K1, L-L1	CT-2	5 V.A	
	1.5KW x 4P	110%	1 SEC	1 SEC	4.2 A	5.4 A	K-K1, L-L1	CT-1	5 V.A	
	5.5KW x 6P	110%	1 SEC	1 SEC	16.3 A	17.8 A	K-K1, L-L1	CT-2	5 V.A	
C7.5 TON	1.0KW x 6P	110%	1 SEC	1 SEC	3.9 A	5.3 A	K-K1, L-L1	CT-1	5 V.A	
	5.5KW x 6P	110%	1 SEC	1 SEC	16.3 A	17.8 A	K-K1, L-L1	CT-2	5 V.A	
	9.0KW x 6P	110%	1 SEC	1 SEC	3.9 A	5.3 A	K-K1, L-L1	CT-1	5 V.A	
C10 TON	9.0KW x 6P	110%	1 SEC	1 SEC	26.0 A	28.6 A	K-K1, L-L1	CT-2	5 V.A	
	1.1KW x 6P	110%	1 SEC	1 SEC	4.6 A	6.1 A	K-K1, L-L1	CT-2	5 V.A	

NOTE

1. 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

LOAD LIMITER 권고 SETTING치

* POWER SOURCE : AC 3Φ 440V 60Hz

극동하이스트(주)

F.CIST	MOTOR 용량	LOAD LIMITER 권고 SETTING치			LOAD CURRENT		C.T MODEL	연결단자 NO	C.T 용량	REMARK
		LOAD CURRENT	ADJ START TIME	SHOCK TIME	100%	110%				
C1 TON	2.4KW x 4P	110%	1 SEC	1 SEC	5.0 A	7.3 A	CT-2	K-K1, L-L1	5 V.A	
	0.4KW x 4P	110%	1 SEC	1 SEC	1.4 A	1.8 A	CT-1	K-K1, L-L1	5 V.A	
C2 TON	3.7KW x 4P	110%	1 SEC	1 SEC	8.0 A	10.8 A	CT-2	K-K1, L-L1	5 V.A	
	0.4KW x 4P	110%	1 SEC	1 SEC	1.4 A	1.8 A	CT-1	K-K1, L-L1	5 V.A	
C3 TON	5.0KW x 4P	110%	1 SEC	1 SEC	10.5 A	13.7 A	CT-2	K-K1, L-L1	5 V.A	
	1.5KW x 4P	110%	1 SEC	1 SEC	3.7 A	4.3 A	CT-1	K-K1, L-L1	5 V.A	
C4 TON	5.5KW x 4P	110%	1 SEC	1 SEC	10.5 A	13.7 A	CT-2	K-K1, L-L1	5 V.A	
	1.5KW x 4P	110%	1 SEC	1 SEC	3.7 A	4.3 A	CT-1	K-K1, L-L1	5 V.A	
C5 TON	5.5KW x 6P	110%	1 SEC	1 SEC	14.1 A	18.5 A	CT-2	K-K1, L-L1	5 V.A	
	1.0KW x 6P	110%	1 SEC	1 SEC	3.3 A	4.7 A	CT-1	K-K1, L-L1	5 V.A	
C7.5 TON	5.5KW x 6P	110%	1 SEC	1 SEC	14.1 A	18.5 A	CT-2	K-K1, L-L1	5 V.A	
	1.0KW x 6P	110%	1 SEC	1 SEC	3.3 A	4.7 A	CT-1	K-K1, L-L1	5 V.A	
C10 TON	5.5KW x 6P	110%	1 SEC	1 SEC	22.5 A	24.8 A	CT-2	K-K1, L-L1	5 V.A	
	1.1KW x 6P	10%	1 SEC	1 SEC	4.0 A	5.4 A	CT-1	K-K1, L-L1	5 V.A	

NOTE

1. 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

LOAD LIMITER 권고 SETTING치

* POWER SOURCE : AC 3Φ 460V 60Hz

극동호이스트(주)

HOIST	MOTOR 용량	LOAD LIMITER 권고 SETTING치			LOAD CURRENT		C.T MODEL	연결단자 NO	C.T 용량	REMARK
		LOAD CURRENT	ADJ START TIME	SHOCK TIME	100%	110%				
C1 TON	2.4KW x 4P	110%	1 SEC	1 SEC	4.8 A	5.2 A	CT-2	K-K1, L-L1	5 V.A	
	0.4KW x 4P	110%	1 SEC	1 SEC	1.3 A	1.5 A	CT-1	K-K1, L-L1	5 V.A	
C2 TON	3.7KW x 4P	110%	1 SEC	1 SEC	7.7 A	8.5 A	CT-2	K-K1, L-L1	5 V.A	
	0.4KW x 4P	110%	1 SEC	1 SEC	1.3 A	1.5 A	CT-1	K-K1, L-L1	5 V.A	
C2.5 TON	5.0KW x 4P	110%	1 SEC	1 SEC	10.0 A	11.5 A	CT-2	K-K1, L-L1	5 V.A	
	1.5KW x 4P	110%	1 SEC	1 SEC	3.5 A	4.3 A	CT-1	K-K1, L-L1	5 V.A	
C3 TON	5.5KW x 4P	110%	1 SEC	1 SEC	10.0 A	11.5 A	CT-2	K-K1, L-L1	5 V.A	
	1.5KW x 4P	110%	1 SEC	1 SEC	3.5 A	4.3 A	CT-1	K-K1, L-L1	5 V.A	
C3.5 TON	5.5KW x 6P	110%	1 SEC	1 SEC	13.5 A	14.7 A	CT-2	K-K1, L-L1	5 V.A	
	1.0KW x 6P	110%	1 SEC	1 SEC	3.2 A	3.6 A	CT-1	K-K1, L-L1	5 V.A	
C7 TON	5.5KW x 6P	110%	1 SEC	1 SEC	13.5 A	14.7 A	CT-2	K-K1, L-L1	5 V.A	
	1.0KW x 6P	110%	1 SEC	1 SEC	3.2 A	3.6 A	CT-1	K-K1, L-L1	5 V.A	
C10 TON	9.0KW x 6P	110%	1 SEC	1 SEC	21.5 A	23.7 A	CT-2	K-K1, L-L1	5 V.A	
	1.1KW x 8P	110%	1 SEC	1 SEC	4.0 A	5.4 A	CT-1	K-K1, L-L1	5 V.A	

NOTE

1. 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

LOAD LIMITER 권고 SETTING치

* POWER SOURCE : AC 3ϕ 480V 60Hz

극동하이스트(주)

H.CIST C1 TON	MOTOR 용량	LOAD LIMITER 권고 SETTING치			LOAD CURRENT		C.T MODEL	연결단자 NO	C.T 용량	REMARK
		LOAD CURRENT	ADJ START TIME	SHOCK TIME	100%	110%				
C1 TON	2.4KW x 4P	110%	1 SEC	1 SEC	4.6 A	5.0 A	CT-2	K-K1, L-L1	5 V.A	
	0.4KW x 4P	110%	1 SEC	1 SEC	1.2 A	1.35 A	CT-1	K-K1, L-L1	5 V.A	
	3.7KW x 4P	110%	1 SEC	1 SEC	7.3 A	8.2 A	CT-2	K-K1, L-L1	5 V.A	
	0.4KW x 4P	110%	1 SEC	1 SEC	1.2 A	1.35 A	CT-1	K-K1, L-L1	5 V.A	
C2 2 TON	5.0KW x 4P	110%	1 SEC	1 SEC	9.6 A	11.2 A	CT-2	K-K1, L-L1	5 V.A	
	1.5KW x 4P	110%	1 SEC	1 SEC	3.4 A	4.3 A	CT-1	K-K1, L-L1	5 V.A	
	5.5KW x 4P	110%	1 SEC	1 SEC	9.6 A	11.2 A	CT-2	K-K1, L-L1	5 V.A	
C3 1 TON	1.5KW x 4P	110%	1 SEC	1 SEC	3.4 A	4.3 A	CT-1	K-K1, L-L1	5 V.A	
	5.5KW x 6P	110%	1 SEC	1 SEC	12.9 A	14.2 A	CT-2	K-K1, L-L1	5 V.A	
	1.0KW x 6P	110%	1 SEC	1 SEC	3.1 A	3.5 A	CT-1	K-K1, L-L1	5 V.A	
C7.5 TON	5.5KW x 6P	110%	1 SEC	1 SEC	12.9 A	14.2 A	CT-2	K-K1, L-L1	5 V.A	
	1.1KW x 6P	110%	1 SEC	1 SEC	3.1 A	3.5 A	CT-1	K-K1, L-L1	5 V.A	
C10 1 TON	5.5KW x 6P	110%	1 SEC	1 SEC	20.6 A	22.7 A	CT-2	K-K1, L-L1	5 V.A	
	1.1KW x 6P	110%	1 SEC	1 SEC	4.0 A	5.4 A	CT-1	K-K1, L-L1	5 V.A	

NOTE

1. 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

E.O.C.R 권고 SETTING치

* POWER SOURCE : AC 3Φ 220V 60Hz

국동호이스트(주)

HOIST	MOTOR 용량	MOTOR 정격 전류	DRIVE TYPE	E.O.C.R TYPE	권고 SETTING 치			REMARK
					DELAY TIME	OPERATION TIME	CURRENT	
C1 TON	2.4KW x 4P	10.0 A	1 DRAVE	SS-30	3 SEC	1 SEC	10.0 A	
	0.4KW x 4P	2.7 A	1 DRAVE	SS-05	3 SEC	1 SEC	2.7 A	
	3.7KW x 4P	16.0 A	1 DRAVE	SS-30	3 SEC	1 SEC	16.0 A	
	0.4KW x 4P	2.7 A	1 DRAVE	SS-05	3 SEC	1 SEC	2.7 A	
C2.8 TON	5.0KW x 4P	22.8 A	1 DRAVE	SS-30	3 SEC	1 SEC	22.8 A	
	1.5KW x 4P	7.3 A	1 DRAVE	SS-30	3 SEC	1 SEC	7.3 A	
	5.5KW x 4P	22.8 A	1 DRAVE	SS-30	3 SEC	1 SEC	22.8 A	
	1.5KW x 4P	7.3 A	1 DRAVE	SS-30	3 SEC	1 SEC	7.3 A	
C3 TON	5.5KW x 6P	28.2 A	1 DRAVE	SS-30	3 SEC	1 SEC	28.2 A	
	1.0KW x 6P	6.7 A	1 DRAVE	SS-30	3 SEC	1 SEC	6.7 A	
	5.5KW x 6P	28.2 A	1 DRAVE	SS-30	3 SEC	1 SEC	28.2 A	
	1.0KW x 6P	6.7 A	1 DRAVE	SS-30	3 SEC	1 SEC	6.7 A	
C4.5 TON	9.0KW x 8P	45.0 A	1 DRAVE	SS-60	3 SEC	1 SEC	45.0 A	
	1.1KW x 3P	8.0 A	1 DRAVE	SS-30	3 SEC	1 SEC	8.0 A	

NOTE

1. 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

E.O.C.R 권고 SETTING치

극동하이스트(주)

* POWER SOURCE : AC 3Φ 380V 60Hz

LIFT	MOTOR 용량	1 정격 전류	DRIVE TYPE	E.O.C.R TYPE	권고 SETTING 치			REMARK
					DELAY TIME	OPERATION TIME	CURRENT	
C1 TON	2.4KW x 4P	5.8 A	1 DRAVE	SS-30	3 SEC	1 SEC	5.8 A	
	0.4KW x 4P	1.6 A	1 DRAVE	SS-05	3 SEC	1 SEC	1.6 A%	
	3.7KW x 4P	9.3 A	1 DRAVE	SS-30	3 SEC	1 SEC	9.3 A	
C2 TON	0.4KW x 4P	1.6 A	1 DRAVE	SS-05	3 SEC	1 SEC	1.6 A	
	5.0KW x 4P	12.2 A	1 DRAVE	SS-30	3 SEC	1 SEC	12.2 A	
C2.8 TON	1.5KW x 4P	4.2 A	1 DRAVE	SS-05	3 SEC	1 SEC	4.2 A	
	5.5KW x 4P	12.2 A	1 DRAVE	SS-30	3 SEC	1 SEC	12.2 A	
C3 TON	1.5KW x 4P	4.2 A	1 DRAVE	SS-05	3 SEC	1 SEC	4.2 A	
	5.5KW x 4P	12.2 A	1 DRAVE	SS-30	3 SEC	1 SEC	12.2 A	
C5 TON	5.5KW x 6P	16.3 A	1 DRAVE	SS-30	3 SEC	1 SEC	16.3 A	
	1.0KW x 6P	3.9 A	1 DRAVE	SS-05	3 SEC	1 SEC	3.9 A	
C7.5 TON	5.5KW x 6P	16.3 A	1 DRAVE	SS-30	3 SEC	1 SEC	16.3 A	
	1.0KW x 6P	3.9 A	1 DRAVE	SS-05	3 SEC	1 SEC	3.9 A	
C10 TON	9.0KW x 8P	20.0 A	1 DRAVE	SS-30	3 SEC	1 SEC	20.0 A	
	1.1KW x 8P	4.6 A	1 DRAVE	SS-05	3 SEC	1 SEC	4.6 A	

NOTE

1. 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

E.O.C.R 권고 SETTING치

* POWER SOURCE : AC 3Φ 440V 60HZ

극동호이스트(주)

	MOTOR 용량	MOTOR 정격 전류	DRIVE TYPE	E.O.C.R TYPE	권고 SETTING 치			REMARK
					DELAY TIME	OPERATION TIME	CURRENT	
C7.5 TON	2.4KW x 4P	5.0 A	1 DRAVE	SS-30	3 SEC	1 SEC	5.0 A	
	0.4KW x 4P	1.4 A	1 DRAVE	SS-05	3 SEC	1 SEC	1.4 A	
	3.7KW x 4P	8.0 A	1 DRAVE	SS-30	3 SEC	1 SEC	8.0 A	
C11 TON	0.4KW x 4P	1.4 A	1 DRAVE	SS-05	3 SEC	1 SEC	1.4 A	
	5.0KW x 4P	10.5 A	1 DRAVE	SS-30	3 SEC	1 SEC	10.5 A	
	1.5KW x 4P	3.7 A	1 DRAVE	SS-05	3 SEC	1 SEC	3.7 A	
C15 TON	5.5KW x 4P	10.5 A	1 DRAVE	SS-30	3 SEC	1 SEC	10.5 A	
	1.5KW x 4P	3.7 A	1 DRAVE	SS-05	3 SEC	1 SEC	3.7 A	
	5.5KW x 6P	14.1 A	1 DRAVE	SS-30	3 SEC	1 SEC	14.1 A	
C20 TON	1.0KW x 6P	3.3 A	1 DRAVE	SS-05	3 SEC	1 SEC	3.3 A	
	5.5KW x 6P	14.1 A	1 DRAVE	SS-30	3 SEC	1 SEC	14.1 A	
	1.0KW x 6P	2.2 A	1 DRAVE	SS-05	3 SEC	1 SEC	2.2 A	
C25 TON	3.0KW x 8P	22.5 A	1 DRAVE	SS-30	3 SEC	1 SEC	22.5 A	
	1.1KW x 8P	4.0 A	1 DRAVE	SS-05	3 SEC	1 SEC	4.0 A	

NOTE

1. 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

E.O.C.R 권고 SETTING치

국동호이스트(주)

* POWER SOURCE : AC 3Φ 460V 60Hz

HOIST TON	MOTOR 용량	MOTOR 정격 전류	DRIVE TYPE	E.O.C.R TYPE	권고 SETTING 치			REMARK
					DELAY TIME	OPERATION TIME	CURRENT	
1.5 TON	2.4KW x 4P	4.8 A	1 DRAVE	SS-30	3 SEC	1 SEC	4.8 A	
	0.4KW x 4P	1.4 A	1 DRAVE	SS-05	3 SEC	1 SEC	1.4 A	
3.0 TON	3.7KW x 4P	7.7 A	1 DRAVE	SS-30	3 SEC	1 SEC	7.7 A	
	0.4KW x 4P	1.4 A	1 DRAVE	SS-05	3 SEC	1 SEC	1.4 A	
5.0 TON	5.0KW x 4P	10.0 A	1 DRAVE	SS-30	3 SEC	1 SEC	10.0 A	
	1.5KW x 4P	3.5 A	1 DRAVE	SS-05	3 SEC	1 SEC	3.5 A	
7.5 TON	5.5KW x 4P	10.0 A	1 DRAVE	SS-30	3 SEC	1 SEC	10.0 A	
	1.5KW x 4P	3.5 A	1 DRAVE	SS-05	3 SEC	1 SEC	3.5 A	
10.0 TON	5.5KW x 6P	13.5 A	1 DRAVE	SS-30	3 SEC	1 SEC	13.5 A	
	1.0KW x 6P	3.2 A	1 DRAVE	SS-05	3 SEC	1 SEC	3.2 A	
15.0 TON	5.5KW x 6P	16.5 A	1 DRAVE	SS-30	3 SEC	1 SEC	16.5 A	
	1.0KW x 6P	3.2 A	1 DRAVE	SS-05	3 SEC	1 SEC	3.2 A	
20.0 TON	9.0KW x 8P	21.5 A	1 DRAVE	SS-30	3 SEC	1 SEC	21.5 A	
	1.1KW x 8P	4.0 A	1 DRAVE	SS-05	3 SEC	1 SEC	4.0 A	

NOTE

1. 상기 TABLE의 수치는 권고 SETTING치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

E.O.C.R 권고 SETTING치

* POWER SOURCE : AC 3Φ 480V 60Hz

국동호이스트(주)

	MOTOR 용량	MOTOR 정격 전류	DRIVE TYPE	E.O.C.R TYPE	권고 SETTING 치			REMARK
					DELAY TIME	OPERATION TIME	CURRENT	
C1 TON	2.4KW x 4P	4.6 A	1 DRAVE	SS-30	3 SEC	1 SEC	4.6 A	
	0.4KW x 4P	1.4 A	1 DRAVE	SS-05	3 SEC	1 SEC	1.4 A	
	3.7KW x 4P	7.3 A	1 DRAVE	SS-30	3 SEC	1 SEC	7.3 A	
C2 TON	0.4KW x 4P	1.4 A	1 DRAVE	SS-05	3 SEC	1 SEC	1.4 A	
	5.0KW x 4P	9.6 A	1 DRAVE	SS-30	3 SEC	1 SEC	9.6 A	
	1.5KW x 4P	3.4 A	1 DRAVE	SS-05	3 SEC	1 SEC	3.4 A	
C3 TON	5.5KW x 4P	9.6 A	1 DRAVE	SS-30	3 SEC	1 SEC	9.6 A	
	1.5KW x 4P	3.4 A	1 DRAVE	SS-05	3 SEC	1 SEC	3.4 A	
	5.5KW x 6P	12.9 A	1 DRAVE	SS-30	3 SEC	1 SEC	12.9 A	
C5 TON	1.0KW x 6P	12.9 A	1 DRAVE	SS-05	3 SEC	1 SEC	3.1 A	
	5.5KW x 6P	12.9 A	1 DRAVE	SS-30	3 SEC	1 SEC	12.9 A	
	1.0KW x 6P	3.1 A	1 DRAVE	SS-05	3 SEC	1 SEC	3.1 A	
C7.5 TON	3.0KW x 8P	20.6 A	1 DRAVE	SS-30	3 SEC	1 SEC	20.6 A	
	1.1KW x 8P	4.0 A	1 DRAVE	SS-05	3 SEC	1 SEC	4.0 A	


NOTE

1. 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA



1. SERVICE	HOISTING
2. MANUFACTURE	극동호이스트(주)
3. FRAME NUMBER	112 S
4. RATED POWER	2.4 KW x 4 P
5. RATED VOLTAGE AND FREQUENCY	220 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 ℃
10. FULL LOAD SPEED	1692 RPM
11. FULL LOAD CURRENT	10 A
12. STARTING CURRENT AT RATED VOLTAGE	59 A
13. MINIMUM STARTING VOLTAGE	200 V
14. EFFICIENCY AT 100% RATED LOAD	75 %
15. POWER FACTOR AT 100% RATED LOAD	77 %
16. STARTING TORQUE	0.85 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6206zz OPL : 6206zz
20. MOUNTING	H Z O N T A L
21. MAXIMUM AMBIENT TEMPERATURE	
22. BEARING LUBRICATION	G R S E
23. STARTING METHOD	F U L L V O L T A G E



THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA


1. SERVICE	HOISTING
2. MANUFACTURE	극동호이스트(주)
3. FRAME NUMBER	112 S
4. RATED POWER	2.4 KW x 4 P
5. RATED VOLTAGE AND FREQUENCY	380 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 ℃
10. FULL LOAD SPEED	1692 RPM
11. FULL LOAD CURRENT	5.8 A
12. STARTING CURRENT AT RATED VOLTAGE	34.2 A
13. MINIMUM STARTING VOLTAGE	245 V
14. EFFICIENCY AT 100% RATED LOAD	75 %
15. POWER FACTOR AT 100% RATED LOAD	77 %S
16. STARTING TORQUE	288 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	TEN V
19. TYPE OF BEARING	PL : 6206zz OPL : 6206zz
20. MOUNTING	H ZONTAL
21. MAXIMUM AMBIENT TEMPERATURE	40 ℃
22. BEARING LUBRICATION	GF SE
23. STARTING METHOD	FULL VOLTAGE



THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	HOISTING
2. MANUFACTURE	극동호이스트(주)
3. FRAME NUMBER	112 S
4. RATED POWER	2.4 KW x 4 P
5. RATED VOLTAGE AND FREQUENCY	440 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 ℃
10. FULL LOAD SPEED	1692 RPM
11. FULL LOAD CURRENT	5.0 A
12. STARTING CURRENT AT RATED VOLTAGE	29.5 A
13. MINIMUM STARTING VOLTAGE	400 V
14. EFFICIENCY AT 100% RATED LOAD	75 %
15. POWER FACTOR AT 100% RATED LOAD	77 %
16. STARTING TORQUE	2.88 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6206zz OPL : 6206zz
20. MOUNTING	H Z O N T A L
21. MAXIMUM AMBIENT TEMPERATURE	
22. BEARING LUBRICATION	G F S E
23. STARTING METHOD	F U L L V O L T A G E




(KOREA ELECTRICAL SAFETY & HEALTH AGENCY)

THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA


1. SERVICE	HOISTING
2. MANUFACTURE	극동호이스트(주)
3. FRAME NUMBER	112 S
4. RATED POWER	2.4 KW x 4 P
5. RATED VOLTAGE AND FREQUENCY	460 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 ℃
10. FULL LOAD SPEED	1692 RPM
11. FULL LOAD CURRENT	4.8 A
12. STARTING CURRENT AT RATED VOLTAGE	28.3 A
13. MINIMUM STARTING VOLTAGE	418 V
14. EFFICIENCY AT 100% RATED LOAD	75 %
15. POWER FACTOR AT 100% RATED LOAD	77 %
16. STARTING TORQUE	1.88 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6206zz OPL : 6206zz
20. MOUNTING	H O ZONTAL
21. MAXIMUM AMBIENT TEMPURE	40
22. BEARING LUBRICATION	G R S E
23. STARTING METHOD	FULL VOLTAGE



THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	HOISTING
2. MANUFACTURE	극동호이스트(주)
3. FRAME NUMBER	112 S
4. RATED POWER	2.4 KW x 4 P
5. RATED VOLTAGE AND FREQUENCY	480 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 ℃
10. FULL LOAD SPEED	1692 RPM
11. FULL LOAD CURRENT	4.6 A
12. STARTING CURRENT AT RATED VOLTAGE	27.1 A
13. MINIMUM STARTING VOLTAGE	438 V
14. EFFICIENCY AT 100% RATED LOAD	75 %
15. POWER FACTOR AT 100% RATED LOAD	77 %
16. STARTING TORQUE	2.88 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6206zz OPL : 6206zz
20. MOUNTING	H I Z O N T A L
21. MAXIMUM AMBIENT TEMPURE	
22. BEARING LUBRICATION	G I S E
23. STARTING METHOD	F U L L V O L T A G E




안전보건공단
안전보건공단

THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	CREEP HOISTING
2. MANUFACTURE	극동호이스트(주)
3. FRAME NUMBER	80
4. RATED POWER	0.4 KW x 4 P
5. RATED VOLTAGE AND FREQUENCY	220 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 ℃
10. FULL LOAD SPEED	1692 RPM
11. FULL LOAD CURRENT	2.7 A
12. STARTING CURRENT AT RATED VOLTAGE	14.2 A
13. MINIMUM STARTING VOLTAGE	200 V
14. EFFICIENCY AT 100% RATED LOAD	63.5 %
15. POWER FACTOR AT 100% RATED LOAD	61.5 %
16. STARTING TORQUE	0.7 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	TEN V
19. TYPE OF BEARING	PL : 6205zz OPL : 6204zz
20. MOUNTING	H ZONTAL
21. MAXIMUM AMBIENT TEMPERATURE	40 ℃
22. BEARING LUBICATION	GR SE
23. STARTING METHOD	FULL VOLTAGE





12/15/2014 OCCUPATIONAL SAFETY & HEALTH AGENCY

THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	CREEP HOISTING
2. MANUFACTURE	극동호이스트(주)
3. FRAME NUMBER	80
4. RATED POWER	0.4 KW x 4 P
5. RATED VOLTAGE AND FREQUENCY	380 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 ℃
10. FULL LOAD SPEED	1692 RPM
11. FULL LOAD CURRENT	1.6 A
12. STARTING CURRENT AT RATED VOLTAGE	8.3 A
13. MINIMUM STARTING VOLTAGE	345 V
14. EFFICIENCY AT 100% RATED LOAD	63.5 %
15. POWER FACTOR AT 100% RATED LOAD	65.5 %
16. STARTING TORQUE	0.7 KG.M
17. SITE ALTTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	TEN V
19. TYPE OF BEARING	PL : 6205zz OPL : 6204zz
20. MOUNTING	HORIZONTAL
21. MAXIMUM AMBIENT TEMPERATURE	
22. BEARING LUBRICATION	GREASE
23. STARTING METHOD	FULL VOLTAGE




KOREA OCCUPATIONAL SAFETY & HEALTH AGENCY

THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	CREEP HOISTING
2. MANUFACTURE	극동호이스트(주)
3. FRAME NUMBER	80
4. RATED POWER	0.4 KW x 4 P
5. RATED VOLTAGE AND FREQUENCY	440 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 ℃
10. FULL LOAD SPEED	1692 RPM
11. FULL LOAD CURRENT	1.4 A
12. STARTING CURRENT AT RATED VOLTAGE	7.1 A
13. MINIMUM STARTING VOLTAGE	400 V
14. EFFICIENCY AT 100% RATED LOAD	53.5 %
15. POWER FACTOR AT 100% RATED LOAD	61.5 %
16. STARTING TORQUE	0.7 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6205zz OPL : 6204zz
20. MOUNTING	H ZONTAL
21. MAXIMUM AMBIENT TEMPERATURE	40 ℃
22. BEARING OIL LUBRICATION	G R S E
23. STARTING METHOD	FULL VOLTAGE




안전보건공단
안전보건공단

INDUSTRIAL SAFETY & HEALTH AGENCY

THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA


1. SERVICE	CREEP HOISTING
2. MANUFACTURE	극동호이스트(주)
3. FRAME NUMBER	80
4. RATED POWER	0.4 KW x 4 P
5. RATED VOLTAGE AND FREQUENCY	460 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 ℃
10. FULL LOAD SPEED	1692 RPM
11. FULL LOAD CURRENT	1.3 A
12. STARTING CURRENT AT RATED VOLTAGE	6.8 A
13. MINIMUM STARTING VOLTAGE	410 V
14. EFFICIENCY AT 100% RATED LOAD	63.5 %
15. POWER FACTOR AT 100% RATED LOAD	61.5 %
16. STARTING TORQUE	0.7 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	TEN V
19. TYPE OF BEARING	PL : 6205zz OPL : 6204zz
20. MOUNTING	H ZONTAL
21. MAXIMUM AMBIENT TEMPURE	40 ℃
22. BEARING LUBRICATION	GR SE
23. STARTING METHCED	FULL VOLTAGE



THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA


1. SERVICE	CREEP HOISTING
2. MANUFACTURE	극동호이스트(주)
3. FRAME NUMBER	80
4. RATED POWER	0.4 KW x 4 P
5. RATED VOLTAGE AND FREQUENCY	480 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATTING	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 ℃
10. FULL LOAD SPEED	1692 RPM
11. FULL LOAD CURRENT	1.2 A
12. STARTING CURRENT AT RATED VOLTAGE	6.6 A
13. MINIMUM STARTING VOLTAGE	436 V
14. EFFICIENCY AT 100% RATED LOAD	63.5 %
15. POWER FACTOR AT 100% RATED LOAD	61.5 %
16. STARTING TORQUE	0.7 K.G.M
17. SITE ALTTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6205zz OPL : 6204zz
20. MOUNTING	H Z O N T A L
21. MAXIMUM AMBIENT TEMPURE	40
22. BEARING LUBEC/TKN	G R S E
23. STARTING METHOD	F U L L V O L T A G E



THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA


1. SERVICE	TRAVERSING
2. MANUFACTURE	극동호이스트 (주)
3. FRAME NUMBER	90 S
4. RATED POWER	0.75 KW x 4 P
5. RATED VOLTAGE AND FREQUENCY	220 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	1760 RPM
11. FULL LOAD CURRENT	4.1 A
12. LOCKED ROTOR CURRENT	22.1 A
13. MINIMUM STARTING VOLTAGE	200 V
14. EFFICIENCY AT 100% RATED LOAD	66 %
15. POWER FACTOR AT 100% RATED LOAD	73.5 %
16. FULL LOAD TORQUE	1.92 KGM
17. SITE ALTTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	TENV
19. TYPE OF BEARING	PL : 6205zz GFL : 6204zz
20. MOUNTING	HORIZONTAL
21. MAXIMUM AMBIENT TEMPRE	°C
22. BEARING LUBRICATION	GREASE
23. STARTING METHOD	FULL VOLTAGE



THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA


1. SERVICE	TRAVERSING
2. MANUFACTURE	극동호이스트 (주)
3. FRAME NUMBER	90 S
4. RATED POWER	0.75 KW x 4 P
5. RATED VOLTAGE AND FREQUENCY	380 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	1760 RPM
11. FULL LOAD CURRENT	2.4 A
12. LOCKED ROTOR CURRENT	12.8 A
13. MINIMUM STARTING VOLTAGE	345 V
14. EFFICIENCY AT 100% RATED LOAD	86 %
15. POWER FACTOR AT 100% RATED LOAD	73.5 %
16. FULL LOAD TORQUE	1.02 KG M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	TENV
19. TYPE OF BEARING	PL : 6205zz ODE : 6204zz
20. MOUNTING	HORIZONTAL
21. MAXIMUM AMBIENT TEMPURE	°C
22. BEARING LUBRICATION	W.F
23. STARTING METHOD	FULL VOLTAGE



THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA


1. SERVICE	TRAVERSING
2. MANUFACTURE	극동호이스트 (주)
3. FRAME NUMBER	90 S
4. RATED POWER	0.75 KW x 4 P
5. RATED VOLTAGE AND FREQUENCY	440 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATTING	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 ℃
10. FULL LOAD SPEED	1760 RPM
11. FULL LOAD CURRENT	2.0 A
12. LOCKED ROTOR CURRENT	11.1 A
13. MINIMUM STARTING VOLTAGE	400 V
14. EFFICIENCY AT 100% RATED LOAD	66 %
15. POWER FACTOR AT 100% RATED LOAD	73.5 %
16. FULL LOAD TORQUE	1.02 KGM
17. SITE ALTTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	TEN V
19. TYPE OF BEARING	PL : 6205zz GFL : 6204zz
20. MOUNTING	HORIZONTAL
21. MAXIMUM AMBIENT TEMPURE	℃
22. BEARING LUBRICATION	GREASE
23. STARTING METHOD	FULL VOLTAGE



THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA


1. SERVICE	TRAVERSING
2. MANUFACTURE	극동호이스트 (주)
3. FRAME NUMBER	90 S
4. RATED POWER	0.75 KW x 4 P
5. RATED VOLTAGE AND FREQUENCY	460 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATTING	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	1760 RPM
11. FULL LOAD CURRENT	2.0 A
12. LOCKED ROTOR CURRENT	10.6 A
13. MINIMUM STARTING VOLTAGE	418 V
14. EFFICIENCY AT 100% RATED LOAD	66 %
15. POWER FACTOR AT 100% RATED LOAD	73.5 %
16. FULL LOAD TORQUE	1.02 KCM
17. SITE ALTTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	TENV
19. TYPE OF BEARING	PL : 6205zzz CFE : 6204zzz
20. MOUNTING	HORIZONTAL
21. MAXIMUM AMBIENT TEMPURE	°C
22. BEARING LUBRICATION	SAE F
23. STARTING METHOD	FULL VOLTAGE



THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	TRAVERSING
2. MANUFACTURE	극동호이스트 (주)
3. FRAME NUMBER	90 S
4. RATED POWER	0.75 KW x 4 P
5. RATED VOLTAGE AND FREQUENCY	480 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATTING	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 ℃
10. FULL LOAD SPEED	1760 RPM
11. FULL LOAD CURRENT	1.9 A
12. LOCKED ROTOR CURRENT	10.2 A
13. MINIMUM STARTING VOLTAGE	436 V
14. EFFICIENCY AT 100% RATED LOAD	85 %
15. POWER FACTOR AT 100% RATED LOAD	75.5 %
16. FULL LOAD TORQUE	1.02 KG.M
17. SITE ALTTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	TENV
19. TYPE OF BEARING	PL : 6205zz ODE : 6204zz
20. MOUNTING	HORIZONTAL
21. MAXIMUM AMBIENT TEMPURE	℃
22. BEARING LUBRICATION	F
23. STARTING METHOD	FULL VOLTAGE



산업재해예방


안전보건공단

KOREA OCCUPATIONAL SAFETY & HEALTH AGENCY

THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA


1. SERVICE	TRAVERSING
2. MANUFACTURE	극동호이스트 (주)
3. FRAME NUMBER	90 S
4. RATED POWER	0.5 KW x 6 P
5. RATED VOLTAGE AND FREQUENCY	220 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATTING	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 ℃
10. FULL LOAD SPEED	1160 RPM
11. FULL LOAD CURRENT	3.4 A
12. LOCKED ROTOR CURRENT	16.4 A
13. MINIMUM STARTING VOLTAGE	200사 V
14. EFFICIENCY AT 100% RATED LOAD	64 %
15. POWER FACTOR AT 100% RATED LOAD	59.5 %
16. FULL LOAD TORQUE	0.80 KGM
17. SITE ALTTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	TENV
19. TYPE OF BEARING	PL : 6205zz CPE : 6204zz
20. MOUNTING	HORIZONTAL
21. MAXIMUM AMBIENT TEMPURE	℃
22. BEARING LUBRICATION	Grease
23. STARTING METHOD	FULL VOLTAGE



THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA


1. SERVICE	TRAVERSING
2. MANUFACTURE	극동호이스트 (주)
3. FRAME NUMBER	90 S
4. RATED POWER	0.5 KW x 6 P
5. RATED VOLTAGE AND FREQUENCY	380 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATTING	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 ℃
10. FULL LOAD SPEED	1160 RPM
11. FULL LOAD CURRENT	2.0 A
12. LOCKED ROTOR CURRENT	9.5 A
13. MINIMUM STARTING VOLTAGE	345 V
14. EFFICIENCY AT 100% RATED LOAD	64 %
15. POWER FACTOR AT 100% RATED LOAD	59.5 %
16. FULL LOAD TORQUE	0.80 KCM
17. SITE ALTTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	TENV
19. TYPE OF BEARING	PL : 6205zz CIL : 6204zz
20. MOUNTING	HORIZONTAL
21. MAXIMUM AMBIENT TEMPURE	℃
22. BEARING LUBRICATION	GRAFOIL
23. STARTING METHOD	FULL VOLTAGE



THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA


1. SERVICE	TRAVERSING
2. MANUFACTURE	극동호이스트 (주)
3. FRAME NUMBER	90 S
4. RATED POWER	0.5 KW x 6 P
5. RATED VOLTAGE AND FREQUENCY	440 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATTING	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	1160 RPM
11. FULL LOAD CURRENT	1.7 A
12. LOCKED ROTOR CURRENT	8.2 A
13. MINIMUM STARTING VOLTAGE	400 V
14. EFFICIENCY AT 100% RATED LOAD	64 %
15. POWER FACTOR AT 100% RATED LOAD	59.5 %
16. FULL LOAD TORQUE	0.80 KGM
17. SITE ALTTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	TENV
19. TYPE OF BEARING	PL : 6205zz OPZ : 6204zz
20. MOUNTING	HORIZONTAL
21. MAXIMUM AMBIENT TEMPURE	°C
22. BEARING LUBRICATION	IP
23. STARTING METHOD	FULL VOLTAGE



THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA


1. SERVICE	TRAVERSING
2. MANUFACTURE	극동호이스트 (주)
3. FRAME NUMBER	90 S
4. RATED POWER	0.5 KW x 6 P
5. RATED VOLTAGE AND FREQUENCY	460 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATTING	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 ℃
10. FULL LOAD SPEED	1160 RPM
11. FULL LOAD CURRENT	1.7 A
12. LOCKED ROTOR CURRENT	7.9 A
13. MINIMUM STARTING VOLTAGE	418 V
14. EFFICIENCY AT 100% RATED LOAD	64 %
15. POWER FACTOR AT 100% RATED LOAD	54.5 %
16. FULL LOAD TORQUE	0.80 KGM
17. SITE ALTTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	TENV
19. TYPE OF BEARING	PL : 6205zz GFL : 6204zz
20. MOUNTING	HORIZONTAL
21. MAXIMUM AMBIENT TEMPURE	℃
22. BEARING LUBRICATION	GRAFOIL
23. STARTING METHOD	FULL VOLTAGE



THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	TRAVERSING
2. MANUFACTURE	극동호이스트 (주)
3. FRAME NUMBER	90 S
4. RATED POWER	0.5 KW x 6 P
5. RATED VOLTAGE AND FREQUENCY	480 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATTING	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	1160 RPM
11. FULL LOAD CURRENT	1.6 A
12. LOCKED ROTOR CURRENT	7.5 A
13. MINIMUM STARTING VOLTAGE	436 V
14. EFFICIENCY AT 100% RATED LOAD	64 %
15. POWER FACTOR AT 100% RATED LOAD	59.5 %
16. FULL LOAD TORQUE	0.80 KGM
17. SITE ALTTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	TENV
19. TYPE OF BEARING	PL : 6205zz C/P : 6204zz
20. MOUNTING	HORIZONTAL
21. MAXIMUM AMBIENT TEMPURE	°C
22. BEARING LUBRICATION	Oil F
23. STARTING METHOD	FULL VOLTAGE





CERT NO. 200703WRU59900

DATE Oct. 26, 2010

MILL TEST CERTIFICATE

THIS IS TO CERTIFY THAT THE MATERIAL DESCRIBED BELOW WAS MANUFACTURED
IN ACCORDANCE WITH KISWIRE LTD SPECIFICATION AND APPLICABLE SECTIONS

OF KSD 3514 - 2002 (B Grade)

TO MESSRS

MATERIAL DESCRIPTION UNGALVANIZED STEEL WIRE ROPE

06 X 19 (SL) + FC 1000 M X 5 REEL

EX NO. 1W4264

ORDER NO. REEL NO. 1 ~ 5 SAMPLING NO. 1

DIAMETER OF ROPE 6.000 mm TYPE OF CORE Fiber Core

SPECIFIED BREAKING LOAD 20.90 kN SAMPLE BROKE AT 26.78 kN

WT. OF ZINC COATING OF OUTER WIRE MIN. 0.000 g/m²

ROPE LAY RHRL LAY LENGTH 38.6 mm

LUBRICATION A-2

CHEMICAL ANALYSIS OF WIRE ROD

CHARGE NO.	C X 100	Si X 100	Mn X 100	P X 100	S X 1000
SA51859	72	21	69	11	

DATE OF SAMPLE TEST Jan. 21, 2010

Approved by O.C Manager H.S. SONG
KISWIRE LTD., KOREA



KS



JIS



ART



AES



KR



NK



G.Lloyd



BV

안전보건공단
Korea Occupational Safety & Health Agency

SUB VENDOR LIST

구분	NO	DESCRIPTION	SUB VENDOR	TEL NO.	REMARK
기 계	1	WIRE ROPE	만호 로우프(주)	051-332-3131	
			고려제강 (주)	02-776-4131	
	2	MAGNET CORE	극동호이스트(주)	031-491-5311	
	3	DRUM	극동호이스트(주)	031-491-5311	
	4	GEAR	극동호이스트(주)	031-491-5311	
	5	HOOK ASS'Y	제 일 단 철	032-527-2817	
			대 흥 단 조	032-561-0541	
	6	MIDDLE SHAFT	극동호이스트(주)	031-491-5311	
	7	RAIL CHANNEL ANGLE	인천제철(주)	032-763-5000	
			강원산업(주)	032-756-8881	
전 기	8	MAG CONTACTOR	L.G 전선 (주)	02-273-4140	전 품
			(주) 대 룩	02-242-4141	한국공업협회
			(주) 대성디제스	055-338-3125	
	9	E.O.C.R	삼화기연 (주)	032-62-1331	K.S
			아산 전기	02-2636-8035	
	10	PUSH BUTTON	한영전기 (주)	02-742-0430	전 품
			(주)케이제오토	02-247-3131	전 품
			반도기계 (주)	031-495-8353-4	전 품
	11	LOAD LIMITER	보 창 기 전	032-431-0150	산 안 검
			반도기계 (주)	031-495-8353-4	산 안 검
			정호 엔지니어링	031-495-8353	산 안 검
	12	SILICON	반도기계 (주)	031-495-8353-4	
			아산 전기	02-2636-8035	
			보 창 기 전	032-431-0150	

EN 60 947-5-1			
Clause	Requirement – Test	Result - Remark	Verdict

	Annex C of IEC 60947-1	P
--	-------------------------------	---

Annex C	Degree of protection of enclosed control circuit-devices	P
C.1	Scope This annex applies to degrees of protection of enclosed switchgear and control gear at rated voltages not exceeding 1000 V a.c. or 1500 V d.c. hereafter referred as "equipment"	
C.2	Object Clause 2 of IEC 60529 applies with additional requirements of this annex	
C.3	Definitions Clause 3 of IEC 60529 applies except that "Enclosure" is replaced by the following: "A part providing a specified degree of protection of equipment against certain external influences and a specified degree of protection against approach to or contact with live parts and moving parts"	
C.4	Designation Clause 4 of IEC 60529 applies except for letters H, M and S	N/A
C.5	Degrees of protection against access to hazardous parts and against ingress of solid foreign objects indicated by the first characteristic numeral Clause 5 of IEC 60529 applies 6	P
C.6	Degrees of protection against ingress of water indicated by the second characteristic numeral Clause 6 of IEC 60529 applies 5	P
C.7	Degrees of protection against access to hazardous parts indicated by the additional letter Clause 7 of IEC 60529 applies	N/A
C.8	Supplementary letters Clause 8 of IEC 60529 applies	N/A
C.9	Examples of designations with IP Code Clause 9 of IEC 60529 applies	P
C.10	Marking	P

TRF-No.: IEC60947_5_1A

전임제해예방

안전보건공단
KOREA OCCUPATIONAL SAFETY & HEALTH AGENCY