



제 2014 - 16554 호

안 전 인 증 서

(사업장명)

극동호이스트(주)

(소재지) (425-833) 경기도 안산시 성곡동 630-2 반월공단 B-607-14

위 사업장에서 제조하는 아래의 품목이 산업안전보건법 제34조 및 같은 법 시행규칙 제58조의4제4항에 따른 안전인증 심사 결과 안전·보건기준에 적합하므로 안전인증표시의 사용을 인증합니다.

_____ 품 목 _____

호이스트

_____ 형식, 모델(용량, 등급)/인증번호 _____

KDC1.5-M (1.5Ton) / 14-AQ2AC-01115

_____ 인 증 기 준 _____

고용노동부 고시 제2012 - 33호 (위험기계, 기구 의무안전인증 고시)

_____ 인 증 조 건 _____

2014년 04월 21일



한국산업안전보건공단이사장



심사결과 통지서

신청인	사업장명	극동호이스트(주)	사업장관리번호	134-81-013350
	사업자등록번호	134-81-01335	대표자 성명	최성찬
	소재지	(425 - 833) 경기도 안산시 성곡동630-2 반월공단 B-607-14		

안전인증대상 기계·기구명

모노레일식호이스트

형식 (규격)	KDC1.5-M	용량 (등급)	1.5 Ton
---------	----------	---------	---------

산업안전보건법 제 34조 및 같은 법 시행규칙 제58조의4에 따라 실시한

☐ 예비심사

☒ 서면심사

☐ 기술능력 및 생산체계 심사

☐ 개별 제품심사

☐ 개별 제품심사(제작중)

☐ 형식별 제품심사

결과가 ☒ 적 합
☐ 부적 합

함을 통지합니다.

2014년 04월 14일

인증심사원

강성두 변명수

(서명 또는 인)

한국산업안전보건공단 경기서부지도원장



서 면 심 사 서 류

형식 번호 : KDC1.5-M

극 동 호 이 스트 (주)

工場 : 경기도 안산시 단원구 해봉로 119 (성곡동)

電話 : 031) 491 - 5311

FAX : 031) 494 - 5315

산업재해예방
안전보건공단

KOREA OCCUPATIONAL SAFETY & HEALTH AGENCY


동 일 형 식 일 램 표

사업장명	극동호이스트㈜	개정일자 및 번호	2014년 03월 28일	인증번호	
형식	모텔	동일 형식 인정범위 및 내역			비 고
		권상속도(m/min)	양정(m)	행방방식	
KDC1.5-M	KDC1.5-L6-M	고속:10M/MIN	6	모터구동식	
	KDC1.5-L6.5-M		6.5		
	KDC1.5-L9-M		9		
	KDC1.5-L12-M		12		
	KDC1.5-L18-M	CREEP:1.0M/MIN	18		
	KDC1.5-L24-M		24		
	KDC1.5-L30-M		30		

산업재해예방

안전보건공단

KOREA OCCUPATIONAL SAFETY & HEALTH AGENCY



호 이 스톱 설 계 조 건

항 목		내 용	
형 식 번 호		KDC1.5-M	모 델 KDC1.5-L6-M, KDC1.5-L6.5-M, KDC1.5-L9-M KDC1.5-L12-M, KDC1.5-L18-M
형 식 번 호		모노 레일식 와이어 호이스트	
정 격 하 중	주 권	정격하중	1.5 TON
		시험하중	1.875 TON
	복 권	정격하중	-
		시험하중	-
주권 달기구	종 류	SINGLE HOOK & DOUBLE HOOK	
	자체하중	0.02	
양 정 (LIFT)		6,6.5,9,12,18 M	
호이스트 (HOIST)	HIGH	SPEED	10.0 / 1.0 M/MIN
		MOTOR	3.7 /0.4 KW x 4P
	BRAKE	D.C MAGNET DISC BRAKE	
TRAVERSING	HIGH	SPEED	24 M/MIN
		MOTOR	0.75 KW x 4P
	LOW	SPEED	16 M/MIN
		MOTOR	0.5 KW x 6P
	DUAL HIGH	SPEED	24 / 12 M/MIN
		MOTOR	0.8/0.4 KW x 4/8P
	DUAL LOW	SPEED	16/8 M/MIN
		MOTOR	0.5/0.25 KW x 6/12P
	BRAKE	D.C MAGNET DISC BRAKE & NO BRAKE	
WIRE ROPE		(6x37) $\phi 10$ x 2 FALLS STAINLESS STEEL(7x19) $\phi 10(3/8")$ x 2 FALLS	
POWER SOURCE	MAIN	AC $\phi 3$ x 220V (380,440,460,480V) x 60Hz	
	CONTROL	AC $\phi 1$ x 110V(120V) x 60Hz	
CONTROL METHOD		F.L 상 PUSH BUTTON 조작	
방 호 장 치		과부하방지장치, 과권방지장치, HOOK 해지장치 횡행 STOPPER, 비상정지장치	
사 용 용 도		창고용 , 정비용 , 일반화물 인양작업	
설 치 위 치		☒ 옥 내 ☒ 옥 외	
하중을 받는 회수		1.2x10 ⁵ 회 이상 2.5x10 ⁵ 회 미만	
사 용 조 건		정격하중63% 이상 80% 이하의 하중용 HOIST	
주 위 온 도		-10 ~ 40℃ 이내	
방 폭 구 조 사 용 유 무		☐ 유 ☒ 무	


호 이 스톱 설 계 조 건


항 목		내 용	
형 식 번 호		KDC1.5-M	모 델 KDC1.5-L24-M, KDC1.5-L30-M
형 식 번 호		모노 레일식 와이어 호이스트	
정 격 하 중	주 권	정격하중	1.5 TON
		시험하중	1.875 TON
	복 권	정격하중	-
		시험하중	-
주권 달기구	종 류	SINGLE HOOK & DOUBLE HOOK	
	자체하중	0.02	
양 정 (LIFT)		24,30 M	
호이스트 (HOIST)	HIGH	SPEED	10.0 / 1.0 M/MIN
		MOTOR	3.7 /0.4 KW x 4P
	BRAKE	D.C MAGNET DISC BRAKE	
TRAVERSING	HIGH	SPEED	24 M/MIN
		MOTOR	(0.75 KW x 4P) x 2UNITS
	LOW	SPEED	16 M/MIN
		MOTOR	(0.5 KW x 6P) x 2UNITS
	DUAL HIGH	SPEED	24 / 12 M/MIN
		MOTOR	(0.8/0.4 KW x 4/8P) x 2UNITS
	DUAL LOW	SPEED	16/8 M/MIN
		MOTOR	(0.5/0.25 KW x 6/12P) x 2UNITS
BRAKE		D.C MAGNET DISC BRAKE & NO BRAKE	
WIRE ROPE		(6x37) ø10 x 2 FALLS STAINLESS STEEL(7x19) ø10(3/8") x 2 FALLS	
POWER SOURCE	MAIN	AC ø3 x 220V (380,440,460,480V) x 60Hz	
	CONTROL	AC ø1 x 110V(120V) x 60Hz	
CONTROL METHOD		F.L 상 PUSH BUTTON 조작	
방 호 장 치		과부하방지장치,과권방지장치, HOOK 해지장치 횡행 STOPPER, 비상정지장치	
사 용 용 도		창고용 , 정비용 , 일반화물 인양작업	
설 치 위 치		☑ 옥 내 ☑ 옥 외	
하중을 받는 회수		1.2x10 ⁵ 회 이상 2.5x10 ⁵ 회 미만	
사 용 조 건		정격하중63% 이상 80% 이하의 하중용 HOIST	
주 위 온 도		-10 ~ 40℃ 이내	
방 폭 구 조 사 용 유 무		☐ 유 ☑ 무	

1) 기 계



산업재해예방
안전보건공단
KOSHA
KOREA OCCUPATIONAL SAFETY & HEALTH AGENCY






TRAVERSING I-BEAM A x B x t	Ix (cm ⁴)	Iy (cm ⁴)	Zx (cm)	Zy (cm)	SUPPORT LENGTH C
I 250 x 125 x 7.5	5180	175	85	450	MAX. 4.5M
I 300 x 150 x 10	12700	849	110	465	MAX. 7.1M
I 350 x 150 x 9	15200	871	120	465	MAX. 7.8M
I 400 x 150 x 10	24100	1220	1740	465	MAX. 9.8M
I 450 x 175 x 11	39200	1740	1740	475	MAX. 12.5M

SPECIFICATION	
RATED LOAD	1500 KG
TESTING LOAD	1875 KG
LIFT	6 M
RATING	30 MIN
HOISTING	SPEED MOTOR 10 / 1.0 M/MIN
	3.7 / 0.4 KW x 4 P
TRAVERSING	SPEED HIGH 24 M/MIN
	MOTOR 0.75 KW x 4 P
	SPEED LOW 16 M/MIN
	MOTOR 0.5 KW x 6 P
	SPEED DUAL HIGH 24/12 M/MIN
	MOTOR 0.8/0.4 KW x 4/8 P
WIRE ROPE	SPEED DUAL LOW 16/8 M/MIN
	MOTOR 0.5/0.25 KW x 6/12 P
(6x37) Ø10 x 2 FALLS	
STAINLESS STEEL (7x19) Ø10(3/8") x 2 FALLS	
POWER SOURCE	AC3Ø 220V(380,440,460,480) 60Hz
COLOR	10 B 3/5
WEIGHT	320 KG

NO.	DESCRIPTION	MTL	QTY		SUB WEIGHT(Kg)	TOTAL WEIGHT(Kg)	REMARKS.
			SUB	TOTAL			
5	I-BEAM	SS400			—		TABLE 형조
4	UPPER LIMIT S/W	SS400			1		
3	SAFETY LATCH	SPC			1		
2	EMERGENCY S/W	—			1		
1	LOAD LIMITER	—			1		
PROJECT							
TITLE		KDC1.5 — L6 — M		DATE		DIM	
DRAWN		DESIGNED		CHECKED		APPROVED	
ARRANGEMENT DRAWING FOR HOIST		SCALE		PROJECTION		3rd	
REF. DRAWING		APPROVED		DATE		DIM	
KDC1.5M600		SHEET No.		DWG No.		KDC1.5M600	






SPECIFICATION			
RATED LOAD	1500	KG	
TESTING LOAD	1875	KG	
LIFT	9	M	
RATING	30	MIN	
HOISTING	SPEED	10 / 1.0	M/MIN
	MOTOR	3.7 / 0.4	KW x 4 P
TRAVERSING	HIGH	SPEED	24 M/MIN
		MOTOR	0.75 KW x 4 P
	LOW	SPEED	16 M/MIN
		MOTOR	0.5 KW x 6 P
	DUAL HIGH	SPEED	24/12 M/MIN
	DUAL LOW	MOTOR	0.8/0.4 KW x 4/8 P
WIRE ROPE	DUAL LOW	SPEED	16/8 M/MIN
	MOTOR	0.5/0.25	KW x 6/12 P
	(6x37) Ø10 x 2 FALLS		
	STAINLESS STEEL (7x19) #10(3/8") x 2 FALLS		
POWER SOURCE	AC3Ø 220V(380,440,480,480) 60Hz		
COLOR	10 B 3/5		
WEIGHT	360	KG	

[illegible]

TRAVERSING I - BEAM	I ₀ (Cm ²)	Z ₀ (Cm ²)	SUPPORT LENGTH	C
I 250 x 125 x 7.5	5180	415	MAX. 4.5M	450
I 300 x 180 x 10	12700	849	MAX. 7.1M	485
I 350 x 150 x 9	15200	871	MAX. 7.8M	485
I 400 x 150 x 10	24100	1220	MAX. 9.8M	485
I 450 x 175 x 11	39200	1740	MAX. 12.5M	475



SPECIFICATION			
RATED LOAD	1500	KG	
TESTING LOAD	1875	KG	
LIFT	12	M	
RATING	30	MIN	
HOISTING	SPEED	10 / 1.0 M/MIN	
	MOTOR	3.7 / 0.4 KW x 4 P	
TRAVERSING	SPEED	24	M/MIN
	MOTOR	0.75 KW x 4 P	
	SPEED	16	M/MIN
	MOTOR	0.5 KW x 6 P	
	SPEED	24/12	M/MIN
	MOTOR	0.8/0.4 KW x 4/8 P	
WIRE ROPE	SPEED	16/8	M/MIN
	MOTOR	0.5/0.25 KW x 6/12 P	
POWER SOURCE	(6x37) Ø10 x 2 FALLS		
	STAINLESS STEEL (7x19) Ø10(3/8") x 2 FALLS		
COLOR	AC3Ø 220V(380,440,480) 60Hz		
	10 B 3/5		
WEIGHT	380	KG	

5	I-BEAM	SS400			—	TABLE 형조	
4	UPPER LIMIT S/W	SS400			1		
3	SAFETY LATCH	SPC			1		
2	EMERGENCY S/W	—			1		
1	LOAD LIMITER	—			1		
NO.	DESCRIPTION	M/TL	SUB	TOTAL	SUB	TOTAL	REMARKS.
			QTY		WEIGHT(kg)		
PROJECT						DATE	DIM
							mm
TITLE	KDC1.5 — L12 — M				SCALE	PROJECTION	
	ARRANGEMENT DRAWING FOR HOIST				A3/15	3rd	
DRAWN	DESIGNED	CHECKED	APPROVED	REF. DRAWING			
 KDC1.5M120				SHEET No.		DWG No.	
KUK DONG HOIST CO., LTD.						KDC1.5M120	


TRAVERSING I-BEAM	I-BEAM	SUPPORT LENGTH	C
A x B x t	(Cm ²)	(Cm)	
I 250 x 125 x 7.5	5180	MAX. 4.5M	450
I 300 x 150 x 10	12700	MAX. 7.1M	465
I 350 x 150 x 9	13200	MAX. 7.8M	465
I 400 x 150 x 10	24100	MAX. 9.8M	465
I 450 x 175 x 11	39200	MAX. 12.5M	475

산업재해예방
안전보건공단


KOREA OCCUPATIONAL SAFETY & HEALTH AGENCY

SPECIFICATION		
RATED LOAD	1500	KG
TESTING LOAD	1875	KG
LIFT	18	M
RATING	30	MIN
HOISTING	SPEED	10 / 1.0 M/MIN
	MOTOR	3.7 / 0.4 KW x 4 P
TRAVERSING	SPEED	24 M/MIN
	MOTOR	0.75 KW x 4 P
	SPEED	16 M/MIN
	MOTOR	0.5 KW x 6 P
DUAL HIGH	SPEED	24/12 M/MIN
	MOTOR	0.8/0.4 KW x 4/8 P
DUAL LOW	SPEED	16/8 M/MIN
	MOTOR	0.5/0.25 KW x 6/12 P
WIRE ROPE	(6x37) Ø10 x 2 FALLS	
	STAINLESS STEEL (7x19) Ø10(3/8") x 2 FALLS	
POWER SOURCE	AC3Ø 220V(380,440,460,480) 60Hz	
COLOR	10 B 3/5	
WEIGHT	438 KG	

5	I-BEAM	SS400	-				대어물 용조
4	UPPER LIMIT S/W	SS400	1				
3	SAFETY LATCH	SPC	1				
2	PENDANT S/W	-	1				
1	LOAD LIMITER	-	1				
NO.	DESCRIPTION	M'T'L	SUB QTY	TOTAL SUB	TOTAL WEIGHT(kg)		REMARKS.
					DATE	DIM	
PROJECT							
TITLE	KDC1.5-L18-M						
	ARRANGEMENT DRAWING FOR HOIST						
DRAWN	DESIGNED	CHECKED	APPROVED	REF. DRAWING			
 KDK KUK DONG HOIST CO., LTD.			SHEET No.		DWG No.		
					KDC1.5 - 1800		



TRAVERSING I - BEAM		I _x (Cm ⁴)	Z _x (Cm ³)	SUPPORT LENGTH	C
A x B x t					
I 250 x 125 x 7.5		5180	415	MAX. 4.5M	450
I 300 x 150 x 10		12700	849	MAX. 7.1M	465
I 350 x 150 x 9		15200	871	MAX. 7.8M	465
I 400 x 150 x 10		24100	1220	MAX. 9.8M	465
I 450 x 175 x 11		39200	1740	MAX. 12.5M	475




SPECIFICATION		
RATED LOAD	2000 KG	
TESTING LOAD	2500 KG	
LIFT	24 M	
RATING	30 MIN	
HOISTING	SPEED	10/1.0 M/MIN
	MOTOR	3.7/0.4 KW x 4 P
	HIGH	SPEED 24 M/MIN MOTOR 0.75KW x 4 P (2UNITS)
	LOW	SPEED 16 M/MIN MOTOR 0.5 KW x 6 P (2UNITS)
	DUAL HIGH	SPEED 24/12 M/MIN MOTOR 0.8/0.4 KW x 4/8P (2UNITS)
	DUAL LOW	SPEED 16/8 M/MIN MOTOR 0.5/0.25 KW x 6/12P(2UNITS)
WIRE ROPE		(6x37) 10 x 2 FALLS
POWER SOURCE		STAINLESS STEEL (7x19) ϕ 10(3/8") x 2 FALLS
COLOR		AC3 ϕ 220V(380,440,460,480) 60Hz
WEIGHT		10 B 3/5 495 KG

5	I-BEAM	SS400	-				TABLE #2
4	UPPER LIMIT S/W	SS400	1				
3	SAFETY LATCH	SPC	1				
2	PENDANT S/W	-	1				
1	LOAD LIMITER	-	1				
NO.	DESCRIPTION	M'T'L	QTY		WEIGHT(kg)	REMARKS.	
			SUB	TOTAL			
PROJECT				DATE	DIM		
TITLE	KDC1.5-L24-M		SCALE		PROJECTION		
	ARRANGEMENT DRAWING FOR HOIST		A3/20		3rd		
DRAWN	DESIGNED	CHECKED	APPROVED	REF. DRAWING			
		SHEET No.		DWG No.			
		구동호이스트 주식회사		KDC1.5 - 2400			
		KUK DONG HOIST CO., LTD.					

TRAVERSING I - BEAM		Ix (Cm ²)	Zx (Cm ²)	SUPPORT LENGTH	C
A x B x t					
I 250 x 125 x 7.5	5180	415	MAX. 4.5M	445	
I 300 x 150 x 10	12700	849	MAX. 7.1M	465	
I 350 x 150 x 9	15200	871	MAX. 7.8M	465	
I 400 x 150 x 10	24100	1220	MAX. 9.8M	465	
I 450 x 175 x 11	39200	1740	MAX. 12.5M	475	

SPECIFICATION			
RATED LOAD	2000 KG		
TESTING LOAD	2500 KG		
LIFT	30 M		
RATING	30 MIN		
HOISTING	SPEED	10/1.0 M/MIN	
	MOTOR	3.7/0.4 KW x 4 P	
TRAVERSING	HIGH	SPEED	24 M/MIN
		MOTOR	0.75KW x 4 P (2UNITS)
	LOW	SPEED	16 M/MIN
		MOTOR	0.5 KW x 6 P (2UNITS)
	DUAL	SPEED	24/12 M/MIN
	HIGH	MOTOR	0.8/0.4 KW x 4/8P (2UNITS)
DUAL	SPEED	16/8 M/MIN	
	MOTOR	0.5/0.25 KW x 6/12P(2UNITS)	
WIRE ROPE	(6x37) 10 x 2 FALLS		
	STAINLESS STEEL (7x19) #10(3/8") x 2 FALLS		
POWER SOURCE	AC3Ø 220V(380,440,460,480) 60Hz		
COLOR	10 B 3/5		
WEIGHT	525 KG		

NO.	I-BEAM	SS400	-	QTY	SUB TOTAL	SUB WEIGHT(Kg)	REMARKS.
5	I-BEAM	SS400	-				TABLE 번호
4	UPPER LIMIT S/W	SS400	1				
3	SAFETY LATCH	SPC	1				
2	PENDANT S/W	-	1				
1	LOAD LIMITER	-	1				
DESCRIPTION		MT'L					
PROJECT							DATE
TITLE							DIM mm
DRAWN							SCALE
DESIGNED							PROJECTION
CHECKED							A3/20
APPROVED							3rd
REF. DRAWING							
KDC1.5-L30-M							
ARRANGEMENT DRAWING FOR HOIST							
KUK DONG HOIST CO., LTD.							
SHEET No.							
DWG No.							
KDC1.5 - 3000							



TRAVERSING I-BEAM	IX (Cm ⁴)	Zx (Cm ³)	SUPPORT LENGTH	C
I 250 x 125 x 7.5	5180	415	MAX. 4.5M	445
I 300 x 150 x 10	12700	849	MAX. 7.1M	465
I 350 x 150 x 9	15200	871	MAX. 7.8M	465
I 400 x 150 x 10	24100	1220	MAX. 9.8M	465
I 450 x 175 x 11	39200	1740	MAX. 12.5M	475

산업재해예방
안전보건공단

KOREA OCCUPATIONAL SAFETY & HEALTH AGENCY




2) 전 기



산업재해예방

안전보건공단

KOREA OCCUPATIONAL SAFETY & HEALTH AGENCY



ELECTRICAL SYMBOL LIST

DESCRIPTION	SYMBOLS	DESCRIPTION	SYMBOLS	DESCRIPTION	SYMBOLS	DESCRIPTION	SYMBOLS
WIRE INTERNAL TO ENCLOSURE	—	CONTROLLER OR REMOTE CONTROLLER CONTACTOR		SOLENOID COIL		FLOOD LIGHTING	
WIRE EXTERNAL TO ENCLOSURE	---	UPPER LIMIT SWITCH (LS-II)		RESISTOR		RECEPTACLE	
WIRE NOT CONNECTED		THERMAL RELAY		VARIABLE RESISTOR			
WIRE CONNECTED		PILOT(SIGNAL) LAMP		SLIP RING			
TERMINAL	⊙	ROTARY LAMP		CABLE REEL			
GROUND (EARTH)	⊥	WARNING SIREN		SPACE HEATER			
PLUG & RECEPTACLE	⋈	BUZZER		SURGE ABSORBER			
MAGNETIC CONTACTOR COIL		AMMETER		LOAD CELL			
AUX. RELAY COIL		VOLT METER		BALLAST WITH RECEPTACLE			
TIMER COIL		FLUORESCENCE LAMP		FAN			

DATE	REVISIONS	CHECK.	APP.	CUSTOMER	DRAWING TITLE	DRAWING	DESIGN	CHECKED	APPROVED	SCALE	DATE	ORDER NO.
					SYMBOL LIST 2/2					NONE		

ELECTRICAL SPECIFICATION

POWER SOURCE : AC 3Φ 220V, 380V, 440V, 460V, 480V 60Hz

CONTROL SOURCE : AC 1Φ 110V(120V) 60Hz

OBJECT	MOTOR OUTPUT	220V		380V		440V	460V	480V	440, 460, 480V	BRAKE	REMARK
		STATOR CURRENT	1st CABLE SIZE	STATOR CURRENT	1st CABLE SIZE	STATOR CURRENT	STATOR CURRENT	STATOR CURRENT	1st CABLE SIZE		
MAIN HOIST	3.7KW x 4P 30 MIN	16.00 A	4.0 sq	9.30 A	4.0 sq	8.0 A	7.7 A	7.3 A	4.0 sq	DC MAG. BRAKE	
CREEP HOIST	0.4KW x 4P 30 MIN	2.70 A	4.0 sq	1.60 A	4.0 sq	1.4 A	1.3 A	1.2 A	4.0 sq	DC MAG. BRAKE	
TRAVERSING	HIGH 0.75KW x 4P 30 MIN	4.10 A	4.0 sq	2.40 A	4.0 sq	2.00 A	2.00 A	1.90 A	4.0 sq	DC MAG. BRAKE	1 DRIVE
	LOW 0.5KW x 6P 30 MIN	3.40 A	4.0 sq	2.00 A	4.0 sq	1.70 A	1.70 A	1.60 A	4.0 sq	DC MAG. BRAKE	1 DRIVE
CONTROL CIRCUIT		2 A	2.5 sq	2 A	2.5 sq	2 A	2 A	2 A	2.5 sq		
LIGHTING & ACC'Y CIRCUIT											
SUB TOTAL (PEAK LOAD)		22.10 A	6.0 sq	13.70 A	4.0 sq	12.00 A	11.70 A	11.20 A	4.0 sq	I(A)=M/H + T/S + ASS'Y	
SUB TOTAL (NORMAL LOAD)		21.40 A	6.0 sq	13.30 A	4.0 sq	11.70 A	11.40 A	10.90 A	4.0 sq	I(A)=M/H + T/S + ASS'Y	

*. 위 계산은 HIGH(MAX.)일때와 LOW(MIN.)일때만 계산한것임.

*. 위 계산은 LIFT 6(6.5, 9, 12, 18)M에 적용.

ELECTRICAL SPECIFICATION

POWER SOURCE : AC 3Φ 220V, 380V, 440V, 460V, 480V 60Hz

CONTROL SOURCE : AC 1Φ 110V(120V) 60Hz

OBJECT	MOTOR OUTPUT	220V		380V		440V	460V	480V	440, 460, 480V	BRAKE	REMARK
		STATOR CURRENT	1st CABLE SIZE	STATOR CURRENT	1st CABLE SIZE	STATOR CURRENT	STATOR CURRENT	STATOR CURRENT	1st CABLE SIZE		
MAIN HOIST	3.7KW x 4P 30 MIN	16.00 A	4.0 sq	9.30 A	4.0 sq	8.0 A	7.7 A	7.3 A	4.0 sq	DC MAG. BRAKE	
CREEP HOIST	0.4KW x 4P 30 MIN	2.70 A	4.0 sq	1.60 A	4.0 sq	1.4 A	1.3 A	1.2 A	4.0 sq	DC MAG. BRAKE	
TRAVERSING	HIGH	(4.1*2)A	4.0 sq	(2.4*2)A	4.0 sq	(2.0*2)A	(2.0*2)A	(1.9*2)A	4.0 sq	DC MAG. BRAKE	2 DRIVE
	LOW	(3.4*2)A	4.0 sq	(2.0*2)A	4.0 sq	(1.7*2)A	(1.7*2)A	(1.6*2)A	4.0 sq	DC MAG. BRAKE	2 DRIVE
CONTROL CIRCUIT											
LIGHTING & ACC'Y CIRCUIT		2 A	2.5 sq	2 A	2.5 sq	2 A	2 A	2 A	2.5 sq		
SUB TOTAL (PEAK LOAD)		HIGH 26.20 A	6.0 sq	16.10 A	4.0 sq	14.00 A	13.70 A	13.10 A	4.0 sq	I(A)=M/H + T/S + ASS'Y	
SUB TOTAL (NORMAL LOAD)		LOW 24.80 A	6.0 sq	15.30 A	4.0 sq	13.40 A	13.10 A	12.50 A	4.0 sq	I(A)=M/H + T/S + ASS'Y	

*. 위 계산은 HIGH(MAX.) 일때와 LOW(MIN.) 일때만 계산한것임.

*. 위 계산은 LIFT 24,30M에 적용

■ 보호본딩회로의 연속성 확인

시험전선의 최소유호 단면적(mm²)	최고 전압 강하(V)
1.0	3.3
1.5	2.6
2.5	1.9
4.0	1.4
>6.0	1.0

① 보호본딩회로의 연속성의 검증은 PELV전원(50/60Hz)에서 최소 10A 이상의 전류를 10초 이상의 인가에 의한다.
 시험은 PE단자와 보호본딩회로의 여러지점 사이에서 이루어진다.

② PE단자와 시험 지점 사이에서 측정된 전압은(표 참조) 값을 초과해서는 아니된다.

■ 절연저항 시험


전원선과 보호본딩선 사이를 직류 500V로 측정된 절연저항 값은 1MΩ 이상이어야 한다.

■ 내전압 시험

① PELV 전압에서 작동되도록 설계된 전기장치의 회로를 제외한 모든 회로와 보호본딩회로의 전선 사이에 1초 이상 지속되는 다음의 시험 전압에 견딜수 있어야 한다.

· 장치의 정격전압의 두배 또는 1,000V 중 큰값의 전압

② 이 시험을 견딜수 없도록 설계된 부품은 시험이 진행되기 전에 차단하여야 한다.



	16	17	18	19	20
NO	DESCRIPTION			CABLE SIZE	
1	MAIN EARTH LINE			USER SCOPE	
2	POWER SOURCE			USER SCOPE	
3	TROLLEY BAR			USER SCOPE	
4	POWER SOURCE WITH EARTH			USER SCOPE	
5	HOST POWER SOURCE WITH EARTH			VCT 6.050 x 1C	
6	HOISTING MOTOR WITH EARTH			VCT 4.050 x 1C	
7	CREEP MOTOR WITH EARTH			VCT 4.050 x 1C	
8	TRAVERSING MOTOR WITH EARTH			VCT 4.050 x 1C	


* CV CABLE 4C중 1C는 EARTH로 사용함.

- NOTE -

1. 전동기 외함, 제어반의 프레임 등은 접지하여 그 접지 저항은

400V 미만 : 100오옴 이하일것.(3종 접지)
400V 이상 : 10오옴 이하일것.(특 3종접지)


2.MAIN S/W BOX는 3종 접지 요.



കിഴക്കേ

1. 전기장비와 기계의 노출된 모든 도전부는 보호접지선으로 연결되어야 하며 적절한 접지연속 기능이 유지되야함.
2. 보호접지선으로는 기때기, 과전류보호장치가 부착되지 않아야 한다.

시험대상 전선의 최소 유효단면적	최고전압강하(V)
1.0	3.3
1.5	2.6
2.5	1.6
4.0	1.4
>6.0	1.0

[illegible]

1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
															NO	DESCRIPTION	CABLE SIZE		
															1	MAIN EARTH LINE	USER SCOPE		
															2	POWER SOURCE	USER SCOPE		
															3	TROLLEY BAR	USER SCOPE		
															4	POWER SOURCE WITH EARTH	USER SCOPE		
															5	HOST POWER SOURCE WITH EARTH	VCT 6.0SQ x 1C		
															6	HOISTING MOTOR WITH EARTH	VCT 4.0SQ x 1C		
															7	CREEP MOTOR WITH EARTH	VCT 4.0SQ x 1C		
															8	TRAVERSING MOTOR WITH EARTH	VCT 4.0SQ x 1C		

* CV CABLE 4C중 1C는 EARTH로 사용함.

- NOTE -

1. 전동기 외함, 제어반의 프레임 등은 접지하여 그 접지 저항은

400V 미만 : 100옴 이하일것.(3종 접지)

400V 이상 : 10옴 이하일것.(특 3종접지)

2.MAIN S/W BOX는 3종 접지 요.

--- USER SCOPE

--- KUKDONG SCOPE

동전위접지

1. 전기장비와 기계의 노출된 모든 도전부는 보호접지회로에 연결되어야 하며 적절한 접지연속성 기능이 유지되어야함.

2. 보호접지회로에는 개폐기, 과전류보호장치가 부착되지 않아야 한다.

시험대상 전선의 최소 유효단면적	최고전압강하(V)
1.0	3.3
1.5	2.6
2.5	1.6
4.0	1.4
>6.0	1.0

양정 : 24(30)M 일대 적용

MAIN S/W BOX

HOISTING BOX

HOISTING MOTOR

CREEP MOTOR

TRAVERSING MOTOR

TROLLEY BAR

MAIN CONTROL BOX & SOFT STARTER

DRAWING	DESIGN	CHECKED	APPROVED	SCALE	DATE	ORDER NO.
				NONE	2003.07.01	

CUSTOMER	DRAWING TITLE	REVISIONS	CHK.	APP.	DATE
	EARTH DETAILS DRAWING				

극동호이스트 주식회사


KUK DONG HOIST CO., LTD.

KD2-EC002

KOREA OCCUPATIONAL SAFETY & HEALTH AGENCY

1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
ADR'S NO.																			A4

* MAIN POWER : AC 3PH 220V,380V,440V,480V,480V 60Hz (LIFT 6,9,12,18M)



산업재해예방
안전보건공단
KOREA OCCUPATIONAL SAFETY & HEALTH AGENCY

본 도면은 EARTH를 명기하기 위한 도면으로서
실제 배치와 다를 수 있으며 HOIST 본체와의
EARTH용 CABLE은 REFERENCE임

*3중 접지공사 100Ω 이하 (AC 3PH 400V 미만)
*4중 접지공사 10Ω 이하 (AC 3PH 400V 이상)

동전회로

1. 전기장비와 기계의 노출된 모든 도전부는 보호본딩회로에 연결되어야 하며 적절한 접지연속성 기능이 유지되어야 함.
2. 보호본딩회로에는 개폐기, 과전류보호장치 등이 부착되지 않아야 함.


CABLE		REMARK	
NO	TYPE	SIZE	REMARK
1	VCT	380V 4.0sq	HOISTING MOTOR WITH EARTH
2	VCT	4.0sq	HOISTING MOTOR WITH EARTH
3	VCT	4.0sq	HOISTING MOTOR WITH EARTH
4	VFCT	4.0sq	MAIN POWER WITH EARTH

시험대상	전선의 최소 유효단면적	최소전압강하(V)
1.0	1.0	3.3
1.5	1.5	2.6
2.5	2.5	1.6
4.0	4.0	1.4
>6.0	>6.0	1.0

Δ	Δ	Δ	Δ	Δ	Δ	Δ	Δ	Δ	Δ	Δ	Δ	Δ	Δ	Δ	Δ	Δ	Δ	Δ	Δ
CUSTOMER										ORDER NO.									
DRAWING TITLE										SCALE									
REVISIONS										NONE									
CHK. APP.										DWG. NO									
DATE										KDC2M-E234									

1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
																			ADR'S NO.
																			A4

* MAIN POWER : AC 3PH 220V,380V,440V,480V 60Hz (LIFT 24,30M)



산업재해예방
안전보건공단
KOREA OCCUPATIONAL SAFETY & HEALTH AGENCY

본 도면은 EARTH를 명기하기 위한 도면으로서
실제 배치와 다를 수 있으며 HOIST 본체와의
EARTH용 CABLE은 REFERENCE

*3중 접지공사 100Ω 이하 (AC 3PH 400V 미만)
*벽 중 접지공사 10Ω 이하 (AC 3PH 400V 이상)

동전위접지

- 1. 전기장비와 기계의 노출된 모든 도전부는 보호본딩회로에 연결되어야 하며 적절한 접지연속성 기능이 유지되어야 함.
- 2. 보호본딩회로에는 개폐기, 과전류보호장치가 부착되지 않아야 한다.

CABLE		REMARK	
NO	TYPE	SIZE	REMARK
1	VCT	380V 4.0sq	HOISTING MOTOR WITH EARTH
2	VCT	440V 4.0sq	HOISTING MOTOR WITH EARTH
3	VCT	4.0sq	HOISTING MOTOR WITH EARTH
4	VCT	4.0sq	HOISTING MOTOR WITH EARTH
5	VCT	4.0sq	HOISTING MOTOR WITH EARTH
6	VCT	4.0sq	HOISTING MOTOR WITH EARTH
7	VCT	4.0sq	HOISTING MOTOR WITH EARTH
8	VCT	4.0sq	HOISTING MOTOR WITH EARTH
9	VCT	4.0sq	HOISTING MOTOR WITH EARTH
10	VCT	4.0sq	HOISTING MOTOR WITH EARTH
11	VCT	4.0sq	HOISTING MOTOR WITH EARTH
12	VCT	4.0sq	HOISTING MOTOR WITH EARTH
13	VCT	4.0sq	HOISTING MOTOR WITH EARTH
14	VCT	4.0sq	HOISTING MOTOR WITH EARTH
15	VCT	4.0sq	HOISTING MOTOR WITH EARTH
16	VCT	4.0sq	HOISTING MOTOR WITH EARTH
17	VCT	4.0sq	HOISTING MOTOR WITH EARTH
18	VCT	4.0sq	HOISTING MOTOR WITH EARTH
19	VCT	4.0sq	HOISTING MOTOR WITH EARTH
20	VCT	4.0sq	HOISTING MOTOR WITH EARTH

시험대상 전선의 최소 유효단면적	최고전압강하(V)
1.0	3.3
1.5	2.6
2.5	1.6
4.0	1.4
>6.0	1.0

Δ	Δ	Δ	Δ	Δ	Δ	Δ	Δ	Δ	Δ	Δ	Δ	Δ	Δ	Δ	Δ	Δ	Δ	Δ	Δ
DRAWING										ORDER NO.									
DESIGN										DATE									
CHECKED										SCALE									
APPROVED										NONE									
KID										KUC DONG HOIST CO., LTD.									
극동호이스트 주식회사										DWG. NO									
GROUND WIRE SYSTEM										KOC2M-E234									
CABLE #18																			
REVISIONS																			
CHK. APP.																			
DATE																			

1 2 3 4 5 6 7 8 9 10 11 12 13 14 15 16 17 18 19 20

POWER CIRCUIT

TRAVELLING POWER SUPPLY SYSTEM

ADR'S NO.

A1

POWER SOURCE

AC 3Φ 60HZ

SELECTION	VOLTAGE	F11	F12	F13	MCB100	TR10
	220V	3A	3A	33AF/30AT		220/110,120V 60VA
	380V	1A	3A	33AF/15AT		380/110,120V 60VA
	440V	1A	3A	33AF/15AT		440/110,120V 60VA
	460V	1A	3A	33AF/15AT		460/110,120V 60VA
	480V	1A	3A	33AF/15AT		480/110,120V 60VA

CRANE MAKER SCOPE

TRAVELLING POWER SUPPLY SYSTEM

TO: CONTROL CIRCUIT

[NOTE]

1. --- MARKED OWNER SCOPE

2. CRANES HOIST 적용시 CRANE MAKER에서 설치: TLB(M1)

3. MONORAIL을 HOIST 적용시 KUKDONG에서 설치: MHB(M1)

1. 전선의 색상은 다음과 같다.

1) 흑 색 : 고압 및 지류전선

2) 적 색 : 교류제어선

3) 청 색 : 지류제어선

4) 녹색 또는 녹색과 황색 혼용 : 접지

2. 표시등의 색상은 다음과 같다.

1) 적 색 : 비상

2) 황 색 : 비정상

3) 녹색 : 정상

4) 청 색 : 의무

5) 흰색 : 중립

3. 조차 버전의 색상은 다음과 같다.

1) 적 색 : 비상

2) 황 색 : 비정상

3) 청 색 : 의무

4) 흰색, 회색 또는 흑색 : 지정된 의미없음

REVISIONS

DATE

CHECK

APP.

CUSTOMER

DRAWING TITLE

SCALE

APPROVED

CHECKED

DESIGN

DATE

ORDER NO.

DWG. NO

KDC02E001

KUK DONG HOIST CO., LTD.

KDC02E001


NOTE.

1. 전선의 색상은 다음과 같다.
- 1) 흑색 : 교류 및 직류 전원선로
- 2) 적색 : 교류제어선
- 3) 파랑색 : 외부 전원에서 공급되는 인동장치 제어회로
- 4) 녹색 또는 녹색과 황색 혼합 : 접지선

2. CABLE MATERIAL : ┌ KIV OR EQUIVALENT
MIN SIZE : 2.5sq

3. 제어용 전선 : 2.5mm KIV,HIV
4. 제어시 다소 변경 될수있음.
5. 외함 기방구조는 다음과 같을것.



- 1) 외함 개방시 충전부분이 차단되도록 할것.
- 2) 외함 개방후 충전되어있는 부분은 IP2X 이상의 차단 효과가 되어있음




NOTES

1. UPPER LIMIT LS-1(LS-2) 전압 허용 범위 : AC 600V, 75A
2. POWER SOURCE : AC 3 ϕ 220V 60Hz
3. EARTH TERMINAL RESISTANCE : 0.018 Ω

[illegible]



안전보건공단
KOREA OCCUPATIONAL SAFETY & HEALTH AGENCY




NOTE 1. 전선의 색상은 다음과 같다.
1) 흑색 : 교류 및 직류 전원선로
2) 적색 : 교류제어선
3) 파랑색 : 외부 전원에서 공급되는 연동장치 제어회로
4) 녹색 또는 녹색과 황색 혼용 : 접지선
2. CABLE MATERIAL : KIV OR EQUIVALENT
MIN SIZE : 2.5sq
3. 제어용 전선 : 2.5mm KIV,HIV
4. 제어시 다소 변경 될수있음.
5. 외함 기밀구조는 다음과 같을것.
1) 외함 개방시 중전부분이 차단되도록 할것.
2) 외함 개방후 승전되어있는 부분은 IP2X 이상의 직접 접촉 방호가 되어있을것.

NO	DESCRIPTION	SPEC	Q'TY	REMARK
1	CHASSIS PLATE	-	1	아 전 도 금
2	CABLE DUCT	-	1	
3	MAGNET CONTACTOR	DMC22C	2	TRAVERSING
4	E.O.C.R	SS-05	1	TRAVERSING
5	SILICON RECTIFIER	SR-30	1	TRAVERSING
6	TERMINAL BLOCK	25A , 15A	1	TRAVERSING

DRAWING	DESIGN	CHECKED	APPROVED	SCALE	DATE	ORDER NO.
TRAVERSING POWER CONTROL BOX				NONE		
ARRANGEMENT DRAWING						
KUK DONG HOIST CO., LTD.				DWG. NO	KDC2bt22	
DATE	REVISIONS	CHK.	APP.			

KOREA OCCUPATIONAL SAFETY & HEALTH AGENCY



산업재해예방
안전보건공단

KOREA OCCUPATIONAL SAFETY & HEALTH AGENCY

KDC02E23

KDC02E24

KDC02E025

KDC02E026

1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
---	---	---	---	---	---	---	---	---	----	----	----	----	----	----	----	----	----	----	----

ADR'S NO.

NO	DESCRIPTION	SPECIFICATION	Q'TY	REMARK
1	CHASSIS PLATE		1	이 연 도 금
2	CABLE DUCT	-	1	
3	N.F.B	33AF/15AT	1	HOISTING
4	MAGNET CONTACTOR	DMC22C	1	MAIN MAG.
5	MAGNET CONTACTOR	DMC22C	2	HOISTING
6	MAGNET CONTACTOR	DMC22C	2	CREEP HOIST
7	SILICON RECTIFIER	SR-30	1	HOISTING
8	SILICON RECTIFIER	SR-30	1	CREEP HOIST
9	E.O.C.R	SS-30	1	HOISTING
10	E.O.C.R	SS-05	1	CREEP HOIST
11	FUSE	1 A	2	
12	FUSE	3 A	1	
13	TRANSFORMER	220V/110V(120V), 60VA	1	
14	UPPER LIMITER	AC 600V, 75A	1	LS-1,2
15	TERMINAL BLOCK	60A,15A		
16	EARTH TERMINAL	3tx20x50	1	

NOTE 1. 전선의 색상은 다음과 같다.

- 1) 흑색 : 교류 및 직류 전원선
- 2) 적색 : 교류제어선
- 3) 파랑색 : 외부 전원에서 공급되는 연동장치 제어회로
- 4) 녹색 또는 녹색과 황색 혼용 : 접지선

2. CABLE MATERIAL : KIV OR EQUIVALENT



3. 제어용 전선 : 2.5mm KIV,HIV

4. 제막시 다소 변경 될수있음.

5. 외함 개방구조는 다음과 같을것.

1) 외함 개방시 충전부분이 차단되도록 할것.

2) 외함 개방후 충전되어있는 부분은 IP2X 이상의 직접 접촉 방호가 되어있을것.



NOTE


- 1. UPPER LIMIT LS-1,LS-2의 접점 허용 전류 용량 : AC 600V, 75A
- 2. POWER SOURCE : AC 3 ϕ 380V 60Hz
- 3. EARTH TERMINAL RESISTANCE : 0.018 Ω





KOREA OCCUPATIONAL SAFETY & HEALTH AGENCY

DRAWING		DESIGN	CHECKED	APPROVED	SCALE	DATE	ORDER NO.
CREEP HOIST CONTROL BOX					NONE		
ARRANGEMENT DRAWING		국동호이스트 주식회사			DWG. NO	KDC2BA31	
		KUK DONG HOIST CO., LTD.					
CUSTOMER							
DRAWING TITLE							
REVISIONS							
DATE							
CHK.							
APP.							

1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
ADR'S NO.																			




안전보건공단
KOREA OCCUPATIONAL SAFETY & HEALTH AGENCY



NOTE 1. 전선의 색상은 다음과 같다.
1) 흑색 : 교류 및 직류 전원선로 5) 청색 : 직류 제어선로
2) 적색 : 교류제어선
3) 주황색 : 외부 전원에서 공급되는 연동장치 제어회로
4) 녹색 또는 녹색과 황색 혼용 : 접지선
2. CABLE MATERIAL : KIV OR EQUIVALENT
MIN SIZE : 2.5sq
3. 제어용 전선 : 2.5mm KIV,HIV
4. 제작시 다소 변경 될수있음.
5. 외함 개방구조는 다음과 같을것.
1) 외함 개방시 승전부분이 차단되도록 할것.
2) 외함 개방후 승전되어있는 부분은 IP2X 이상의 직접 접촉 방호가 되어있을것.

NO	DESCRIPTION	SPEC	Q'TY	REMARK
1	CHASSIS PLATE	-	1	아 연 도 급
2	CABLE DUCT	-	1	
3	MAGNET CONTACTOR	DMC22C	2	TRAVERSING
4	E.O.C.R	SS-05	1	TRAVERSING
5	SILICON RECTIFIER	SR-30	1	TRAVERSING
6	TERMINAL BLOCK	25A , 15A	1	TRAVERSING

A																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																															</
---	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	----



KDC02E31

POWER CIRCUIT

HOISTING MOTION


CREEP HOIST MOTION

ADR'S NO.

B1


SPECIFICATION SYMBOLS	HOISTING POWER HOIST	HOISTING MOTOR	DC MAG. BRAKE	DC MAG. BREAKER	TRANSFORMER	FUSE	MAIN MAGNET	MAGNET CONTACTOR	UPPER LIMIT	ELECTRIC OVER CURRENT RELAY	SILICON RECTIFIER	LOAD LIMITER	CABLE
DESCRIPTION	1.5TON AC 3PH 380V 60Hz	IM 10 3.7KW X 4P 0.4KWx4P	IM 11	DB10, 11	TR 1 380V/200V, 60VA	F1, F12 1A 3A	M1 DMC22C	M101, M102 DMC22C	LS-I, LS-II AC 600V 75A	EOCR100 SS-05	RF100 SR-30	LDL-100 VFCT 4.0sqx4c	C20-01
SELECTION MAKER		KUKDONG		LS	SHINHAN	-		DONG-A	KUKDONG	ASECO			DONGIL
CUSTOMER													
DRAWING TITLE													
REVISIONS													
DATE													
CHK.													
APP.													
DWG. NO													KDC02E31
ORDER NO.													

KOREA OCCUPATIONAL SAFETY & HEALTH AGENCY



SPECIFICATION SYMBOLS		TRAVERSING MOTOR		DC MAG. BRAKE		MAGNET CONTACTOR		SILICON RECTIFIER		ELECTRIC OVER CURRENT RELAY		LIMIT SWITCH	
DESCRIPTION		IM 30		DB 30		M301, M302		RF 300		EOCR 300		LS-301, LS-302	
		0.75KW x 4P AC 3PH 380V 60Hz		DC 100V		DMC22C		SR-30 AC 220V/DC 100V		SS-05		HY - W904	
		0.5KW x 6P AC 3PH 380V 60Hz		DC 100V		DMC22C		SR-30 AC 220V/DC 100V		SS-05		HY - W904	
SELECTION MAKER		KUKDONG		DONG-A		ASECO							
CUSTOMER				DRAWING		DESIGN		CHECKED		APPROVED		SCALE	
DRAWING TITLE		TRAVERSING POWER CONTROL CIRCUIT										DATE	
REVISIONS													
DATE													
CHK. APP.													
DWG. NO		KDC02E33											
ORDER NO.													


산업재해예방
안전보건공단



KDC02E33


KOREA OCCUPATIONAL SAFETY & HEALTH AGENCY

1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
POWER CIRCUIT																			
TRAVERSING MOTION																			
ADR'S NO.																			C2



MK	DATE	REVISIONS				CHK.	APP.	CUSTOMER	TRAVERSING POWER CONTROL CIRCUIT								
		DRAWING TITLE															
									DIAGRAM								
DRAWING		DESIGN		CHECKED		APPROVED		SCALE		DATE		ORDER NO.					
								NONE									
극동호이스트 주식회사 KUK DONG HOIST CO., LTD.														DWG. NO		KDC02E34	

산업재해예방
안전보건공단



KDC02E34

KOREA OCCUPATIONAL SAFETY & HEALTH AGENCY

[illegible]

[illegible]

NO	DESCRIPTION	SPECIFICATION	Q'TY	REMARK
1	CHASSIS PLATE		1	아 연 도 금
2	CABLE DUCT	-	1	
3	N.F.B	33AF/15AT	1	HOISTING
4	MAGNET CONTACTOR	DMC22C	1	MAIN MAG.
5	MAGNET CONTACTOR	DMC22C	2	HOISTING
6	MAGNET CONTACTOR	DMC22C	2	CREEP HOIST
7	SILICON RECTIFIER	SR-30	1	HOISTING
8	SILICON RECTIFIER	SR-30	1	CREEP HOIST
9	E.O.C.R	SS-30	1	HOISTING
10	E.O.C.R	SS-05	1	CREEP HOIST
11	FUSE	1 A	2	
12	FUSE	3 A	1	
13	TRANSFORMER	220V/110V(120V), 60VA	1	
14	UPPER LIMITER	AC 600V, 75A	1	LS-1,2
15	TERMINAL BLOCK	60A,15A		
16	EARTH TERMINAL	3tx20x50	1	

NOTE 1. 전선의 색상은 다음과 같다.

1) 흑색 : 교류 및 직류 전원선으로 5) 정색 : 직류 제어선으로

2) 적색 : 교류제어선

3) 주황색 : 외부 전원에서 공급되는 연동장치 제어회로

4) 녹색 또는 녹색과 황색 혼용 : 접지선

2. CABLE MATERIAL : KIV OR EQUIVALENT


3. 제어용 전선 : 2.5mm KIV,HIV

4. 제하시 다스 변경 필수있음.

5. 외함 개방구조는 다음과 같을것.

1) 외함 개방시 중전부분이 차단되도록 할것.

2) 외함 개방후 중전되어있는 부분은 IP2X 이상의 직접 접촉 방호가 되어있을것.



NOTE

1. UPPER LIMIT LS-1,LS-2의 접점 허용전류 용량 : AC 600V, 75A


2. POWER SOURCE : AC 3φ 440V 60Hz

3. EARTH TERMINAL RESISTANCE : 0.018Ω




DRAWING	DESIGN	CHECKED	APPROVED	SCALE	DATE	ORDER NO.
CREEP HOIST CONTROL BOX						
ARRANGEMENT DRAWING						
KID KUK DONG HOIST CO., LTD.						KDC2BA41
DATE	REVISIONS	CHK.	APP.			

1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
ADR'S NO.																			



신업재해예방
안전보건공단
 KOREA OCCUPATIONAL SAFETY & HEALTH AGENCY



- NOTE** 1. 전선의 색상은 다음과 같다.
 1) 흑색 : 교류 및 직류 전원선
 2) 적색 : 교류제어선
 3) 주황색 : 외부 전원에서 공급되는 전동장치 제어회로
 4) 녹색 또는 녹색과 황색 혼용 : 접지선
 2. CABLE MATERIAL : KIV OR EQUIVALENT
 MIN SIZE : 2.5sq
 3. 제어용 전선 : 2.5mm KIV,HIV
 4. 제라시 다스 변경 필수있음.
 5. 외함 개방구조는 다음과 같을것.
 1) 외함 개방시 충전부분이 차단되도록 할것.
 2) 외함 개방후 충전되어있는 부분은 IP2X 이상의 격전 접촉 접촉 방호가 되어있을것.

NO	DESCRIPTION	SPEC	Q'TY	REMARK
1	CHASSIS PLATE	-	1	아 전 도 금
2	CABLE DUCT	-	1	
3	MAGNET CONTACTOR	DMC22C	2	TRAVERSING
4	E.O.C.R	SS-05	1	TRAVERSING
5	SILICON RECTIFIER	SR-30	1	TRAVERSING
6	TERMINAL BLOCK	25A , 15A	1	TRAVERSING


DRAWING	DESIGN	CHECKED	APPROVED	SCALE	DATE	ORDER NO.
TRAVERSING POWER CONTROL BOX						
ARRANGEMENT DRAWING						
 KUDONGHOIST 주식회사 KUK DONG HOIST CO., LTD.						
DATE	REVISIONS	CHK.	APP.	DWG. NO	KDC2bt42	

192.168.11.76 / 2014-04-19 09:50:43

[illegible]

192.168.11.76 / 2014-04-19 09:50:43

[illegible]



NO	DESCRIPTION	SPECIFICATION	Q'TY	REMARK
1	CHASSIS PLATE		1	아 연 도 금
2	CABLE DUCT	-	1	
3	N.F.B	33AF/15AT	1	HOISTING
4	MAGNET CONTACTOR	DMC22C	1	MAIN MAG.
5	MAGNET CONTACTOR	DMC22C	2	HOISTING
6	MAGNET CONTACTOR	DMC22C	2	CREEP HOIST
7	SILICON RECTIFIER	SR-30	1	HOISTING
8	SILICON RECTIFIER	SR-30	1	CREEP HOIST
9	E.O.C.R	SS-30	1	HOISTING
10	E.O.C.R	SS-05	1	CREEP HOIST
11	FUSE	1 A	2	
12	FUSE	3 A	1	
13	TRANSFORMER	220V/110V(120V), 60VA	1	
14	UPPER LIMITER	AC 600V, 75A	1	LS-1,2
15	TERMINAL BLOCK	60A,15A		
16	EARTH TERMINAL	3tx20x50	1	

NOTE 1. 전선의 색상은 다음과 같다.

1) 흑색 : 교류 및 직류 전원선으로 5) 정색 : 직류 제어선으로

2) 황색 : 교류 제어선

3) 주황색 : 외부 전원에서 공급되는 연동장치 제어회로

4) 녹색 또는 녹색과 황색 혼용 : 접지선

2. CABLE MATERIAL : KIV OR EQUIVALENT


3. 제어용 전선 : 2.5mm KIV,HIV

4. 접착시 다소 변경 될수있음.

5. 외함 기방구조는 다음과 같을것.

1) 외함 기방시 중전부분이 차단되도록 할것.

2) 외함 기방후 중전되어있는 부분은 IP2X 이상의 직접 접촉 방호가 되어있을것.



NOTE

1. UPPER LIMIT LS-1,LS-2의 직접 허용 전류 용량 : AC 600V, 75A

2. POWER SOURCE : AC 3φ 460V 60Hz


3. EARTH TERMINAL RESISTANCE : 0.018Ω





KOREA OCCUPATIONAL SAFETY & HEALTH AGENCY

DRAWING	DESIGN	CHECKED	APPROVED	SCALE	DATE	ORDER NO.
CREEP HOIST CONTROL BOX						
ARRANGEMENT DRAWING						
CUSTOMER						
DRAWING TITLE						
REVISIONS						
DATE	CHK.	APP.				
국동호이스트 주식회사 KUK DONG HOIST CO., LTD.						KDC2BA51

1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
ADR'S NO.																			



산업재해예방
안전보건공단
KOREA OCCUPATIONAL SAFETY & HEALTH AGENCY



NOTE 1. 전선의 색상은 다음과 같다.
1) 흑색 : 교류 및 직류 전원선로 5) 적색 : 외부 제어선로
2) 적색 : 교류 제어선
3) 주황색 : 외부 전원에서 공급되는 연동장치 제어회로
4) 녹색 또는 녹색과 황색 혼용 : 접지선
2. CABLE MATERIAL : KIV OR EQUIVALENT
MIN SIZE : 2.5sq
3. 제어용 전선 : 2.5mm KIV,HIV
4. 제어시 다소 변경 될수있음.
5. 외함 개방구조는 다음과 같을것.
1) 외함 개방시 중전부분이 차단되도록 할것.
2) 외함 개방후 중전되어있는 부분은 IP2X 이상의 직접 접촉 방호가 되어있을것.

NO	DESCRIPTION	SPEC	Q'TY	REMARK
1	CHASSIS PLATE	-	1	아 연 도 금
2	CABLE DUCT	-	1	
3	MAGNET CONTACTOR	DMC22C	2	TRAVERSING
4	E.O.C.R	SS-05	1	TRAVERSING
5	SILICON RECTIFIER	SR-30	1	TRAVERSING
6	TERMINAL BLOCK	25A , 15A	1	TRAVERSING

DRAWING	DESIGN	CHECKED	APPROVED	SCALE	DATE	ORDER NO.
				NONE		
국동호이스트 주식회사 KUK DONG HOIST CO., LTD.						
KDC2bt52						

The diagram illustrates the electrical control system for a monorail hoist, divided into two main sections: **POWER CIRCUIT** and **CONTROL CIRCUIT**.

POWER CIRCUIT:

- Hoisting Motion:** Powered by a 20-ton AC 3PH 460V 60Hz supply. It includes a main switch (MCCB100), a fuse (F1), and a contactor (C1). The motor (IM10) is protected by a thermal relay (TR1) and a DC magnetic brake (DB10).
- Creeping Motion:** Powered by a 4.0sqx3c supply. It includes a fuse (F2), a contactor (C2), and a motor (IM11) with a DC magnetic brake (DB11).

CONTROL CIRCUIT:

- Hoisting Motion:** Controlled by a stop button (S1) and a limit switch (LS-1). The motor (IM10) is started by a start button (S2) through a thermal relay (TR1).
- Creeping Motion:** Controlled by a stop button (S3) and a limit switch (LS-2). The motor (IM11) is started by a start button (S4) through a thermal relay (TR2).

Legend:

- HOISTING POWER:** 20TON AC 3PH 460V 60Hz
- HOISTING MOTOR:** IM 10
- HOISTING POWER:** 4.0sqx3c
- HOISTING MOTOR:** IM 11

[illegible]


Technical drawing of a traversing motor (IM 30) with a circular symbol and a table of specifications.

IM 30

TRAVERSING MOTOR

SPECIFICATION	SYMBOLS	DESCRIPTION	SELECTION
TRA	705V	0.75KW	0.5KW x
		0.60V	

[illegible]





KDC02E056


ADR'S NO.

NO	DESCRIPTION	SPECIFICATION	Q'TY	REMARK
1	CHASSIS PLATE		1	아 연 도 금
2	CABLE DUCT	-	1	
3	N.F.B	33AF/15AT	1	HOISTING
4	MAGNET CONTACTOR	DMC22C	1	MAIN MAG.
5	MAGNET CONTACTOR	DMC22C	2	HOISTING
6	MAGNET CONTACTOR	DMC22C	2	CREEP HOIST
7	SILICON RECTIFIER	SR-30	1	HOISTING
8	SILICON RECTIFIER	SR-30	1	CREEP HOIST
9	E.O.C.R	SS-30	1	HOISTING
10	E.O.C.R	SS-05	1	CREEP HOIST
11	FUSE	1 A	2	
12	FUSE	3 A	1	
13	TRANSFORMER	220V/110V(120V), 60VA	1	
14	UPPER LIMITER	AC 600V, 75A	1	LS-1,2
15	TERMINAL BLOCK	60A,15A		
16	EARTH TERMINAL	3tx20x50	1	


NOTE 1. 전선의 색상은 다음과 같다.
 1) 흑색 : 교류 및 직류 전원선로
 2) 적색 : 교류제어선
 3) 주황색 : 외부 전원에서 공급되는 연동장치 제어회로
 4) 녹색 또는 녹색과 황색 혼용 : 접지선
 2. CABLE MATERIAL : KIV OR EQUIVALENT
 MIN SIZE : 2.5sq
 3. 제어용 전선 : 2.5mm KIV,HIV
 4. 제하시 디스플레이 필수있음.
 5. 외함 개방구조는 다음과 같을것.
 1) 외함 개방시 충전부분이 차단되도록 할것.
 2) 외함 개방후 충전되어있는 부분은 IP2X 이상의 직접 접촉 방호가 되어있을것.



NOTE
 1. UPPER LIMIT LS-1,LS-2의 전원 허용 전류 용량 : AC 600V, 75A
 2. POWER SOURCE : AC, 3φ 480V 60Hz
 3. EARTH TERMINAL RESISTANCE : 0.018Ω



DRAWING		DESIGN	CHECKED	APPROVED	SCALE	DATE	ORDER NO.
CREEP HOIST CONTROL BOX					NONE		
ARRANGEMENT DRAWING		KUK DONG HOIST CO., LTD.			DWG. NO	KDC2BA61	
CUSTOMER							
DRAWING TITLE							
DATE	REVISIONS	CHK.	APP.				
1							



NOTE.


1. 전선의 색상은 다음과 같다.
- 1) 흑색 : 교류 및 직류 전원선
- 2) 적색 : 교류제어선
- 3) 파랑색 : 외부 전원에서 공급되는 연동장치 제어회로
- 4) 녹색 또는 녹색과 황색 혼합 : 접지선

2. CABLE MATERIAL : ┌ KIV OR EQUIVALENT
└ MIN SIZE : 2.5sq

3. 제어용 전선 : 2.5mm KIV,HIV
4. 제막시 다소 변형 될수있음.
5. 외함 개방구조는 다음과 같을것.

- 1) 외함 개방시 중전부분이 차단되도록 할것.
- 2) 외함 개방후 응전되어있는 부분은 IP2X 이상의 차단 전압 방호가 되어

[illegible]



KDC02E62

1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
POWER CIRCUIT																			
TRAVERSING MOTION																			
ADR'S NO.																			
C1																			

TSB

4.0sq x 4c

(B1/19) (B1/19) (B1/19)

E R1 S1 T1

T101

R101

M301

M302

CT

(A5/06) (A5/02)

EOR 300

(A5/06) (A5/06)

E U301 V301 W301 X301

IM30

TRAVERSING MOTOR

VCT 4.0sqx4c+2.5sqx3c

DB30

DC.MAG.BRAKE

RF300

N301 P301

SPECIFICATION SYMBOLS	DESCRIPTION	TRAVERSING MOTOR	DC MAG' BRAKE	MAGNET CONTACTOR	SILICON RECTIFIER	ELECTRIC OVER CURRENT RELAY	LIMIT SWITCH
IM 30	0.75KW x 4P AC 3PH 480V 60Hz	IM 30	DB 30	M301, M302	RF 300	EOCR 300	LS-301, LS-302
480V	0.5KW x 6P AC 3PH 480V 60Hz		DC 100V	DMC22C		SS-05	HY - W904
			DC 100V	DMC22C		SS-05	HY - W904

SELECTION	MAKER	DONG-A	ASECO

CUSTOMER	DRAWING	DESIGN	CHECKED	APPROVED	SCALE	DATE	ORDER NO.

TRAVERSING POWER CONTROL CIRCUIT	DIAGRAM

DATE	REVISIONS	CHK.	APP.

KDC02E63

한국산업안전보건공단

안전보건공단

산업재해예방


한국동호시스템 주식회사

KUK DONG HOIST CO., LTD.

DWG. NO

KDC02E63

KOREA OCCUPATIONAL SAFETY & HEALTH AGENCY



산업재해예방
안전보건공단

KOREA OCCUPATIONAL SAFETY & HEALTH AGENCY

[illegible]

1

2

3

4

5

6

7

8

9

10

11

12

13

14

15

16

17

18

19

20

ADR'S NO.

C2

POWER CIRCUIT

TRaversing MOTION

TRaversing MOTION

TRaversing MOTOR

SPECIFICATION	SYMBOLS	DESCRIPTION	MAGNET CONTACTOR	SILICON RECTIFIER	ELECTRIC OVER CURRENT RELAY	TRANSFORMER
480V	IM 30	0.5/0.25KW/12P AC 3PH 480V 60Hz	M301, M302, M303	RF 300	EOCR 301,302	TR300
480V	IM 31	0.8/0.4KW/4/8P AC 3PH 480V 60Hz	DMC22C	SR-30	SS-05	AC480/220V, 300VA
			DMC22C	SR-30	SS-05	AC480/220V, 300VA

TRaversing MOTOR

TRaversing MOTOR

SPECIFICATION	SYMBOLS	DESCRIPTION	MAGNET CONTACTOR	SILICON RECTIFIER	ELECTRIC OVER CURRENT RELAY	TRANSFORMER
480V	IM 30	0.5/0.25KW/12P AC 3PH 480V 60Hz	M301, M302, M303	RF 300	EOCR 301,302	TR300
480V	IM 31	0.8/0.4KW/4/8P AC 3PH 480V 60Hz	DMC22C	SR-30	SS-05	AC480/220V, 300VA
			DMC22C	SR-30	SS-05	AC480/220V, 300VA

TRaversing MOTOR

TRaversing MOTOR

SPECIFICATION	SYMBOLS	DESCRIPTION	MAGNET CONTACTOR	SILICON RECTIFIER	ELECTRIC OVER CURRENT RELAY	TRANSFORMER
480V	IM 30	0.5/0.25KW/12P AC 3PH 480V 60Hz	M301, M302, M303	RF 300	EOCR 301,302	TR300
480V	IM 31	0.8/0.4KW/4/8P AC 3PH 480V 60Hz	DMC22C	SR-30	SS-05	AC480/220V, 300VA
			DMC22C	SR-30	SS-05	AC480/220V, 300VA

TRaversing MOTOR

TRaversing MOTOR

SPECIFICATION	SYMBOLS	DESCRIPTION	MAGNET CONTACTOR	SILICON RECTIFIER	ELECTRIC OVER CURRENT RELAY	TRANSFORMER
480V	IM 30	0.5/0.25KW/12P AC 3PH 480V 60Hz	M301, M302, M303	RF 300	EOCR 301,302	TR300
480V	IM 31	0.8/0.4KW/4/8P AC 3PH 480V 60Hz	DMC22C	SR-30	SS-05	AC480/220V, 300VA
			DMC22C	SR-30	SS-05	AC480/220V, 300VA

TRaversing MOTOR

TRaversing MOTOR

SPECIFICATION	SYMBOLS	DESCRIPTION	MAGNET CONTACTOR	SILICON RECTIFIER	ELECTRIC OVER CURRENT RELAY	TRANSFORMER
480V	IM 30	0.5/0.25KW/12P AC 3PH 480V 60Hz	M301, M302, M303	RF 300	EOCR 301,302	TR300
480V	IM 31	0.8/0.4KW/4/8P AC 3PH 480V 60Hz	DMC22C	SR-30	SS-05	AC480/220V, 300VA
			DMC22C	SR-30	SS-05	AC480/220V, 300VA

TRaversing MOTOR


TRaversing MOTOR

SPECIFICATION	SYMBOLS	DESCRIPTION	MAGNET CONTACTOR	SILICON RECTIFIER	ELECTRIC OVER CURRENT RELAY	TRANSFORMER
480V	IM 30	0.5/0.25KW/12P AC 3PH 480V 60Hz	M301, M302, M303	RF 300	EOCR 301,302	TR300
480V	IM 31	0.8/0.4KW/4/8P AC 3PH 480V 60Hz	DMC22C	SR-30	SS-05	AC480/220V, 300VA
			DMC22C	SR-30	SS-05	AC480/220V, 300VA

TRaversing MOTOR

TRaversing MOTOR

SPECIFICATION	SYMBOLS	DESCRIPTION	MAGNET CONTACTOR	SILICON RECTIFIER	ELECTRIC OVER CURRENT RELAY	TRANSFORMER
4						




2	수량	SS400		1			
1	T/S BOX	PUR		1			
NO.	DESCRIPTION	MTL	SUB QTY	TOTAL QTY	SUB WEIGHT(kg)	TOTAL	REMARKS.
PROJECT			DATE		DIM mm		
TITLE			SCALE		PROJECTION		
T/S CONTROL PANEL(INVERTER)			A3/3		3rd		
DRAWN	DESIGNED	CHECKED	APPROVED	REF. DRAWING			
 KUDONGHOIST 주식회사 KUK DONG HOIST CO., LTD.			SHEET No.		DWG No.		
					KDO2E1001		



10	EARTH BUS BAR	PUR	1		
9	DUCT	PUR	1		
8	TERMINAL BLOCK	PUR	1		
7	INVERTER	PUR	1		
6	TR	PUR	1		
5	RELAY & SOCKET	PUR	1		
4	RF	PUR	1		
3	MC	PUR	1		
2	MOCB	PUR	1		
1					

The diagram illustrates a motor control circuit. Key components and their connections are as follows:

- Power Supply:** A transformer (T2000) is connected to a bridge rectifier (BR300). The rectifier's output is filtered by a capacitor (M301) and connected to the positive terminal of the motor (IM30).
- Motor:** The motor (IM30) is connected to the positive terminal of the power supply and the output of the inverter (INV300).
- Control Circuit:** A MOSFET (MOS3300) is used to drive the inverter (INV300). The MOSFET's gate is connected to a potentiometer (POT300) and a feedback capacitor (M301).
- Feedback Loop:** The feedback capacitor (M301) is connected between the MOSFET's gate and the inverter's output.
- Labels and Notes:**
 - Labels include: MOS3300, INV300, BR300, T2000, M301, IM30, POT300, and a note about the motor's specifications: "TRAVELING MOTOR DB.30 100W 100V 50/60Hz".
 - A note at the bottom right states: "E. MOTOR 100W 100V 50/60Hz".




1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
TRAVERSING MOTION										CONTROL CIRCUIT DIAGRAM									
POWER CIRCUIT DIAGRAM										HIGH SPEED									
BRAKE										WEST									
EAST										ORDER NO.									




SPECIFICATION SYMBOLS	DESCRIPTION	TRAVERSING POWER	TRAVERSING MOTOR	DC MAG. BRAKE	NO FUSE BREAKER	TRANSFORMER	BRAKE MAGNET	CONTROL RELAY	INVERTER	SILICON RECTIFIER					
		AC 3PH 220V 60Hz	IM 30.5T	DB30.31	MCCB300	TR 300	M301	CR301,302,303	INV300	RF300					
		AC 3PH 380(440,460,480)W 60Hz	Q.75KW x 4P	DC 100V	DBE-33AF/15AT	220/220V,300VA	DM-22C	MINI 4a4b(Coil AC110V)	SVO37IGSA-2	SR-30					
			0.75KW x 4P	DC 100V	DBE-33AF/10AT	380(440,460,480)/220V,300VA	DM-22C	MINI 4a4b(Coil AC110V)	SVO37IGSA-4	SR-30					
SELECTION MAKER									LS	ASAN					
KUK DONG HOIST															
CUSTOMER					INVERTER CONTROL					ORDER NO.					
DRAWING TITLE					TRAVERSING POWER & CONTROL CIRCUIT					DATE					
REVISIONS					DIAGRAM					DWG. NO					
DATE															
CHK.															
APP.															
KUK DONG HOIST CO., LTD.											KD02E1005				

1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20.
EM, STOP										CONTROL CIRCUIT									
LOAD LIMIT										UPPER LIMIT CREEP UP UP DOWN EAST WEST									
ADP'S NO.										AS									



SPECIFICATION SYMBOLS DESCRIPTION		PENDANT P.B.S/W		LOAD LIMITER		LIMIT SWITCH	
LS-1		E.S.B		JDL-70		LS-301,302	
AC 600V 75A		250V 3A		JDL-70		HY - W904	
AC 600V 3A		250V 3A		JDL-70		HY - W904	
MAKER		KUKOONG		JUNGHO		HANYOUNG	
DRAWING		DESIGN		APPROVED		DATE	
MAIN POWER 2 & CONTROL CIRCUIT		NONE		DWG. NO		KDC2E001	
CUSTOMER		KUK DONG HOIST CO., LTD.		ORDER NO.			
DRAWING TITLE		KUK DONG HOIST CO., LTD.					
REVISIONS		CHK. APP.					
DATE							




구분	색상	조작버튼	표시등
적색	비상	비상	비상
황색	비정상	비정상	비정상
녹색	정상	정상	정상
청색	의무	의무	의무
흰색, 회색 - 흑색	지정된의미없음		기타

* MATERIAL : POLYCARBOBATE(PLASTIC)


* BODY COLOR : YELLOW, BLACK

* IP : 55 이상

NO	SYMBOL	TYPE	SPEC.	COLOR
1	E.B.S	PUSH LOCK TURN RESET TYPE	250VAC x 6A	RED
2	SPARE			
3	상	1PUSH BUTTON 2STEP		BLACK
4	하	1PUSH BUTTON 2STEP		
5	동(전)	1PUSH BUTTON 1STEP		
6	서(후)	1PUSH BUTTON 1STEP		
7	보조 와이어	ø 2.0		



CUSTOMER	DRAWING	DESIGN	CHECKED	APPROVED	SCALE	DATE
DRAWING TITLE	PENDANT PUSH BUTTON SWITCH					
APP.	LAY OUT					
CHK.						
REVISIONS						
DATE						
MK						
	KUK DONG HOIST CO., LTD. DWG. NO					



색상	구분	조작버튼	표시등
적색		비상	비상
황색		비정상	비정상
녹색		정상	정상
청색		의무	의무
흰색, 회색 - 흑색		지정된의미없음	기타


* MATERIAL : POLYCARBONATE(PLASTIC)

* BODY COLOR : YELLOW, BLACK

* IP : 55 이상

NO	SYMBOL	TYPE	SPEC.	COLOR
1	E.B.S	PUSH LOCK TURN RESET TYPE		RED
2	SPARE			
3	상	1PUSH BUTTON 2STEP	250VAC x 6A	BLACK
4	하	1PUSH BUTTON 2STEP		
5	통 (좌)	1PUSH BUTTON 1STEP		
6	서 (우)	1PUSH BUTTON 1STEP		
7	남 (전)	1PUSH BUTTON 1STEP		
8	북 (후)	1PUSH BUTTON 1STEP		
9	보조 WIRE	Ø 2.0		

DRAWING	DESIGN	CHECKED	APPROVED	SCALE	DATE
PENDANT PUSH BUTTON SWITCH					
LAY OUT					
KUK DONG HOIST CO., LTD.					
DWG. NO					




* MATERIAL : POLYCARBOBATE(PLASTIC)

* BODY COLOR : YELLOW, BLACK

* IP : 55 이상

NO	SYMBOL	TYPE	SPEC.	COLOR
1	E.B.S	PUSH LOCK TURN RESET TYPE	250VAC x 6A	RED
2	SPARE			BLACK
3	상	1PUSH BUTTON 2STEP		
4	하	1PUSH BUTTON 2STEP		
5	동(전)	1PUSH BUTTON 2STEP		
6	서(후)	1PUSH BUTTON 2STEP		
7	보조 와이어	ø 2.0		

[illegible]



구분 색상	구분 색상	조각버튼	표시등
회색	회색	비상	비상
황색	황색	비정상	비정상
녹색	녹색	정상	정상
청색	청색	어무	어무
흰색, 회색 - 흑색	흰색, 회색 - 흑색	지정된미있음	기타

* MATERIAL : POLYCARBOBATE(PLASTIC)

* BODY COLOR : YELLOW, BLACK

* 1P : 55 이상 *

NO	SYMBOL	TYPE	SPEC.	COLOR
1	E.B.S	PUSH LOCK TURN RESET TYPE	250VAC x 6A	RED
2	SPARE			BLACK
3	상	1PUSH BUTTON 2STEP		
4	하	1PUSH BUTTON 2STEP		
5	등 (좌)	1PUSH BUTTON 2STEP		
6	서 (우)	1PUSH BUTTON 2STEP		
7	남 (전)	1PUSH BUTTON 1STEP		
8	북 (후)	1PUSH BUTTON 1STEP		
9	보조 WIRE	∅ 2.0		

					CUSTOMER		DRAWING	DESIGN	CHECKED	APPROVED	SCALE	DATE
A						PENDANT PUSH BUTTON SWITCH LAY OUT						
A												
A												
MK	DATE	REVISIONS	CHK.	APP.		KUK DONG HOIST CO., LTD.				DWG. NO		

IV. 참 고 도 서


- 1 LOAD LIMITER 권고 SETTING 치
- 2 E.O.C.R 권고 SETTING치
- 3 MOTOR DATA SHEET
- 4 WIRE ROPE 성적서
- 5 SUB VENDOR LIST
- 6 HOIST 취급설명서
- 7 과부하 방지장치 취급설명서
- 8 INVERTER 취급설명서



산업재해예방

안전보건공단

KOREA OCCUPATIONAL SAFETY & HEALTH AGENCY



LOAD LIMITER 권고 SETTING치

* POWER SOURCE : AC 3Φ 220V 60Hz

극동호이스트(주)

HOIST	MOTOR 용량	LOAD LIMITER 권고 SETTING치			LOAD CURRENT		C.T MODEL	연결단자 NO	C.T 용량	REMARK
		LOAD CURRENT	ADJ START TIME	SHOCK TIME	100%	110%				
C1 TON	2.4KW x 4P	110%	1 SEC	1 SEC	10 A	11.2 A	CT-2	K-K1, L-L1	5 V.A	
	0.4KW x 4P	110%	1 SEC	1 SEC	2.7 A	3.1 A	CT-1	K-K1, L-L1	5 V.A	
C1.5 TON	3.7KW x 4P	110%	1 SEC	1 SEC	16.0 A	17.4 A	CT-2	K-K1, L-L1	5 V.A	
	0.4KW x 4P	110%	1 SEC	1 SEC	2.7 A	3.1 A	CT-1	K-K1, L-L1	5 V.A	
C2.8 TON	5.0KW x 4P	110%	1 SEC	1 SEC	22.8 A	24.2 A	CT-2	K-K1, L-L1	5 V.A	
	1.5KW x 4P	110%	1 SEC	1 SEC	7.3 A	8.3 A	CT-1	K-K1, L-L1	5 V.A	
C3 TON	5.5KW x 4P	110%	1 SEC	1 SEC	22.8 A	24.3 A	CT-2	K-K1, L-L1	5 V.A	
	1.5KW x 4P	110%	1 SEC	1 SEC	7.3 A	8.3 A	CT-1	K-K1, L-L1	5 V.A	
C5 TON	5.5KW x 6P	110%	1 SEC	1 SEC	28.2 A	30.1 A	CT-2	K-K1, L-L1	5 V.A	
	1.0KW x 6P	110%	1 SEC	1 SEC	6.7 A	8.1 A	CT-1	K-K1, L-L1	5 V.A	
C7.5 TON	5.5KW x 6P	110%	1 SEC	1 SEC	28.2 A	30.1 A	CT-2	K-K1, L-L1	5 V.A	
	1.0KW x 6P	110%	1 SEC	1 SEC	6.7 A	8.1 A	CT-1	K-K1, L-L1	5 V.A	
C10 TON	9.0KW x 8P	110%	1 SEC	1 SEC	45.0 A	49.1 A	CT-2	K-K1, L-L1	5 V.A	
	1.1KW x 8P	110%	1 SEC	1 SEC	8.0 A	9.6 A	CT-2	K-K1, L-L1	5 V.A	

NOTE

1. 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

LOAD LIMITER 권고 SETTING치

* POWER SOURCE : AC 3Φ 380V 60Hz

극동호이스트(주)

HOIST	MOTOR 용량	LOAD LIMITER 권고 SETTING치			LOAD CURRENT		C.T MODEL	연결단자 NO	C.T 용량	REMARK
		LOAD CURRENT	ADJ	SHOCK TIME	100%	110%				
C1 TON	2.4KW x 4P	110%	1 SEC	1 SEC	5.8 A	6.3 A	CT-2	K-K1, L-L1	5 V.A	
	0.4KW x 4P	110%	1 SEC	1 SEC	1.6 A	2.1 A	CT-1	K-K1, L-L1	5 V.A	
	3.7KW x 4P	110%	1 SEC	1 SEC	9.3 A	11.3 A	CT-2	K-K1, L-L1	5 V.A	
	0.4KW x 4P	110%	1 SEC	1 SEC	1.6 A	2.1 A	CT-1	K-K1, L-L1	5 V.A	
C2.8 TON	5.0KW x 4P	110%	1 SEC	1 SEC	12.2 A	13.6 A	CT-2	K-K1, L-L1	5 V.A	
	1.5KW x 4P	110%	1 SEC	1 SEC	4.2 A	5.4 A	CT-1	K-K1, L-L1	5 V.A	
	5.5KW x 4P	110%	1 SEC	1 SEC	12.2 A	13.6 A	CT-2	K-K1, L-L1	5 V.A	
	1.5KW x 4P	110%	1 SEC	1 SEC	4.2 A	5.4 A	CT-1	K-K1, L-L1	5 V.A	
C3 TON	5.5KW x 6P	110%	1 SEC	1 SEC	16.3 A	17.8 A	CT-2	K-K1, L-L1	5 V.A	
	1.0KW x 6P	110%	1 SEC	1 SEC	3.9 A	5.3 A	CT-1	K-K1, L-L1	5 V.A	
	5.5KW x 6P	110%	1 SEC	1 SEC	16.3 A	17.8 A	CT-2	K-K1, L-L1	5 V.A	
	1.0KW x 6P	110%	1 SEC	1 SEC	3.9 A	5.3 A	CT-1	K-K1, L-L1	5 V.A	
C7.5 TON	9.0KW x 8P	110%	1 SEC	1 SEC	26.0 A	28.6 A	CT-2	K-K1, L-L1	5 V.A	
	1.1KW x 8P	110%	1 SEC	1 SEC	4.6 A	6.1 A	CT-2	K-K1, L-L1	5 V.A	
	9.0KW x 8P	110%	1 SEC	1 SEC	26.0 A	28.6 A	CT-2	K-K1, L-L1	5 V.A	
	1.1KW x 8P	110%	1 SEC	1 SEC	4.6 A	6.1 A	CT-2	K-K1, L-L1	5 V.A	

NOTE

1. 상기 TABLE의 값치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

LOAD LIMITER 권고 SETTING치

* POWER SOURCE : AC 3Φ 440V 60Hz

극동호이스트(주)

HOIST	MOTOR 용량	LOAD LIMITER 권고 SETTING치			LOAD CURRENT		C.T MODEL	연결단자 NO	C.T 용량	REMARK
		LOAD CURRENT	ADJ START TIME	SHOCK TIME	100%	110%				
C1 TON	2.4KW x 4P	110%	1 SEC	1 SEC	5.0 A	7.3 A	CT-2	K-K1, L-L1	5 V.A	
	0.4KW x 4P	110%	1 SEC	1 SEC	1.4 A	1.8 A	CT-1	K-K1, L-L1	5 V.A	
C1.5 TON	3.7KW x 4P	110%	1 SEC	1 SEC	8.0 A	10.8 A	CT-2	K-K1, L-L1	5 V.A	
	0.4KW x 4P	110%	1 SEC	1 SEC	1.4 A	1.8 A	CT-1	K-K1, L-L1	5 V.A	
C2.8 TON	5.0KW x 4P	110%	1 SEC	1 SEC	10.5 A	13.7 A	CT-2	K-K1, L-L1	5 V.A	
	1.5KW x 4P	110%	1 SEC	1 SEC	3.7 A	4.3 A	CT-1	K-K1, L-L1	5 V.A	
C3 TON	5.5KW x 4P	110%	1 SEC	1 SEC	10.5 A	13.7 A	CT-2	K-K1, L-L1	5 V.A	
	1.5KW x 4P	110%	1 SEC	1 SEC	3.7 A	4.3 A	CT-1	K-K1, L-L1	5 V.A	
C5 TON	5.5KW x 6P	110%	1 SEC	1 SEC	14.1 A	18.5 A	CT-2	K-K1, L-L1	5 V.A	
	1.0KW x 6R	110%	1 SEC	1 SEC	3.3 A	4.7 A	CT-1	K-K1, L-L1	5 V.A	
C7.5 TON	5.5KW x 6P	110%	1 SEC	1 SEC	14.1 A	18.5 A	CT-2	K-K1, L-L1	5 V.A	
	1.0KW x 6P	110%	1 SEC	1 SEC	3.3 A	4.7 A	CT-1	K-K1, L-L1	5 V.A	
C10 TON	9.0KW x 8P	110%	1 SEC	1 SEC	22.5 A	24.8 A	CT-2	K-K1, L-L1	5 V.A	
	1.1KW x 8P	110%	1 SEC	1 SEC	4.0 A	5.4 A	CT-1	K-K1, L-L1	5 V.A	

NOTE

1. 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

LOAD LIMITER 권고 SETTING치

* POWER SOURCE : AC 3Φ 460V 60Hz

극동하이스트(주)

HOIST	MOTOR 용량	LOAD LIMITER 권고 SETTING치			LOAD CURRENT		C.T MODEL	연결단자 NO	C.T 용량	REMARK
		LOAD CURRENT	ADJ START TIME	SHOCK TIME	100%	110%				
C1 TON	2.4KW x 4P	110%	1 SEC	1 SEC	4.8 A	5.2 A	CT-2	K-K1, L-L1	5 V.A	
	0.4KW x 4P	110%	1 SEC	1 SEC	1.3 A	1.5 A	CT-1	K-K1, L-L1	5 V.A	
C1.5 TON	3.7KW x 4P	110%	1 SEC	1 SEC	7.7 A	8.5 A	CT-2	K-K1, L-L1	5 V.A	
	0.4KW x 4P	110%	1 SEC	1 SEC	1.3 A	1.5 A	CT-1	K-K1, L-L1	5 V.A	
C2.8 TON	5.0KW x 4P	110%	1 SEC	1 SEC	10.0 A	11.5 A	CT-2	K-K1, L-L1	5 V.A	
	1.5KW x 4P	110%	1 SEC	1 SEC	3.5 A	4.3 A	CT-1	K-K1, L-L1	5 V.A	
C3 TON	5.5KW x 4P	110%	1 SEC	1 SEC	10.0 A	11.5 A	CT-2	K-K1, L-L1	5 V.A	
	1.5KW x 4P	110%	1 SEC	1 SEC	3.5 A	4.3 A	CT-1	K-K1, L-L1	5 V.A	
C5 TON	5.5KW x 6P	110%	1 SEC	1 SEC	13.5 A	14.7 A	CT-2	K-K1, L-L1	5 V.A	
	1.0KW x 6P	110%	1 SEC	1 SEC	3.2 A	3.6 A	CT-1	K-K1, L-L1	5 V.A	
C7.5 TON	5.5KW x 6P	110%	1 SEC	1 SEC	13.5 A	14.7 A	CT-2	K-K1, L-L1	5 V.A	
	1.0KW x 6P	110%	1 SEC	1 SEC	3.2 A	3.6 A	CT-1	K-K1, L-L1	5 V.A	
C10 TON	9.0KW x 8P	110%	1 SEC	1 SEC	21.5 A	23.7 A	CT-2	K-K1, L-L1	5 V.A	
	1.1KW x 8P	110%	1 SEC	1 SEC	4.0 A	5.4 A	CT-1	K-K1, L-L1	5 V.A	

NOTE

1. 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

LOAD LIMITER 권고 SETTING치

극동하이스트(주)

* POWER SOURCE : AC 3Φ 480V 60Hz

HOIST	MOTOR 용량	LOAD LIMITER 권고 SETTING치			LOAD CURRENT		C.T MODEL	연결단자 NO	C.T 용량	REMARK
		LOAD CURRENT	ADJ START TIME	SHOCK TIME	100%	110%				
C1 TON	2.4KW x 4P	110%	1 SEC	1 SEC	4.6 A	5.0 A	CT-2	K-K1, L-L1	5 V.A	
	0.4KW x 4P	110%	1 SEC	1 SEC	1.2 A	1.35 A	CT-1	K-K1, L-L1	5 V.A	
	3.7KW x 4P	110%	1 SEC	1 SEC	7.3 A	8.2 A	CT-2	K-K1, L-L1	5 V.A	
C1.5 TON	0.4KW x 4P	110%	1 SEC	1 SEC	1.2 A	1.35 A	CT-1	K-K1, L-L1	5 V.A	
	5.0KW x 4P	110%	1 SEC	1 SEC	9.6 A	11.2 A	CT-2	K-K1, L-L1	5 V.A	
	1.5KW x 4P	110%	1 SEC	1 SEC	3.4 A	4.3 A	CT-1	K-K1, L-L1	5 V.A	
C2.8 TON	5.5KW x 4P	110%	1 SEC	1 SEC	9.6 A	11.2 A	CT-2	K-K1, L-L1	5 V.A	
	1.5KW x 4P	110%	1 SEC	1 SEC	3.4 A	4.3 A	CT-1	K-K1, L-L1	5 V.A	
	5.5KW x 4P	110%	1 SEC	1 SEC	9.6 A	11.2 A	CT-2	K-K1, L-L1	5 V.A	
C3 TON	1.5KW x 4P	110%	1 SEC	1 SEC	3.4 A	4.3 A	CT-1	K-K1, L-L1	5 V.A	
	5.5KW x 6P	110%	1 SEC	1 SEC	12.9 A	14.2 A	CT-2	K-K1, L-L1	5 V.A	
	1.0KW x 6P	110%	1 SEC	1 SEC	3.1 A	3.5 A	CT-1	K-K1, L-L1	5 V.A	
C5 TON	5.5KW x 6P	110%	1 SEC	1 SEC	12.9 A	14.2 A	CT-2	K-K1, L-L1	5 V.A	
	1.0KW x 6P	110%	1 SEC	1 SEC	3.1 A	3.5 A	CT-1	K-K1, L-L1	5 V.A	
	9.0KW x 8P	110%	1 SEC	1 SEC	20.6 A	22.7 A	CT-2	K-K1, L-L1	5 V.A	
C7.5 TON	1.1KW x 8P	110%	1 SEC	1 SEC	4.0 A	5.4 A	CT-1	K-K1, L-L1	5 V.A	
	5.5KW x 6P	110%	1 SEC	1 SEC	12.9 A	14.2 A	CT-2	K-K1, L-L1	5 V.A	
	1.0KW x 6P	110%	1 SEC	1 SEC	3.1 A	3.5 A	CT-1	K-K1, L-L1	5 V.A	
C10 TON	9.0KW x 8P	110%	1 SEC	1 SEC	20.6 A	22.7 A	CT-2	K-K1, L-L1	5 V.A	
	1.1KW x 8P	110%	1 SEC	1 SEC	4.0 A	5.4 A	CT-1	K-K1, L-L1	5 V.A	
	5.5KW x 6P	110%	1 SEC	1 SEC	12.9 A	14.2 A	CT-2	K-K1, L-L1	5 V.A	

NOTE

1. 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

E.O.C.R 권고 SETTING치

* POWER SOURCE : AC 3Φ 220V 60Hz

극동호이스트(주)

HOIST	MOTOR 용량	MOTOR 정격 전류	DRIVE TYPE	E.O.C.R TYPE	권고 SETTING 치			REMARK
					DELAY TIME	OPERATION TIME	CURRENT	
C1 TON	2.4KW x 4P	10.0 A	1 DRAVE	SS-30	3 SEC	1 SEC	10.0 A	
	0.4KW x 4P	2.7 A	1 DRAVE	SS-05	3 SEC	1 SEC	2.7 A	
C1.5 TON	3.7KW x 4P	16.0 A	1 DRAVE	SS-30	3 SEC	1 SEC	16.0 A	
	0.4KW x 4P	2.7 A	1 DRAVE	SS-05	3 SEC	1 SEC	2.7 A	
C2.8 TON	5.0KW x 4P	22.8 A	1 DRAVE	SS-30	3 SEC	1 SEC	22.8 A	
	1.5KW x 4P	7.3 A	1 DRAVE	SS-30	3 SEC	1 SEC	7.3 A	
C3 TON	5.5KW x 4P	22.8 A	1 DRAVE	SS-30	3 SEC	1 SEC	22.8 A	
	1.5KW x 4P	7.3 A	1 DRAVE	SS-30	3 SEC	1 SEC	7.3 A	
C5 TON	5.5KW x 6P	28.2 A	1 DRAVE	SS-30	3 SEC	1 SEC	28.2 A	
	1.0KW x 6P	6.7 A	1 DRAVE	SS-30	3 SEC	1 SEC	6.7 A	
C7.5 TON	5.5KW x 6P	28.2 A	1 DRAVE	SS-30	3 SEC	1 SEC	28.2 A	
	1.0KW x 6P	6.7 A	1 DRAVE	SS-30	3 SEC	1 SEC	6.7 A	
C10 TON	9.0KW x 8P	45.0 A	1 DRAVE	SS-60	3 SEC	1 SEC	45.0 A	
	1.7KW x 8P	8.0 A	1 DRAVE	SS-30	3 SEC	1 SEC	8.0 A	

NOTE
1. 상기 TABLE의 설정치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

E.O.C.R 권고 SETTING치

* POWER SOURCE : AC 3Φ 380V 60Hz

극동호이스트(주)

HOIST	MOTOR 용량	1 정격 전류	DRIVE TYPE	E.O.C.R TYPE	권고 SETTING 치			REMARK
					DELAY TIME	OPERATION TIME	CURRENT	
C1 TON	2.4KW x 4P	5.8 A	1 DRAVE	SS-30	3 SEC	1 SEC	5.8 A	
	0.4KW x 4P	1.6 A	1 DRAVE	SS-05	3 SEC	1 SEC	1.6 A%	
C1.5 TON	3.7KW x 4P	9.3 A	1 DRAVE	SS-30	3 SEC	1 SEC	9.3 A	
	0.4KW x 4P	1.6 A	1 DRAVE	SS-05	3 SEC	1 SEC	1.6 A	
C2.8 TON	5.0KW x 4P	12.2 A	1 DRAVE	SS-30	3 SEC	1 SEC	12.2 A	
	1.5KW x 4P	4.2 A	1 DRAVE	SS-05	3 SEC	1 SEC	4.2 A	
C3 TON	5.5KW x 4P	12.2 A	1 DRAVE	SS-30	3 SEC	1 SEC	12.2 A	
	1.5KW x 4P	4.2 A	1 DRAVE	SS-05	3 SEC	1 SEC	4.2 A	
C5 TON	5.5KW x 6P	16.3 A	1 DRAVE	SS-30	3 SEC	1 SEC	16.3 A	
	1.0KW x 6P	3.9 A	1 DRAVE	SS-05	3 SEC	1 SEC	3.9 A	
C7.5 TON	5.5KW x 8P	16.3 A	1 DRAVE	SS-30	3 SEC	1 SEC	16.3 A	
	1.0KW x 8P	3.9 A	1 DRAVE	SS-05	3 SEC	1 SEC	3.9 A	
C10 TON	9.0KW x 8P	26.0 A	1 DRAVE	SS-30	3 SEC	1 SEC	26.0 A	
	1.1KW x 8P	4.6 A	1 DRAVE	SS-05	3 SEC	1 SEC	4.6 A	

NOTE
1. 상기 TABLE의 SETTING치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

E.O.C.R 권고 SETTING치

* POWER SOURCE : AC 3Φ 440V 60Hz

극동호이스트(주)

HOIST	MOTOR 용량	MOTOR 정격 전류	DRIVE TYPE	E.O.C.R TYPE	권고 SETTING 치			REMARK
					DELAY TIME	OPERATION TIME	CURRENT	
C1 TON	2.4KW x 4P	5.0 A	1 DRAVE	SS-30	3 SEC	1 SEC	5.0 A	
	0.4KW x 4P	1.4 A	1 DRAVE	SS-05	3 SEC	1 SEC	1.4 A	
C1.5 TON	3.7KW x 4P	8.0 A	1 DRAVE	SS-30	3 SEC	1 SEC	8.0 A	
	0.4KW x 4P	1.4 A	1 DRAVE	SS-05	3 SEC	1 SEC	1.4 A	
C2.8 TON	5.0KW x 4P	10.5 A	1 DRAVE	SS-30	3 SEC	1 SEC	10.5 A	
	1.5KW x 4P	3.7 A	1 DRAVE	SS-05	3 SEC	1 SEC	3.7 A	
C3 TON	5.5KW x 4P	10.5 A	1 DRAVE	SS-30	3 SEC	1 SEC	10.5 A	
	1.5KW x 4P	3.7 A	1 DRAVE	SS-05	3 SEC	1 SEC	3.7 A	
C5 TON	5.5KW x 6P	14.1 A	1 DRAVE	SS-30	3 SEC	1 SEC	14.1 A	
	1.0KW x 6P	3.3 A	1 DRAVE	SS-05	3 SEC	1 SEC	3.3 A	
C7.5 TON	5.5KW x 6P	14.1 A	1 DRAVE	SS-30	3 SEC	1 SEC	14.1 A	
	1.0KW x 6P	3.3 A	1 DRAVE	SS-05	3 SEC	1 SEC	3.3 A	
C10 TON	9.0KW x 8P	22.5 A	1 DRAVE	SS-30	3 SEC	1 SEC	22.5 A	
	1.5KW x 8P	4.0 A	1 DRAVE	SS-05	3 SEC	1 SEC	4.0 A	

NOTE

1. 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

E.O.C.R 권고 SETTING치

* POWER SOURCE : AC 3Φ 460V 60Hz

극동호이스트(주)

HOIST	MOTOR 용량	MOTOR 정격 전류	DRIVE TYPE	E.O.C.R TYPE	권고 SETTING 치			REMARK
					DELAY TIME	OPERATION TIME	CURRENT	
C1 TON	2.4KW x 4P	4.8 A	1 DRAVE	SS-30	3 SEC	1 SEC	4.8 A	
	0.4KW x 4P	1.4 A	1 DRAVE	SS-05	3 SEC	1 SEC	1.4 A	
C1.5 TON	3.7KW x 4P	7.7 A	1 DRAVE	SS-30	3 SEC	1 SEC	7.7 A	
	0.4KW x 4P	1.3 A	1 DRAVE	SS-05	3 SEC	1 SEC	1.4 A	
C2.8 TON	5.0KW x 4P	10.0 A	1 DRAVE	SS-30	3 SEC	1 SEC	10.0 A	
	1.5KW x 4P	3.5 A	1 DRAVE	SS-05	3 SEC	1 SEC	3.5 A	
C3 TON	5.5KW x 4P	10.0 A	1 DRAVE	SS-30	3 SEC	1 SEC	10.0 A	
	1.5KW x 4P	3.5 A	1 DRAVE	SS-05	3 SEC	1 SEC	3.5 A	
C5 TON	5.5KW x 6P	13.5 A	1 DRAVE	SS-30	3 SEC	1 SEC	13.5 A	
	1.0KW x 6P	3.2 A	1 DRAVE	SS-05	3 SEC	1 SEC	3.2 A	
C7.5 TON	5.5KW x 6P	13.5 A	1 DRAVE	SS-30	3 SEC	1 SEC	13.5 A	
	1.0KW x 6P	3.2 A	1 DRAVE	SS-05	3 SEC	1 SEC	3.2 A	
C10 TON	9.0KW x 8P	21.5 A	1 DRAVE	SS-30	3 SEC	1 SEC	21.5 A	
	1.7KW x 8P	4.0 A	1 DRAVE	SS-05	3 SEC	1 SEC	4.0 A	

NOTE: 1. 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

E.O.C.R 권고 SETTING치

* POWER SOURCE : AC 3Φ 480V 60HZ

극동호이스트(주)

HOIST	MOTOR 용량	MOTOR 정격 전류	DRIVE TYPE	E.O.C.R TYPE	권고 SETTING 치			REMARK
					DELAY TIME	OPERATION TIME	CURRENT	
C1 TON	2.4KW x 4P	4.6 A	1 DRAVE	SS-30	3 SEC	1 SEC	4.6 A	
	0.4KW x 4P	1.4 A	1 DRAVE	SS-05	3 SEC	1 SEC	1.4 A	
C1.5 TON	3.7KW x 4P	7.3 A	1 DRAVE	SS-30	3 SEC	1 SEC	7.3 A	
	0.4KW x 4P	1.2 A	1 DRAVE	SS-05	3 SEC	1 SEC	1.4 A	
C2.8 TON	5.0KW x 4P	9.6 A	1 DRAVE	SS-30	3 SEC	1 SEC	9.6 A	
	1.5KW x 4P	3.4 A	1 DRAVE	SS-05	3 SEC	1 SEC	3.4 A	
C3 TON	5.5KW x 4P	9.6 A	1 DRAVE	SS-30	3 SEC	1 SEC	9.6 A	
	1.5KW x 4P	3.4 A	1 DRAVE	SS-05	3 SEC	1 SEC	3.4 A	
C5 TON	5.5KW x 6P	12.9 A	1 DRAVE	SS-30	3 SEC	1 SEC	12.9 A	
	1.0KW x 6P	3.1 A	1 DRAVE	SS-05	3 SEC	1 SEC	3.1 A	
C7.5 TON	5.5KW x 6P	12.9 A	1 DRAVE	SS-30	3 SEC	1 SEC	12.9 A	
	1.0KW x 6P	3.1 A	1 DRAVE	SS-05	3 SEC	1 SEC	3.1 A	
C10 TON	9.0KW x 8P	20.6 A	1 DRAVE	SS-30	3 SEC	1 SEC	20.6 A	
	1.7KW x 8P	4.0 A	1 DRAVE	SS-05	3 SEC	1 SEC	4.0 A	


NOTE

1. 상가 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA


1. SERVICE	HOISTING
2. MANUFACTURE	극동호이스트 (주)
3. FRAME NUMBER	112 M
4. RATED POWER	3.7 KW x 4 P
5. RATED VOLTAGE AND FREQUENCY	220 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATTING	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 ℃
10. FULL LOAD SPEED	1760 RPM
11. FULL LOAD CURRENT	16 A
12. LOCKED ROTOR CURRENT	81.5 A
13. MINIMUM STARTING VOLTAGE	200 V
14. EFFICIENCY AT 100% RATED LOAD	83.5 %
15. POWER FACTOR AT 100% RATED LOAD	79.3 %
16. FULL LOAD TORQUE	4.4 KGM
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	TENV
19. TYPE OF BEARING	PL : 6206zz OPL : 6206zz
20. MOUNTING	HORIZONTAL
21. MAXIMUM AMBIENT TEMPURE	40 ℃
22. BEARING LUBRICATION	GREASE
23. STARTING METHOD	FULL VOLTAGE



THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA


1. SERVICE	HOISTING
2. MANUFACTURE	극동호이스트 (주)
3. FRAME NUMBER	112 M
4. RATED POWER	3.7 KW x 4 P
5. RATED VOLTAGE AND FREQUENCY	380 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 ℃
10. FULL LOAD SPEED	1760 RPM
11. FULL LOAD CURRENT	9.3 A
12. LOCKED ROTOR CURRENT	56.8 A
13. MINIMUM STARTING VOLTAGE	342 V
14. EFFICIENCY AT 100% RATED LOAD	83.5 %
15. POWER FACTOR AT 100% RATED LOAD	79.3 %
16. FULL LOAD TORQUE	44 KGM
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	TENV
19. TYPE OF BEARING	PL : 6206zz OPL : 6206zz
20. MOUNTING	HORIZONTAL
21. MAXIMUM AMBIENT TEMPURE	40 ℃
22. BEARING LUBRICATION	GREASE
23. STARTING METHOD	FULL VOLTAGE



THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA


1. SERVICE	HOISTING
2. MANUFACTURE	극동호이스트 (주)
3. FRAME NUMBER	112 M
4. RATED POWER	3.7 KW x 4 P
5. RATED VOLTAGE AND FREQUENCY	440 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 ℃
10. FULL LOAD SPEED	1760 RPM
11. FULL LOAD CURRENT	8.0 A
12. LOCKED ROTOR CURRENT	44.7 A
13. MINIMUM STARTING VOLTAGE	400 V
14. EFFICIENCY AT 100% RATED LOAD	83.5 %
15. POWER FACTOR AT 100% RATED LOAD	79.8 %
16. FULL LOAD TORQUE	4.4 KGM
17. SITE ALTTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	TENV
19. TYPE OF BEARING	PL : 6206zz OPL : 6206zz
20. MOUNTING	HORIZONTAL
21. MAXIMUM AMBIENT TEMPURE	40 ℃
22. BEARING LUBRICATION	GREASE
23. STARTING METHOD	FULL VOLTAGE



THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA


1. SERVICE	HOISTING
2. MANUFACTURE	극동호이스트 (주)
3. FRAME NUMBER	112 M
4. RATED POWER	3.7 KW x 4 P
5. RATED VOLTAGE AND FREQUENCY	460 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATTING	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 ℃
10. FULL LOAD SPEED	1760 RPM
11. FULL LOAD CURRENT	8.0 A
12. LOCKED ROTOR CURRENT	44.7 A
13. MINIMUM STARTING VOLTAGE	400 V
14. EFFICIENCY AT 100% RATED LOAD	83.5 %
15. POWER FACTOR AT 100% RATED LOAD	79.3 %
16. FULL LOAD TORQUE	4.4 KG.M
17. SITE ALTTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	TEN V
19. TYPE OF BEARING	PL : 6206zz OPL : 6206zz
20. MOUNTING	HORIZONTAL
21. MAXIMUM AMBIENT TEMPURE	40 ℃
22. BEARING LUBRICATION	GREASE
23. STARTING METHOD	FULL VOLTAGE



THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA


1. SERVICE	HOISTING
2. MANUFACTURE	극동호이스트 (주)
3. FRAME NUMBER	112 M
4. RATED POWER	3.7 KW x 4 P
5. RATED VOLTAGE AND FREQUENCY	480 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 ℃
10. FULL LOAD SPEED	1760 RPM
11. FULL LOAD CURRENT	8.0 A
12. LOCKED ROTOR CURRENT	44.7 A
13. MINIMUM STARTING VOLTAGE	400 V
14. EFFICIENCY AT 100% RATED LOAD	83.5 %
15. POWER FACTOR AT 100% RATED LOAD	79.8 %
16. FULL LOAD TORQUE	44 K.G.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	TEN V
19. TYPE OF BEARING	PL : 6206zz OPL : 6206zz
20. MOUNTING	HORIZONTAL
21. MAXIMUM AMBIENT TEMPURE	40 ℃
22. BEARING LUBRICATION	GREASE
23. STARTING METHOD	FULL VOLTAGE



THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA


1. SERVICE	CREEP HOISTING
2. MANUFACTURE	극동호이스트 (주)
3. FRAME NUMBER	80
4. RATED POWER	0.4 KW x 4 P
5. RATED VOLTAGE AND FREQUENCY	220 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 ℃
10. FULL LOAD SPEED	1740 RPM
11. FULL LOAD CURRENT	2.7 A
12. LOCKED ROTOR CURRENT	14.2 A
13. MINIMUM STARTING VOLTAGE	200 V
14. EFFICIENCY AT 100% RATED LOAD	63.5 %
15. POWER FACTOR AT 100% RATED LOAD	61.5 %
16. FULL LOAD TORQUE	0.7 KGM
17. SITE ALTTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	TENV
19. TYPE OF BEARING	PL : 6205zz OPL : 6204zz
20. MOUNTING	HORIZONTAL
21. MAXIMUM AMBIENT TEMPURE	40 ℃
22. BEARING LUBRICATION	GREASE
23. STARTING METHOD	FULL VOLTAGE



THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA


1. SERVICE	CREEP HOISTING
2. MANUFACTURE	극동호이스트 (주)
3. FRAME NUMBER	80
4. RATED POWER	0.4 KW x 4 P
5. RATED VOLTAGE AND FREQUENCY	380 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	1740 RPM
11. FULL LOAD CURRENT	1.6 A
12. LOCKED ROTOR CURRENT	8.3 A
13. MINIMUM STARTING VOLTAGE	345 V
14. EFFICIENCY AT 100% RATED LOAD	63.5 %
15. POWER FACTOR AT 100% RATED LOAD	61.5 %
16. FULL LOAD TORQUE	0.7 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	
19. TYPE OF BEARING	PL : 6205zz OPL : 6204zz
20. MOUNTING	HORIZONTAL
21. MAXIMUM AMBIENT TEMPURE	40 °C
22. BEARING LUBRICATION	GREASE
23. STARTING METHOD	FULL VOLTAGE



THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA


1. SERVICE	CREEP HOISTING
2. MANUFACTURE	극동호이스트 (주)
3. FRAME NUMBER	80
4. RATED POWER	0.4 KW x 4 P
5. RATED VOLTAGE AND FREQUENCY	440 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATTING	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 ℃
10. FULL LOAD SPEED	1740 RPM
11. FULL LOAD CURRENT	1.4 A
12. LOCKED ROTOR CURRENT	7.1 A
13. MINIMUM STARTING VOLTAGE	400 V
14. EFFICIENCY AT 100% RATED LOAD	63.5 %
15. POWER FACTOR AT 100% RATED LOAD	61.5 %
16. FULL LOAD TORQUE	0.7 KG.M
17. SITE ALTTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	TENV
19. TYPE OF BEARING	PL : 6205zz OPL : 6204zz
20. MOUNTING	HORIZONTAL
21. MAXIMUM AMBIENT TEMPURE	40 ℃
22. BEARING LUBRICATION	GREASE
23. STARTING METHOD	FULL VOLTAGE



THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA


1. SERVICE	CREEP HOISTING
2. MANUFACTURE	극동호이스트 (주)
3. FRAME NUMBER	80
4. RATED POWER	0.4 KW x 4 P
5. RATED VOLTAGE AND FREQUENCY	460 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	1740 RPM
11. FULL LOAD CURRENT	1.3 A
12. LOCKED ROTOR CURRENT	6.8 A
13. MINIMUM STARTING VOLTAGE	418 V
14. EFFICIENCY AT 100% RATED LOAD	63.5 %
15. POWER FACTOR AT 100% RATED LOAD	61.5 %
16. FULL LOAD TORQUE	0.7 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	
19. TYPE OF BEARING	PL : 6205zz OPL : 6204zz
20. MOUNTING	HORIZONTAL
21. MAXIMUM AMBIENT TEMPURE	40 °C
22. BEARING LUBRICATION	GREASE
23. STARTING METHOD	FULL VOLTAGE



THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	CREEP HOISTING
2. MANUFACTURE	극동호이스트 (주)
3. FRAME NUMBER	80
4. RATED POWER	0.4 KW x 4 P
5. RATED VOLTAGE AND FREQUENCY	480 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 ℃
10. FULL LOAD SPEED	1740 RPM
11. FULL LOAD CURRENT	1.2 A
12. LOCKED ROTOR CURRENT	6.6 A
13. MINIMUM STARTING VOLTAGE	436 V
14. EFFICIENCY AT 100% RATED LOAD	63.5 %
15. POWER FACTOR AT 100% RATED LOAD	61.5 %
16. FULL LOAD TORQUE	0.7 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	TENV
19. TYPE OF BEARING	PL : 6205zz OPL : 6204zz
20. MOUNTING	HORIZONTAL
21. MAXIMUM AMBIENT TEMPURE	40 ℃
22. BEARING LUBRICATION	GREASE
23. STARTING METHOD	FULL VOLTAGE




산업안전보건공단
KOSHA
KOREA OCCUPATIONAL SAFETY & HEALTH AGENCY

THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA


1. SERVICE	TRAVERSING
2. MANUFACTURE	극동호이스트(주)
3. FRAME NUMBER	90 S
4. RATED POWER	0.75 KW x 4 P
5. RATED VOLTAGE AND FREQUENCY	220 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 ℃
10. FULL LOAD SPEED	1764 RPM
11. FULL LOAD CURRENT	4.1 A
12. LOCKED ROTOR CURRENT	23.5 A
13. MINIMUM STARTING VOLTAGE	200 V
14. EFFICIENCY AT 100% RATED LOAD	67 %
15. POWER FACTOR AT 100% RATED LOAD	69.5 %
16. FULL LOAD TORQUE	0.85 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	TEFC
19. TYPE OF BEARING	PL : 6205zz OPL : 6204zz
20. MOUNTING	HORIZONTAL
21. MAXIMUM AMBIENT TEMPURE	40 ℃
22. BEARING LUBRICATION	GREASE
23. STARTING METHOD	FULL VOLTAGE



THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA


1. SERVICE	TRAVERSING
2. MANUFACTURE	극동호이스트(주)
3. FRAME NUMBER	90 S
4. RATED POWER	0.75 KW x 4 P
5. RATED VOLTAGE AND FREQUENCY	380 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATTING	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 ℃
10. FULL LOAD SPEED	1764 RPM
11. FULL LOAD CURRENT	2.45 A
12. LOCKED ROTOR CURRENT	13.5 A
13. MINIMUM STARTING VOLTAGE	342 V
14. EFFICIENCY AT 100% RATED LOAD	67 %
15. POWER FACTOR AT 100% RATED LOAD	69.5 %
16. FULL LOAD TORQUE	0.85 KG.M
17. SITE ALTTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	TEFC
19. TYPE OF BEARING	PL : 6205zz OPL : 6204zz
20. MOUNTING	HORIZONTAL
21. MAXIMUM AMBIENT TEMPURE	40 ℃
22. BEARING LUBRICATION	GREASE
23. STARTING METHOD	FULL VOLTAGE



THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA


1. SERVICE	TRAVERSING
2. MANUFACTURE	극동호이스트(주)
3. FRAME NUMBER	90 S
4. RATED POWER	0.75 KW x 4 P
5. RATED VOLTAGE AND FREQUENCY	440 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATTING	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 ℃
10. FULL LOAD SPEED	1764 RPM
11. FULL LOAD CURRENT	2.1 A
12. LOCKED ROTOR CURRENT	13.5 A
13. MINIMUM STARTING VOLTAGE	400 V
14. EFFICIENCY AT 100% RATED LOAD	67 %
15. POWER FACTOR AT 100% RATED LOAD	69.5 %
16. FULL LOAD TORQUE	0.85 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	TEFC
19. TYPE OF BEARING	PL : 6205zz OPL : 6204zz
20. MOUNTING	HORIZONTAL
21. MAXIMUM AMBIENT TEMPURE	40 ℃
22. BEARING LUBRICATION	GREASE
23. STARTING METHOD	FULL VOLTAGE



THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA


1. SERVICE	TRAVERSING
2. MANUFACTURE	극동호이스트(주)
3. FRAME NUMBER	90 S
4. RATED POWER	0.75 KW x 4 P
5. RATED VOLTAGE AND FREQUENCY	460 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATTING	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 ℃
10. FULL LOAD SPEED	1764 RPM
11. FULL LOAD CURRENT	2.1 A
12. LOCKED ROTOR CURRENT	13.5 A
13. MINIMUM STARTING VOLTAGE	416 V
14. EFFICIENCY AT 100% RATED LOAD	67 %
15. POWER FACTOR AT 100% RATED LOAD	69.5 %
16. FULL LOAD TORQUE	0.85 KG.M
17. SITE ALTTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	TEFC
19. TYPE OF BEARING	PL : 6205zz OPL : 6204zz
20. MOUNTING	HORIZONTAL
21. MAXIMUM AMBIENT TEMPURE	40 ℃
22. BEARING LUBRICATION	GREASE
23. STARTING METHOD	FULL VOLTAGE



THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA


1. SERVICE	TRAVERSING
2. MANUFACTURE	극동호이스트(주)
3. FRAME NUMBER	90 S
4. RATED POWER	0.75 KW x 4 P
5. RATED VOLTAGE AND FREQUENCY	480 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATTING	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 ℃
10. FULL LOAD SPEED	1764 RPM
11. FULL LOAD CURRENT	2.1 A
12. LOCKED ROTOR CURRENT	13.5 A
13. MINIMUM STARTING VOLTAGE	432 V
14. EFFICIENCY AT 100% RATED LOAD	67 %
15. POWER FACTOR AT 100% RATED LOAD	69.5 %
16. FULL LOAD TORQUE	0.85 KG.M
17. SITE ALTTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	TEFC
19. TYPE OF BEARING	PL : 6205zz OPL : 6204zz
20. MOUNTING	HORIZONTAL
21. MAXIMUM AMBIENT TEMPURE	40 ℃
22. BEARING LUBRICATION	GREASE
23. STARTING METHOD	FULL VOLTAGE



THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA


1. SERVICE	TRAVERSING
2. MANUFACTURE	극동호이스트(주)
3. FRAME NUMBER	90 S
4. RATED POWER	0.5 KW x 6 P
5. RATED VOLTAGE AND FREQUENCY	220 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 ℃
10. FULL LOAD SPEED	1176 RPM
11. FULL LOAD CURRENT	3.4 A
12. LOCKED ROTOR CURRENT	16.4 A
13. MINIMUM STARTING VOLTAGE	200 V
14. EFFICIENCY AT 100% RATED LOAD	64 %
15. POWER FACTOR AT 100% RATED LOAD	59.5 %
16. FULL LOAD TORQUE	0.80 KG.M
17. SITE ALTTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	TENV
19. TYPE OF BEARING	PL : 6205zz OPL : 6204zz
20. MOUNTING	HORIZONTAL
21. MAXIMUM AMBIENT TEMPURE	40 ℃
22. BEARING LUBRICATION	GREASE
23. STARTING METHOD	FULL VOLTAGE



THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA


1. SERVICE	TRAVERSING
2. MANUFACTURE	극동호이스트(주)
3. FRAME NUMBER	90 S
4. RATED POWER	0.5 KW x 6 P
5. RATED VOLTAGE AND FREQUENCY	380 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATTING	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	1176 RPM
11. FULL LOAD CURRENT	2.0 A
12. LOCKED ROTOR CURRENT	9.5 A
13. MINIMUM STARTING VOLTAGE	345 V
14. EFFICIENCY AT 100% RATED LOAD	64 %
15. POWER FACTOR AT 100% RATED LOAD	59.5 %
16. FULL LOAD TORQUE	0.80 K.G.M
17. SITE ALTTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	TENV
19. TYPE OF BEARING	PL : 6205zz OPL : 6204zz
20. MOUNTING	HORIZONTAL
21. MAXIMUM AMBIENT TEMPURE	40 °C
22. BEARING LUBRICATION	GREASE
23. STARTING METHOD	FULL VOLTAGE



THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA


1. SERVICE	TRAVERSING
2. MANUFACTURE	극동호이스트(주)
3. FRAME NUMBER	90 S
4. RATED POWER	0.5 KW x 6 P
5. RATED VOLTAGE AND FREQUENCY	440 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATTING	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 ℃
10. FULL LOAD SPEED	1176 RPM
11. FULL LOAD CURRENT	1.7 A
12. LOCKED ROTOR CURRENT	8.2 A
13. MINIMUM STARTING VOLTAGE	400 V
14. EFFICIENCY AT 100% RATED LOAD	64 %
15. POWER FACTOR AT 100% RATED LOAD	59.5 %
16. FULL LOAD TORQUE	0.80 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	TENV
19. TYPE OF BEARING	PL : 6205zz OPL : 6204zz
20. MOUNTING	HORIZONTAL
21. MAXIMUM AMBIENT TEMPURE	40 ℃
22. BEARING LUBRICATION	GREASE
23. STARTING METHOD	FULL VOLTAGE



THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA


1. SERVICE	TRAVERSING
2. MANUFACTURE	극동호이스트(주)
3. FRAME NUMBER	90 S
4. RATED POWER	0.5 KW x 6 P
5. RATED VOLTAGE AND FREQUENCY	460 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 ℃
10. FULL LOAD SPEED	1176 RPM
11. FULL LOAD CURRENT	1.7 A
12. LOCKED ROTOR CURRENT	7.9 A
13. MINIMUM STARTING VOLTAGE	418 V
14. EFFICIENCY AT 100% RATED LOAD	64 %
15. POWER FACTOR AT 100% RATED LOAD	59.5 %
16. FULL LOAD TORQUE	0.80 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	TEN V
19. TYPE OF BEARING	PL : 6205zz OPL : 6204zz
20. MOUNTING	HORIZONTAL
21. MAXIMUM AMBIENT TEMPURE	40 ℃
22. BEARING LUBRICATION	GREASE
23. STARTING METHOD	FULL VOLTAGE



THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	TRAVERSING
2. MANUFACTURE	극동호이스트(주)
3. FRAME NUMBER	90 S
4. RATED POWER	0.5 KW x 6 P
5. RATED VOLTAGE AND FREQUENCY	480 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATTING	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 ℃
10. FULL LOAD SPEED	1176 RPM
11. FULL LOAD CURRENT	1.6 A
12. LOCKED ROTOR CURRENT	7.5 A
13. MINIMUM STARTING VOLTAGE	436 V
14. EFFICIENCY AT 100% RATED LOAD	64 %
15. POWER FACTOR AT 100% RATED LOAD	59.5 %
16. FULL LOAD TORQUE	0.80 K.G.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	TENV
19. TYPE OF BEARING	PL : 6205zz OPL : 6204zz
20. MOUNTING	HORIZONTAL
21. MAXIMUM AMBIENT TEMPURE	40 ℃
22. BEARING LUBRICATION	GREASE
23. STARTING METHOD	FULL VOLTAGE



THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	TRAVERSING
2. MANUFACTURE	극동호이스트 (주)
3. FRAME NUMBER	90 L
4. RATED POWER	0.8/0.4 KW x 4/8 P
5. RATED VOLTAGE AND FREQUENCY	220 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 ℃
10. FULL LOAD SPEED	1750 / 850 RPM
11. FULL LOAD CURRENT	4.8/4.25 A
12. LOCKED ROTOR CURRENT	14.2/13.6 A
13. MINIMUM STARTING VOLTAGE	200 V
14. EFFICIENCY AT 100% RATED LOAD	72.8/65.8 %
15. POWER FACTOR AT 100% RATED LOAD	82.3/75 %
16. FULL LOAD TORQUE	0.80 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	PL : 6205zz OPL : 6204zz
19. TYPE OF BEARING	HORIZONTAL
20. MOUNTING	40 ℃
21. MAXIMUM AMBIENT TEMPURE	GREASE
22. BEARING LUBRICATION	FULL VOLTAGE
23. STARTING METHOD	

THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	TRAVERSING
2. MANUFACTURE	극동호이스트 (주)
3. FRAME NUMBER	90 L
4. RATED POWER	0.8/0.4 KW x 4/8 P
5. RATED VOLTAGE AND FREQUENCY	380 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 ℃
10. FULL LOAD SPEED	1750 / 850 RPM
11. FULL LOAD CURRENT	2.78/2.63 A
12. LOCKED ROTOR CURRENT	9.2/6.3 A
13. MINIMUM STARTING VOLTAGE	345 V
14. EFFICIENCY AT 100% RATED LOAD	72.8/65.8 %
15. POWER FACTOR AT 100% RATED LOAD	82.3/75 %
16. FULL LOAD TORQUE	0.80 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	DE N.V.
19. TYPE OF BEARING	PL : 6205zz OPL : 6204zz
20. MOUNTING	HORIZONTAL
21. MAXIMUM AMBIENT TEMPRE	40 ℃
22. BEARING LUBRICATION	GREASE
23. STARTING METHOD	FULL VOLTAGE

THREE PHASE INDUCTION MOTOR DATE SHEET


SCHEDULE OF TECHNICAL DATA

1. SERVICE	TRAVERSING
2. MANUFACTURE	극동호이스트 (주)
3. FRAME NUMBER	90 L
4. RATED POWER	0.8/0.4 KW x 4/8 P
5. RATED VOLTAGE AND FREQUENCY	440 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATTING	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 ℃
10. FULL LOAD SPEED	1750 / 850 RPM
11. FULL LOAD CURRENT	2.4/2.27 A
12. LOCKED ROTOR CURRENT	8.6/6.21 A
13. MINIMUM STARTING VOLTAGE	400 V
14. EFFICIENCY AT 100% RATED LOAD	72.8/65.8 %
15. POWER FACTOR AT 100% RATED LOAD	82.3/75 %
16. FULL LOAD TORQUE	0.80 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	TEN V
19. TYPE OF BEARING	PL : 6205zz OPL : 6204zz
20. MOUNTING	HORIZONTAL
21. MAXIMUM AMBIENT TEMPURE	40 ℃
22. BEARING LUBRICATION	GREASE
23. STARTING METHOD	FULL VOLTAGE

THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	TRAVERSING
2. MANUFACTURE	극동호이스트 (주)
3. FRAME NUMBER	90 L
4. RATED POWER	0.8/0.4 KW x 4/8 P
5. RATED VOLTAGE AND FREQUENCY	460 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 ℃
10. FULL LOAD SPEED	1750 / 850 RPM
11. FULL LOAD CURRENT	2.3/2.17 A
12. LOCKED ROTOR CURRENT	8.5/6.18 A
13. MINIMUM STARTING VOLTAGE	418 V
14. EFFICIENCY AT 100% RATED LOAD	72.8/65.8 %
15. POWER FACTOR AT 100% RATED LOAD	82.3/75 %
16. FULL LOAD TORQUE	0.80 K.G.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	TEN V
19. TYPE OF BEARING	PL : 6205zz OPL : 6204zz
20. MOUNTING	HORIZONTAL
21. MAXIMUM AMBIENT TEMPURE	40 ℃
22. BEARING LUBRICATION	GREASE
23. STARTING METHOD	FULL VOLTAGE



THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	TRAVERSING
2. MANUFACTURE	극동호이스트 (주)
3. FRAME NUMBER	90 L
4. RATED POWER	0.8/0.4 KW x 4/8 P
5. RATED VOLTAGE AND FREQUENCY	480 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATTING	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	1750 / 850 RPM
11. FULL LOAD CURRENT	2.3/2.1 A
12. LOCKED ROTOR CURRENT	8.4/6.15 A
13. MINIMUM STARTING VOLTAGE	436 V
14. EFFICIENCY AT 100% RATED LOAD	72.8/65.8 %
15. POWER FACTOR AT 100% RATED LOAD	82.3/75 %
16. FULL LOAD TORQUE	0.80 KG.M
17. SITE ALTTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	TENV
19. TYPE OF BEARING	PL : 6205zz OPL : 6204zz
20. MOUNTING	HORIZONTAL
21. MAXIMUM AMBIENT TEMPURE	40 °C
22. BEARING LUBRICATION	GREASE
23. STARTING METHOD	FULL VOLTAGE

THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE

TRAVERSING

2. MANUFACTURE

극동호이스트 (주)

3. FRAME NUMBER

90 L

4. RATED POWER

0.5/025 KW x 6/12 P

5. RATED VOLTAGE AND FREQUENCY

220 V 60 Hz

6. MOTOR TYPE

SQUIRREL CAGE ROTOR TYPE

7. SERVICE FACTOR AND RATting

1.0 , 30 MIN

8. LOCATION AND INSULATION CLASS

INDOOR, OUTDOOR, B CLASS

9. DESIGN TRMPERATURE RISE(BY RESISTANCE)

80 °C

10. FULL LOAD SPEED

1050/460 RPM

11. FULL LOAD CURRENT

3.2/3.6 A

12. STARTING CURRENT AT RATED VOLTAGE

12.8/10.8 A

13. MINIMUM STARTING VOLTAGE

200 V

14. EFFICIENCY AT 100% RATED LOAD

57.5/35 %

15. POWER FACTOR AT 100% RATED LOAD

64.5/50 %

16. STARTING TORQUE

0.75/0.506 KG.M

17. SITE ALTITUDE(UNDER)

1000 M

18. ENCLOSURE & COOLING METHOD

PL : 6205zz OPL : 6204zz

19. TYPE OF BEARING

HORIZONTAL

20. MOUNTING

40 °C


21. MAXIMUM AMBIENT TEMPURE

22. BEARING LUBRICATION

GREASE

23. STARTING METHOD


FULL VOLTAGE



THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	TRAVERSING
2. MANUFACTURE	극동호이스트 (주)
3. FRAME NUMBER	90 L
4. RATED POWER	0.5/025 KW x 6/12 P
5. RATED VOLTAGE AND FREQUENCY	380 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 ℃
10. FULL LOAD SPEED	1050/460 RPM
11. FULL LOAD CURRENT	1.85/2.08 A
12. STARTING CURRENT AT RATED VOLTAGE	7.41/6.25 A
13. MINIMUM STARTING VOLTAGE	345 V
14. EFFICIENCY AT 100% RATED LOAD	57.5/35 %
15. POWER FACTOR AT 100% RATED LOAD	64.5/50 %
16. STARTING TORQUE	0.757/0.506 KG.M
17. SITE ALTTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	TENV
19. TYPE OF BEARING	PL : 6205zz OPL : 6204zz
20. MOUNTING	HORIZONTAL
21. MAXIMUM AMBIENT TEMPURE	40 ℃
22. BEARING LUBRICATION	GREASE
23. STARTING METHOD	FULL VOLTAGE




안전보건공단
KOSHA

THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA


1. SERVICE	TRAVERSING
2. MANUFACTURE	극동호이스트 (주)
3. FRAME NUMBER	90 L
4. RATED POWER	0.5/025 KW x 6/12 P
5. RATED VOLTAGE AND FREQUENCY	440 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATTING	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	1050/460 RPM
11. FULL LOAD CURRENT	1.6/1.8 A
12. STARTING CURRENT AT RATED VOLTAGE	6.4/5.4 A
13. MINIMUM STARTING VOLTAGE	400 V
14. EFFICIENCY AT 100% RATED LOAD	57.5/35 %
15. POWER FACTOR AT 100% RATED LOAD	64.5/50 %
16. STARTING TORQUE	0.75/0.506 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	TENV
19. TYPE OF BEARING	PL : 6205zz OPL : 6204zz
20. MOUNTING	HORIZONTAL
21. MAXIMUM AMBIENT TEMPURE	40 °C
22. BEARING LUBRICATION	GREASE
23. STARTING METHOD	FULL VOLTAGE



THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	TRAVERSING
2. MANUFACTURE	극동호이스트 (주)
3. FRAME NUMBER	90 L
4. RATED POWER	0.5/025 KW x 6/12 P
5. RATED VOLTAGE AND FREQUENCY	460 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	1050/460 RPM
11. FULL LOAD CURRENT	1.5/1.72 A
12. STARTING CURRENT AT RATED VOLTAGE	6.2/5.3 A
13. MINIMUM STARTING VOLTAGE	418 V
14. EFFICIENCY AT 100% RATED LOAD	57.5/35 %
15. POWER FACTOR AT 100% RATED LOAD	64.5/50 %
16. STARTING TORQUE	0.757/0.506 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	PENV
19. TYPE OF BEARING	PL : 6205zz OPL : 6204zz
20. MOUNTING	HORIZONTAL
21. MAXIMUM AMBIENT TEMPURE	40 °C
22. BEARING LUBRICATION	GREASE
23. STARTING METHOD	FULL VOLTAGE



THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE

TRAVERSING

2. MANUFACTURE

극동호이스트 (주)

3. FRAME NUMBER

90 L

4. RATED POWER

0.5/025 KW x 6/12 P

5. RATED VOLTAGE AND FREQUENCY

480 V 60 Hz

6. MOTOR TYPE

SQUIRREL CAGE ROTOR TYPE

7. SERVICE FACTOR AND RATting

1.0 , 30 MIN

8. LOCATION AND INSULATION CLASS

INDOOR, OUTDOOR, B CLASS

9. DESIGN TRMPERATURE RISE(BY RESISTANCE)

80 °C

10. FULL LOAD SPEED

1050/460 RPM

11. FULL LOAD CURRENT

1.4/1.6 A

12. STARTING CURRENT AT RATED VOLTAGE

5.82/4.93 A

13. MINIMUM STARTING VOLTAGE

436 V

14. EFFICIENCY AT 100% RATED LOAD

57.5/35 %

15. POWER FACTOR AT 100% RATED LOAD

64.5/50 %

16. STARTING TORQUE

0.757/0.506 KG.M

17. SITE ALTITUDE(UNDER)

1000 M

18. ENCLOSURE & COOLING METHOD

TENV

19. TYPE OF BEARING

PL : 6205zz OPL : 6204zz

20. MOUNTING

HORIZONTAL

21. MAXIMUM AMBIENT TEMPURE

40 °C

22. BEARING LUBRICATION

GREASE

23. STARTING METHOD

FULL VOLTAGE

ORIGINAL



No.600 Chuangye Road, Qingdao Development Zone, Shandong, P.R.China
Tel: 86-532-86821916, Fax: 86-532-86821949 www.kiswire.com

ISSUE NO. PW9034

DATE May. 27. 2009

MILL TEST CERTIFICATE

THIS IS TO CERTIFY THAT THE MATERIAL DESCRIBED BELOW WAS MANUFACTURED
IN ACCORDANCE WITH KISWIRE LTD SPECIFICATION AND APPLICABLE SECTIONS

OF **KSD 3514** (B Grade)

TO MESSRS **KISWIRE LTD.**

MATERIAL DESCRIPTION **UNGALVANIZED STEEL WIRE ROPE**

06 X 37 + FC 1000M X 2 REEL

EX NO. **PW9034**

T/T NO.

ORDER NO.

REEL NO.

1~2

SAMPLING NO.

1

DIAMETER OF ROPE

10.0

mm

TYPE OF CORE

Fiber Core

SPECIFIED BREAKING LOAD

56.6

kN

SAMPLE BROKE AT

60.4

kN

WT. OF ZINC COATING OF OUTER WIRE

MIN.

g/m²

MAX.

g/m²

ROPE LAY

RRRL

LAY LENGTH

62.8

mm

LUBRICATION

A-2

CHEMICAL ANALYSIS OF WIRE ROD

CHARGE NO.	C×100	Si×100	Mn×100	P×1000	S×1000
050695E	73	21	092	13	4

DATE OF SAMPLE TEST

May. 27. 2009

CHIEF INSPECTOR D.S.NA
KISWIRE QINGDAO LTD.

산업재해예방

안전보건공단

KOREA OCCUPATIONAL SAFETY & HEALTH AGENCY

COSMO WIRE LTD.

#4-10, KOYEON-RI, WOONGCHON-MYUN,
ULJU-KU, ULSAN, KOREA

TEL : 82. 52. 261. 0478/9
FAX : 82. 52. 261. 0480

MILL TEST CERTIFICATE

D N V Det Norske Veritas
ISO 9001:2008 International Certification Registrar Ltd

SHEET NO.:

Customer/Messrs.: **삼전로푸**

L/C No.:	Order No.:
Commodity : STAINLESS STEEL WIRE ROPE	Our Ref No:
Nominal Dia. Of Cable : 3/8"	Type : AISI 304
Construction : 7 X 19	Lube : DRY
Specification : EN12385-4	Type of Lay : R. H. O. L
Order Quantity : 1,525M X 1R/L	Reel No.:
Net Weight/Reel : 551.14KG	Gross Weight/Reel :

CHEMICAL ANALYSIS OF WIRE ROD (%)

Component	C	Si	Mn	P	S	Ni	Cr	Mo	Cu	others
Heat no.										
S 28040	0.066	0.39	1.30	0.028	0.003	8.32	18.46			

TEST RESULTS

ITEM	UNIT	SPEC.	ACTUAL
Diameter of Cable	MM	9.60 - 10.08	9.78 - 9.92
Breaking Strength	KG	5,455	6,513
Preforming			Good
Length of Lay	MM		66.00
Diameter of Wires	MM	0.685	0.636
Tensile Strength of Wires	N/mm ²	1,770	1,860

REMARKS :

We hereby certify that the above results are true and correct in every details.

MAR/ 10/ 2011

Date



In who Kim
Manager of Quality Assurance Dept.

Test by : In who kim
E-Mail : meqno7777@nate.com

COSMO WIRE LTD.

MANUFACTURERS & EXPORTERS

KOREA OCCUPATIONAL SAFETY & HEALTH AGENCY