



제2020 - 2113441 호

안 전 인 증 서

(사업장명) 극동호이스트(주)

(소 재 지) (15423)경기도 안산시 단원구 해봉로 119(성곡동)

위 사업장에서 제조하는 아래의 품목이 산업안전보건법 제84조 및 시행규칙 제110조제1항에 따른 안전인증 심사 결과 안전·보건기준에 적합하므로 안전인증표시의 사용을 인증합니다.

품 목

호이스트 (국내품)

형식,모델(용량,등급)/인증번호

KDC20/10-MA (20/10Ton) / 20-AE2AC-00031

인 증 기 준

고용노동부 고시 제2020 - 41호 (위험기계·기구 안전인증 고시)


인 증 조 건

(15423)경기도 안산시 단원구 해봉로 119(성곡동)에서 생산된 동일 형식 제품에 한함

설치장소 : 극동호이스트(주)

2020년 04월 03일

한국산업안전보건공단 이사장





심사결과 통지서

신청인	사업장명	극동호이스트(주)	사업장관리번호	134-81-013350
	사업자등록번호	134-81-01335	대표자 성명	최성찬
	소재지	(154 - 23) 경기도 안산시 단원구 해봉로 119(성곡동)		

안전인증대상 기계·기구명

호이스트 [동일형식 인정 - “별첨” 참조(4모델)]

형 식 (규 격)	KDC20/10-MA	용 량 (등 급)	20(20/10) Ton
-----------	-------------	-----------	---------------

산업안전보건법 제 84조 및 같은 법 시행규칙 제110조에 따라 실시한

] 예비심사

V] 서면심사

] 기술능력 및 생산체제 심사

] 개별 제품심사

] 개별 제품심사(제작중)

] 형식별 제품심사

결과가 [V] 적 합
[] 부적합

합을 통지합니다.

2020년 03월 11일

인증심사원

이승태 정용하 정영애

이 승 태

(서명 또는 인)

한국산업안전보건공단 이사장



[별첨] 동일형식 일람표

사업장명	극동하이스트(주)	개정일자 및 번호	-	인증번호		
형식 및 모델번호		동일형식 항목 및 내역			비고	
형식번호	모델번호	권상속도(m/min)	횡행속도(m/min)	양정(m)		
KDC20/10-MA	KDC20/10-L12-MA	20톤 고속 : 4.2 10톤 고속 : 4.5	고속 : 15 (INVERTER : 2-15)	12		모터구동식 INVERTER 포함
	KDC20/10-L18-MA			18		
	KDC20/10-L24-MA	20톤 CREEP : 0.42 10톤 CREEP : 0.45	저속 : 10 (INVERTER : 2-10)	24		
	KDC20/10-L30-MA			30		

서 면 심 사 서 류

형식 번호 : KDC20/10-MA

극 동 호 이 스톱 (주)



工場 : 경기도 안산시 단원구 해봉로 119 (성곡동)

電話 : 031) 491 - 5311

FAS : 031) 494 - 5315

안전보건공단
Korea Occupational Safety & Health Agency

동일형식 일람표

사업장명		극동호이스트(주)	개정일자 및 번호		인증번호	
형식 및 모델			동일 형식 인정범위 및 내역			
형식	모델		권상속도(m/min)	회행속도(m/min)	양정(m)	회행방식
	KDC20/10-L12-MA		고속 20T : 4.2M/MIN	고속:15M/MIN (INVERTER : 2~15M/MIN) 저속:10M/MIN (INVERTER : 2~10M/MIN)	12	모터구동식
	KDC20/10-L18-MA		고속 10T : 4.5M/MIN		18	
	KDC20/10-L24-MA		CREEP 20T : 0.42M/MIN		24	
	KDC20/10-L30-MA		CREEP 10T : 0.45M/MIN		30	
KDC20/10-MA						INVERTER 포함
			비 고			



제 2012-BJ-0009 호



안 전 인 증 서

정호엔지니어링

경기도 광명시 노동사동 440-5

위 사업장에서 제조하는 아래의 품목이 산업안전보건법 제34조 및 같은 법 시행규칙 제58조의4제4항에 따른 안전인증 심사 결과 안전·보건기준에 적합하므로 안전인증표시의 사용을 인증합니다.

품 목

양중기용 과부하방지장치

형식·모델/용량·등급/인증번호

형식·모델	용량·등급	인증번호
JDL-100	J-2	12-AV2BJ-0009

인 증 기 준

방호장치 의무안전인증 고시(고용노동부고시 제2010-36호)


인 증 조 건

아래 주소에서 생산되는 제품에 한함.
정호엔지니어링, 경기도 광명시 노동사동 440-5

2012년 06월 11일

한국산업안전보건공단 이사장





1		2		3		4		5		6		7		8		9		10	
형식번호 KDC20/10-MA		도명 KDC20/10-L18-MA																	
NO		DESCRIPTION		MATERIAL		QTY		SIZE		REMARK									
1		O.L.P		PUR		1													
2		PUSH BUTTON		PUR		1													
3		SAFETY LATCH		SS400		2													
4		UPPER LIMIT SW		SS400		2													
5		T/S RAIL		SS400		-													

Lift : 18 M

Lift : 18 M

2

SPECIFICATION			
HOISTING LOAD	20,000 KG	10,000 KG	
TEST LOAD	25,000 KG	12,500 KG	
LIFT	18 M		
RATING	30 MIN		
HOISTING	SPEED	4.2/0.42 M/MIN	4.5/0.45 M/MIN
	MOTOR	17/1.8 KW x 8P	9.0/1.1 KW x 8P
TRAVERSING	SPEED	15 M/MIN (INVERTER : 2~15M/MIN)	
	MOTOR	1.5 KW x 4P	
TRAVERSING	SPEED	10 M/MIN (INVERTER : 2~10M/MIN)	
	MOTOR	1.0 KW x 6P	
WIRE ROPE	(6x37) #22.4x4FALLS #16x4FALLS		
POWER SOURCE	AC #3 220V(380,440,460,480V) 60Hz		
TRAVERSING RAIL	22 KG/M		
GROSS WEIGHT	4150 KG		

극동호이스트
제한하중
20,000 kg

VIEW-A

극동호이스트
제한하중
10,000 kg

VIEW-B

REDRAWING	K.H.Han	CHECK	APPRVD
DATE		DRAWN	
PROJECT		DESCRIPTION	
CLIENT			
MANUFACTURER	극동호이스트 주식회사 KUDONG HOIST CO., LTD.		
TITLE	ARRANGEMENT DRAWING KDC20/10-L18-MA		
SCALE	DWG. NO.	SHT. NO.	REV.
N/S			

The image contains two technical drawings of door seals, labeled 'OUT DOOR' and 'IN DOOR'. Each drawing shows a cross-section of a door frame with a seal profile. The 'OUT DOOR' seal has a width of 20, a height of 20, and a depth of 25. The 'IN DOOR' seal has a width of 15 and a height of 20. Both seals are labeled 'SPONGE' and have a hatched pattern indicating the material. A callout line points to the seal in the 'OUT DOOR' drawing.

7	0
6	1
5	2
4	3
3	4
2	5
1	6
0	7

SELECTION	HOIST CAPACITY	DESCRIPTION	IN DOOR			OUT DOOR			REMARK
			A	B	L	A	B	L	
	10 TON	HOISTING	440	200	690	440	200	690	

<u>A</u>					CUSTOMER	KDWMA-20/10T18L-C
<u>A</u>						
<u>A</u>					DRAWING TITLE	HOISTING CONTROL BOX
<u>A</u>						LAY-OUT
MK	DATE	REVISIONS	CHK.	APP.		



2. 제어용 전선 : 1.5mm KIV, HIV
3. 제작시 다스 변경 될수있음.
4. 외함 개방구조는 다음과 같을것.

외함 개방 후 충전되어 있는 부피는 IP2X 이상의 직접 접촉 방호가 되어있을 것.

SELECTION	VOLTAGE	F11 F12	F13	MCCB100
	220V	3A	5A	125AF/125AT
	380V	3A	5A	125AF/75AT
	440V	3A	5A	60AF/60AT
	460V	3A	5A	60AF/60AT
	480V	3A	5A	60AF/60AT

2			
1			
MK	DATE	REVISIONS	

DRAWING	TITLE
---------	-------

MAIN POWER CIRCUIT 1 DIAGRAM

DRAWING	DESIGN	CHECKED	APPROVED	SCALE	DATE	ORDER NO.
 극동호이스트 주식회사 KUK DONG HOIST CO., LTD.				NONE		
				DWG. NO		




NOTE

- NOTE 1. 전자의 세상은 다예 같다.

- 

☒													
☒													
☒													
☒													
MK	DATE	REVISIONS	CHK.	APP.	CUSTOMER	DRAWING TITLE	DRAWING	DESIGN	CHECKED	APPROVED	SCALE	DATE	ORDER NO.
						MAIN (20T) HOIST CONTROL BOX					NONE		
						ARRANGEMENT DRAWING		극동호이스트 주식회사 KIUK DONG HOIST CO LTD			DWG. NO	KDC20BA22	




1. UPPER LIMIT LS-1의 접점 허용 전류 용량 : AC 600V, 3A
2. UPPER LIMIT LS-2의 접점 허용 전류 용량 : NFB 125AF/7
3. EARTH TERMINAL RESISTANCE : 0.018 Ω
4. POWER SOURCE : AC, 3 ϕ 220V 60HZ




NOTE


- 전선의 색상은 다음과 같다.
 - 1) 흑색 : 교류 및 직류 전원선로
 - 2) 적색 : 교류 제어회로
 - 3) 주황색 : 외부 전원에서 공급되는 연동장치 제어회로
 - 4) 녹색 또는 녹색과 황색 혼용 : 접지선
- CABLE MATERIAL : KIV OR EQUIVALENT
 └ MIN SIZE : 1.5sq
- 제어용 전선 : 1.5mm KIV,HIV
- 제작시 다소 변경 될수있음.
- 외함 개방구조는 다음과 같을것.
 - 1) 외함 개방시 충전부분이 차단되도록 할것.
 - 2) 외함 개방후 충전되어있는 부분은 IP2X 이상의 직접 접촉 방지


[illegible]






SPECIFICATION SYMBOLS	HOISTING POWER	HOISTING MOTOR	CREEP MOTOR	DC MAG. BRAKE	NO FUSE BREAKER	TRANSFORMER	FUSE	MAGNET CONTACTOR	UPPER LIMIT	ELECTRIC OVER CURRENT RELAY	SILICON RECTIFIER	LOAD LIMITER	CABLE				
DESCRIPTION	HOIST	IM 10	IM 11	DB10, 11	LS-II & MCCB100	TR 1	F1,F12	M101,M102	LS-I, LS-II	EOCR100	RF100	LOAD LIMITER	C20-01				
	10TON AC3PH 220V 60Hz	9KWx8P	1.1KWx8P	DC 100V	ABS-103c/75AT	220/110V/120V/200VA	3A	5A	MC-130a	DMC22b	AC 600V 3A	SS-60	SS-30	SR-60	SR-30	JDL-100	VCT 16sqx4c
SELECTION MAKER	KUKDONG													ASECO		JUNGHO	DONGIL
REVISIONS	DATE	CHK.	APP.	DRAWING TITLE	CUSTOMER	DRAWING	DESIGN	CHECKED	APPROVED	SCALE	DATE	ORDER NO.	KDC10E22				
CIRCUIT DIAGRAM													DWG. NO		KDC10E22		

[illegible]

[illegible]



NOTE


- 1. UPPER LIMIT LS-1의 접점 허용 전류 용량 : AC 600V, 3A
- 2. UPPER LIMIT LS-2의 접점 허용 전류 용량 : NFB 125AF/75AT
- 3. EARTH TERMINAL RESISTANCE : 0.018 Ω
- 4. POWER SOURCE : AC. 3φ 380V 60HZ



- NOTE 1. 전선의 색상은 다음과 같다.
- 1) 흑색 : 교류 및 직류 전원선로
 - 2) 적색 : 교류제어회로
 - 3) 주황색 : 외부 전원에서 공급되는 연동장치 제어회로
 - 4) 녹색 또는 녹색과 황색 혼용 : 접지선
2. CABLE MATERIAL : KIV OR EQUIVALENT
MIN SIZE : 1.5sq
- 3. 제어용 전선 : 1.5mm KIV,HIV
 - 4. 제직시 다소 변경 될수있음.
 - 5. 외함 개방구조는 다음과 같을것.
 - 1) 외함 개방시 충전부분이 차단되도록 할것.
 - 2) 외함 개방후 충전되어있는 부분은 IP2X 이상의 직접 접촉 방호가 되어있을것.

NO	DESCRIPTION	SPECIFICATION	Q'TY	REMARK
1	CHASSIS PLATE		1	아 전 도 급
2	MAGNET CONTACT	MC-130a	2	HOISTING
3	MAGNET CONTACT	DMC22b	2	CREEP HOISTING
4	MAGNET CONTACT	DMC22b	2	TRAVERSING
5	SILICON RECTIFIER	SR-60	1	HOISTING
6	SILICON RECTIFIER	SR-30	1	CREEP HOISTING
7	SILICON RECTIFIER	SR-30	1	TRAVERSING
8	E.O.C.R	SS-60	1	HOISTING
9	E.O.C.R	SS-30	1	CREEP HOISTING
10	E.O.C.R	SS-05	1	TRAVERSING
11	NFB	125AF/75AT	1	LS-2
12	UPPER LIMIT	AC 600V/3A	1	LS-1
13	LIMIT LEVER	SS400	1	
14	FUSE (F1,F12)	2 A	2	
15	FUSE (F13)	5 A	1	
16	TRANSFORMER	380V/110,120V, 200VA	1	
17	TERMINAL BLOCK	100A,25A		
18	TERMINAL BLOCK	15A		
19	EARTH TERMINAL	5t25x50	1	
20	CABLE DUCT	-	1	

DRAWING		DESIGN	CHECKED	APPROVED	SCALE	DATE	ORDER NO.
MAIN (20T) HOIST CONTROL BOX					NONE		
ARRANGEMENT DRAWING							
CUSTOMER		KDK			KDK		
DRAWING TITLE		KDK			KDK		
REVISIONS		KDK			KDK		
DATE	CHK.	APP.	DWG. NO		KDC20BA32		

[illegible]

2. CABLE MATERIAL : KIV OR EQUIVALENT

MIN SIZE : 1.5sq

3. 제어용 전선 : 1.5mm KIV,HIV


4. 제주시 다소면 정남리수영장.

1) 외환 개방시 중전부분이 차단되도록 함.


[illegible]NOTE

1. UPPER LIMIT LS-1의 접점 허용 전류 용량. : AC 600V, 3A
2. UPPER LIMIT LS-2의 접점 허용 전류 용량. : NFB 50AF/50AT
3. EARTH TERMINAL RESISTANCE : 0.018 Ω
4. POWER SOURCE : AC. 3 ϕ 380V 60HZ

[illegible]




SPECIFICATION SYMBOLS		HOISTING POWER	HOISTING MOTOR	CREEP MOTOR	DC MAG. BRAKE	NO FUSE BREAKER	TRANSFORMER	FUSE	MAGNET CONTACTOR	UPPER LIMIT	ELECTRIC OVER CURRENT RELAY	SILICON RECTIFIER	LOAD LIMITER	CABLE			
DESCRIPTION		HOIST	IM 10	IM 11	DB10, 11	LS-II & MCCB100	TR 1	F11,F12	M101,M102	LS-I, LS-II	EOCR100	RF100	LOAD LIMITER	C20-01			
SELECTION MAKER		10TON AC3PH 380V 60Hz	9KWx8P	1.1KWx8P	DC 100V	ABS-53c/50AT	SHINHAN	2A	DMC85	AC 600V 3A	SS-60	SR-60	JDL-100	VCT 6.0sqx4c			
KUKDONG		LS		SHINHAN		DONG-A		KUK DONG		ASECO		JUNGHO		DONGIL			
CUSTOMER																	
DRAWING TITLE		AUX (10T) CREEP HOISTING POWER & CONTROL															
REVISIONS		CHK.	APP.	CIRCUIT DIAGRAM											DWG. NO		KDC10E32
DATE																	
MK																	



1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
POWER CIRCUIT																			
TRAVERSING MOTION																			
																			ADR'S NO.
																			C1

1 2 3 4 5 6 7 8 9 10 11 12 13 14 15 16 17 18 19 20



NOTE

- 1. UPPER LIMIT LS-1의 접점 허용 전류 용량 : AC 600V, 3A
- 2. UPPER LIMIT LS-2의 접점 허용 전류 용량 : NFB 60AF/60AT
- 3. EARTH TERMINAL RESISTANCE : 0.018 Ω
- 4. POWER SOURCE : AC. 3φ 440V 60HZ



NOTE 1. 전선의 색상은 다음과 같다.

- 1) 흑색 : 교류 및 직류 전원선로
- 2) 적색 : 교류제어회로
- 3) 주황색 : 외부 전원에서 공급되는 연동장치 제어회로
- 4) 녹색 또는 녹색과 황색 혼용 : 접지선

2. CABLE MATERIAL : KIV OR EQUIVALENT

3. 제어용 전선 : 1.5mm KIV,HIV
MIN SIZE : 1.5sq

- 4. 제작시 다소 변경 될수있음.
- 5. 외함 개방구조는 다음과 같을것.

1) 외함 개방시 충전부분이 차단되도록 할것.

2) 외함 개방후 충전되어있는 부분은 IP2X 이상의 직접 접촉 방호가 되어있을것.

NO	DESCRIPTION	SPECIFICATION	Q'TY	REMARK
1	CHASSIS PLATE		1	아 전 도 플
2	MAGNET CONTACT	MC-130a	2	HOISTING
3	MAGNET CONTACT	DMC22b	2	CREEP HOISTING
4	MAGNET CONTACT	DMC22b	2	TRAVERSING
5	SILICON RECTIFIER	SR-60	1	HOISTING
6	SILICON RECTIFIER	SR-30	1	CREEP HOISTING
7	SILICON RECTIFIER	SR-30	1	TRAVERSING
8	E.O.C.R	SS-60	1	HOISTING
9	E.O.C.R	SS-30	1	CREEP HOISTING
10	E.O.C.R	SS-05	1	TRAVERSING
11	N.F.B	60AF/60AT	1	LS-2
12	UPPER LIMIT	AC 600V/3A	1	LS-1
13	LIMIT LEVER	SS400	1	
14	FUSE (F1,F12)	2 A	2	
15	FUSE (F13)	5 A	1	
16	TRANSFORMER	440V/110,120V, 200VA	1	
17	TERMINAL BLOCK	100A,25A		
18	TERMINAL BLOCK	15A		
19	EARTH TERMINAL	5tX25X50	1	
20	CABLE DUCT	-	1	


DRAWING	DESIGN	CHECKED	APPROVED	SCALE	DATE	ORDER NO.
				NONE		
KDD KIK DONG HOIST CO. LTD						KDC20BA42
ARRANGEMENT DRAWING						
MAIN (20T) HOIST CONTROL BOX						
DRAWING TITLE						
CUSTOMER						
REVISIONS						
DATE	CHK	APP				

NOTE 1. 전선의 세상은 다윈과 같다.


- ## NOTE

- 


[illegible]




△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△	△
---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---




SPECIFICATION SYMBOLS	HOISTING POWER	HOISTING MOTOR	CREEP MOTOR	DC MAG. BRAKE	NO FUSE BREAKER	TRANSFORMER	FUSE	MAGNET CONTACTOR	UPPER LIMIT	ELECTRIC OVER CURRENT RELAY	SILICON RECTIFIER	LOAD LIMITER	CABLE
DESCRIPTION	10TON AC3PH 440V 60Hz	IM 10	IM 11	DB10, 11	LS - II & MCCB100	TR 1	F11, F12	M101, M102	LS-I, LS-II	EOCR100	RF100	JDL-100	C20-01
SELECTION MAKER													
KUKDONG													
CUSTOMER													
DRAWING TITLE													
AUX (10T) CREEP HOISTING POWER & CONTROL													
CIRCUIT DIAGRAM													
DWG. NO													
KDC10E42													
ORDER NO.													
DATE													
REVISIONS													
CHK. APP.													
KUKDONG ELECTRIC CO., LTD.													
극동호이스트 주식회사													
NONE													
SCALE													
ASECO													
JUNCHO													
DONGIL													

[illegible]



SPECIFICATION SYMBOLS		TRAVERSING MOTOR		TRAVERSING MOTOR		DC MAG. BRAKE		DC MAG. BRAKE		MAGNET CONTACTOR		SILICON RECTIFIER		ELECTRIC OVER CURRENT RELAY		LIMIT SWITCH	
DESCRIPTION		IM 30 , IM31		IM 30 , IM31		DB 30		DB 31		M301 , M302		RF 300		EOCR 300		LS-301 , LS-302	
1.5KW x 4P AC 3PH 440V 60Hz						DC 100V		DC 100V		DMC22b		SR-30		SS-30			
1.0KW x 6P AC 3PH 440V 60Hz						DC 100V		DC 100V		DMC22b		SR-30		SS-30			
SELECTION MAKER		KUK DONG						DONG-A				ASECO					
CUSTOMER																	
DRAWING TITLE		TRAVERSING POWER CONTROL CIRCUIT															
REVISIONS																	
DATE																	
CHK. APP.																	
DWG. NO		KDC20E44															
DATE																	
ORDER NO.																	



TRAVERSING POWER CONTROL CIRCUIT
DIAGRAM

극동시스템 주식회사
KUK DONG SYSTEM CO., LTD.

DWG. NO

DATE

CHK. APP.

REVISIONS

ORDER NO.

KDC20E44


1 2 3 4 5 6 7 8 9 10 11 12 13 14 15 16 17 18 19 20

ADR'S NO.

NO	DESCRIPTION	SPECIFICATION	Q'TY	REMARK
1	CHASSIS PLATE		1	아 연 도 금
2	MAGNET CONTACT	MC-130a	2	HOISTING
3	MAGNET CONTACT	DMC22b	2	CREEP HOISTING
4	MAGNET CONTACT	DMC22b	2	TRAVERSING
5	SILICON RECTIFIER	SR-60	1	HOISTING
6	SILICON RECTIFIER	SR-30	1	CREEP HOISTING
7	SILICON RECTIFIER	SR-30	1	TRAVERSING
8	E.O.C.R	SS-60	1	HOISTING
9	E.O.C.R	SS-30	1	CREEP HOISTING
10	E.O.C.R	SS-05	1	TRAVERSING
11	N.F.B	60AF/60AT	1	LS-2
12	UPPER LIMIT	AC 600V/3A	1	LS-1
13	LIMIT LEVER	SS400	1	
14	FUSE (F11,F12)	2 A	2	
15	FUSE (F13)	5 A	1	
16	TRANSFORMER	460V/110,120V, 200VA	1	
17	TERMINAL BLOCK	100A,25A		
18	TERMINAL BLOCK	15A		
19	EARTH TERMINAL	5x25x50	1	
20	CABLE DUCT	-	1	

NOTE 1. 전선의 색상은 다음과 같다.

- 1) 흑색 : 교류 및 직류 전원선로
 - 2) 적색 : 교류제어회로
 - 3) 주황색 : 외부 전원에서 공급되는 연동장치 제어회로
 - 4) 녹색 또는 녹색과 황색 혼용 : 접지선
2. CABLE MATERIAL : KIV OR EQUIVALENT
MIN SIZE : 1.5sq
3. 제어용 전선 : 1.5mm KIV,HIV
4. 제작시 다소 변경 될수있음.
5. 외함 개방구조는 다음과 같을것.
- 1) 외함 개방시 충전부분이 차단되도록 할것.
- 2) 외함 개방후 충전되어있는 부분은 IP2X 이상의 직접 접촉 방호가 되어있을것.



NOTE

- 1. UPPER LIMIT LS-1의 접점 허용 전류 용량 : AC 600V, 3A
- 2. UPPER LIMIT LS-2의 접점 허용 전류 용량 : NFB 60AF/60AT
- 3. EARTH TERMINAL RESISTANCE : 0.018 Ω
- 4. POWER SOURCE : AC. 3Φ 460V 60HZ




DRAWING	DESIGN	CHECKED	APPROVED	SCALE	DATE	ORDER NO.
				NONE		
KDK KIKONG HOIST CO. LTD.						KDC15BA52
ARRANGEMENT DRAWING						
MAIN (20T) HOIST CONTROL BOX						
DRAWING TITLE						
REVISIONS						
DATE	CHK.	APP.				

NOTE


1. 전선의 색상은 다음과 같다.
 - 1) 흑색 : 교류 및 직류 전원선으로
 - 2) 적색 : 교류제어회로
 - 3) 주황색 : 외부 전원에서 공급되는 연동장치 제어회로
 - 4) 녹색 또는 녹색과 황색 혼용 : 접지선
2. CABLE MATERIAL : KIV OR EQUIVALENT

MIN SIZE : 1.5sq
3. 제어용 전선 : 1.5mm KIV,HIV
4. 제작시 다소 변경 될수있음.
5. 외함 개방구조는 다음과 같을것.
 - 1) 외함 개방시 충전부분이 차단되도록 할것.
 - 2) 외함 개방후 충전되어있는 부분은 IP2X 이상의 직접 접촉 방지




192.168.11.51 / 2020-03-16 10:52:57





SPECIFICATION SYMBOLS	HOISTING POWER	HOISTING MOTOR	CREEP MOTOR	DC MAG. BRAKE	NO FUSE BREAKER	TRANSFORMER	FUSE	MAGNET CONTACTOR	UPPER LIMIT	ELECTRIC OVER CURRENT RELAY	SILICON RECTIFIER	LOAD LIMITER	CABLE																			
DESCRIPTION	HOIST	IM 10	IM 11	DB10, 11	LS-II & MCCB100	TR 1	F11,F12	M101,M102	LS-I, LS-II	EOCR100	RF100	LOAD LIMITER	C20-01																			
SELECTION MAKER	10TON AC3PH 460V 60Hz	9KWx8P	1.1KWx8P	DC 100V	ABS-53c/50AT	460/110V, 120V/200VA	2A	DMC65	DMC22b	AC 600V 3A	SS-60	SR-60	JDL-100	VCT 6.0sqx4c																		
KUKDONG															DONG-A		KUK DONG		ASECO		JUNGHO		DONGIL									
CUSTOMER															DRAWING		DESIGN		CHECKED		APPROVED		SCALE		DATE		ORDER NO.					
DRAWING TITLE															AUX (10T) CREEP HOISTING POWER & CONTROL																	
REVISIONS															CIRCUIT DIAGRAM																KDC10E52	
MK	DATE	CHK.										APP.																				

[illegible]

[illegible]



- 

NOTE
1. 전선의 색상은 다음과 같다.

- 5) 형색 : 직류 제어선도
- 1) 흑색 : 교류 및 직류 전원선로
 - 2) 적색 : 교류제어회로
 - 3) 주황색 : 외부 전원에서 공급되는 인동장치 제어회로
 - 4) 녹색 또는 녹색과 황색 혼합 : 접지선
2. CABLE MATERIAL : [KIV OR EQUIVALENT
MIN SIZE : 1.5sq
3. 제어용 전선 : 1.5mm KIV,HIV
 4. 제자시 다소 변경 될수있음.
 5. 외함 개방구조는 다음과 같을것.
- 1) 외함 개방시 중전부분이 차단되도록 할것.
 - 2) 외함 개방후 중전되어있는 부분은 IP2X 이상의 직접 접촉 방호가

NO	DESCRIPTION	SPECIFICATION	Q'TY	REMARK
1	CHASSIS PLATE		1	아 연 도 ㄹ
2	MAGNET CONTACT	MC-130a	2	HOISTING
3	MAGNET CONTACT	DMC22b	2	CREEP HOISTING
4	MAGNET CONTACT	DMC22b	2	TRAVERSING
5	SILICON RECTIFIER	SR-60	1	HOISTING
6	SILICON RECTIFIER	SR-30	1	CREEP HOISTING
7	SILICON RECTIFIER	SR-30	1	TRAVERSING
8	E.O.C.R	SS-60	1	HOISTING
9	E.O.C.R	SS-30	1	CREEP HOISTING
10	E.O.C.R	SS-05	1	TRAVERSING
11	N.F.B	60AF/60AT	1	LS-2
12	UPPER LIMIT	AC 600V/3A	1	LS-1
13	LIMIT LEVER	SS400	1	
14	FUSE (F11,F12)	2 A	2	
15	FUSE (F13)	5 A	1	
16	TRANSFORMER	480V/110,120V, 200VA	1	
17	TERMINAL BLOCK	100A,25A		
18	TERMINAL BLOCK	15A		
19	EARTH TERMINAL	5tx25x50	1	
20	CABLE DUCT	-	1	

[illegible]


NOTE 1. 전신의 세상은 다 영향 받는다.

- 1) 목적 : 교류 및 직류 전원선로
 - 2) 목적 : 교류제어회로
 - 3) 주황색 : 외부 전원에서 공급되는 연동장치 제어회로
 - 4) 녹색 또는 녹색과 황색 혼용 : 접지선
2. CABLE MATERIAL : KIV OR EQUIVALENT
MIN SIZE : 1.5sq
3. 제어용 전선 : 1.5mm KIV,HIV
4. 제자시 다스 변경 될수있음.
5. 외함 개방구조는 다음과 같을것.
- 1) 외함 개방시 충전부분이 차단되도록 함것.
 - 2) 외함 개방후 충전되어있는 부분은 IP2X 이상의 직접 접촉 방지




1. UPPER LIMIT LS-1의 접점 허용 전류 용량.: AC 600V, 3A
2. UPPER LIMIT LS-2의 접점 허용 전류 용량.: NFB 50AF/50AT
3. EARTH TERMINAL RESISTANCE : 0.018 Ω
4. POWER SOURCE : AC. 3 ϕ 480V 60HZ


[illegible]





SPECIFICATION SYMBOLS	HOISTING POWER	HOISTING MOTOR	CREEP MOTOR	DC MAG. BRAKE	NO FUSE BREAKER	TRANSFORMER	FUSE	MAGNET CONTACTOR	UPPER LIMIT	ELECTRIC OVER CURRENT RELAY	SILICON RECTIFIER	LOAD LIMITER	CABLE
	20TON AC3PH 480V 60Hz	IM 10	IM 11	DB10, 11	LS-II & MCCB100	TR 1	F1, F12	M101, M102	LS-I, LS-II	EOCR100	RF100	JDL-100	C20-01
SELECTION MAKER													
CIRCUIT DIAGRAM													
MAIN (20T) CREEP HOISTING POWER & CONTROL													
DRAWING TITLE													
CUSTOMER													
REVISIONS													
CHK. APP.													
DATE													
DWG. NO.													
KDC20E62													



SPECIFICATION SYMBOLS	HOISTING POWER	HOISTING MOTOR	CREEP MOTOR	DC MAG. BRAKE	NO FUSE BREAKER	TRANSFORMER	FUSE	MAGNET CONTACTOR	UPPER LIMIT	ELECTRIC OVER CURRENT RELAY	SILICON RECTIFIER	LOAD LIMITER	CABLE
DESCRIPTION	HOIST	IM 10	IM 11	DB10, 11	LS-II & MCCB100	TR 1	F11,F12 F13	M101,M102 M111,M112	LS-I, LS-II	EOCR100 EOCR110	RF100 RF110	LOAD LIMITER	C20-01
SELECTION MAKER	10TON AC3PH 480V 60Hz	9KWx8P	1.1KWx8P	DC 100V	ABS-53c/50AT	480/110V,120V,200V/A	2A 5A	DMC65 DMC22b	AC 600V 3A	SS-60 SS-30	SR-60 SR-30	JDL-100	VCT 6.0sqx4c
KUKDONG				LS		SHINHAN		DONG-A	KUK DONG	ASECO		JUNGHO	DONGIL
CUSTOMER								DRAWING	DESIGN	APPROVED	SCALE	DATE	ORDER NO.
DRAWING TITLE											NONE		
REVISIONS													
DATE													
CHK.													
APP.													
AUX (10T) CREEP HOISTING POWER & CONTROL										DWG. NO			
CIRCUIT DIAGRAM										KDC10E62			

[illegible]

[illegible]




SPECIFICATION	EMERGENCY STOP	SELECT S/W	MINI RELAY
SYMBOLS	ESB	SS1	CRMA
DESCRIPTION	AC 250V 6A	KDS	MY4
MAKER	KG-AUTO	KG-AUTO	KACON


CUSTOMER	ORDER NO.
극동호이스트 주식회사 KUKDONG HOIST CO., LTD.	

TITLE	DESCRIPTION
CONTROL CIRCUIT DIAGRAM 1	KDC20/10-MA

REV	DATE	DESCRIPTION	DRAWN	CHECK	APPRVD
1	19.FEB.2020	REDRAWING	K.H.Han	-	-









R1	S1	T1	U30	V30	W30	P30	N30	C2	P	E01	R301A	W01	R302A	HS1
----	----	----	-----	-----	-----	-----	-----	----	---	-----	-------	-----	-------	-----

11	EARTH BUS BAR	PUR	1		
10	DUCT	PUR	1		
9	TERMINAL BLOCK	PUR	1		
8	INVERTER	PUR	1		
7	TR	PUR	1		
6	RELAY & SCKET	PUR	1		
5	RF	PUR	1		
4	MC	PUR	1		
3	MCCB	PUR	1		

2	속판	SS400		1					
1	T/S BOX	PUR		1					
NO.	DESCRIPTION	M ^T L	SUB	TOTAL	SUB	TOTAL	REMARKS.	DIM	PROJECTION
			QTY	WEIGHT(Kg)					
PROJECT						DATE			
TITLE			T/S CONTROL PANEL(INVERTER)			SCALE	A3/3		
DRAWN	DESIGNED	CHECKED	APPROVED	REF. DRAWING					
 KDK 극동호이스트 주식회사 KUK DONG HOIST CO., LTD.			SHEET No.			DWG No.			
						KDC20E1001			




																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																					</
--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	----

KDC20E1003




TRAVERSING MOTION




ADR'S NO.

[illegible]



△																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																			
---	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--



NOTE:

1. MATERIAL: ABS
2. COLOR: YELLOW
3. CONTACTOR: AC250V 6A
4. CABLE: VCT1.5sq
5. IP55 이상

구분	조작버튼	표시등
색상	비상	비상
황색	비정상	비정상
녹색	정상	정상
장식	의무	의무
원색, 회색, 흑색	지정된의미없음	기타

N10	N	NORTH(1STEP or 2STEP)	
N9	S	SOUTH(1STEP or 2STEP)	
N8	W	WEST(1STEP or 2STEP)	
N7	E	EAST(1STEP or 2STEP)	
N6	D	DOWN(2STEP)	
N5	U	UP(2STEP)	
N4	-	SPARE	
N3	-	SPARE	
N2	MAIN-AUX	MAIN-AUX	
N1	EBS	EMERGENCY STOP	
NO	NAME	DESCRIPTION	REMARK

NO	DESCRIPTION	MATERIAL	Q'TY	SIZE	REMARK
1	PUSH BUTTON SWITCH	PUR.	1		

14.06.01	DATE	FIRST ISSUE	M.H.Kim	DWG.	CHK.	APP.
No.	Scale	N/S	Pro-section	Mass	Kg	Title
REVISION RECORD						ELECTRIC WIRE HOIST
OWNER						PENDANT CONTROL SWITCH
KDC20/10-MA						
KUK DONG HOIST CO., LTD.						
KUK DONG HOIST CO., LTD.						

SALES OFFICE : 7th floor, 145, Teheran-ro, Gangnam-gu, Seoul, Korea

TEL : 82-2-3420-3500, FAX : 82-2-3420-3600, E-mail : sales@dsrcorp.com, http://www.dsrcorp.com

MILL TEST CERTIFICATE / CERTIFICATE OF INSPECTION

Certificate No : 201804-Do637-1

Reel/Coil No : 1

Purchaser : -

Date : 2018. 04. 18

P.O No : -

L/C No. : -

Invoice No : Do637-224

1. TYPE / GRADE

Construction : 6X37+FC

Diameter : 22.4 MM

Length : 1,000 MTRS

Specification : KS D 3514

Coating : BRIGHT

Grade : 1,770

Lay : RHRL

Lubrication : A-2

2. ROPE TEST RESULTS

Items	Normal or Specified	Actual
Diameter	22.4 MM	22.9 MM
Breaking Strength	284.0 KN	291.5 KN
Lay Length	- MM	149 MM
Preforming	Good	Good

3. WIRE TEST RESULTS

Items	Normal or Specified	Actual
Diameter	1.00 MM	1.01 MM
Tensile Strength	1,770 N/MM2	1,822 N/MM2
Break Force	1,389 N	1,459 N
Torsion	27	35
Weight of Coating	- G/M2	- G/M2

We hereby certify that the above results are true and correct in every detail.

CHEMICAL ANALYSIS OF WIRE ROD

Charge No	Chemical Composition (%)				
	C	Si	Mn	P	S
SF 94504	0.73	0.19	0.46	0.010	0.009

Approval or Inspection Possibility

WIRE ROPE

Suncheon Factory : 15, Sandan 1-gil, Seo-myeon, Suncheon-si Jeonnam-do, Korea
Yulchon Factory : 80-21, Yulchonsandan 1-ro, Haeryong-myeon, Suncheon-si, Jeonnam-do, Korea



WIRE

Suncheon 2 Factory : 38, Sandan 4-gil, Seo-myeon, Suncheon-si Jeonnam-do, Korea

Quality Management Dept.



Handwritten signature
Chief Inspector

SALES OFFICE : 7th floor, 145, Teheran-ro, Gangnam-gu, Seoul, Korea

TEL : 82-2-3420-3500, FAX : 82-2-3420-3600, E-mail : sales@dsrcorp.com, http://www.dsrcorp.com

MILL TEST CERTIFICATE / CERTIFICATE OF INSPECTION

Certificate No : 201810-Do637-1

Date : 2018. 10. 10

Reel/Coil No : 1 - 2

P.O No : -

Purchaser : -

L/C No. : -

Invoice No : Do637-160

1. TYPE / GRADE

Construction : 6X37+FC

Coating : BRIGHT

Diameter : 16 MM

Grade : 1,770

Length : 1,000 MTRS X 2 R/L

Lay : RHRL

Specification : KS D 3514

Lubrication : A-2

2. ROPE TEST RESULTS

Items	Normal or Specified	Actual
Diameter	16 MM	16.4 MM
Breaking Strength	145.0 KN	149 KN
Lay Length	- MM	107 MM
Preforming	Good	Good

3. WIRE TEST RESULTS

Items	Normal or Specified	Actual
Diameter	0.72 MM	0.73 MM
Tensile Strength	1,770 N/MM2	1,833 N/MM2
Break Force	720 N	767 N
Torsion	27	40
Weight of Coating	- G/M2	- G/M2

We hereby certify that the above results are true and correct in every detail.

CHEMICAL ANALYSIS OF WIRE ROD

Charge No	Chemical Composition (%)				
	C	Si	Mn	P	S
SF 97502	0.71	0.20	0.47	0.009	0.007

Approval or Inspection Possibility

WIRE ROPE

Suncheon Factory : 15, Sandan 1-gil, Seo-myeon, Suncheon-si, Jeonnam-do, Korea
Yulchon Factory : 80-21, Yulchonsandan 1-ro, Haeryong-myeon, Suncheon-si, Jeonnam-do, Korea

WIRE

Suncheon 2 Factory : 39, Sandan 4-gil, Seo-myeon, Suncheon-si, Jeonnam-do, Korea

Quality Management Dept.



Handwritten signature

Chief Inspector

E.O.C.R 권고 SETTING치

* POWER SOURCE : AC 3Φ 220V 60Hz

극동호이스트(주)

HOIST	MOTOR 용량	MOTOR 정격 전류	DRIVE TYPE	E.O.C.R TYPE	권고 SETTING 치			REMARK
					DELAY TIME	OPERATION TIME	CURRENT	
C15 TON	13KW x 8P	59.0 A	1 DRAVE	SS-100	3 SEC	1 SEC	64.9 A	
	1.8KW x 8P	11.0 A	1 DRAVE	SS-30	3 SEC	1 SEC	12.1 A	
C20 TON	17KW x 8P	76.6 A	1 DRAVE	SS-100	3 SEC	1 SEC	84.3 A	
	1.8KW x 8P	11.0 A	1 DRAVE	SS-30	3 SEC	1 SEC	12.1 A	
C30 TON	17KW x 8P	76.6 A	1 DRAVE	SS-100	3 SEC	1 SEC	84.3 A	
	1.8KW x 8P	11.0 A	1 DRAVE	SS-30	3 SEC	1 SEC	12.1 A	
C35 TON	33KW x 6P	126.6 A	1 DRAVE	SS-150	3 SEC	1 SEC	139.3 A	
	3.7KW x 4P	16.0 A	1 DRAVE	SS-30	3 SEC	1 SEC	17.6 A	
C40 TON	33KW x 6P	126.6 A	1 DRAVE	SS-150	3 SEC	1 SEC	139.3 A	
	3.7KW x 4P	16.0 A	1 DRAVE	SS-30	3 SEC	1 SEC	17.6 A	
C50TON	33KW x 6P	126.6 A	1 DRAVE	SS-150	3 SEC	1 SEC	139.3 A	
	3.7KW x 4P	16.0 A	1 DRAVE	SS-30	3 SEC	1 SEC	17.6 A	
C60 TON	33KW x 6P	126.6 A	1 DRAVE	SS-150	3 SEC	1 SEC	139.3 A	
	3.7KW x 4P	16.0 A	1 DRAVE	SS-30	3 SEC	1 SEC	17.6 A	
C70 TON	33KW x 6P	126.6 A	1 DRAVE	SS-150	3 SEC	1 SEC	139.3 A	
	3.7KW x 4P	16.0 A	1 DRAVE	SS-30	3 SEC	1 SEC	17.6 A	

NOTE

1. 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

E.O.C.R 권고 SETTING치

* POWER SOURCE : AC 3Φ 380V 60Hz

극동호이스트(주)

HOIST	MOTOR 용량	1 정격 전류	DRIVE TYPE	E.O.C.R TYPE	권고 SETTING 치			REMARK
					DELAY TIME	OPERATION TIME	CURRENT	
C15 TON	13KW x 8P	34.2 A	1 DRAVE	SS-60	3 SEC	1 SEC	37.6 A	
	1.8KW x 8P	6.4 A	1 DRAVE	SS-30	3 SEC	1 SEC	7.0 A	
C20 TON	17KW x 8P	44.3 A	1 DRAVE	SS-60	3 SEC	1 SEC	48.7 A	
	1.8KW x 8P	6.4 A	1 DRAVE	SS-30	3 SEC	1 SEC	7.0 A	
C30 TON	17KW x 8P	44.3 A	1 DRAVE	SS-60	3 SEC	1 SEC	48.7 A	
	1.8KW x 8P	6.4 A	1 DRAVE	SS-30	3 SEC	1 SEC	7.0 A	
C35 TON	33KW x 6P	77.3 A	1 DRAVE	SS-100	3 SEC	1 SEC	85.0 A	
	3.7KW x 4P	9.3 A	1 DRAVE	SS-30	3 SEC	1 SEC	10.2 A	
C40 TON	33KW x 6P	77.3 A	1 DRAVE	SS-100	3 SEC	1 SEC	85.0 A	
	3.7KW x 4P	9.3 A	1 DRAVE	SS-30	3 SEC	1 SEC	10.2 A	
C50 TON	33KW x 6P	77.3 A	1 DRAVE	SS-100	3 SEC	1 SEC	85.0 A	
	3.7KW x 4P	9.3 A	1 DRAVE	SS-30	3 SEC	1 SEC	10.2 A	
C60 TON	33KW x 6P	77.3 A	1 DRAVE	SS-100	3 SEC	1 SEC	85.0 A	
	3.7KW x 4P	9.3 A	1 DRAVE	SS-30	3 SEC	1 SEC	10.2 A	
C70 TON	33KW x 6P	77.3 A	1 DRAVE	SS-100	3 SEC	1 SEC	85.0 A	
	3.7KW x 4P	9.3 A	1 DRAVE	SS-30	3 SEC	1 SEC	10.2 A	

NOTE

1. 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

E.O.C.R 권고 SETTING치

* POWER SOURCE : AC 3Φ 440V 60HZ

극동호이스트(주)

HOIST	MOTOR 용량	MOTOR 정격 전류	DRIVE TYPE	E.O.C.R TYPE	권고 SETTING 치			REMARK
					DELAY TIME	OPERATION TIME	CURRENT	
C15 TON	13KW x 8P	29.5 A	1 DRAVE	SS-60	3 SEC	1 SEC	32.5 A	
	1.8KW x 8P	5.5 A	1 DRAVE	SS-30	3 SEC	1 SEC	6.1 A	
C20 TON	17KW x 8P	38.3 A	1 DRAVE	SS-60	3 SEC	1 SEC	42.1 A	
	1.8KW x 8P	5.5 A	1 DRAVE	SS-30	3 SEC	1 SEC	6.1 A	
C30 TON	17KW x 8P	38.3 A	1 DRAVE	SS-60	3 SEC	1 SEC	42.1 A	
	1.8KW x 8P	5.5 A	1 DRAVE	SS-30	3 SEC	1 SEC	6.1 A	
C35 TON	33KW x 6P	63.3 A	1 DRAVE	SS-100	3 SEC	1 SEC	69.6 A	
	3.7KW x 4P	8.0 A	1 DRAVE	SS-30	3 SEC	1 SEC	8.8 A	
C40 TON	33KW x 6P	63.3 A	1 DRAVE	SS-100	3 SEC	1 SEC	69.6 A	
	3.7KW x 4P	8.0 A	1 DRAVE	SS-30	3 SEC	1 SEC	8.8 A	
C50 TON	33KW x 6P	63.3 A	1 DRAVE	SS-100	3 SEC	1 SEC	69.6 A	
	3.7KW x 4P	8.0 A	1 DRAVE	SS-30	3 SEC	1 SEC	8.8 A	
C60 TON	33KW x 6P	63.3 A	1 DRAVE	SS-100	3 SEC	1 SEC	69.6 A	
	3.7KW x 4P	8.0 A	1 DRAVE	SS-30	3 SEC	1 SEC	8.8 A	
C70 TON	33KW x 6P	63.3 A	1 DRAVE	SS-100	3 SEC	1 SEC	69.6 A	
	3.7KW x 4P	8.0 A	1 DRAVE	SS-30	3 SEC	1 SEC	8.8 A	

NOTE

1. 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

E.O.C.R 권고 SETTING치

* POWER SOURCE : AC 3Φ 460V 60HZ

극동호이스트(주)

HOIST	MOTOR 용량	MOTOR 정격 전류	DRIVE TYPE	E.O.C.R TYPE	권고 SETTING 치			REMARK
					DELAY TIME	OPERATION TIME	CURRENT	
C15 TON	13KW x 8P	28.4 A	1 DRAVE	SS-60	3 SEC	1 SEC	31.2 A	
	1.8KW x 8P	5.3 A	1 DRAVE	SS-30	3 SEC	1 SEC	5.8 A	
C20 TON	17KW x 8P	36.7 A	1 DRAVE	SS-60	3 SEC	1 SEC	40.4 A	
	1.8KW x 8P	5.3 A	1 DRAVE	SS-30	3 SEC	1 SEC	5.8 A	
C30 TON	17KW x 8P	36.7 A	1 DRAVE	SS-60	3 SEC	1 SEC	40.4 A	
	1.8KW x 8P	5.3 A	1 DRAVE	SS-30	3 SEC	1 SEC	5.8 A	
C35 TON	33KW x 6P	60.5 A	1 DRAVE	SS-100	3 SEC	1 SEC	66.6 A	
	3.7KW x 4P	7.7 A	1 DRAVE	SS-30	3 SEC	1 SEC	8.5 A	
C40 TON	33KW x 6P	60.5 A	1 DRAVE	SS-100	3 SEC	1 SEC	66.6 A	
	3.7KW x 4P	7.7 A	1 DRAVE	SS-30	3 SEC	1 SEC	8.5 A	
C50 TON	33KW x 6P	60.5 A	1 DRAVE	SS-100	3 SEC	1 SEC	66.6 A	
	3.7KW x 4P	7.7 A	1 DRAVE	SS-30	3 SEC	1 SEC	8.5 A	
C60 TON	33KW x 6P	60.5 A	1 DRAVE	SS-100	3 SEC	1 SEC	66.6 A	
	3.7KW x 4P	7.7 A	1 DRAVE	SS-30	3 SEC	1 SEC	8.5 A	
C70 TON	33KW x 6P	60.5 A	1 DRAVE	SS-100	3 SEC	1 SEC	66.6 A	
	3.7KW x 4P	7.7 A	1 DRAVE	SS-30	3 SEC	1 SEC	8.5 A	

NOTE

1. 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

E.O.C.R 권고 SETTING치

* POWER SOURCE : AC 3Φ 480V 60Hz

극동하이스트(주)

HOIST	MOTOR 용량	MOTOR 정격 전류	DRIVE TYPE	E.O.C.R TYPE	권고 SETTING 치			REMARK
					DELAY TIME	OPERATION TIME	CURRENT	
C15 TON	13KW x 8P	27.2 A	1 DRAVE	SS-30	3 SEC	1 SEC	29.9 A	
	1.8KW x 8P	5.1 A	1 DRAVE	SS-30	3 SEC	1 SEC	5.6 A	
C20 TON	17KW x 8P	35.2 A	1 DRAVE	SS-60	3 SEC	1 SEC	38.7 A	
	1.8KW x 8P	5.1 A	1 DRAVE	SS-30	3 SEC	1 SEC	5.6 A	
C30 TON	17KW x 8P	35.2 A	1 DRAVE	SS-60	3 SEC	1 SEC	38.7 A	
	1.8KW x 8P	5.1 A	1 DRAVE	SS-30	3 SEC	1 SEC	5.6 A	
C35 TON	33KW x 6P	58.0 A	1 DRAVE	SS-100	3 SEC	1 SEC	63.8 A	
	3.7KW x 4P	7.3 A	1 DRAVE	SS-30	3 SEC	1 SEC	8.0 A	
C40 TON	33KW x 6P	58.0 A	1 DRAVE	SS-100	3 SEC	1 SEC	63.8 A	
	3.7KW x 4P	7.3 A	1 DRAVE	SS-30	3 SEC	1 SEC	8.0 A	
C650 TON	33KW x 6P	58.0 A	1 DRAVE	SS-100	3 SEC	1 SEC	63.8 A	
	3.7KW x 4P	7.3 A	1 DRAVE	SS-30	3 SEC	1 SEC	8.0 A	
C60 TON	33KW x 6P	58.0 A	1 DRAVE	SS-100	3 SEC	1 SEC	63.8 A	
	3.7KW x 4P	7.3 A	1 DRAVE	SS-30	3 SEC	1 SEC	8.0 A	
C70 TON	33KW x 6P	58.0 A	1 DRAVE	SS-100	3 SEC	1 SEC	63.8 A	
	3.7KW x 4P	7.3 A	1 DRAVE	SS-30	3 SEC	1 SEC	8.0 A	

NOTE

1. 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

LOAD LIMITER 권고 SETTING치

* POWER SOURCE : AC 3Φ 220V 60Hz

극동하이스트(주)

HOIST	MOTOR 용량	LOAD LIMITER 권고 SETTING치			LOAD CURRENT		C.T MODEL	연결단자 NO	C.T 용량	REMARK
		LOAD CURRENT	ADJ START TIME	SHOCK TIME	100%	110%				
C15 TON	13KW x 8P	110%	1 SEC	1 SEC	59.0 A	64.9 A	CT-2	K-K1, L-L1	5 V.A	
	1.8KW x 8P	110%	1 SEC	1 SEC	11.0 A	12.1 A	CT-2	K-K1, L-L1	5 V.A	
C20 TON	17KW x 8P	110%	1 SEC	1 SEC	76.6 A	84.3 A	CT-2	K-K1, L-L1	5 V.A	
	1.8KW x 8P	110%	1 SEC	1 SEC	11.0 A	12.1 A	CT-2	K-K1, L-L1	5 V.A	
C30 TON	17KW x 8P	110%	1 SEC	1 SEC	76.6 A	84.3 A	CT-2	K-K1, L-L1	5 V.A	
	1.8KW x 8P	110%	1 SEC	1 SEC	11.0 A	12.1 A	CT-2	K-K1, L-L1	5 V.A	
C35 TON	33KW x 6P	110%	1 SEC	1 SEC	126.6 A	139.3 A	CT-2	K-K1, L-L1	5 V.A	
	3.7KW x 4P	110%	1 SEC	1 SEC	16.0 A	17.6 A	CT-2	K-K1, L-L1	5 V.A	
C40 TON	33KW x 6P	110%	1 SEC	1 SEC	126.6 A	139.3 A	CT-2	K-K1, L-L1	5 V.A	
	3.7KW x 4P	110%	1 SEC	1 SEC	16.0 A	17.6 A	CT-2	K-K1, L-L1	5 V.A	
C50 TON	33KW x 6P	110%	1 SEC	1 SEC	126.6 A	139.3 A	CT-2	K-K1, L-L1	5 V.A	
	3.7KW x 4P	110%	1 SEC	1 SEC	16.0 A	17.6 A	CT-2	K-K1, L-L1	5 V.A	
C60 TON	33KW x 6P	110%	1 SEC	1 SEC	126.6 A	139.3 A	CT-2	K-K1, L-L1	5 V.A	
	3.7KW x 4P	110%	1 SEC	1 SEC	16.0 A	17.6 A	CT-2	K-K1, L-L1	5 V.A	
C70 TON	33KW x 6P	110%	1 SEC	1 SEC	126.6 A	139.3 A	CT-2	K-K1, L-L1	5 V.A	
	3.7KW x 4P	110%	1 SEC	1 SEC	16.0 A	17.6 A	CT-2	K-K1, L-L1	5 V.A	

NOTE

1. 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

LOAD LIMITER 권고 SETTING치

* POWER SOURCE : AC 3Φ 380V 60Hz

극동하이스트(주)

HOIST	MOTOR 용량	LOAD LIMITER 권고 SETTING치			LOAD CURRENT		C.T MODEL	연결단자 NO	C.T 용량	REMARK
		LOAD CURRENT	ADJ START TIME	SHOCK TIME	100%	110%				
C15 TON	13KW x 8P	110%	1 SEC	1 SEC	34.2 A	37.6 A	CT-2	K-K1, L-L1	5 V.A	
	1.8KW x 8P	110%	1 SEC	1 SEC	6.4 A	7.0 A	CT-2	K-K1, L-L1	5 V.A	
C20 TON	17KW x 8P	110%	1 SEC	1 SEC	44.3 A	48.7 A	CT-2	K-K1, L-L1	5 V.A	
	1.8KW x 8P	110%	1 SEC	1 SEC	6.4 A	7.0 A	CT-2	K-K1, L-L1	5 V.A	
C30 TON	17KW x 8P	110%	1 SEC	1 SEC	44.3 A	48.7 A	CT-2	K-K1, L-L1	5 V.A	
	1.8KW x 8P	110%	1 SEC	1 SEC	6.4 A	7.0 A	CT-2	K-K1, L-L1	5 V.A	
C35 TON	33KW x 6P	110%	1 SEC	1 SEC	77.3 A	85.0 A	CT-2	K-K1, L-L1	5 V.A	
	3.7KW x 4P	110%	1 SEC	1 SEC	9.3 A	10.2 A	CT-2	K-K1, L-L1	5 V.A	
C40 TON	33KW x 6P	110%	1 SEC	1 SEC	77.3 A	85.0 A	CT-2	K-K1, L-L1	5 V.A	
	3.7KW x 4P	110%	1 SEC	1 SEC	9.3 A	10.2 A	CT-2	K-K1, L-L1	5 V.A	
C50 TON	33KW x 6P	110%	1 SEC	1 SEC	77.3 A	85.0 A	CT-2	K-K1, L-L1	5 V.A	
	3.7KW x 4P	110%	1 SEC	1 SEC	9.3 A	10.2 A	CT-2	K-K1, L-L1	5 V.A	
C60 TON	33KW x 6P	110%	1 SEC	1 SEC	77.3 A	85.0 A	CT-2	K-K1, L-L1	5 V.A	
	3.7KW x 4P	110%	1 SEC	1 SEC	9.3 A	10.2 A	CT-2	K-K1, L-L1	5 V.A	
C70 TON	33KW x 6P	110%	1 SEC	1 SEC	77.3 A	85.0 A	CT-2	K-K1, L-L1	5 V.A	
	3.7KW x 4P	110%	1 SEC	1 SEC	9.3 A	10.2 A	CT-2	K-K1, L-L1	5 V.A	

NOTE

1. 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

LOAD LIMITER 권고 SETTING치

* POWER SOURCE : AC 3Φ 440V 60Hz

극동하이스트(주)

HOIST	MOTOR 용량	LOAD LIMITER 권고 SETTING치			LOAD CURRENT		C.T MODEL	연결단자 NO	C.T 용량	REMARK
		LOAD CURRENT	ADJ START TIME	SHOCK TIME	100%	110%				
C15 TON	13KW x 8P	110%	1 SEC	1 SEC	29.5 A	32.5 A	CT-2	K-K1, L-L1	5 V.A	
	1.8KW x 8P	110%	1 SEC	1 SEC	5.5 A	6.1 A	CT-2	K-K1, L-L1	5 V.A	
C20 TON	17KW x 8P	110%	1 SEC	1 SEC	38.3 A	42.1 A	CT-2	K-K1, L-L1	5 V.A	
	1.8KW x 8P	110%	1 SEC	1 SEC	5.5 A	6.1 A	CT-2	K-K1, L-L1	5 V.A	
C30 TON	17KW x 8P	110%	1 SEC	1 SEC	38.3 A	42.1 A	CT-2	K-K1, L-L1	5 V.A	
	1.8KW x 8P	110%	1 SEC	1 SEC	5.5 A	6.1 A	CT-2	K-K1, L-L1	5 V.A	
C35 TON	33KW x 6P	110%	1 SEC	1 SEC	63.3 A	69.6 A	CT-2	K-K1, L-L1	5 V.A	
	3.7KW x 4P	110%	1 SEC	1 SEC	8.0 A	8.8 A	CT-2	K-K1, L-L1	5 V.A	
C40 TON	33KW x 6P	110%	1 SEC	1 SEC	63.3 A	69.6 A	CT-2	K-K1, L-L1	5 V.A	
	3.7KW x 4P	110%	1 SEC	1 SEC	8.0 A	8.8 A	CT-2	K-K1, L-L1	5 V.A	
C50 TON	33KW x 6P	110%	1 SEC	1 SEC	63.3 A	69.6 A	CT-2	K-K1, L-L1	5 V.A	
	3.7KW x 4P	110%	1 SEC	1 SEC	8.0 A	8.8 A	CT-2	K-K1, L-L1	5 V.A	
C60 TON	33KW x 6P	110%	1 SEC	1 SEC	63.3 A	69.6 A	CT-2	K-K1, L-L1	5 V.A	
	3.7KW x 4P	110%	1 SEC	1 SEC	8.0 A	8.8 A	CT-2	K-K1, L-L1	5 V.A	
C70 TON	33KW x 6P	110%	1 SEC	1 SEC	63.3 A	69.6 A	CT-2	K-K1, L-L1	5 V.A	
	3.7KW x 4P	110%	1 SEC	1 SEC	8.0 A	8.8 A	CT-2	K-K1, L-L1	5 V.A	

NOTE

1. 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

LOAD LIMITER 권고 SETTING치

* POWER SOURCE : AC 3Φ 460V 60Hz

극동하이스트(주)

HOIST	MOTOR 용량	LOAD LIMITER 권고 SETTING치			LOAD CURRENT		C.T MODEL	연결단자 NO	C.T 용량	REMARK
		LOAD CURRENT	ADJ START TIME	SHOCK TIME	100%	110%				
C15 TON	13KW x 8P	110%	1 SEC	1 SEC	28.4 A	31.2 A	CT-2	K-K1, L-L1	5 V.A	
	1.8KW x 8P	110%	1 SEC	1 SEC	5.3 A	5.8 A	CT-2	K-K1, L-L1	5 V.A	
C20 TON	17KW x 8P	110%	1 SEC	1 SEC	36.7 A	40.4 A	CT-2	K-K1, L-L1	5 V.A	
	1.8KW x 8P	110%	1 SEC	1 SEC	5.3 A	5.8 A	CT-2	K-K1, L-L1	5 V.A	
C30 TON	17KW x 8P	110%	1 SEC	1 SEC	36.7 A	40.4 A	CT-2	K-K1, L-L1	5 V.A	
	1.8KW x 8P	110%	1 SEC	1 SEC	5.3 A	5.8 A	CT-2	K-K1, L-L1	5 V.A	
C35 TON	33KW x 6P	110%	1 SEC	1 SEC	60.5 A	66.6 A	CT-2	K-K1, L-L1	5 V.A	
	3.7KW x 4P	110%	1 SEC	1 SEC	7.7 A	8.5 A	CT-2	K-K1, L-L1	5 V.A	
C40 TON	33KW x 6P	110%	1 SEC	1 SEC	60.5 A	66.6 A	CT-2	K-K1, L-L1	5 V.A	
	3.7KW x 4P	110%	1 SEC	1 SEC	7.7 A	8.5 A	CT-2	K-K1, L-L1	5 V.A	
C50 TON	33KW x 6P	110%	1 SEC	1 SEC	60.5 A	66.6 A	CT-2	K-K1, L-L1	5 V.A	
	3.7KW x 4P	110%	1 SEC	1 SEC	7.7 A	8.5 A	CT-2	K-K1, L-L1	5 V.A	
C60 TON	33KW x 6P	110%	1 SEC	1 SEC	60.5 A	66.6 A	CT-2	K-K1, L-L1	5 V.A	
	3.7KW x 4P	110%	1 SEC	1 SEC	7.7 A	8.5 A	CT-2	K-K1, L-L1	5 V.A	
C70 TON	33KW x 6P	110%	1 SEC	1 SEC	60.5 A	66.6 A	CT-2	K-K1, L-L1	5 V.A	
	3.7KW x 4P	110%	1 SEC	1 SEC	7.7 A	8.5 A	CT-2	K-K1, L-L1	5 V.A	

NOTE

1. 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

LOAD LIMITER 권고 SETTING치

* POWER SOURCE : AC 3Φ 480V 60Hz

극동하이스트(주)

HOIST	MOTOR 용량	LOAD LIMITER 권고 SETTING치			LOAD CURRENT		C.T MODEL	연결단자 NO	C.T 용량	REMARK
		LOAD CURRENT	ADJ START TIME	SHOCK TIME	100%	110%				
C15 TON	13KW x 8P	110%	1 SEC	1 SEC	27.2 A	29.9 A	CT-2	K-K1, L-L1	5 V.A	
	1.8KW x 8P	110%	1 SEC	1 SEC	5.1 A	5.6 A	CT-2	K-K1, L-L1	5 V.A	
C20 TON	17KW x 8P	110%	1 SEC	1 SEC	35.2 A	38.7 A	CT-2	K-K1, L-L1	5 V.A	
	1.8KW x 8P	110%	1 SEC	1 SEC	5.1 A	5.6 A	CT-2	K-K1, L-L1	5 V.A	
C30 TON	17KW x 8P	110%	1 SEC	1 SEC	35.2 A	38.7 A	CT-2	K-K1, L-L1	5 V.A	
	1.8KW x 8P	110%	1 SEC	1 SEC	5.1 A	5.6 A	CT-2	K-K1, L-L1	5 V.A	
C35 TON	33KW x 6P	110%	1 SEC	1 SEC	58.0 A	63.8 A	CT-2	K-K1, L-L1	5 V.A	
	3.7KW x 4P	110%	1 SEC	1 SEC	7.3 A	8.0 A	CT-2	K-K1, L-L1	5 V.A	
C40 TON	33KW x 6P	110%	1 SEC	1 SEC	58.0 A	63.8 A	CT-2	K-K1, L-L1	5 V.A	
	3.7KW x 4P	110%	1 SEC	1 SEC	7.3 A	8.0 A	CT-2	K-K1, L-L1	5 V.A	
C50 TON	33KW x 6P	110%	1 SEC	1 SEC	58.0 A	63.8 A	CT-2	K-K1, L-L1	5 V.A	
	3.7KW x 4P	110%	1 SEC	1 SEC	7.3 A	8.0 A	CT-2	K-K1, L-L1	5 V.A	
C60 TON	33KW x 6P	110%	1 SEC	1 SEC	58.0 A	63.8 A	CT-2	K-K1, L-L1	5 V.A	
	3.7KW x 4P	110%	1 SEC	1 SEC	7.3 A	8.0 A	CT-2	K-K1, L-L1	5 V.A	
C70 TON	33KW x 6P	110%	1 SEC	1 SEC	58.0 A	63.8 A	CT-2	K-K1, L-L1	5 V.A	
	3.7KW x 4P	110%	1 SEC	1 SEC	7.3 A	8.0 A	CT-2	K-K1, L-L1	5 V.A	

NOTE

1. 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

E.O.C.R 권고 SETTING치

* POWER SOURCE : AC 3Φ 220V 60Hz

극동호이스트(주)

HOIST	MOTOR 용량	MOTOR 정격 전류	DRIVE TYPE	E.O.C.R TYPE	권고 SETTING 치			REMARK
					DELAY TIME	OPERATION TIME	CURRENT	
C1 TON	2.4KW x 4P	10.0 A	1 DRAVE	SS-30	3 SEC	1 SEC	11.0 A	
	0.4KW x 4P	2.7 A	1 DRAVE	SS-05	3 SEC	1 SEC	3.0 A	
C2 TON	3.7KW x 4P	16.0 A	1 DRAVE	SS-30	3 SEC	1 SEC	17.6 A	
	0.4KW x 4P	2.7 A	1 DRAVE	SS-05	3 SEC	1 SEC	3.0 A	
C2.8 TON	5.0KW x 4P	22.8 A	1 DRAVE	SS-30	3 SEC	1 SEC	25.1 A	
	1.5KW x 4P	7.3 A	1 DRAVE	SS-30	3 SEC	1 SEC	8.0 A	
C3 TON	5.5KW x 4P	22.8 A	1 DRAVE	SS-30	3 SEC	1 SEC	25.1 A	
	1.5KW x 4P	7.3 A	1 DRAVE	SS-30	3 SEC	1 SEC	8.0 A	
C5 TON	5.5KW x 6P	28.2 A	1 DRAVE	SS-30	3 SEC	1 SEC	31.0 A	
	1.0KW x 6P	6.7 A	1 DRAVE	SS-30	3 SEC	1 SEC	7.4 A	
C7.5 TON	5.5KW x 6P	28.2 A	1 DRAVE	SS-30	3 SEC	1 SEC	31.0 A	
	1.0KW x 6P	6.7 A	1 DRAVE	SS-30	3 SEC	1 SEC	7.4 A	
C10 TON	9.0KW x 8P	45.0 A	1 DRAVE	SS-60	3 SEC	1 SEC	49.5 A	
	1.1KW x 8P	8.0 A	1 DRAVE	SS-30	3 SEC	1 SEC	8.7 A	

NOTE

1. 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

E.O.C.R 권고 SETTING치

* POWER SOURCE : AC 3Φ 380V 60Hz

극동호이스트(주)

HOIST	MOTOR 용량	MOTOR 정격 전류	DRIVE TYPE	E.O.C.R TYPE	권고 SETTING 치			REMARK
					DELAY TIME	OPERATION TIME	CURRENT	
C1 TON	2.4KW x 4P	5.8 A	1 DRAVE	SS-30	3 SEC	1 SEC	6.4 A	
	0.4KW x 4P	1.6 A	1 DRAVE	SS-05	3 SEC	1 SEC	1.8 A	
C2 TON	3.7KW x 4P	9.3 A	1 DRAVE	SS-30	3 SEC	1 SEC	10.2 A	
	0.4KW x 4P	1.6 A	1 DRAVE	SS-05	3 SEC	1 SEC	1.8 A	
C2.8 TON	5.0KW x 4P	12.2 A	1 DRAVE	SS-30	3 SEC	1 SEC	13.4 A	
	1.5KW x 4P	4.2 A	1 DRAVE	SS-05	3 SEC	1 SEC	4.6 A	
C3 TON	5.5KW x 4P	12.2 A	1 DRAVE	SS-30	3 SEC	1 SEC	13.4 A	
	1.5KW x 4P	4.2 A	1 DRAVE	SS-05	3 SEC	1 SEC	4.6 A	
C5 TON	5.5KW x 6P	16.3 A	1 DRAVE	SS-30	3 SEC	1 SEC	17.9 A	
	1.0KW x 6P	3.9 A	1 DRAVE	SS-05	3 SEC	1 SEC	4.3 A	
C7.5 TON	5.5KW x 6P	16.3 A	1 DRAVE	SS-30	3 SEC	1 SEC	17.9 A	
	1.0KW x 6P	3.9 A	1 DRAVE	SS-05	3 SEC	1 SEC	4.3 A	
C10 TON	9.0KW x 8P	26.0 A	1 DRAVE	SS-30	3 SEC	1 SEC	28.6 A	
	1.1KW x 8P	4.6 A	1 DRAVE	SS-05	3 SEC	1 SEC	5.0 A	

NOTE

1. 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

E.O.C.R 권고 SETTING치

* POWER SOURCE : AC 3Φ 440V 60Hz

극동호이스트(주)

HOIST	MOTOR 용량	MOTOR 정격 전류	DRIVE TYPE	E.O.C.R TYPE	권고 SETTING 치			REMARK
					DELAY TIME	OPERATION TIME	CURRENT	
C1 TON	2.4KW x 4P	5.0 A	1 DRAVE	SS-30	3 SEC	1 SEC	5.5 A	
	0.4KW x 4P	1.4 A	1 DRAVE	SS-05	3 SEC	1 SEC	1.5 A	
C2 TON	3.7KW x 4P	8.0 A	1 DRAVE	SS-30	3 SEC	1 SEC	8.8 A	
	0.4KW x 4P	1.4 A	1 DRAVE	SS-05	3 SEC	1 SEC	1.5 A	
C2.8 TON	5.0KW x 4P	10.5 A	1 DRAVE	SS-30	3 SEC	1 SEC	11.6 A	
	1.5KW x 4P	3.7 A	1 DRAVE	SS-05	3 SEC	1 SEC	4.1 A	
C3 TON	5.5KW x 4P	10.5 A	1 DRAVE	SS-30	3 SEC	1 SEC	11.6 A	
	1.5KW x 4P	3.7 A	1 DRAVE	SS-05	3 SEC	1 SEC	4.1 A	
C5 TON	5.5KW x 6P	14.1 A	1 DRAVE	SS-30	3 SEC	1 SEC	15.5 A	
	1.0KW x 6P	3.3 A	1 DRAVE	SS-05	3 SEC	1 SEC	3.6 A	
C7.5 TON	5.5KW x 6P	14.1 A	1 DRAVE	SS-30	3 SEC	1 SEC	15.5 A	
	1.0KW x 6P	3.3 A	1 DRAVE	SS-05	3 SEC	1 SEC	3.6 A	
C10 TON	9.0KW x 8P	22.5 A	1 DRAVE	SS-30	3 SEC	1 SEC	24.8 A	
	1.1KW x 8P	4.0 A	1 DRAVE	SS-05	3 SEC	1 SEC	4.3 A	

NOTE

1. 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

E.O.C.R 권고 SETTING치

* POWER SOURCE : AC 3Φ 460V 60Hz

극동호이스트(주)

HOIST	MOTOR 용량	MOTOR 정격 전류	DRIVE TYPE	E.O.C.R TYPE	권고 SETTING 치			REMARK
					DELAY TIME	OPERATION TIME	CURRENT	
C1 TON	2.4KW x 4P	4.8 A	1 DRAVE	SS-30	3 SEC	1 SEC	5.3 A	
	0.4KW x 4P	1.4 A	1 DRAVE	SS-05	3 SEC	1 SEC	1.5 A	
C2 TON	3.7KW x 4P	7.7 A	1 DRAVE	SS-30	3 SEC	1 SEC	8.5 A	
	0.4KW x 4P	1.4 A	1 DRAVE	SS-05	3 SEC	1 SEC	1.5 A	
C2.8 TON	5.0KW x 4P	10.0 A	1 DRAVE	SS-30	3 SEC	1 SEC	11.0 A	
	1.5KW x 4P	3.5 A	1 DRAVE	SS-05	3 SEC	1 SEC	3.9 A	
C3 TON	5.5KW x 4P	10.0 A	1 DRAVE	SS-30	3 SEC	1 SEC	11.0 A	
	1.5KW x 4P	3.5 A	1 DRAVE	SS-05	3 SEC	1 SEC	3.9 A	
C5 TON	5.5KW x 6P	13.5 A	1 DRAVE	SS-30	3 SEC	1 SEC	14.9 A	
	1.0KW x 6P	3.2 A	1 DRAVE	SS-05	3 SEC	1 SEC	3.5 A	
C7.5 TON	5.5KW x 6P	13.5 A	1 DRAVE	SS-30	3 SEC	1 SEC	14.9 A	
	1.0KW x 6P	3.2 A	1 DRAVE	SS-05	3 SEC	1 SEC	3.5 A	
C10 TON	9.0KW x 8P	21.5 A	1 DRAVE	SS-30	3 SEC	1 SEC	23.7 A	
	1.1KW x 8P	3.7 A	1 DRAVE	SS-05	3 SEC	1 SEC	4.1 A	

NOTE

1. 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

E.O.C.R 권고 SETTING치

* POWER SOURCE : AC 3Φ 480V 60Hz

극동호이스트(주)

HOIST	MOTOR 용량	MOTOR 정격 전류	DRIVE TYPE	E.O.C.R TYPE	권고 SETTING 치			REMARK
					DELAY TIME	OPERATION TIME	CURRENT	
C1 TON	2.4KW x 4P	4.6 A	1 DRAVE	SS-30	3 SEC	1 SEC	5.1 A	
	0.4KW x 4P	1.4 A	1 DRAVE	SS-05	3 SEC	1 SEC	1.5 A	
C2 TON	3.7KW x 4P	7.3 A	1 DRAVE	SS-30	3 SEC	1 SEC	8.0 A	
	0.4KW x 4P	1.4 A	1 DRAVE	SS-05	3 SEC	1 SEC	1.5 A	
C2.8 TON	5.0KW x 4P	9.6 A	1 DRAVE	SS-30	3 SEC	1 SEC	10.6 A	
	1.5KW x 4P	3.4 A	1 DRAVE	SS-05	3 SEC	1 SEC	3.7 A	
C3 TON	5.5KW x 4P	9.6 A	1 DRAVE	SS-30	3 SEC	1 SEC	10.6 A	
	1.5KW x 4P	3.4 A	1 DRAVE	SS-05	3 SEC	1 SEC	3.7 A	
C5 TON	5.5KW x 6P	12.9 A	1 DRAVE	SS-30	3 SEC	1 SEC	14.2 A	
	1.0KW x 6P	3.1 A	1 DRAVE	SS-05	3 SEC	1 SEC	3.4 A	
C7.5 TON	5.5KW x 6P	12.9 A	1 DRAVE	SS-30	3 SEC	1 SEC	14.2 A	
	1.0KW x 6P	3.1 A	1 DRAVE	SS-05	3 SEC	1 SEC	3.4 A	
C10 TON	9.0KW x 8P	20.6 A	1 DRAVE	SS-30	3 SEC	1 SEC	22.7 A	
	1.1KW x 8P	3.6 A	1 DRAVE	SS-05	3 SEC	1 SEC	4.0 A	

NOTE

1. 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

LOAD LIMITER 권고 SETTING치

극동호이스트(주)

* POWER SOURCE : AC 3Φ 220V 60Hz

HOIST	MOTOR 용량	LOAD LIMITER 권고 SETTING치			LOAD CURRENT		C.T MODEL	연결단자 NO	C.T 용량	REMARK
		LOAD CURRENT	ADJ START TIME	SHOCK TIME	100%	110%				
C1 TON	2.4KW x 4P	110%	1 SEC	1 SEC	10 A	11.2 A	CT-2	K-K1, L-L1	5 V.A	
	0.4KW x 4P	110%	1 SEC	1 SEC	2.7 A	3.1 A	CT-1	K-K1, L-L1	5 V.A	
C2 TON	3.7KW x 4P	110%	1 SEC	1 SEC	16.0 A	17.4 A	CT-2	K-K1, L-L1	5 V.A	
	0.4KW x 4P	110%	1 SEC	1 SEC	2.7 A	3.1 A	CT-1	K-K1, L-L1	5 V.A	
C2.8 TON	5.0KW x 4P	110%	1 SEC	1 SEC	22.8 A	24.2 A	CT-2	K-K1, L-L1	5 V.A	
	1.5KW x 4P	110%	1 SEC	1 SEC	7.3 A	8.3 A	CT-1	K-K1, L-L1	5 V.A	
C3 TON	5.5KW x 4P	110%	1 SEC	1 SEC	22.8 A	24.3 A	CT-2	K-K1, L-L1	5 V.A	
	1.5KW x 4P	110%	1 SEC	1 SEC	7.3 A	8.3 A	CT-1	K-K1, L-L1	5 V.A	
C5 TON	5.5KW x 6P	110%	1 SEC	1 SEC	28.2 A	30.1 A	CT-2	K-K1, L-L1	5 V.A	
	1.0KW x 6P	110%	1 SEC	1 SEC	6.7 A	8.1 A	CT-1	K-K1, L-L1	5 V.A	
C7.5 TON	5.5KW x 6P	110%	1 SEC	1 SEC	28.2 A	30.1 A	CT-2	K-K1, L-L1	5 V.A	
	1.0KW x 6P	110%	1 SEC	1 SEC	6.7 A	8.1 A	CT-1	K-K1, L-L1	5 V.A	
C10 TON	9.0KW x 8P	110%	1 SEC	1 SEC	45.0 A	49.1 A	CT-2	K-K1, L-L1	5 V.A	
	1.1KW x 8P	110%	1 SEC	1 SEC	7.95A	8.7 A	CT-2	K-K1, L-L1	5 V.A	

NOTE

1. 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능하다.

LOAD LIMITER 권고 SETTING치

극동하이스트(주)

* POWER SOURCE : AC 3Φ 380V 60Hz

HOIST	MOTOR 용량	LOAD LIMITER 권고 SETTING치			LOAD CURRENT		C.T MODEL	연결단자 NO	C.T 용량	REMARK
		LOAD CURRENT	ADJ START TIME	SHOCK TIME	100%	110%				
C1 TON	2.4KW x 4P	110%	1 SEC	1 SEC	5.8 A	6.3 A	CT-2	K-K1, L-L1	5 V.A	
	0.4KW x 4P	110%	1 SEC	1 SEC	1.6 A	2.1 A	CT-1	K-K1, L-L1	5 V.A	
C2 TON	3.7KW x 4P	110%	1 SEC	1 SEC	9.3 A	11.3 A	CT-2	K-K1, L-L1	5 V.A	
	0.4KW x 4P	110%	1 SEC	1 SEC	1.6 A	2.1 A	CT-1	K-K1, L-L1	5 V.A	
C2.8 TON	5.0KW x 4P	110%	1 SEC	1 SEC	12.2 A	13.6 A	CT-2	K-K1, L-L1	5 V.A	
	1.5KW x 4P	110%	1 SEC	1 SEC	4.2 A	5.4 A	CT-1	K-K1, L-L1	5 V.A	
C3 TON	5.5KW x 4P	110%	1 SEC	1 SEC	12.2 A	13.6 A	CT-2	K-K1, L-L1	5 V.A	
	1.5KW x 4P	110%	1 SEC	1 SEC	4.2 A	5.4 A	CT-1	K-K1, L-L1	5 V.A	
C5 TON	5.5KW x 6P	110%	1 SEC	1 SEC	16.3 A	17.8 A	CT-2	K-K1, L-L1	5 V.A	
	1.0KW x 6P	110%	1 SEC	1 SEC	3.9 A	5.3 A	CT-1	K-K1, L-L1	5 V.A	
C7.5 TON	5.5KW x 6P	110%	1 SEC	1 SEC	16.3 A	17.8 A	CT-2	K-K1, L-L1	5 V.A	
	1.0KW x 6P	110%	1 SEC	1 SEC	3.9 A	5.3 A	CT-1	K-K1, L-L1	5 V.A	
C10 TON	9.0KW x 8P	110%	1 SEC	1 SEC	26.0 A	28.6 A	CT-2	K-K1, L-L1	5 V.A	
	1.1KW x 8P	110%	1 SEC	1 SEC	4.6 A	5.1 A	CT-2	K-K1, L-L1	5 V.A	

NOTE

1. 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

LOAD LIMITER 권고 SETTING치

극동호이스트(주)

* POWER SOURCE : AC 3Φ 440V 60Hz

HOIST	MOTOR 용량	LOAD LIMITER 권고 SETTING치			LOAD CURRENT		C.T MODEL	연결단자 NO	C.T 용량	REMARK
		LOAD CURRENT	ADJ START TIME	SHOCK TIME	100%	110%				
C1 TON	2.4KW x 4P	110%	1 SEC	1 SEC	5.0 A	7.3 A	CT-2	K-K1, L-L1	5 V.A	
	0.4KW x 4P	110%	1 SEC	1 SEC	1.4 A	1.8 A	CT-1	K-K1, L-L1	5 V.A	
C2 TON	3.7KW x 4P	110%	1 SEC	1 SEC	8.0 A	10.8 A	CT-2	K-K1, L-L1	5 V.A	
	0.4KW x 4P	110%	1 SEC	1 SEC	1.4 A	1.8 A	CT-1	K-K1, L-L1	5 V.A	
C2.8 TON	5.0KW x 4P	110%	1 SEC	1 SEC	10.5 A	13.7 A	CT-2	K-K1, L-L1	5 V.A	
	1.5KW x 4P	110%	1 SEC	1 SEC	3.7 A	4.3 A	CT-1	K-K1, L-L1	5 V.A	
C3 TON	5.5KW x 4P	110%	1 SEC	1 SEC	10.5 A	13.7 A	CT-2	K-K1, L-L1	5 V.A	
	1.5KW x 4P	110%	1 SEC	1 SEC	3.7 A	4.3 A	CT-1	K-K1, L-L1	5 V.A	
C5 TON	5.5KW x 6P	110%	1 SEC	1 SEC	14.1 A	18.5 A	CT-2	K-K1, L-L1	5 V.A	
	1.0KW x 6P	110%	1 SEC	1 SEC	3.3 A	4.7 A	CT-1	K-K1, L-L1	5 V.A	
C7.5 TON	5.5KW x 6P	110%	1 SEC	1 SEC	14.1 A	18.5 A	CT-2	K-K1, L-L1	5 V.A	
	1.0KW x 6P	110%	1 SEC	1 SEC	3.3 A	4.7 A	CT-1	K-K1, L-L1	5 V.A	
C10 TON	9.0KW x 8P	110%	1 SEC	1 SEC	22.5 A	24.8 A	CT-2	K-K1, L-L1	5 V.A	
	1.1KW x 8P	110%	1 SEC	1 SEC	4.0 A	4.4 A	CT-1	K-K1, L-L1	5 V.A	



NOTE

1. 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

LOAD LIMITER 권고 SETTING치

극동호이스트(주)

* POWER SOURCE : AC 3Φ 460V 60Hz

HOIST	MOTOR 용량	LOAD LIMITER 권고 SETTING치			LOAD CURRENT		C.T MODEL	연결단자 NO	C.T 용량	REMARK
		LOAD CURRENT	ADJ START TIME	SHOCK TIME	100%	110%				
C1 TON	2.4KW x 4P	110%	1 SEC	1 SEC	4.8 A	5.2 A	CT-2	K-K1, L-L1	5 V.A	
	0.4KW x 4P	110%	1 SEC	1 SEC	1.3 A	1.5 A	CT-1	K-K1, L-L1	5 V.A	
C2 TON	3.7KW x 4P	110%	1 SEC	1 SEC	7.7 A	8.5 A	CT-2	K-K1, L-L1	5 V.A	
	0.4KW x 4P	110%	1 SEC	1 SEC	1.3 A	1.5 A	CT-1	K-K1, L-L1	5 V.A	
C2.8 TON	5.0KW x 4P	110%	1 SEC	1 SEC	10.0 A	11.5 A	CT-2	K-K1, L-L1	5 V.A	
	1.5KW x 4P	110%	1 SEC	1 SEC	3.5 A	4.3 A	CT-1	K-K1, L-L1	5 V.A	
C3 TON	5.5KW x 4P	110%	1 SEC	1 SEC	10.0 A	11.5 A	CT-2	K-K1, L-L1	5 V.A	
	1.5KW x 4P	110%	1 SEC	1 SEC	3.5 A	4.3 A	CT-1	K-K1, L-L1	5 V.A	
C5 TON	5.5KW x 6P	110%	1 SEC	1 SEC	13.5 A	14.7 A	CT-2	K-K1, L-L1	5 V.A	
	1.0KW x 6P	110%	1 SEC	1 SEC	3.2 A	3.6 A	CT-1	K-K1, L-L1	5 V.A	
C7.5 TON	5.5KW x 6P	110%	1 SEC	1 SEC	13.5 A	14.7 A	CT-2	K-K1, L-L1	5 V.A	
	1.0KW x 6P	110%	1 SEC	1 SEC	3.2 A	3.6 A	CT-1	K-K1, L-L1	5 V.A	
C10 TON	9.0KW x 8P	110%	1 SEC	1 SEC	21.5 A	23.7 A	CT-2	K-K1, L-L1	5 V.A	
	1.1KW x 8P	110%	1 SEC	1 SEC	3.7 A	4.1 A	CT-1	K-K1, L-L1	5 V.A	



NOTE

1. 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

LOAD LIMITER 권고 SETTING치

* POWER SOURCE : AC 3Φ 480V 60Hz

극동하이스트(주)

HOIST	MOTOR 용량	LOAD LIMITER 권고 SETTING치			LOAD CURRENT		C.T MODEL	연결단자 NO	C.T 용량	REMARK
		LOAD CURRENT	ADJ START TIME	SHOCK TIME	100%	110%				
C1 TON	2.4KW x 4P	110%	1 SEC	1 SEC	4.6 A	5.0 A	CT-2	K-K1, L-L1	5 V.A	
	0.4KW x 4P	110%	1 SEC	1 SEC	1.2 A	1.35 A	CT-1	K-K1, L-L1	5 V.A	
C2 TON	3.7KW x 4P	110%	1 SEC	1 SEC	7.3 A	8.2 A	CT-2	K-K1, L-L1	5 V.A	
	0.4KW x 4P	110%	1 SEC	1 SEC	1.2 A	1.35 A	CT-1	K-K1, L-L1	5 V.A	
C2.8 TON	5.0KW x 4P	110%	1 SEC	1 SEC	9.6 A	11.2 A	CT-2	K-K1, L-L1	5 V.A	
	1.5KW x 4P	110%	1 SEC	1 SEC	3.4 A	4.3 A	CT-1	K-K1, L-L1	5 V.A	
C3 TON	5.5KW x 4P	110%	1 SEC	1 SEC	9.6 A	11.2 A	CT-2	K-K1, L-L1	5 V.A	
	1.5KW x 4P	110%	1 SEC	1 SEC	3.4 A	4.3 A	CT-1	K-K1, L-L1	5 V.A	
C5 TON	5.5KW x 6P	110%	1 SEC	1 SEC	12.9 A	14.2 A	CT-2	K-K1, L-L1	5 V.A	
	1.0KW x 6P	110%	1 SEC	1 SEC	3.1 A	3.5 A	CT-1	K-K1, L-L1	5 V.A	
C7.5 TON	5.5KW x 6P	110%	1 SEC	1 SEC	12.9 A	14.2 A	CT-2	K-K1, L-L1	5 V.A	
	1.0KW x 6P	110%	1 SEC	1 SEC	3.1 A	3.5 A	CT-1	K-K1, L-L1	5 V.A	
C10 TON	9.0KW x 8P	110%	1 SEC	1 SEC	20.6 A	22.7 A	CT-2	K-K1, L-L1	5 V.A	
	1.1KW x 8P	110%	1 SEC	1 SEC	3.6 A	4.0 A	CT-1	K-K1, L-L1	5 V.A	



NOTE

1. 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

E.O.C.R 권고 SETTING 치

극동하이스트(주)

* POWER SOURCE : AC3Φ 220V 60Hz

MOTOR 용량	MOTOR 정격 전류	DRIVE TYPE	E.O.C.R TYPE	권고 SETTING 치			REMARK
				DELAY TIME	OPERATION TIME	CURRENT	
0.2KW x 6P	2.1 A	1 DRIVE	SS - 05	3 SEC	1 SEC	2.3 A	
		2DRIVE	SS - 05	3 SEC	1 SEC	4.6 A	
0.4KW x 4P	2.7 A	1 DRIVE	SS - 05	3 SEC	1 SEC	3.0 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	5.9 A	
0.5KW x 6P	3.5 A	1 DRIVE	SS - 05	3 SEC	1 SEC	3.9 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	7.7 A	
0.75KW x 4P	4.1 A	1 DRIVE	SS - 05	3 SEC	1 SEC	4.5 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	9.0 A	
1.0KW x 6P	6.8 A	1 DRIVE	SS - 30	3 SEC	1 SEC	7.5 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	15.0 A	
1.5KW x 4P	7.4 A	1 DRIVE	SS - 30	3 SEC	1 SEC	8.1 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	16.3 A	
1.5KW x 6P	7.6 A	1 DRIVE	SS - 30	3 SEC	1 SEC	8.4 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	16.7 A	
2.2KW x 4P	10.0 A	1 DRIVE	SS - 30	3 SEC	1 SEC	11.0 A	
		2 DRIVE	SS - 30	3 SEC	1 SEC	22.0 A	
0.8/0.4KW x 4/8P	4.8/4.25 A	1 DRIVE	SS - 30	3 SEC	1 SEC	5.3 A	
		2 DRIVE	SS - 05	3 SEC	1 SEC	4.7 A	
2.2KW x 6P	12.0 A	1 DRIVE	SS - 30	3 SEC	1 SEC	10.6 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	9.4 A	
3.7KW x 4P	16.0 A	1 DRIVE	SS - 30	3 SEC	1 SEC	13.2 A	
		2DRIVE	SS - 60	3 SEC	1 SEC	26.4 A	
				3 SEC	1 SEC	17.6 A	
				3 SEC	1 SEC	35.2 A	

NOTE

1, 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

E.O.C.R 권고 SETTING 치

극동하이스트(주)

* POWER SOURCE : AC3Φ 380V 60Hz

MOTOR 용량	MOTOR 정격 전류	DRIVE TYPE	E.O.C.R TYPE	권고 SETTING 치			REMARK
				DELAY TIME	OPERATION TIME	CURRENT	
0.2KW x 6P	1.6 A	1 DRIVE	SS - 05	3 SEC	1 SEC	1.8 A	
		2DRIVE	SS - 05	3 SEC	1 SEC	3.5 A	
0.4KW x 4P	1.8 A	1 DRIVE	SS - 05	3 SEC	1 SEC	2.0 A	
		2DRIVE	SS - 05	3 SEC	1 SEC	4.0 A	
0.5KW x 6P	2.0 A	1 DRIVE	SS - 05	3 SEC	1 SEC	2.2 A	
		2DRIVE	SS - 05	3 SEC	1 SEC	4.4 A	
0.75KW x 4P	2.4 A	1 DRIVE	SS - 05	3 SEC	1 SEC	2.6 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	5.3 A	
1.0KW x 6P	3.9 A	1 DRIVE	SS - 05	3 SEC	1 SEC	4.3 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	8.6 A	
1.5KW x 4P	4.3 A	1 DRIVE	SS - 05	3 SEC	1 SEC	4.7 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	9.5 A	
1.5KW x 6P	4.4 A	1 DRIVE	SS - 05	3 SEC	1 SEC	4.8 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	9.7 A	
2.2KW x 4P	5.8 A	1 DRIVE	SS - 30	3 SEC	1 SEC	6.4 A	
		2 DRIVE	SS - 30	3 SEC	1 SEC	12.8 A	
0.8/0.4KW x 4/8P	2.78/2.63 A	1 DRIVE	SS - 05	3 SEC	1 SEC	3.1 A	
		2 DRIVE	SS - 05	3 SEC	1 SEC	2.9 A	
2.2KW x 6P	7.0 A	1 DRIVE	SS - 30	3 SEC	1 SEC	6.1 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	15.4 A	
3.7KW x 4P	9.3 A	1 DRIVE	SS - 30	3 SEC	1 SEC	10.2 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	20.5 A	

NOTE

1, 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

E.O.C.R 권고 SETTING 치

극동하이스트(주)

* POWER SOURCE : AC3Φ 440V 60Hz

MOTOR 용량	MOTOR 정격 전류	DRIVE TYPE	E.O.C.R TYPE	권고 SETTING 치			REMARK
				DELAY TIME	OPERATION TIME	CURRENT	
0.2KW x 6P	1.2 A	1 DRIVE	SS - 05	3 SEC	1 SEC	1.3 A	
		2DRIVE	SS - 05	3 SEC	1 SEC	2.6 A	
0.4KW x 4P	1.4 A	1 DRIVE	SS - 05	3 SEC	1 SEC	1.5 A	
		2DRIVE	SS - 05	3 SEC	1 SEC	3.1 A	
0.5KW x 6P	1.8 A	1 DRIVE	SS - 05	3 SEC	1 SEC	2.0 A	
		2DRIVE	SS - 05	3 SEC	1 SEC	4.0 A	
0.75KW x 4P	2.1 A	1 DRIVE	SS - 05	3 SEC	1 SEC	2.3 A	
		2DRIVE	SS - 05	3 SEC	1 SEC	4.6 A	
1.0KW x 6P	2.8 A	1 DRIVE	SS - 05	3 SEC	1 SEC	3.1 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	6.2 A	
1.5KW x 4P	3.7 A	1 DRIVE	SS - 05	3 SEC	1 SEC	4.1 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	8.1 A	
1.5KW x 6P	3.8 A	1 DRIVE	SS - 05	3 SEC	1 SEC	4.2 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	8.4 A	
2.2KW x 4P	5.0 A	1 DRIVE	SS - 30	3 SEC	1 SEC	5.5 A	
		2 DRIVE	SS - 30	3 SEC	1 SEC	11.0 A	
0.8/0.4KW x 4/8P	2.4/2.27 A	1 DRIVE	SS - 05	3 SEC	1 SEC	2.6 A	
		2 DRIVE	SS - 05	3 SEC	1 SEC	2.5 A	
2.2KW x 6P	5.8 A	1 DRIVE	SS - 30	3 SEC	1 SEC	5.3 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	12.8 A	
3.7KW x 4P	8.0 A	1 DRIVE	SS - 30	3 SEC	1 SEC	8.8 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	17.6 A	

NOTE

1, 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

E.O.C.R 권고 SETTING 치

* POWER SOURCE : AC3Φ 460V 60Hz

극동호이스트(주)

MOTOR 용량	MOTOR 정격 전류	DRIVE TYPE	E.O.C.R TYPE	권고 SETTING 치			REMARK
				DELAY TIME	OPERATION TIME	CURRENT	
0.2KW x 6P	1.2 A	1 DRIVE	SS - 05	3 SEC	1 SEC	1.3 A	
		2DRIVE	SS - 05	3 SEC	1 SEC	2.6 A	
0.4KW x 4P	1.4 A	1 DRIVE	SS - 05	3 SEC	1 SEC	1.5 A	
		2DRIVE	SS - 05	3 SEC	1 SEC	3.1 A	
0.5KW x 6P	1.8 A	1 DRIVE	SS - 05	3 SEC	1 SEC	2.0 A	
		2DRIVE	SS - 05	3 SEC	1 SEC	4.0 A	
0.75KW x 4P	2.0 A	1 DRIVE	SS - 05	3 SEC	1 SEC	2.2 A	
		2DRIVE	SS - 05	3 SEC	1 SEC	4.4 A	
1.0KW x 6P	2.8 A	1 DRIVE	SS - 05	3 SEC	1 SEC	3.1 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	6.2 A	
1.5KW x 4P	3.7 A	1 DRIVE	SS - 05	3 SEC	1 SEC	4.1 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	8.1 A	
1.5KW x 6P	3.8 A	1 DRIVE	SS - 05	3 SEC	1 SEC	4.2 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	8.4 A	
2.2KW x 4P	5.0 A	1 DRIVE	SS - 30	3 SEC	1 SEC	5.5 A	
		2 DRIVE	SS - 30	3 SEC	1 SEC	11.0 A	
0.8/0.4KW x 4/8P	2.4/2.27 A	1 DRIVE	SS - 05	3 SEC	1 SEC	2.6 A	
		2 DRIVE	SS - 05	3 SEC	1 SEC	5.3 A	
2.2KW x 6P	5.8 A	1 DRIVE	SS - 30	3 SEC	1 SEC	6.4 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	12.8 A	
3.7KW x 4P	8.0 A	1 DRIVE	SS - 30	3 SEC	1 SEC	8.8 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	17.6 A	

NOTE

1, 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

E.O.C.R 권고 SETTING 치

* POWER SOURCE : AC3Φ 480V 60Hz

극동하이스트(주)

MOTOR 용량	MOTOR 정격 전류	DRIVE TYPE	E.O.C.R TYPE	권고 SETTING 치			REMARK
				DELAY TIME	OPERATION TIME	CURRENT	
0.2KW x 6P	1.2 A	1 DRIVE	SS - 05	3 SEC	1 SEC	1.3 A	
		2DRIVE	SS - 05	3 SEC	1 SEC	2.6 A	
0.4KW x 4P	1.4 A	1 DRIVE	SS - 05	3 SEC	1 SEC	1.5 A	
		2DRIVE	SS - 05	3 SEC	1 SEC	3.1 A	
0.5KW x 6P	1.8 A	1 DRIVE	SS - 05	3 SEC	1 SEC	2.0 A	
		2DRIVE	SS - 05	3 SEC	1 SEC	4.0 A	
0.75KW x 4P	1.9 A	1 DRIVE	SS - 05	3 SEC	1 SEC	2.1 A	
		2DRIVE	SS - 05	3 SEC	1 SEC	4.2 A	
1.0KW x 6P	2.8 A	1 DRIVE	SS - 05	3 SEC	1 SEC	3.1 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	6.2 A	
1.5KW x 4P	3.7 A	1 DRIVE	SS - 05	3 SEC	1 SEC	4.1 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	8.1 A	
1.5KW x 6P	3.8 A	1 DRIVE	SS - 05	3 SEC	1 SEC	4.2 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	8.4 A	
2.2KW x 4P	5.0 A	1 DRIVE	SS - 30	3 SEC	1 SEC	5.5 A	
		2 DRIVE	SS - 30	3 SEC	1 SEC	11.0 A	
0.8/0.4KW x 4/8P	2.4/2.27 A	1 DRIVE	SS - 05	3 SEC	1 SEC	2.6 A	
			SS - 05	3 SEC	1 SEC	2.5 A	
		2 DRIVE	SS - 30	3 SEC	1 SEC	5.3 A	
			SS - 05	3 SEC	1 SEC	5.0 A	
2.2KW x 6P	5.8 A	1 DRIVE	SS - 30	3 SEC	1 SEC	6.4 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	12.8 A	
3.7KW x 4P	8.0 A	1 DRIVE	SS - 30	3 SEC	1 SEC	8.8 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	17.6 A	

NOTE

1, 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

THREE PHASE INDUCTION MOTOR DATA SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	HOISTING
2. MANUFACTURE	극동 호이스트 (주)
3. FRAME NUMBER	200 L
4. RATED POWER	17 KW x 8 P
5. RATED VOLTAGE AND FREQUENCY	220 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TEMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	850 RPM
11. FULL LOAD CURRENT	76.6 A
12. STARTING CURRENT AT RATED VOLTAGE	455.8 A
13. MINIMUM STARTING VOLTAGE	198 V
14. EFFICIENCY AT 100% RATED LOAD	82.0 %
15. POWER FACTOR AT 100% RATED LOAD	71.5 %
16. STARTING TORQUE	39.72 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E F C
19. TYPE OF BEARING	PL : 6312zz OPL : 6311zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPERATURE	40 °C
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

THREE PHASE INDUCTION MOTOR DATA SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	HOISTING
2. MANUFACTURE	극동 호이스트 (주)
3. FRAME NUMBER	200 L
4. RATED POWER	17 KW x 8 P
5. RATED VOLTAGE AND FREQUENCY	380 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TEMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	850 RPM
11. FULL LOAD CURRENT	44.3 A
12. STARTING CURRENT AT RATED VOLTAGE	263.8 A
13. MINIMUM STARTING VOLTAGE	342 V
14. EFFICIENCY AT 100% RATED LOAD	82.0 %
15. POWER FACTOR AT 100% RATED LOAD	71.5 %
16. STARTING TORQUE	39.72 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E F C
19. TYPE OF BEARING	PL : 6312zz OPL : 6311zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPERATURE	40 °C
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

THREE PHASE INDUCTION MOTOR DATA SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	HOISTING
2. MANUFACTURE	극동 호이스트 (주)
3. FRAME NUMBER	200 L
4. RATED POWER	17 KW x 8 P
5. RATED VOLTAGE AND FREQUENCY	440 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TEMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	850 RPM
11. FULL LOAD CURRENT	38.3 A
12. STARTING CURRENT AT RATED VOLTAGE	227.9 A
13. MINIMUM STARTING VOLTAGE	396 V
14. EFFICIENCY AT 100% RATED LOAD	82.0 %
15. POWER FACTOR AT 100% RATED LOAD	71.5 %
16. STARTING TORQUE	39.72 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E F C
19. TYPE OF BEARING	PL : 6312zz OPL : 6311zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPERATURE	40 °C
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

THREE PHASE INDUCTION MOTOR DATA SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	HOISTING
2. MANUFACTURE	극동 호이스트 (주)
3. FRAME NUMBER	200 L
4. RATED POWER	17 KW x 8 P
5. RATED VOLTAGE AND FREQUENCY	460 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TEMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	850 RPM
11. FULL LOAD CURRENT	36.6 A
12. STARTING CURRENT AT RATED VOLTAGE	218.4 A
13. MINIMUM STARTING VOLTAGE	414 V
14. EFFICIENCY AT 100% RATED LOAD	82.0 %
15. POWER FACTOR AT 100% RATED LOAD	71.5 %
16. STARTING TORQUE	39.72 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E F C
19. TYPE OF BEARING	PL : 6312zz OPL : 6311zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPERATURE	40 °C
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

THREE PHASE INDUCTION MOTOR DATA SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	HOISTING
2. MANUFACTURE	극동 호이스트 (주)
3. FRAME NUMBER	200 L
4. RATED POWER	17 KW x 8 P
5. RATED VOLTAGE AND FREQUENCY	480 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1 . 0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TEMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	850 RPM
11. FULL LOAD CURRENT	35.2 A
12. STARTING CURRENT AT RATED VOLTAGE	209.8 A
13. MINIMUM STARTING VOLTAGE	432 V
14. EFFICIENCY AT 100% RATED LOAD	82.0 %
15. POWER FACTOR AT 100% RATED LOAD	71.5 %
16. STARTING TORQUE	39.72 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E F C
19. TYPE OF BEARING	PL : 6312zz OPL : 6311zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPERATURE	40 °C
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

THREE PHASE INDUCTION MOTOR DATA SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	HOISTING
2. MANUFACTURE	극동 호이스트 (주)
3. FRAME NUMBER	112 M
4. RATED POWER	1.8 KW x 8 P
5. RATED VOLTAGE AND FREQUENCY	220 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1 . 0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TEMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	850 RPM
11. FULL LOAD CURRENT	11.0 A
12. STARTING CURRENT AT RATED VOLTAGE	55.0 A
13. MINIMUM STARTING VOLTAGE	198 V
14. EFFICIENCY AT 100% RATED LOAD	71.5 %
15. POWER FACTOR AT 100% RATED LOAD	60.0 %
16. STARTING TORQUE	6.93 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6206zz OPL : 6206zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPERATURE	40 °C
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

THREE PHASE INDUCTION MOTOR DATA SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	HOISTING
2. MANUFACTURE	극동 호이스트 (주)
3. FRAME NUMBER	112 M
4. RATED POWER	1.8 KW x 8 P
5. RATED VOLTAGE AND FREQUENCY	380 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1 . 0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TEMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	850 RPM
11. FULL LOAD CURRENT	6.4 A
12. STARTING CURRENT AT RATED VOLTAGE	31.9 A
13. MINIMUM STARTING VOLTAGE	342 V
14. EFFICIENCY AT 100% RATED LOAD	71.5 %
15. POWER FACTOR AT 100% RATED LOAD	60.0 %
16. STARTING TORQUE	6.93 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6206zz OPL : 6206zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPERATURE	40 °C
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

THREE PHASE INDUCTION MOTOR DATA SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	HOISTING
2. MANUFACTURE	극동 호이스트 (주)
3. FRAME NUMBER	112 M
4. RATED POWER	1.8 KW x 8 P
5. RATED VOLTAGE AND FREQUENCY	440 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TEMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	850 RPM
11. FULL LOAD CURRENT	5.5 A
12. STARTING CURRENT AT RATED VOLTAGE	27.5 A
13. MINIMUM STARTING VOLTAGE	396 V
14. EFFICIENCY AT 100% RATED LOAD	71.5 %
15. POWER FACTOR AT 100% RATED LOAD	60.0 %
16. STARTING TORQUE	6.93 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6206zz OPL : 6206zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPERATURE	40 °C
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

THREE PHASE INDUCTION MOTOR DATA SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	HOISTING
2. MANUFACTURE	극동 호이스트 (주)
3. FRAME NUMBER	112 M
4. RATED POWER	1.8 KW x 8 P
5. RATED VOLTAGE AND FREQUENCY	460 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TEMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	850 RPM
11. FULL LOAD CURRENT	5.3 A
12. STARTING CURRENT AT RATED VOLTAGE	26.3 A
13. MINIMUM STARTING VOLTAGE	414 V
14. EFFICIENCY AT 100% RATED LOAD	71.5 %
15. POWER FACTOR AT 100% RATED LOAD	60.0 %
16. STARTING TORQUE	6.93 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6206zz OPL : 6206zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPERATURE	40 °C
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

THREE PHASE INDUCTION MOTOR DATA SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	HOISTING
2. MANUFACTURE	극동 호이스트 (주)
3. FRAME NUMBER	112 M
4. RATED POWER	1.8 KW x 8 P
5. RATED VOLTAGE AND FREQUENCY	480 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1 . 0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TEMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	850 RPM
11. FULL LOAD CURRENT	5.1 A
12. STARTING CURRENT AT RATED VOLTAGE	25.3 A
13. MINIMUM STARTING VOLTAGE	432 V
14. EFFICIENCY AT 100% RATED LOAD	71.5 %
15. POWER FACTOR AT 100% RATED LOAD	60.0 %
16. STARTING TORQUE	6.93 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6206zz OPL : 6206zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPERATURE	40 °C
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

THREE PHASE INDUCTION MOTOR DATA SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	HOISTING
2. MANUFACTURE	극동 호이스트 (주)
3. FRAME NUMBER	160 L
4. RATED POWER	9.0 KW x 8 P
5. RATED VOLTAGE AND FREQUENCY	220 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1 . 0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TEMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	825 RPM
11. FULL LOAD CURRENT	45.0 A
12. STARTING CURRENT AT RATED VOLTAGE	213 A
13. MINIMUM STARTING VOLTAGE	198 V
14. EFFICIENCY AT 100% RATED LOAD	79.5 %
15. POWER FACTOR AT 100% RATED LOAD	66.4 %
16. STARTING TORQUE	15.9 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6309zz OPL : 6308zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPERATURE	40 °C
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

THREE PHASE INDUCTION MOTOR DATA SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	HOISTING
2. MANUFACTURE	극동 호이스트 (주)
3. FRAME NUMBER	160 L
4. RATED POWER	9.0 KW x 8 P
5. RATED VOLTAGE AND FREQUENCY	380 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TEMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	825 RPM
11. FULL LOAD CURRENT	26.0 A
12. STARTING CURRENT AT RATED VOLTAGE	122.9 A
13. MINIMUM STARTING VOLTAGE	342 V
14. EFFICIENCY AT 100% RATED LOAD	79.5 %
15. POWER FACTOR AT 100% RATED LOAD	66.4 %
16. STARTING TORQUE	15.9 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6309zz OPL : 6308zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPERATURE	40 °C
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

THREE PHASE INDUCTION MOTOR DATA SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	HOISTING
2. MANUFACTURE	극동 호이스트 (주)
3. FRAME NUMBER	160 L
4. RATED POWER	9.0 KW x 8 P
5. RATED VOLTAGE AND FREQUENCY	440 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TEMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	825 RPM
11. FULL LOAD CURRENT	22.5 A
12. STARTING CURRENT AT RATED VOLTAGE	106.0 A
13. MINIMUM STARTING VOLTAGE	396 V
14. EFFICIENCY AT 100% RATED LOAD	79.5 %
15. POWER FACTOR AT 100% RATED LOAD	66.4 %
16. STARTING TORQUE	15.9 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6309zz OPL : 6308zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPERATURE	40 °C
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

THREE PHASE INDUCTION MOTOR DATA SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	HOISTING
2. MANUFACTURE	극동 호이스트 (주)
3. FRAME NUMBER	160 L
4. RATED POWER	9.0 KW x 8 P
5. RATED VOLTAGE AND FREQUENCY	460 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TEMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	825 RPM
11. FULL LOAD CURRENT	21.5 A
12. STARTING CURRENT AT RATED VOLTAGE	102.2 A
13. MINIMUM STARTING VOLTAGE	414 V
14. EFFICIENCY AT 100% RATED LOAD	79.5 %
15. POWER FACTOR AT 100% RATED LOAD	66.4 %
16. STARTING TORQUE	15.9 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6309zz OPL : 6308zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPERATURE	40 °C
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

THREE PHASE INDUCTION MOTOR DATA SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	HOISTING
2. MANUFACTURE	극동 호이스트 (주)
3. FRAME NUMBER	160 L
4. RATED POWER	9.0 KW x 8 P
5. RATED VOLTAGE AND FREQUENCY	480 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1 . 0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TEMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	825 RPM
11. FULL LOAD CURRENT	20.6 A
12. STARTING CURRENT AT RATED VOLTAGE	97.97 A
13. MINIMUM STARTING VOLTAGE	432 V
14. EFFICIENCY AT 100% RATED LOAD	79.5 %
15. POWER FACTOR AT 100% RATED LOAD	66.4 %
16. STARTING TORQUE	15.9 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6309zz OPL : 6308zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPERATURE	40 °C
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

THREE PHASE INDUCTION MOTOR DATA SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	HOISTING
2. MANUFACTURE	극동 호이스트 (주)
3. FRAME NUMBER	112 S
4. RATED POWER	1.1 KW x 8 P
5. RATED VOLTAGE AND FREQUENCY	220 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1 . 0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TEMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	830 RPM
11. FULL LOAD CURRENT	7.95 A
12. LOCKED ROTOR CURRENT	41.1 A
13. MINIMUM STARTING VOLTAGE	198 V
14. EFFICIENCY AT 100% RATED LOAD	71.0 %
15. POWER FACTOR AT 100% RATED LOAD	51.5 %
16. STARTING TORQUE	2.85 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6208zz OPL : 6206zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPERATURE	40 °C
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

THREE PHASE INDUCTION MOTOR DATA SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	HOISTING
2. MANUFACTURE	극동 호이스트 (주)
3. FRAME NUMBER	112 S
4. RATED POWER	1.1 KW x 8 P
5. RATED VOLTAGE AND FREQUENCY	380 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1 . 0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TEMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	830 RPM
11. FULL LOAD CURRENT	4.57 A
12. LOCKED ROTOR CURRENT	23.8 A
13. MINIMUM STARTING VOLTAGE	342 V
14. EFFICIENCY AT 100% RATED LOAD	71.0 %
15. POWER FACTOR AT 100% RATED LOAD	51.5 %
16. STARTING TORQUE	2.85 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6208zz OPL : 6206zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPERATURE	40 °C
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

THREE PHASE INDUCTION MOTOR DATA SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	HOISTING
2. MANUFACTURE	극동 호이스트 (주)
3. FRAME NUMBER	112 S
4. RATED POWER	1.1 KW x 8 P
5. RATED VOLTAGE AND FREQUENCY	440 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1 . 0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TEMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	830 RPM
11. FULL LOAD CURRENT	3.95 A
12. LOCKED ROTOR CURRENT	20.55 A
13. MINIMUM STARTING VOLTAGE	396 V
14. EFFICIENCY AT 100% RATED LOAD	71.0 %
15. POWER FACTOR AT 100% RATED LOAD	51.5 %
16. STARTING TORQUE	2.85 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6208zz OPL : 6006zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPERATURE	40 °C
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

THREE PHASE INDUCTION MOTOR DATA SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	HOISTING
2. MANUFACTURE	극동 호이스트 (주)
3. FRAME NUMBER	112 S
4. RATED POWER	1.1 KW x 8 P
5. RATED VOLTAGE AND FREQUENCY	460 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1 . 0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TEMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	830 RPM
11. FULL LOAD CURRENT	3.7 A
12. LOCKED ROTOR CURRENT	18.73 A
13. MINIMUM STARTING VOLTAGE	414 V
14. EFFICIENCY AT 100% RATED LOAD	71.0 %
15. POWER FACTOR AT 100% RATED LOAD	51.5 %
16. STARTING TORQUE	2.85 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6208zz OPL : 6006zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPERATURE	40 °C
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

THREE PHASE INDUCTION MOTOR DATA SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	HOISTING
2. MANUFACTURE	극동 호이스트 (주)
3. FRAME NUMBER	112 S
4. RATED POWER	1.1 KW x 8 P
5. RATED VOLTAGE AND FREQUENCY	480 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TEMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	830 RPM
11. FULL LOAD CURRENT	3.6 A
12. LOCKED ROTOR CURRENT	18.53 A
13. MINIMUM STARTING VOLTAGE	432 V
14. EFFICIENCY AT 100% RATED LOAD	71.0 %
15. POWER FACTOR AT 100% RATED LOAD	51.5 %
16. STARTING TORQUE	2.85 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6208zz OPL : 6006zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPERATURE	40 °C
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E