



제 2013 - 4103 호

안 전 인 증 서

(사업장명)

극동호이스트(주)

(소재지) (425-833)경기도 안산시 성곡동630-2 반월공단 B-607-14

위 사업장에서 제조하는 아래의 품목이 산업안전보건법 제34조 및 같은 법 시행규칙 제58조의4제4항에 따른 안전인증 심사 결과 안전·보건기준에 적합하므로 안전인증표시의 사용을 인증합니다.

_____ 품 목 _____

호이스트

_____ 형식,모델(용량,등급)/인증번호 _____


KDC20_7.5T-MA (20/7.5Ton) /13-AQ2AC-05382

_____ 인 증 기 준 _____

고용노동부 고시 제2012 - 33호 (위험기계,기구 의무안전인증 고시)

_____ 인 증 조 건 _____

2013년 12월 24일



한국산업안전보건공단이사장



심사결과 통지서

신청인	사업장명	극동호이스트(주)	사업장관리번호	134-81-013350
	사업자등록번호	134-81-01335	대표자 성명	최성찬
	소재지	(425 - 833) 경기도 안산시 성곡동630-2 반월공단 B-607-14		

안전인증대상 기계·기구명		호이스트	
형 식 (규 격)	KDC20_7.5T-MA	용 량 (등 급)	20/7.5 Ton

산업안전보건법 제 34조 및 같은 법 시행규칙 제58조의4에 따라 실시한

☐ 예비심사

☒ 서면심사

☐ 기술능력 및 생산체계 심사

결과가 ☒ 적 합
☐ 부적합

함을 통지합니다.

☐ 개별 제품심사

☐ 개별 제품심사(제작중)

☐ 형식별 제품심사

2013년 12월 17일

인증심사원

강성두 변명수

 (인)

한국산업안전보건공단 경기서부지도원장



서 면 심 사 서 류

형식 번호 : KDC20/7.5-MA

극 동 호 이 스트 (주)


工場 : 경기도 안산시 단원구 성곡동 630-2 반월공단 607-14

電話 : 031) 491 - 5311

FAX : 031) 494 - 5315

산업재해예방
안전보건공단

KOREA OCCUPATIONAL SAFETY & HEALTH AGENCY



동일 형식 일람 표

사업장명	구동호이스트(주)	개정일자 및 번호	2013년 12월 02일	인증번호	
형식 및 모델		동일 형식 인정범위 및 내역			
형식	모델	권상속도(m/min)	회행속도(m/min)	양정(m)	회행방식
KDC20/7.5-MA	KDC20/7.5-L12-MA	[20T] 고속: 4.8 CREEP: 0.48	고속: 15 저속: 10	12	모터구동식
	KDC20/7.5-L18-MA			18	
	KDC20/7.5-L24-MA	[7.5T] 고속: 3.8 CREEP: 0.38	두열고속: 15/7.5 두열저속: 10/5	24	
	KDC20/7.5-L30-MA			30	
	-			-	
					비 고



산업재해예방
안전보건공단

KOREA OCCUPATIONAL SAFETY & HEALTH AGENCY

제 2012-BJ-0009 호



안 전 인 증 서

정호엔지니어링

경기도 광명시 노동사동 440-5

위 사업장에서 제조하는 아래의 품목이 산업안전보건법 제34조 및 같은 법 시행규칙 제58조의4제4항에 따른 안전인증 심사 결과 안전·보건기준에 적합하므로 안전인증표시의 사용을 인증합니다.

품 목
양중기용 과부하방지장치

형식·모델/용량·등급/인증번호

형식·모델
JDL-100

용량·등급
J-2

인증번호
12-AV2BJ-0009

인 증 기 준

방호장치 의무안전인증 고시(고용노동부고시 제2010-36호)

인 증 조 건

아래 주소에서 생산되는 제품에 한함.
정호엔지니어링, 경기도 광명시 노동사동 440-5




한국산업안전보건공단 이사장

1-안전인증서.jpg 123 KB

산업재해예방

안전보건공단

KOREA OCCUPATIONAL SAFETY & HEALTH AGENCY




PC저장 · 클라우드 저장 · 삭제

2. 도 면




산업재해예방
안전보건공단
KOREA OCCUPATIONAL SAFETY & HEALTH AGENCY




1) 기 계




산업재해예방
안전보건공단
KOREA OCCUPATIONAL SAFETY & HEALTH AGENCY





NO.	DESCRIPTION	M/T	SUB QTY	TOTAL QTY	SUB WEIGHT(KG)	TOTAL WEIGHT(KG)	REMARKS.
5	T/S RAIL	-	-	-	-	22KG/M	
4	UPPER LIMIT S/W	SS400	2	2			
3	SAFETY LATCH	SS400	2	2			
2	EMERGENCY S/W	-	1	1			
1	LOAD LIMITER	-	2	2			
PROJECT							
TITLE							
DRAWN							
DESIGNED							
CHECKED							
APPROVED							
REF. DRAWING							
DATE							
SCALE							
PROJECTION							
3rd							
ARRANGEMENT DRAWING FOR HOIST							
KDC20/7.5-L12-MA							
SHEET No. DWG No.							
KUK DONG HOIST CO., LTD.							





SPECIFICATION		20000 KG		7500 KG	
HOISTING LOAD	20000 KG	22500 KG	9375 KG		
TEST LOAD	22500 KG	9375 KG			
LIFT					
HOISTING	HIGH	SPEED 4.2/0.42 M/MIN	3.8/0.38 M/MIN		
HOISTING	LOW	MOTOR 17/1.8KW x 8P	5.5/1.0KW x 8P		
TRAVERSING	HIGH	SPEED 15 M/MIN			
TRAVERSING	LOW	MOTOR 1.5KW x 4P			
TRAVERSING	DUAL	SPEED 10 M/MIN			
TRAVERSING	DUAL	MOTOR 1.0KW x 6P			
TRAVERSING	DUAL	SPEED 15/7.5 M/MIN			
TRAVERSING	DUAL	MOTOR 1.5/0.75KW x 4/8P			
TRAVERSING	DUAL	SPEED 10/5 M/MIN			
TRAVERSING	DUAL	MOTOR 1.0/0.5KW x 6/12P			
WIRE ROPE	(6x37) #22.4x4FALLS	#14x4FALLS			
POWER SOURCE	AC#3 220V(380,440,480V) 60Hz				
TRAVERSING RAIL	22 KG/M				
GROSS WEIGHT	3750 KG				

극동호이스트
20000KG
제한하중
VIEW A

극동호이스트
7500KG
제한하중
VIEW B

산업재해예방
안전보건공단

KOREA OCCUPATIONAL SAFETY & HEALTH AGENCY



SPECIFICATION			
HOISTING LOAD	20000 KG	7500 KG	KG
TEST LOAD	22500 KG	9375 KG	KG
LIFT	18 M		
HOISTING	SPEED HIGH	4.2/0.42 M/MIN	3.9/0.38 M/MIN
	MOTOR	17/1.8KW x 8P	5.5/1.0KW x 8P
TRAVERSING	SPEED HIGH	15 M/MIN	
	MOTOR	1.5KW x 4P	
	SPEED LOW	10 M/MIN	
	MOTOR	1.0KW x 6P	
	SPEED DUAL HIGH	15/7.5 M/MIN	
	MOTOR	1.5/0.75KW x 4/8P	
	SPEED DUAL LOW	10/5 M/MIN	
	MOTOR	1.0/0.5KW x 6/12P	
WIRE ROPE	(6x37) #22.4x4FALLS	#14x4FALLS	
POWER SOURCE	AC#3 220V(380,440,480V)	60Hz	
TRAVERSING RAIL			
GROSS WEIGHT	22 KG/M	3950 KG	

5	T/S RAIL	-	-	-	22KG/M	
4	UPPER LIMIT S/W	SS400	2			
3	SAFETY LATCH	SS400	2			
2	EMERGENCY S/W	-	1			
1	LOAD LIMITER	-	2			
NO.	DESCRIPTION	MT'L	SUB QTY	TOTAL	SUB WEIGHT(KG)	REMARKS.
PROJECT						
TITLE						
KDC20/7.5-L18-MA						
ARRANGEMENT DRAWING FOR HOIST						
DRAWN	DESIGNED	CHECKED	APPROVED	SCALE	PROJECTION	
				A3/20	3rd	
REF. DRAWING						
DATE						
DIM mm						

극동호이스트
20000KG
제한하중

극동호이스트
7500KG
제한하중



극동호이스트 주식회사
KUK DONG HOIST CO., LTD.

SHEET No.

DWG No.

안전보건공단

KOREA OCCUPATIONAL SAFETY & HEALTH AGENCY



SPECIFICATION		20000 KG	7500 KG
HOISTING LOAD		20000 KG	7500 KG
TEST LOAD		22500 KG	9375 KG
LIFT		24 M	
HOISTING	HIGH	SPEED 42/0.42 M/MIN MOTOR 17/1.8KW x 8P	3.8/0.38 M/MIN 5.5/1.0KW x 8P
HOISTING	HIGH	SPEED 15 M/MIN MOTOR 1.5KW x 4P (2UNITS)	
TRAVERSING	LOW	SPEED 10 M/MIN MOTOR 1.0KW x 6P (2UNITS)	
TRAVERSING	DUAL HIGH	SPEED 15/7.5 M/MIN MOTOR 1.5/0.75KW x 4/8P (2UNITS)	
TRAVERSING	DUAL LOW	SPEED 10/5 M/MIN MOTOR 1.0/0.5KW x 6/12P (2UNITS)	
WIRE ROPE		(6x37) #22.4x4FALLS #14x4FALLS	
POWER SOURCE		AC#3 220V(380,440,460,480V) 60Hz	
TRAVERSING RAIL		22 KG/M	
GROSS WEIGHT		4150 KG	

극동호이스트
20000KG
제한하중

VIEW A

극동호이스트
7500KG
제한하중

VIEW B




1


NO.	DESCRIPTION	MT'L	SUB QTY	TOTAL QTY	REMARKS.
5	T/S RAIL	-	-	-	22KG/M
4	UPPER LIMIT S/W	SS400	2	2	
3	SAFETY LATCH	SS400	2	2	
2	EMERGENCY S/W	-	1	1	
1	LOAD LIMITER	-	2	2	
NO.	DESCRIPTION	MT'L	SUB QTY	TOTAL QTY	REMARKS.
PROJECT					
TITLE					
ARRANGEMENT DRAWING FOR HOIST					
DESIGNED CHECKED APPROVED					
DATE					
SCALE					
PROJECTION					
REF. DRAWING					
DIM					
mm					
3rd					
KDC20/7.5-L24-MA					
KUK DONG HOIST CO., LTD.					
SHEET No. DWG No.					

안전보건공단

KOREA OCCUPATIONAL SAFETY & HEALTH AGENCY



NO.	DESCRIPTION	MT'L	SUB QTY	TOTAL QTY	SUB WEIGHT(kg)	TOTAL WEIGHT(kg)	REMARKS.	DIM	
								DATE	mm
5	T/S RAIL	-	-	-	-	-	22KG/M		
4	UPPER LIMIT S/W	SS400	2	2					
3	SAFETY LATCH	SS400	2	2					
2	EMERGENCY S/W	-	1	1					
1	LOAD LIMITER	-	2	2					
								PROJECT	
								TITLE	
								KDC20/7.5-L30-MA	
								ARRANGEMENT DRAWING FOR HOIST	
								SCALE	
								A3/20	
								3rd	
								REF. DRAWING	
								DRAWN	
								DESIGNED	
								CHECKED	
								APPROVED	
								SHEET No.	
								DWG No.	



SPECIFICATION		20000 KG	7500 KG
HOISTING LOAD		20000 KG	7500 KG
TEST LOAD		22500 KG	9375 KG
LIFT		30 M	
HOISTING	SPEED	4.2/0.42 M/MIN	3.8/0.38 M/MIN
	MOTOR	17/1.8KW x 8P	5.5/1.0KW x 8P
TRAVERSING	SPEED	15 M/MIN	
	MOTOR	1.5KW x 4P (2UNITS)	
TRAVERSING	SPEED	10 M/MIN	
	MOTOR	1.0KW x 6P (2UNITS)	
TRAVERSING	SPEED	15/7.5 M/MIN	
	MOTOR	1.5/0.75KW x 4/8P (2UNITS)	
TRAVERSING	SPEED	10/5 M/MIN	
	MOTOR	1.0/0.5KW x 8/12P (2UNITS)	
WIRE ROPE		6x37 #22.4x4FALLS	#14x4FALLS
		ACB3 220V(380,440,460,480V) 60Hz	
TRAVERSING RAIL		22 KG/M	
		4400 KG	

극동호이스트
20000KG
제한하중

VIEW A

극동호이스트
7500KG
제한하중

VIEW B


안전보건공단

KOREA OCCUPATIONAL SAFETY & HEALTH AGENCY

2) 전 기



산업재해예방
안전보건공단
KOSHA
KOREA OCCUPATIONAL SAFETY & HEALTH AGENCY



ELECTRICAL SYMBOL LIST

DESCRIPTION	SYMBOLS	DESCRIPTION	SYMBOLS	DESCRIPTION	SYMBOLS
WIRE INTERNAL TO ENCLOSURE		CONTROLLER OR REMOTE CONTROLLER CONTACTOR		SOLENOID COIL	
WIRE EXTERNAL TO ENCLOSURE		UPPER LIMIT SWITCH (LS-II)		RESISTER	
WIRE NOT CONNECTED		THERMAL RELAY		VARIABLE RESISTOR	
WIRE CONNECTED		PILOT(SIGNAL) LAMP		SLIP RING	
TERMINAL		ROTARY LAMP		CABLE REEL	
GROUND (EARTH)		WARNING SIREN		SPACE HEATER	
PLUG & RECEPTACLE		BUZZER		SURGE ABSORBER	
MAGNETIC CONTACTOR COIL		AMMETER		LOAD CELL	
AUX. RELAY COIL		VOLT METER		BALLAST WITH RECEPTACLE	
TIMER COIL		FLUORESCENCE LAMP		FAN	

			CUSTOMER										
			DRAWING TITLE		SYMBOL LIST 2/2								
REV IS I O N S			CHK. APP.										
MK	DATE												
△													
△													
△													
△													
					KDD					KUK DONG HOIST CO., LTD.			
					DRAWING	DESIGN	CHECKED	APPROVED	SCALE	DATE	ORDER NO.		
									NONE				
					KUK DONG HOIST 주식회사					DWG. NO	KDSM0002		

ELECTRICAL SPECIFICATION

POWER SOURCE : AC 3 Φ 220V, 380V, 440V, 460V, 480V 60Hz

CONTROL SOURCE : AC 1 Φ 48V, 110V, 120V 60Hz

OBJECT	MOTOR OUTPUT	220V		380V		440V	460V	480V	440, 460, 480V	BRAKE	REMARK
		STATOR CURRENT	1st CABLE SIZE	STATOR CURRENT	1st CABLE SIZE	STATOR CURRENT	STATOR CURRENT	STATOR CURRENT	1st CABLE SIZE		
MAIN HOIST	MAIN	76.60 A	35 sq	44.30 A	16 sq	38.3 A	36.6 A	35.2 A	16 sq	DC MAG. BRAKE	
	CREEP	11.00 A	4 sq	6.40 A	4 sq	5.5 A	5.3 A	5.1 A	4 sq	DC MAG. BRAKE	
AUX HOIST	MAIN	28.20 A	10 sq	16.30 A	6 sq	14.1 A	13.5 A	12.9 A	6 sq	DC MAG. BRAKE	
	CREEP	6.70 A	4 sq	3.90 A	4 sq	3.3 A	3.2 A	3.1 A	4 sq	DC MAG. BRAKE	
TRAVERSING	HIGH	7.80 A	4 sq	4.20 A	4 sq	3.70 A	3.50 A	3.40 A	4 sq	DC MAG. BRAKE	1 DRIVE
	LOW	6.80 A	4 sq	3.90 A	4 sq	3.30 A	3.20 A	3.10 A	4 sq	DC MAG. BRAKE	1 DRIVE
	CONTROL CIRCUIT	2 A	2.5 sq	2 A	2.5 sq	2 A	2 A	2 A	2.5 sq		
LIGHTING & ACC'Y CIRCUIT											
SUB TOTAL (NORMAL LOAD)		86.40 A	50 sq	50.50 A	25 sq	44.00 A	42.10 A	40.60 A	25 sq	I(A)=M/H + T/S + ASS'Y	
SUB TOTAL		86.40 A	50 sq	50.50 A	25 sq	43.60 A	41.80 A	40.30 A	25 sq	I(A)=M/H + T/S + ASS'Y	

*. 위 계산은 HIGH(MAX.)일때와 LOW(MIN.)일때만 계산한것임.

*. 위 계산은 LIFT 12.18M에 적용.

ELECTRICAL SPECIFICATION

POWER SOURCE : AC 3 Φ 220V, 380V, 440V, 460V, 480V 60Hz

CONTROL SOURCE : AC 1 Φ 48V, 110V, 120V 60Hz

OBJECT	MOTOR OUTPUT	220V		380V		440V	460V	480V	440, 460, 480V	BRAKE	REMARK
		STATOR CURRENT	1st CABLE SIZE	STATOR CURRENT	1st CABLE SIZE	STATOR CURRENT	STATOR CURRENT	STATOR CURRENT	1st CABLE SIZE		
MAIN HOIST	MAIN	76.60 A	35 sq	44.30 A	16 sq	38.3 A	36.6 A	35.2 A	16 sq	DC MAG. BRAKE	
	CREEP	11.00 A	4 sq	6.40 A	4 sq	5.5 A	5.3 A	5.1 A	4 sq	DC MAG. BRAKE	
AUX HOIST	MAIN	28.20 A	10 sq	16.30 A	6 sq	14.1 A	13.5 A	12.9 A	6 sq	DC MAG. BRAKE	
	CREEP	6.70 A	4 sq	3.90 A	4 sq	3.3 A	3.2 A	3.1 A	4 sq	DC MAG. BRAKE	
TRAVERSING	HIGH	7.80 A	4 sq	4.20 A	4 sq	3.70 A	3.50 A	3.40 A	4 sq	DC MAG. BRAKE	2 DRIVE
	LOW	6.80 A	4 sq	3.90 A	4 sq	3.30 A	3.20 A	3.10 A	4 sq	DC MAG. BRAKE	2 DRIVE
CONTROL CIRCUIT		2 A	2.5 sq	2 A	2.5 sq	2 A	2 A	2 A	2.5 sq		
LIGHTING & ACC'Y CIRCUIT											
SUB TOTAL (NORMAL LOAD)		94.20 A	50 sq	54.70 A	25 sq	47.70 A	45.60 A	44.00 A	25 sq	I(A)=M/H + T/S + ASS'Y	
SUB TOTAL		92.20 A	50 sq	54.10 A	25 sq	46.90 A	45.00 A	43.40 A	25 sq	I(A)=M/H + T/S + ASS'Y	

*. 위 계산은 HIGH(MAX.) 일때와 LOW(MIN.) 일때만 계산한것임.

*. 위 계산은 LIFT 24.30M에 적용.

■ 보호본딩회로의 연속성 확인

시험전선의 최소유효 단면적(mm ²)	최고 전압 강하(V)
1.0	3.3
1.5	2.6
2.5	1.9
4.0	1.4
>6.0	1.0

① 보호본딩회로의 연속성의 검증은 PELV전원(50/60Hz)에서 최소 10A 이상의 전류를 10초 이상의 인가에 의한다.
시험은 PE단자와 보호본딩회로의 여러지점 사이에서 이루어진다.

② PE단자와 시험 지점 사이에서 측정된 전압은(표 참조) 값을 초과해서는 아니된다.

■ 절연저항 시험

전원선과 보호본딩선 사이를 직류 500V로 측정된 절연저항 값은 1MΩ 이상이어야 한다.

■ 내전압 시험


① PELV 전압에서 작동되도록 설계된 전기장치의 회로를 제외한 모든 회로와 보호본딩회로의 전선 사이에 1초 이상 지속되는 다음의 시험 전압에 견딜수 있어야 한다.

- 장치의 정격전압의 두배 또는 1,000V 중 큰값의 전압

② 이 시험을 견딜수 없도록 설계된 부품은 시험이 진행되기 전에 차단하여야 한다.

1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
---	---	---	---	---	---	---	---	---	----	----	----	----	----	----	----	----	----	----	----

* MAIN POWER : AC 3PH 220V(380,440,460,480)V 60Hz (12,18M)




산림재해예방

안전보건공단

KOREA OCCUPATIONAL SAFETY & HEALTH AGENCY


* MAIN POWER : AC 3PH 220V(380,440,460,480)V 60Hz (24,30M)



본 도면은 EARTH를 명기하기 위한 도면으로서
실제 배치와 다를 수 있으며 HOIST 본체와의
EARTH용 CABLE은 REFERENCE임

*3층 접지공사 100Ω 이하 (AC 3PH 400V 미만)

*특3 중 접지공사 10Ω 이하 (AC 3PH 400V 이상)



농업전위점지



1. 전기장비와 기계의 노출된 모든 도전부는 보호본딩회로에 연결되어야 하며 적절한 접지연성 기능이 유지되어야함.
2. 보호본딩회로에는 기폐기, 과전류보호장치가 부착되지 않아야 한다.

NO		TYPE	SIZE		TYPE	SIZE	REMARK
			220V	380V		440V, 460V, 480V	
1	VCT	MAIN	35sqx4c	16sqx5c	VCT	16sqx5c	M/H MOTOR WITH EARTH
		AUX	10sqx4c	6sqx5c		6.0sqx5c	A/H MOTOR WITH EARTH
2	VCT	MAIN	4.0sqx4c	4.0sqx5c	VCT	4.0sqx5c	M/H CREEP MOTOR WITH EARTH
		AUX	4.0sqx4c	4.0sqx5c		4.0sqx5c	A/H CREEP MOTOR WITH EARTH
3	VCT	10sqx4c	6sqx4c		VCT	6.0sqx4c	A/H POWER WITH EARTH
4	VCT	4.0sqx4c+2.5sqx3c			VCT	4.0sqx4c+2.5sqx3c	T/S MOTOR WITH EARTH
5	VCT	HIGH	50sqx4c	25sqx4c	VCT	25sqx4c	MAIN POWER WITH EARTH
		LOW	50sqx4c	25sqx4c		25sqx4c	

시험대상 전선의 최소 유효단면적	최고전압강하(V)
1.0	3.3
1.5	2.6
2.5	1.6
4.0	1.4
>6.0	1.0

[illegible]

* MAIN POWER : AC 3PH 220V(380,440,460,480)V 60Hz (12,18,24,30M)



ELECTRIC WIRE ROPE HOIST		
MODEL	RATING	
CAPACITY	Kg	min
HOIST SPEED	m/min	m/min
HOIST MOTOR	Kw	P
TRAV.SPEED	m/min	AMP.S R&T HOIST
TRAV.MOTOR	Kw	P
WIDTH OF RAIL	mm	AMP.S R&T TRAV.
DATE	WEIGHT	kg
	SERIAL	

3 PHASE INDUCTION MOTOR			
KW	P	TYPE	TENV
VOLTS	V	RATING	min
AMP.S	A	AMP. TEMP	40°C
HEARTS		INS. CLASS	F
R.P.M		BEARING	
ROTOR	C	BEARING	
SERIAL.		DATE	
KUKDONG HOIST CO.,LTD			

		3 PHASE INDUCTION MOTOR	
VOLTS	KW	PI TYPE	TENV
AMP.S		VIRATING	
HEARTS		A	40C
R.P.M		INS.CLASS	F
		BEARING	
ROTOR	C	BEARING	
SERIAL		DATE	
KUKDONG HOIST CO.,LTD			

[illegible]

	16	17	18	19	20
NO	DESCRIPTION			CABLE SIZE	
1	MAIN EARTH LINE			USER SCOPE	
2	POWER SOURCE			USER SCOPE	
3	TROLLEY BAR			USER SCOPE	
4	POWER SOURCE WITH EARTH			USER SCOPE	
5	H01ST POWER SOURCE WITH EARTH			VCT 50SQ x 1C (FOR 220V)	
6	20T HOISTING MOTOR WITH EARTH			VCT 35SQ x 1C (FOR 220V)	
7	20T CREEP MOTOR WITH EARTH			VCT 4,0SQ x 1C	
8	TRAVERSING MOTOR WITH EARTH			VCT 4,0SQ x 1C	
9	7.5T HOISTING MOTOR WITH EARTH			VCT 10(6)SQ x 1C	
10	7.5T CREEP MOTOR WITH EARTH			VCT 4,0SQ x 1C	

* CV CABLE 4C 중 1C는 EARTH로 사용함.


- NOTE -

1. 전통기 외함, 재어반의 프레임 등은 접지하여 그 접지 저항은

400V 미만 : 100오옴 이하일것.(3층 접지)

400V 이상 : 10오옴 이하일것.(특 3종접지)


2.MAIN S/W BOX는 3종 접지 요.



보전와적지

1. 전기장비와 기계의 노출된 모든 도선부는 보호봉딩회로에 연결되어야 하며, 적절한 접지연속성 기능이 유지되어야함,
2. 보호봉딩회로에는 기때기, 과전류보호장치가 부착되지 않아야 한다.

시험대상 전선의 최소 유효단면적	최고전압강하(V)
1.0	3.3
1.5	2.6
2.5	1.6
4.0	1.4
>6.0	1.0

[illegible]

산업재해예방

아저보거공단

KOREA OCCUPATIONAL SAFETY & HEALTH AGENCY

192.168.11.76 / 2013-12-17 15:49:47

NO	DESCRIPTION	17	18	19	20
1	MAIN EARTH LINE			CABLE SIZE	
2	POWER SOURCE			USER SCOPE	
3	TROLLEY BAR			USER SCOPE	
4	POWER SOURCE WITH EARTH			USER SCOPE	
5	HQIST POWER SOURCE WITH EARTH			VCT 5050 x 1C (FOR 220V)	
6	20T HOISTING MOTOR WITH EARTH			VCT 3550 x 1C (FOR 220V)	
7	20T CREEP MOTOR WITH EARTH			VCT 4.050 x 1C	
8	TRAVERSING MOTOR WITH EARTH			VCT 4.050 x 1C	
9	7.5T HOISTING MOTOR WITH EARTH			VCT 10(0)50 x 1C	
10	7.5T CREEP MOTOR WITH EARTH			VCT 4.050 x 1C	

* CV CABLE 4C 중 1C는 EARTH로 사용함.

- NOTE -

1. 전통기 외항, 제어반의 프레임 등은 접지하여

400V 미만 : 100오옴 이하일것.(3종 접지)

400V 이상 : 10오을 이하일것.(특 3종점지)

2.MAIN S/W BOX는 3종 점지 요.


USER SCOPE _____

KUKDONG SCOPE _____


통전위접지

1. 전기장벽과 기계의 노출된 모든 도전부는 보호분리표에 연결되어야 하며 적절한 접지연속성 기능이 유지되어야함.
2. 보호분리표에는 기폐기, 과전류보호장치가 부착되지 않아야 함다.

시험대상 전선의 최소 유효단면적	최고전압강하(V)
1.0	3.3
1.5	2.6
2.5	1.6
4.0	1.4
>6.0	1.0



☒																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																
-------------------------------------	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--



1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
---	---	---	---	---	---	---	---	---	----	----	----	----	----	----	----	----	----	----	----

ADR'S NO. _____
 DATE _____

ORDER NO. _____
 DWG. NO. KDC20EB00

**극동호이스트
제한하중
20000K**

산업재해예방
안전보건공단

사용 전압 : 000V
조작 전압 : 000V

NO	DESCRIPTION	MT'L	REMARKS
1	PANEL CASE	SPC	1.6t
2	PANEL COVER	SPC	1.6t
3	HINGE	PUR'	
4	CLAMP	PUR'	
5	SPONGE	PUR'	

NOTE
 1.PROTECTION DEGREE :
 A. INDOOR TYPE : DUST PROOF
 B. OUT DOOR TYPE : SPLASH PROOF
 2.FINAL PAINTING COLOR (MUNSELL NO.)
 A. IN SIDE : 10B 3/5
 B. OUT SIDE : 10B 3/5
 3.PAINTING THICKNESS : ABOVE 40 um
 4.APPLICATION VOLTAGE : 220V,380V,440V,460V,480V
 5.제어용 전선 : 2.5sq KIV,HIV
 6.외함 개방시 충전부분이 차단되도록 한다.
 1) 외함 개방 후 충전되어있는 부분은 IP2X 이상의
 직접접촉 방호가 되어있을것.

SELECTION	HOIST CAPACITY	DESCRIPTION	IN DOOR			OUT DOOR			REMARK
			A	B	L	A	B	L	
	20 TON	CREEP	650	220	850	660	220	860	
	20 TON	TRAVERSING	210	125	380	210	125	380	


DRAWING	DESIGN	CHECKED	APPROVED	SCALE	DATE	ORDER NO.
				NONE		

CUSTOMER		DRAWING TITLE	
		HOISTING CONTROL BOX	

Korea Occupational Safety & Health Agency

KDC20E22

1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
POWER CIRCUIT																			
TRAVERSING MOTION																			
ADR'S NO.																			C1




SPECIFICATION		TRAVERSING MOTOR		DC MAG. BRAKE		MAGNET CONTACTOR		SILICON RECTIFIER		ELECTRIC OVER CURRENT RELAY		LIMIT SWITCH	
SYMBOLS	DESCRIPTION	IM 30	1.5KW x 4P AC 3PH 220V 60Hz	DB 30	DC 100V	M301, M302	DOC-22P AC 110V	RF 300	EOCR 300	SS-30	SS-30	LS-301, LS-302	HY - W904
SELECTION		KUKDONG		DAERYUK		ASECO		HY - W904		HY - W904		HY - W904	
CUSTOMER		DRAWING		DESIGN		CHECKED		APPROVED		SCALE		DATE	
DRAWING		TITLE		TRAVERSING POWER CONTROL CIRCUIT		DAERYUK		KUKDONG		NONE		ORDER NO.	
DATE		REVISIONS		CHK. APP.		KUKDONG		KUKDONG		DWG. NO		KDC20E23	

1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
---	---	---	---	---	---	---	---	---	----	----	----	----	----	----	----	----	----	----	----


POWER CIRCUIT

TRAVERSING MOTION




SPECIFICATION SYMBOLS		TRAVERSING MOTOR		MAGNET CONTACTOR		SILICON RECTIFIER		ELECTRIC OVER CURRENT RELAY		LIMIT SWITCH	
DESCRIPTION		IM 30, 1M31		M301, M302		RF 300		EOCR 300		LS-301, LS-302	
1.5KW x 4P AC 3PH 220V 60Hz				DOC-22P AC 110V		SR-30		SS-30		HY - W804	
1.0KW x 6P AC 3PH 220V 60Hz				DOC-22P AC 110V		SR-30		SS-30		HY - W804	
SELECTION MAKER		KUK DONG		DAERYUK		ASECO					
CUSTOMER				DRAWING		DESIGN		CHECKED		APPROVED	
DRAWING TITLE		TRAVERSING POWER CONTROL CIRCUIT									
DATE		REVISIONS		CHK.		APP.					
MK											
DWG. NO.		KDC20E24									
ORDER NO.											

1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
POWER CIRCUIT																			
TRAVERSING MOTION																			
ADR'S NO.																			C2




SPECIFICATION SYMBOLS DESCRIPTION	TRAVERSING MOTOR	DC MAG' BRAKE	MAGNET CONTACTOR	SILICON RECTIFIER	ELECTRIC OVER CURRENT RELAY	TRANSFORMER
220V	1.5/0.75KWx6/1/2P AC3PH 220V 60Hz	DB30	M301, M302, M303, M304, M305	RF 300	EOCR 301,302	TR300
220V	1.0/0.5KWx4/8P AC3PH 220V 60Hz	DC 100V	DOC-22P	SR-30	SS-30	AC220/220V, 300VA
SELECTION MAKER		DC 100V	DOC-22P	SR-30	SS-30	AC220/220V, 300VA
KUKDONG						
DAERYUK						
ASECO						
SHINHAN						
ORDER NO.						
DATE						
SCALE						
NONE						
DWG. NO						
KDC20E25						

1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
POWER CIRCUIT																			
TRAVERSING MOTION																			
																			ADR'S NO.
																			C2

[illegible]


1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
POWER CIRCUIT										CREEP HOIST MOTION									
HOISTING MOTION										CREEP HOIST MOTION									
C20-01										B1									
ADR'S NO.										B1									



SPECIFICATION SYMBOLS	DESCRIPTION	HOISTING MOTOR	HOIST	HOISTING MOTOR	HOIST	HOISTING MOTOR	HOIST	HOISTING MOTOR	HOIST	HOISTING MOTOR	HOIST	HOISTING MOTOR	HOIST	HOISTING MOTOR	HOIST	HOISTING MOTOR	HOIST	HOISTING MOTOR	HOIST
20TON	AC3PH	380V	60Hz	17KWx8P	1.8KWx8P	DC 100V	ABS-103AF/75AT	880/10V/20V/200VA	2A	5A	MC-130a	DMC-22C	AC 600V 3A	SS-60	SR-60	SR-30	JDL-100	VCT 25sqx4c	C20-01
SELECTION MAKER		KUKDONG		LS		SHINHAN		-		LS		DONGA		KUK DONG		ASECO		JUNCHO	
CUSTOMER		KUKDONG		LS		SHINHAN		-		LS		DONGA		KUK DONG		ASECO		JUNCHO	
DRAWING TITLE		CREEP HOISTING POWER & CONTROL		CREEP HOISTING POWER & CONTROL		CREEP HOISTING POWER & CONTROL		CREEP HOISTING POWER & CONTROL		CREEP HOISTING POWER & CONTROL		CREEP HOISTING POWER & CONTROL		CREEP HOISTING POWER & CONTROL		CREEP HOISTING POWER & CONTROL		CREEP HOISTING POWER & CONTROL	
REVISIONS		CHK.		APP.		CHK.		APP.		CHK.		APP.		CHK.		APP.		CHK.	
DATE		MK		DATE		MK		DATE		MK		DATE		MK		DATE		MK	
DWG. NO		KDC20E32		KDC20E32		KDC20E32		KDC20E32		KDC20E32		KDC20E32		KDC20E32		KDC20E32		KDC20E32	
ORDER NO.		KDC20E32		KDC20E32		KDC20E32		KDC20E32		KDC20E32		KDC20E32		KDC20E32		KDC20E32		KDC20E32	


안전보건공단
KOREA OCCUPATIONAL SAFETY & HEALTH AGENCY

1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
POWER CIRCUIT																			
TRAVERSING MOTION																			
ADR'S NO.																			C1




△																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																														</
---	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	----

1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
POWER CIRCUIT																			
TRAVERSING MOTION																			
ADR'S NO.																			C2


[illegible]

1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
POWER CIRCUIT																			
TRAVERSING MOTION																			
C2																			ADR'S NO.



SPECIFICATION SYMBOLS		DESCRIPTION		MAGNET CONTACTOR		ELECTRIC OVER CURRENT RELAY		TRANSFORMER	
TRAVERSING MOTOR		IM 30		M301, M302, M303, M304, M305		EOCR 301, 302		TR300	
380V		1.5/0.75KWx6/12P AC3PH 380V 60Hz		DOC-22P		SS-30		AC380/220V, 300VA	
380V		1.0/0.5KWx4/8P AC3PH 380V 60Hz		DOC-22P		SS-30		AC380/220V, 300VA	
SELECTION MAKER		KUKDONG		DAERYUK		ASECO		SHINHAN	
CUSTOMER		DAERYUK		DAERYUK		DAERYUK		DAERYUK	
DRAWING TITLE		TRAVERSING POWER CONTROL CIRCUIT		DRAWING DESIGN		CHECKED		APPROVED	
CHK. APP.		DATE		SCALE		DATE		ORDER NO.	
REV. NO.		REV. NO.		REV. NO.		REV. NO.		REV. NO.	
MK		DATE		REV. NO.		REV. NO.		REV. NO.	
KUKDONG		KUKDONG HOIST CO., LTD.		DWG. NO.		DWG. NO.		DWG. NO.	
KDC20E35		KDC20E35		KDC20E35		KDC20E35		KDC20E35	


1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
POWER CIRCUIT																			ADR'S NO.
TRAVERSING MOTION																			C2



SPECIFICATION SYMBOLS		TRAVERSING MOTOR		DC MAG. BRAKE		MAGNET CONTACTOR		SILICON RECTIFIER		ELECTRIC OVER CURRENT RELAY		TRANSFORMER	
DESCRIPTION		IM 30, IM31		DB30, DB31		M301, M302, M303, M304, M305		RF 300		EOCR 301,302		TR300	
380V		1.5/0.75KW/6/2P AC3PH 380V 60Hz		DC 100V		DOC-22P		SR-30		SS-30		AC380/220V, 300VA	
380V		1.0/0.15KW/4/8P AC3PH 380V 60Hz		DC 100V		DOC-22P		SR-30		SS-30		AC380/220V, 300VA	
SELECTION MAKER		KUKDONG		KUKDONG		DAERYUK		ASECO		SHINHAN			
CUSTOMER						DRAWING		DESIGN		CHECKED		APPROVED	
DRAWING TITLE		TRAVERSING POWER CONTROL CIRCUIT											
CHK. APP.													
REVISIONS													
DATE													
DWG. NO													
KDC20E36													


KDC20E22

1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
POWER CIRCUIT										TRaversing Motion									
ADR'S NO.										C1									




SPECIFICATION SYMBOLS		TRAVERSING MOTOR		DC MAG. BRAKE		MAGNET CONTACTOR		SILICON RECTIFIER		ELECTRIC OVER CURRENT RELAY		LIMIT SWITCH	
DESCRIPTION		IM 30		DB 30		M301, M302		RF 300		EOCR 300		LS-301, LS-302	
SELECTION		1.5KW x 4P AC 3PH 440V 50Hz		DC 100V		DC-22P AC 110V		SR-30		SS-05		HY - W304	
MAKER		KUKDONG		DAERYUK		ASECO		SR-30		SS-05		HY - W304	
CUSTOMER		KUKDONG		DAERYUK		ASECO		SR-30		SS-05		HY - W304	
DRAWING TITLE		TRAVERSING POWER CONTROL CIRCUIT		DAERYUK		ASECO		SR-30		SS-05		HY - W304	
REVISIONS		CHK. APP.		DATE		DWG. NO		KDC20F43		ORDER NO.			

1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
POWER CIRCUIT																			
TRAVERSING MOTION																			
ADR'S NO.																			C2




△																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																												
---	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--

1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
POWER CIRCUIT																			
TRAVERSING MOTION																			
ADR'S NO.																			C2



SPECIFICATION		SYMBOLS		DESCRIPTION		TRAVERSING MOTOR		MAGNET CONTACTOR		SILICON RECTIFIER		ELECTRIC OVER CURRENT RELAY		TRANSFORMER	
440V		1.5/0.75KWx6/12P		AC3PH 440V 60Hz		M301, M302, M303		M304, M305		RF 300		EOCR 301,302		TR300	
440V		1.0/0.5KWx4/8P		AC3PH 440V 60Hz		DOC-22P		DOC-22R		SR-30		SS-05		AC440/220V, 300VA	
440V		1.0/0.5KWx4/8P		AC3PH 440V 60Hz		DOC-22P		DOC-22R		SR-30		SS-05		AC440/220V, 300VA	
DAERYUK		KUKDONG		DAERYUK		DAERYUK		DAERYUK		DAERYUK		DAERYUK		DAERYUK	
CUSTOMER		DRAWING		DESIGN		CHECKED		APPROVED		SCALE		DATE		SHINWHAN	
DRAWING TITLE		TRAVERSING POWER CONTROL CIRCUIT		DAERYUK		DAERYUK		DAERYUK		DAERYUK		DAERYUK		DAERYUK	
CHK. APP.		REVISIONS		DATE		DATE		DATE		DATE		DATE		DATE	
DWG. NO		KUKDONG HOIST CO., LTD.		KDC20E45		KDC20E45		KDC20E45		KDC20E45		KDC20E45		KDC20E45	

1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
																			ADR'S NO.



산업재해예방
안전보건공단
KOREA OCCUPATIONAL SAFETY & HEALTH AGENCY

NOTE

1. 전선의 색상은 다음과 같다.
 - 1) 흑색 : 교류 및 직류 전원회로
 - 2) 적색 : 교류 제어회로
 - 3) 청색 : 직류 제어회로
 - 4) 주황색 : 외부 안전장치 제어회로
2. CABLE MATERIAL : KIV OR EQUIVALENT
MIN SIZE : 2.5sq
3. 제어용 전선 : 2.5mm KIV,HIV
4. 제막시 다소 변경 될수있음.
5. 외함 개방구조는 다음과 같을것.
- 1) 외함 개방시 충전부분이 차단되도록 할것.
- 2) 외함 개방후 충전되어있는 부분은 IP2X 이상의 직접 접촉 방호가 되어있을것.

NO	DESCRIPTION	SPECIFICATION	QTY	REMARK
1	CHASSIS PLATE		1	아 연 도 금
2	MAGNET CONTACT	MC-130a	2	HOISTING
3	MAGNET CONTACT	DMC22C	2	CREEP HOISTING
4	MAGNET CONTACT	DMC22C	2	TRAVERSING
5	SILICON RECTIFIER	SR-60	1	HOISTING
6	SILICON RECTIFIER	SR-30	1	CREEP HOISTING
7	SILICON RECTIFIER	SR-30	1	TRAVERSING
8	E.O.C.R	SS-60	1	HOISTING
9	E.O.C.R	SS-30	1	CREEP HOISTING
10	E.O.C.R	SS-05	1	TRAVERSING
11	N.F.B	125AF/60AT	1	LS-2
12	UPPER LIMIT	AC 600V/3A	1	LS-1
13	LIMIT LEVER	SS-400	1	
14	FUSE (F11,F12)	2 A	2	
15	FUSE (F13)	5 A	1	
16	TRANSFORMER	460V/110,120V, 200VA	1	
17	TERMINAL BLOCK	100A,25A		
18	TERMINAL BLOCK	15A		
19	EARTH TERMINAL	5t25x50	1	
20	CABLE DUCT	-	1	
21	RELAY	4c4b	2	

NOTE

1. 전선의 색상은 다음과 같다.
 - 1) 흑색 : 교류 및 직류 전원회로
 - 2) 적색 : 교류 제어회로
 - 3) 청색 : 직류 제어회로
 - 4) 주황색 : 외부 안전장치 제어회로
2. CABLE MATERIAL : KIV OR EQUIVALENT
MIN SIZE : 2.5sq
3. 제어용 전선 : 2.5mm KIV,HIV
4. 제막시 다소 변경 될수있음.
5. 외함 개방구조는 다음과 같을것.
- 1) 외함 개방시 충전부분이 차단되도록 할것.
- 2) 외함 개방후 충전되어있는 부분은 IP2X 이상의 직접 접촉 방호가 되어있을것.

DRAWING	DESIGN	CHECKED	APPROVED	SCALE	DATE	ORDER NO.
				NONE		

HOISTING CONTROL BOX(CRANE)

ARRANGEMENT DRAWING

DATE	REVISIONS	CHK.	APP.	CUSTOMER

고객호이스트 주식회사
KUK DONG HOIST CO., LTD.


KDC15BA52

[illegible]

1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
---	---	---	---	---	---	---	---	---	----	----	----	----	----	----	----	----	----	----	----

POWER CIRCUIT

TRAVERSING MOTION




SPECIFICATION SYMBOLS		DESCRIPTION		TRAVERSING MOTOR		DC MAG. BRAKE		MAGNET CONTACTOR		SILICON RECTIFIER		ELECTRIC OVER CURRENT RELAY		LIMIT SWITCH	
IM 30		1.5KW x 4P AC 3PH 460V 60Hz		DB 30		M301, M302		RF 300		SR-30		SS-05		LS-301, LS-302	
IM 30		1.0KW x 6P AC 3PH 460V 60Hz		DC 100V		DOC-22P AC 110V		SR-30		SR-30		SS-05		HY - W804	
IM 30		1.0KW x 6P AC 3PH 460V 60Hz		DC 100V		DOC-22P AC 110V		SR-30		SR-30		SS-05		HY - W804	
KUKDONG		KUKDONG		DAERYUK		ASECO		DAERYUK		ASECO		DAERYUK		ASECO	
CUSTOMER		DRAWING		DESIGN		CHECKED		APPROVED		SCALE		DATE		ORDER NO.	
KUKDONG		KUKDONG		KUKDONG		KUKDONG		KUKDONG		KUKDONG		KUKDONG		KUKDONG	
DRAWING TITLE		REVISIONS		CHK.		APP.		DATE		DWG. NO.		KDC20E53			
TRAVERSING POWER CONTROL CIRCUIT															
DIAGRAM															

[illegible]

1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
---	---	---	---	---	---	---	---	---	----	----	----	----	----	----	----	----	----	----	----


POWER CIRCUIT

TRAVERING MOTION



SPECIFICATION SYMBOLS		DESCRIPTION		MAGNET CONTACTOR		SILICON RECTIFIER		ELECTRIC OVER CURRENT RELAY		TRANSFORMER	
TRAVERING MOTOR		IM 30		M301, M302, M303, M304, M305		RF 300		EOCR 301,302		TR300	
460V		1.5/0.75KWx6/12P AC3PH 460V 60Hz		DOC-22P		DOC-22R		SS-05		AC460/220V, 300VA	
480V		1.0/0.5KWx4/8P AC3PH 480V 60Hz		DOC-22P		DOC-22R		SS-05		AC460/220V, 300VA	
SELECTION MAKER		KUKDONG		DAERYUK		ASECO		SHINHAN			
CUSTOMER				DRAWING		DESIGN		CHECKED		APPROVED	
DRAWING TITLE		TRAVERING POWER CONTROL CIRCUIT		DATE		SCALE		NONE			
CHK. APP.				DWG. NO		KDC20E55					
REVISIONS				KUKDONG HOIST CO., LTD.							

1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
POWER CIRCUIT																			
TRAVERSING MOTION																			
ADR'S NO.																			C2



SPECIFICATION SYMBOLS				MAGNET CONTACTOR				ELECTRIC OVER CURRENT RELAY				TRANSFORMER			
DESCRIPTION				DB30, DB31				EOCR 301, 302				TR300			
460V				DC 100V				SS-30				AC460/220V, 300VA			
460V				DC 100V				SS-30				AC460/220V, 300VA			
SELECTION MAKER				DAERYUK				ASECO				SHINHAN			
KUKDONG				KUKDONG				KUKDONG				KUKDONG			
CUSTOMER				DRAWING				CHECKED				APPROVED			
DRAWING TITLE				DESIGN				SCALE				DATE			
TRAVERSING POWER CONTROL CIRCUIT								NONE							
CHK. APP.				DWG. NO				KDC20E56							
REVISIONS															
DATE															

1 2 3 4 5 6 7 8 9 10 11 12 13 14 15 16 17 18 19 20.

ADR'S NO.

NO	DESCRIPTION	SPECIFICATION	Q'TY	REMARK
1	CHASSIS PLATE		1	이 전 도 플
2	MAGNET CONTACT	MC-130a	2	HOISTING
3	MAGNET CONTACT	DMC22C	2	CREEP HOISTING
4	MAGNET CONTACT	DMC22C	2	TRAVERSING
5	SILICON RECTIFIER	SR-60	1	HOISTING
6	SILICON RECTIFIER	SR-30	1	CREEP HOISTING
7	SILICON RECTIFIER	SR-30	1	TRAVERSING
8	E.O.C.R	SS-60	1	HOISTING
9	E.O.C.R	SS-30	1	CREEP HOISTING
10	E.O.C.R	SS-05	1	TRAVERSING
11	N.F.B	125AF/60AT	1	LS-2
12	UPPER LIMIT	AC 600V/3A	1	LS-1
13	LIMIT LEVER	SS-400	1	
14	FUSE (F11,F12)	2 A	2	
15	FUSE (F13)	5 A	1	
16	TRANSFORMER	480V/110,120V, 200VA	1	
17	TERMINAL BLOCK	100A,25A		
18	TERMINAL BLOCK	15A		
19	EARTH TERMINAL	5x25x50	1	
20	CABLE DUCT	-	1	
21	RELAY	4g4b	2	

NOTE 1. 전선의 색상은 다음과 같다.

- 1) 흑색 : 교류 및 직류 전원회로
- 2) 파색 : 교류 제어회로
- 3) 청색 : 직류 제어회로
- 4) 주황색 : 외부 연동장치 제어회로

2. CABLE MATERIAL : KIV OR EQUIVALENT


3. 제어용 전선 : 2.5mm KIV,HIV

4. 제어시 다소 변경 될수있음.

5. 외함 개방구조는 다음과 같을것.


1) 외함 개방시 충전부분이 차단되도록 할것.

2) 외함 개방후 충전되어있는 부분은 IP2X 이상의 직접 접촉 방호가 되어있을것.



NOTE

1. UPPER LIMIT LS-1의 점접 허용 전류 용량 : AC 600V 3A
2. UPPER LIMIT LS-2의 점접 허용 전류 용량 : NFB 103AF
3. EARTH TERMINAL RESISTANCE : 0.018 Ω
4. POWER SOURCE : AC 3Φ 480V 60HZ



DRAWING	DESIGN	CHECKED	APPROVED	SCALE	DATE	ORDER NO.
				NONE		
KUK DONG HOIST CO., LTD.						KDC20BA62
ARRANGEMENT DRAWING						
HOISTING CONTROL BOX(CRANE)						
DATE	REVISIONS	CHK.	APP.			
MK						

안전보건공단

안전보건공단

KOREA OCCUPATIONAL SAFETY & HEALTH AGENCY

HOISTING MOTION

(A1/06)(A1/06)(A1/07)(A1/07)

POWER CIRCUIT

HOISTING MOTION

UPPER LIMIT LS - II & MCCB100

TO: LOAD LIMITER (A5/06) (A5/06) (A5/06)

IM10 HOISTING MOTOR

IM11 HOISTING MOTOR

DB10 DC MAG. BRAKE

DB11 DC MAG. BRAKE

CREEP HOIST MOTOR


CREEP HOIST MOTION

ADP'S NO. B1

SPECIFICATION SYMBOLS	HOISTING POWER	HOISTING MOTOR	CREEP MOTOR	DC MAG. BRAKE	NO FUSE BREAKER	TRANSFORMER	FUSE	MAGNET CONTACTOR	UPPER LIMIT	ELECTRIC OVER CURRENT RELAY	SILICON RECTIFIER	LOAD LIMITER	CABLE
DESCRIPTION	HOIST	IM 10	IM 11	DB10, 11	LS-II & MCCB100	TR 1	F11, F12	M101, M102	LS-I, LS-II	EOCR100	RF100	LDL-100	C20-01
SELECTION	20TON AC3PH 480V 60Hz	17KWx8P	17KWx8P	DC 100V	ABS-103AF/60AT	480/100V, 120V, 200V/4	2A	MC-130a	AC 600V 3A	SS-60	SR-60	VCT 25sqx4c	


REVISIONS	CHK.	APP.	CUSTOMER	DRAWING TITLE	DWG. NO.	ORDER NO.
				CREEP HOISTING POWER & CONTROL	KDC20FE62	

1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
POWER CIRCUIT																			
TRAVERSING MOTION																			
C1																			ADR'S NO.




KUKDONG		DAERYUK		ASECO									
DRAWING		DESIGN		CHECKED		APPROVED		SCALE		DATE		ORDER NO.	
CUSTOMER													
DRAWING TITLE		TRAVERSING POWER CONTROL CIRCUIT											
REVISIONS		DIAGRAM											
DATE													
CHK.													
APP.													
KUKDONG HOIST CO., LTD.		KUKDONG HOIST CO., LTD.										KDC20E63	

1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
POWER CIRCUIT																			
TRaversing Motion																			
ADR'S NO.																			C2



산업재해예방
안전보건공단
KOREA OCCUPATIONAL SAFETY & HEALTH AGENCY




CUSTOMER		DRAWING		DESIGN		CHECKED		APPROVED		SCALE		DATE		ORDER NO.	
KUK DONG		DAERYUK		MAGNET CONTACTOR		SILICON RECTIFIER		ELECTRIC OVER CURRENT RELAY		LIMIT SWITCH		NONE			
TRAVERSING MOTOR		TRAVERSING MOTOR		DC MAG. BRAKE		DC MAG. BRAKE		DC MAG. BRAKE		DC MAG. BRAKE		DC MAG. BRAKE		DC MAG. BRAKE	
IM30		IM31		DB30		DB30		DB30		DB30		DB30		DB30	
1.5KW x 4P AC 3PH 480V 60Hz		1.5KW x 4P AC 3PH 480V 60Hz		DC 100V		DC 100V		DC 100V		DC 100V		DC 100V		DC 100V	
1.0KW x 6P AC 3PH 480V 60Hz		1.0KW x 6P AC 3PH 480V 60Hz		DC 100V		DC 100V		DC 100V		DC 100V		DC 100V		DC 100V	
KUK DONG		KUK DONG		KUK DONG		KUK DONG		KUK DONG		KUK DONG		KUK DONG		KUK DONG	
TRAVERSING POWER CONTROL CIRCUIT		TRAVERSING POWER CONTROL CIRCUIT		TRAVERSING POWER CONTROL CIRCUIT		TRAVERSING POWER CONTROL CIRCUIT		TRAVERSING POWER CONTROL CIRCUIT		TRAVERSING POWER CONTROL CIRCUIT		TRAVERSING POWER CONTROL CIRCUIT		TRAVERSING POWER CONTROL CIRCUIT	
DIAGRAM		DIAGRAM		DIAGRAM		DIAGRAM		DIAGRAM		DIAGRAM		DIAGRAM		DIAGRAM	
CHK. APP.		REVISIONS		DATE		DATE		DATE		DATE		DATE		DATE	
KDC20E64		KDC20E64		KDC20E64		KDC20E64		KDC20E64		KDC20E64		KDC20E64		KDC20E64	

1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20																																																								
POWER CIRCUIT																																																																											
TRAVERSING MOTION																																																																											
<table><tr><td>SPECIFICATION SYMBOLS DESCRIPTION</td><td>TRAVERSING MOTOR IM 30 IM31</td><td>TRAVERSING MOTOR IM 30 IM31</td><td>DC MAG. BRAKE DB30, DB31</td><td>MAGNET CONTACTOR M301, M302, M303, M304, M305</td><td>SILICON RECTIFIER RF 300</td><td>ELECTRIC OVER CURRENT RELAY EOCR 301, 302</td><td>TRANSFORMER TR300</td></tr><tr><td>SELECTION MAKER</td><td>480V 1.5/0.75KWx6/12P AC3PH 480V 60Hz</td><td>480V 1.0/0.5KWx4/8P AC3PH 480V 60Hz</td><td>DC 100V</td><td>DC 100V</td><td>DC 100V</td><td>SS-30</td><td>AC480/220V, 300VA</td></tr></table> <table><tr><td>CUSTOMER</td><td>KUKDONG</td><td>DRAWING</td><td>DAERYUK</td><td>CHECKED</td><td>APPROVED</td><td>SCALE</td><td>DATE</td><td>ORDER NO.</td></tr><tr><td>DRAWING TITLE</td><td>TRAVERSING POWER CONTROL CIRCUIT</td><td></td><td></td><td></td><td></td><td>NONE</td><td></td><td></td></tr><tr><td>REVISIONS</td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td></tr><tr><td>CHK. DATE</td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td></tr></table> <table><tr><td>DWG. NO.</td><td>KDC20E66</td></tr><tr><td>SHINHAN</td><td></td></tr></table>																				SPECIFICATION SYMBOLS DESCRIPTION	TRAVERSING MOTOR IM 30 IM31	TRAVERSING MOTOR IM 30 IM31	DC MAG. BRAKE DB30, DB31	MAGNET CONTACTOR M301, M302, M303, M304, M305	SILICON RECTIFIER RF 300	ELECTRIC OVER CURRENT RELAY EOCR 301, 302	TRANSFORMER TR300	SELECTION MAKER	480V 1.5/0.75KWx6/12P AC3PH 480V 60Hz	480V 1.0/0.5KWx4/8P AC3PH 480V 60Hz	DC 100V	DC 100V	DC 100V	SS-30	AC480/220V, 300VA	CUSTOMER	KUKDONG	DRAWING	DAERYUK	CHECKED	APPROVED	SCALE	DATE	ORDER NO.	DRAWING TITLE	TRAVERSING POWER CONTROL CIRCUIT					NONE			REVISIONS									CHK. DATE									DWG. NO.	KDC20E66	SHINHAN	
SPECIFICATION SYMBOLS DESCRIPTION	TRAVERSING MOTOR IM 30 IM31	TRAVERSING MOTOR IM 30 IM31	DC MAG. BRAKE DB30, DB31	MAGNET CONTACTOR M301, M302, M303, M304, M305	SILICON RECTIFIER RF 300	ELECTRIC OVER CURRENT RELAY EOCR 301, 302	TRANSFORMER TR300																																																																				
SELECTION MAKER	480V 1.5/0.75KWx6/12P AC3PH 480V 60Hz	480V 1.0/0.5KWx4/8P AC3PH 480V 60Hz	DC 100V	DC 100V	DC 100V	SS-30	AC480/220V, 300VA																																																																				
CUSTOMER	KUKDONG	DRAWING	DAERYUK	CHECKED	APPROVED	SCALE	DATE	ORDER NO.																																																																			
DRAWING TITLE	TRAVERSING POWER CONTROL CIRCUIT					NONE																																																																					
REVISIONS																																																																											
CHK. DATE																																																																											
DWG. NO.	KDC20E66																																																																										
SHINHAN																																																																											
KUKDONG HOIST CO., LTD.																																																																											
KDC20E66																																																																											

[illegible]

1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
TRaversing Motion										CONTROL CIRCUIT DIAGRAM									
POWER CIRCUIT DIAGRAM										BRAKE EAST WEST HIGH SPEED									
KDD2010E1003										ADR'S NO.									



SPECIFICATION SYMBOLS DESCRIPTION		TRaversing Motor	TRaversing Power	DC MAG. BRAKE	NO FUSE BREAKER	TRANSFORMER	BRAKE MAGNET	CONTROL RELAY	INVERTER	SILICON RECTIFIER
IM 30		IM 30	1.5KW x 4P	DB30	MCCB300	TR 300	M301	CR301, 302, 303	INV300	RF300
AC 3PH 220V 60Hz			AC 3PH 220V 60Hz	DC 100V	DBE-33AF/20AT	220/220V, 300VA	DN-22C	MINI 4a4b(Coil AC110V)	SV037IG5A-2	SR-30
AC 3PH 220V 60Hz			AC 3PH 220V 60Hz	DC 100V	DBE-33AF/20AT	220/220V, 300VA	DN-22C	MINI 4a4b(Coil AC110V)	SV037IG5A-2	SR-30
AC 3PH 380V, 440V, 460V, 480V 60Hz			AC 3PH 380V, 440V, 460V, 480V 60Hz	DC 100V	DBE-33AF/20AT	380/220V, 300VA	DN-22C	MINI 4a4b(Coil AC110V)	SV037IG5A-4	SR-30
AC 3PH 380V, 440V, 460V, 480V 60Hz			AC 3PH 380V, 440V, 460V, 480V 60Hz	DC 100V	DBE-33AF/20AT	440/220V, 300VA	DN-22C	MINI 4a4b(Coil AC110V)	SV037IG5A-4	SR-30
SELECTION MAKER		KUK DONG HOIST								
CUSTOMER		KUK DONG HOIST CO., LTD.								
DRAWING TITLE		TRaversing Power & CONTROL CIRCUIT								
REVISIONS		DIAGRAM								
DATE		KDD2010E1003								
CHK. APP.		KUK DONG HOIST CO., LTD.								
DRAWING		KDD								
DESIGN		KUK DONG HOIST CO., LTD.								
CHECKED		KUK DONG HOIST CO., LTD.								
APPROVED		KUK DONG HOIST CO., LTD.								
SCALE		KUK DONG HOIST CO., LTD.								
DATE		KUK DONG HOIST CO., LTD.								
ORDER NO.		KUK DONG HOIST CO., LTD.								
DWG. NO		KDD2010E1003								



1

2

3

4

5

6

7

8

9

10

11

12

13

14

15

16

17

18

19

20

ADR'S NO.

1

2

3

4

5

NO

DESCRIPTION

MT'L

REMARKS

1

PANEL CASE

SPC

1.6t

2

PANEL COVER

SPC

1.6t

3

HINGE

PUR'

4

CLAMP

PUR'

5

SPONGE

PUR'

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

2

3

4

1

<

[illegible]

[illegible]


KOREA OCCUPATIONAL SAFETY & HEALTH AGENCY

KOREA OCCUPATIONAL SAFETY & HEALTH AGENCY

1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20.																																																																											
KDC75BA51																			ADR'S NO.																																																																											
NOTE 1. 전선의 색상은 다음과 같다. 1) 흑색 : 교류 및 직류 전원선로 5) 청색 : 직류 제어선로 2) 적색 : 교류 제어선 3) 주황색 : 외부 전원에서 공급되는 운동장치 제어회로 4) 녹색 또는 녹색과 황색 혼용 : 접지선 2. CABLE MATERIAL : KIV OR EQUIVALENT 3. 제어용 전선 : 2.5mm KIV,HIV MIN SIZE : 2.5sq 4. 제자시 다소 변경 될수있음. 5. 외함 기밀구조는 다음과 같을것. 1) 외함 개방시 충전부분이 차단되도록 할것. 2) 외함 개방후 충전되어있는 부분은 IP2X 이상의 직접 접촉 방호가 되어있을것.																																																																																														
<table border="1"> <thead> <tr> <th>NO</th><th>DESCRIPTION</th><th>SPECIFICATION</th><th>Q'TY</th><th>REMARK</th></tr> </thead> <tbody> <tr> <td>1</td><td>CHASSIS PLATE</td><td></td><td>1</td><td>아 연 도 금</td></tr> <tr> <td>2</td><td>CABLE DUCT</td><td>-</td><td>1</td><td></td></tr> <tr> <td>3</td><td>N.F.B</td><td>33AF/30AT</td><td>1</td><td>HOISTING</td></tr> <tr> <td>4</td><td></td><td></td><td></td><td></td></tr> <tr> <td>5</td><td>MAGNET CONTACTOR</td><td>DMC48C</td><td>2</td><td>HOISTING</td></tr> <tr> <td>6</td><td>MAGNET CONTACTOR</td><td>DMC22C</td><td>2</td><td>CREEP HOIST</td></tr> <tr> <td>7</td><td>SILICON RECTIFIER</td><td>SR-60</td><td>1</td><td>HOISTING</td></tr> <tr> <td>8</td><td>SILICON RECTIFIER</td><td>SR-30</td><td>1</td><td>CREEP HOIST</td></tr> <tr> <td>9</td><td>E.O.C.R</td><td>SS-30</td><td>1</td><td>HOISTING</td></tr> <tr> <td>10</td><td>E.O.C.R</td><td>SS-30</td><td>1</td><td>CREEP HOIST</td></tr> <tr> <td>12</td><td>RELAY & SOCKET</td><td>4a4b</td><td>1</td><td></td></tr> <tr> <td>14</td><td>UPPER LIMITER</td><td>AC 600V, 75A</td><td>1</td><td>LS-1,2</td></tr> <tr> <td>15</td><td>TERMINAL BLOCK</td><td>60A,15A</td><td></td><td></td></tr> <tr> <td>16</td><td>EARTH TERMINAL</td><td>3tx20x50</td><td>1</td><td></td></tr> </tbody> </table>																			NO	DESCRIPTION	SPECIFICATION	Q'TY	REMARK	1	CHASSIS PLATE		1	아 연 도 금	2	CABLE DUCT	-	1		3	N.F.B	33AF/30AT	1	HOISTING	4					5	MAGNET CONTACTOR	DMC48C	2	HOISTING	6	MAGNET CONTACTOR	DMC22C	2	CREEP HOIST	7	SILICON RECTIFIER	SR-60	1	HOISTING	8	SILICON RECTIFIER	SR-30	1	CREEP HOIST	9	E.O.C.R	SS-30	1	HOISTING	10	E.O.C.R	SS-30	1	CREEP HOIST	12	RELAY & SOCKET	4a4b	1		14	UPPER LIMITER	AC 600V, 75A	1	LS-1,2	15	TERMINAL BLOCK	60A,15A			16	EARTH TERMINAL	3tx20x50	1		
NO	DESCRIPTION	SPECIFICATION	Q'TY	REMARK																																																																																										
1	CHASSIS PLATE		1	아 연 도 금																																																																																										
2	CABLE DUCT	-	1																																																																																											
3	N.F.B	33AF/30AT	1	HOISTING																																																																																										
4																																																																																														
5	MAGNET CONTACTOR	DMC48C	2	HOISTING																																																																																										
6	MAGNET CONTACTOR	DMC22C	2	CREEP HOIST																																																																																										
7	SILICON RECTIFIER	SR-60	1	HOISTING																																																																																										
8	SILICON RECTIFIER	SR-30	1	CREEP HOIST																																																																																										
9	E.O.C.R	SS-30	1	HOISTING																																																																																										
10	E.O.C.R	SS-30	1	CREEP HOIST																																																																																										
12	RELAY & SOCKET	4a4b	1																																																																																											
14	UPPER LIMITER	AC 600V, 75A	1	LS-1,2																																																																																										
15	TERMINAL BLOCK	60A,15A																																																																																												
16	EARTH TERMINAL	3tx20x50	1																																																																																											
<table border="1"> <thead> <tr> <th>DRAWING</th><th>DESIGN</th><th>CHECKED</th><th>APPROVED</th><th>SCALE</th><th>DATE</th><th>ORDER NO.</th></tr> </thead> <tbody> <tr> <td colspan="6"></td><td>KDC75BA51</td></tr> </tbody> </table>																			DRAWING	DESIGN	CHECKED	APPROVED	SCALE	DATE	ORDER NO.							KDC75BA51																																																														
DRAWING	DESIGN	CHECKED	APPROVED	SCALE	DATE	ORDER NO.																																																																																								
						KDC75BA51																																																																																								


192.168.11.76 / 2013-12-17 15:49:47

KOREAN OCCUPATIONAL SAFETY & HEALTH AGENCY



안전보건공단 KOSHA

KOREA OCCUPATIONAL SAFETY & HEALTH AGENCY



KDC20E106-075

KOREA OCCUPATIONAL SAFETY & HEALTH AGENCY

1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20.		
CONTROL CIRCUIT												NORTH								D2	
EAST												WEST								D2	

(B1/10) C

(B1/10) P

M301	A	C2/07	a	b	D2/11

M302	A	C2/13	a	b	D2/09

한국산업안전보건공단

(B1/10) C


산업재해예방

안전보건공단

(B1/10) P

KDC20E107-075

KOREA OCCUPATIONAL SAFETY & HEALTH AGENCY



구분	조각비트	표시
원형	비상	비상
원형	비정상	비정상
원형	정상	정상
원형	이무	이무
원형, 원형-원형	지정된미끄럼	기타

NO	DESCRIPTION	NAME	REMARK
1	PUSH BUTTON CASE		
2	PUSH BUTTON COVER		
3	AUX. WIRE		#2
4	CABLE	VCT 2.0eqx15c	
5	CONNECTOR		RUBBER
6	E.M.B	PUSH BUTTON S/W	RESET TYPE
7	SELECTOR S/W (2 STEP)	PUSH BUTTON S/W	MAIN/AUX
8	HOIST UP	PUSH BUTTON S/W	1 BUTTON 2STEP
9	HOIST DOWN	PUSH BUTTON S/W	1 BUTTON 2STEP
10	EAST	PUSH BUTTON S/W	1 BUTTON 2STEP
11	WEST	PUSH BUTTON S/W	1 BUTTON 2STEP
12	SOUTH	PUSH BUTTON S/W	1 BUTTON 1STEP
13	NORTH	PUSH BUTTON S/W	1 BUTTON 1STEP

* CRANE 설치시 발광포시 BUTTON과 동일하게 표시할것,
* IP 55이상


NOTE

1. BOX MAT ' L : POLYCARBONATE
2. E.S.B 規格番号 : CAPACITY : 3A 250V
3. PROTECTION DEGREE : SPLASH PROOF

[illegible]

4. 참 고 도 서

- 1 LOAD LIMITER 권고 SETTING 치
- 2 E.O.C.R 권고 SETTING치
- 3 MOTOR DATA SHEET
- 4 WIRE ROPE 성적서
- 5 SUB VENDOR LIST
- 6 HOIST 취급설명서
- 7 과부하 방지장치 취급설명서
- 8 INVERTER 취급설명서



LOAD LIMITER 권고 SETTING치

* POWER SOURCE : AC 3Φ 220V 60Hz

국동호이스트(주)

HOIST	MOTOR 용량	LOAD LIMITER 권고 SETTING치			LOAD CURRENT		C.T MODEL	연결단자 NO	C.T 용량	REMARK
		LOAD CURRENT	ADJ START TIME	SHOCK TIME	100%	110%				
C15 TON	13KW x 8P	110%	1 SEC	1 SEC	59.0 A	64.0 A	CT-2	K-K1, L-L1	5 V.A	
	1.8KW x 8P	110%	1 SEC	1 SEC	11.0 A	12.7 A	CT-2	K-K1, L-L1	5 V.A	
C20 TON	17KW x 8P	110%	1 SEC	1 SEC	76.6 A	81.9 A	CT-2	K-K1, L-L1	5 V.A	
	1.8KW x 8P	110%	1 SEC	1 SEC	11.0 A	12.7 A	CT-2	K-K1, L-L1	5 V.A	
C30 TON	17KW x 8P	110%	1 SEC	1 SEC	76.6 A	81.9 A	CT-2	K-K1, L-L1	5 V.A	
	1.8KW x 8P	110%	1 SEC	1 SEC	11.0 A	12.7 A	CT-2	K-K1, L-L1	5 V.A	
C35 TON	33KW x 6P	110%	1 SEC	1 SEC	126.6 A	134.2 A	CT-2	K-K1, L-L1	5 V.A	
	3.7KW x 4P	110%	1 SEC	1 SEC	16.0 A	17.8 A	CT-2	K-K1, L-L1	5 V.A	
C40 TON	33KW x 6P	110%	1 SEC	1 SEC	126.6 A	134.2 A	CT-2	K-K1, L-L1	5 V.A	
	3.7KW x 4P	110%	1 SEC	1 SEC	16.0 A	17.8 A	CT-2	K-K1, L-L1	5 V.A	
C50 TON	33KW x 6P	110%	1 SEC	1 SEC	126.6 A	134.2 A	CT-2	K-K1, L-L1	5 V.A	
	3.7KW x 4P	110%	1 SEC	1 SEC	16.0 A	17.8 A	CT-2	K-K1, L-L1	5 V.A	
C60 TON	33KW x 6P	110%	1 SEC	1 SEC	126.6 A	134.2 A	CT-2	K-K1, L-L1	5 V.A	
	3.7KW x 4P	110%	1 SEC	1 SEC	16.0 A	17.8 A	CT-2	K-K1, L-L1	5 V.A	
C70 TON	33KW x 6P	110%	1 SEC	1 SEC	126.6 A	134.2 A	CT-2	K-K1, L-L1	5 V.A	
	3.7KW x 4P	110%	1 SEC	1 SEC	16.0 A	17.8 A	CT-2	K-K1, L-L1	5 V.A	

NOTE

1. 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

LOAD LIMITER 권고 SETTING치

* POWER SOURCE : AC 3Φ 380V 60Hz

극동호이스트(주)

HOIST	MOTOR 용량	LOAD LIMITER 권고 SETTING치			LOAD CURRENT		C.T MODEL	연결단자 NO	C.T 용량	REMARK
		LOAD CURRENT	ADJ START TIME	SHOCK TIME	100%	110%				
C15 TON	13KW x 8P	110%	1 SEC	1 SEC	35.0 A	37.2 A	CT-2	K-K1, L-L1	5 V.A	
	1.8KW x 8P	110%	1 SEC	1 SEC	6.4 A	7.9 A	CT-2	K-K1, L-L1	5 V.A	
C20 TON	17KW x 8P	110%	1 SEC	1 SEC	44.3 A	48.6 A	CT-2	K-K1, L-L1	5 V.A	
	1.8KW x 8P	110%	1 SEC	1 SEC	6.4 A	7.9 A	CT-2	K-K1, L-L1	5 V.A	
C30 TON	17KW x 8P	110%	1 SEC	1 SEC	44.3 A	48.6 A	CT-2	K-K1, L-L1	5 V.A	
	1.8KW x 8P	110%	1 SEC	1 SEC	6.4 A	7.9 A	CT-2	K-K1, L-L1	5 V.A	
C35 TON	33KW x 6P	110%	1 SEC	1 SEC	77.3 A	82.8 A	CT-2	K-K1, L-L1	5 V.A	
	3.7KW x 4P	110%	1 SEC	1 SEC	9.3 A	11.3 A	CT-2	K-K1, L-L1	5 V.A	
C40 TON	33KW x 6P	110%	1 SEC	1 SEC	77.3 A	82.8 A	CT-2	K-K1, L-L1	5 V.A	
	3.7KW x 4P	110%	1 SEC	1 SEC	9.3 A	11.3 A	CT-2	K-K1, L-L1	5 V.A	
C50 TON	33KW x 6P	110%	1 SEC	1 SEC	77.3 A	82.8 A	CT-2	K-K1, L-L1	5 V.A	
	3.7KW x 4P	110%	1 SEC	1 SEC	9.3 A	11.3 A	CT-2	K-K1, L-L1	5 V.A	
C60 TON	33KW x 6P	110%	1 SEC	1 SEC	77.3 A	82.8 A	CT-2	K-K1, L-L1	5 V.A	
	3.7KW x 4P	110%	1 SEC	1 SEC	9.3 A	11.3 A	CT-2	K-K1, L-L1	5 V.A	
C70 TON	33KW x 6P	110%	1 SEC	1 SEC	77.3 A	82.8 A	CT-2	K-K1, L-L1	5 V.A	
	3.7KW x 4P	110%	1 SEC	1 SEC	9.3 A	11.3 A	CT-2	K-K1, L-L1	5 V.A	

NOTE

1. 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

LOAD LIMITER 권고 SETTING치

* POWER SOURCE : AC 3Φ 440V 60Hz

극동하이스트(주)

HOIST	MOTOR 용량	LOAD LIMITER 권고 SETTING치			LOAD CURRENT		C.T MODEL	연결단자 NO	C.T 용량	REMARK
		LOAD CURRENT	ADJ START TIME	SHOCK TIME	100%	110%				
C15 TON	13KW x 8P	110%	1 SEC	1 SEC	29.5 A	32.6 A	CT-2	K-K1, L-L1	5 V.A	
	1.8KW x 8P	110%	1 SEC	1 SEC	5.5 A	7.0 A	CT-2	K-K1, L-L1	5 V.A	
	17KW x 8P	110%	1 SEC	1 SEC	38.3 A	42.6 A	CT-2	K-K1, L-L1	5 V.A	
C20 TON	1.8KW x 8P	110%	1 SEC	1 SEC	5.5 A	7.0 A	CT-2	K-K1, L-L1	5 V.A	
	17KW x 8P	110%	1 SEC	1 SEC	38.3 A	42.6 A	CT-2	K-K1, L-L1	5 V.A	
	1.8KW x 8P	110%	1 SEC	1 SEC	5.5 A	7.0 A	CT-2	K-K1, L-L1	5 V.A	
C30 TON	1.8KW x 8P	110%	1 SEC	1 SEC	5.5 A	7.0 A	CT-2	K-K1, L-L1	5 V.A	
	17KW x 8P	110%	1 SEC	1 SEC	38.3 A	42.6 A	CT-2	K-K1, L-L1	5 V.A	
	1.8KW x 8P	110%	1 SEC	1 SEC	5.5 A	7.0 A	CT-2	K-K1, L-L1	5 V.A	
C35 TON	33KW x 6P	110%	1 SEC	1 SEC	63.3 A	68.6 A	CT-2	K-K1, L-L1	5 V.A	
	3.7KW x 4P	110%	1 SEC	1 SEC	8.0 A	10.8 A	CT-2	K-K1, L-L1	5 V.A	
	33KW x 6P	110%	1 SEC	1 SEC	63.3 A	68.6 A	CT-2	K-K1, L-L1	5 V.A	
C40 TON	33KW x 6P	110%	1 SEC	1 SEC	63.3 A	68.6 A	CT-2	K-K1, L-L1	5 V.A	
	3.7KW x 4P	110%	1 SEC	1 SEC	8.0 A	10.8 A	CT-2	K-K1, L-L1	5 V.A	
	33KW x 6P	110%	1 SEC	1 SEC	63.3 A	68.6 A	CT-2	K-K1, L-L1	5 V.A	
C50 TON	33KW x 6P	110%	1 SEC	1 SEC	63.3 A	68.6 A	CT-2	K-K1, L-L1	5 V.A	
	3.7KW x 4P	110%	1 SEC	1 SEC	8.0 A	10.8 A	CT-2	K-K1, L-L1	5 V.A	
	33KW x 6P	110%	1 SEC	1 SEC	63.3 A	68.6 A	CT-2	K-K1, L-L1	5 V.A	
C60 TON	33KW x 6P	110%	1 SEC	1 SEC	63.3 A	68.6 A	CT-2	K-K1, L-L1	5 V.A	
	3.7KW x 4P	110%	1 SEC	1 SEC	8.0 A	10.8 A	CT-2	K-K1, L-L1	5 V.A	
	33KW x 6P	110%	1 SEC	1 SEC	63.3 A	68.6 A	CT-2	K-K1, L-L1	5 V.A	
C70 TON	33KW x 6P	110%	1 SEC	1 SEC	63.3 A	68.6 A	CT-2	K-K1, L-L1	5 V.A	
	3.7KW x 4P	110%	1 SEC	1 SEC	8.0 A	10.8 A	CT-2	K-K1, L-L1	5 V.A	
	33KW x 6P	110%	1 SEC	1 SEC	63.3 A	68.6 A	CT-2	K-K1, L-L1	5 V.A	

NOTE

1. 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

LOAD LIMITER 권고 SETTING치

* POWER SOURCE : AC 3Φ 460V 60Hz

극동하이스트(주)

HOIST	MOTOR 용량	LOAD LIMITER 권고 SETTING치			LOAD CURRENT		C.T MODEL	연결단자 NO	C.T 용량	REMARK
		LOAD CURRENT	ADJ START TIME	SHOCK TIME	100%	110%				
C15 TON	13KW x 8P	110%	1 SEC	1 SEC	28.4 A	31.3 A	CT-2	K-K1, L-L1	5 V.A	
	1.8KW x 8P	110%	1 SEC	1 SEC	5.5 A	7.0 A	CT-2	K-K1, L-L1	5 V.A	
C20 TON	17KW x 8P	110%	1 SEC	1 SEC	36.7 A	40.4 A	CT-2	K-K1, L-L1	5 V.A	
	1.8KW x 8P	110%	1 SEC	1 SEC	5.5 A	7.0 A	CT-2	K-K1, L-L1	5 V.A	
C30 TON	17KW x 8P	110%	1 SEC	1 SEC	36.7 A	40.4 A	CT-2	K-K1, L-L1	5 V.A	
	1.8KW x 8P	110%	1 SEC	1 SEC	5.3 A	7.0 A	CT-2	K-K1, L-L1	5 V.A	
C35 TON	33KW x 6P	110%	1 SEC	1 SEC	60.5 A	65.5 A	CT-2	K-K1, L-L1	5 V.A	
	3.7KW x 4P	110%	1 SEC	1 SEC	7.7 A	8.5 A	CT-2	K-K1, L-L1	5 V.A	
C40 TON	33KW x 6P	110%	1 SEC	1 SEC	60.5 A	65.5 A	CT-2	K-K1, L-L1	5 V.A	
	3.7KW x 4P	110%	1 SEC	1 SEC	7.7 A	8.5 A	CT-2	K-K1, L-L1	5 V.A	
C50 TON	33KW x 6P	110%	1 SEC	1 SEC	60.5 A	65.5 A	CT-2	K-K1, L-L1	5 V.A	
	3.7KW x 4P	110%	1 SEC	1 SEC	7.7 A	8.5 A	CT-2	K-K1, L-L1	5 V.A	
C60 TON	33KW x 6P	110%	1 SEC	1 SEC	60.5 A	65.5 A	CT-2	K-K1, L-L1	5 V.A	
	3.7KW x 4P	110%	1 SEC	1 SEC	7.7 A	8.5 A	CT-2	K-K1, L-L1	5 V.A	
C70 TON	33KW x 6P	110%	1 SEC	1 SEC	60.5 A	65.5 A	CT-2	K-K1, L-L1	5 V.A	
	3.7KW x 4P	110%	1 SEC	1 SEC	7.7 A	8.5 A	CT-2	K-K1, L-L1	5 V.A	

NOTE

1. 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

LOAD LIMITER 권고 SETTING치

* POWER SOURCE : AC 3Φ 480V 60Hz

극동호이스트(주)

HOIST	MOTOR 용량	LOAD LIMITER 권고 SETTING치			LOAD CURRENT		C.T MODEL	연결단자 NO	C.T 용량	REMARK
		LOAD CURRENT	ADJ START TIME	SHOCK TIME	100%	110%				
C15 TON	13KW x 8P	110%	1 SEC	1 SEC	27.2 A	30.0 A	CT-2	K-K1, L-L1	5 V.A	
	1.8KW x 8P	110%	1 SEC	1 SEC	5.5 A	7.0 A	CT-2	K-K1, L-L1	5 V.A	
C20 TON	17KW x 8P	110%	1 SEC	1 SEC	35.2 A	38.7 A	CT-2	K-K1, L-L1	5 V.A	
	1.8KW x 8P	110%	1 SEC	1 SEC	5.5 A	7.0 A	CT-2	K-K1, L-L1	5 V.A	
C30 TON	17KW x 8P	110%	1 SEC	1 SEC	35.2 A	38.7 A	CT-2	K-K1, L-L1	5 V.A	
	1.8KW x 8P	110%	1 SEC	1 SEC	5.1 A	7.0 A	CT-2	K-K1, L-L1	5 V.A	
C35 TON	33KW x 6P	110%	1 SEC	1 SEC	58.0 A	62.8 A	CT-2	K-K1, L-L1	5 V.A	
	3.7KW x 4P	110%	1 SEC	1 SEC	7.3 A	8.2 A	CT-2	K-K1, L-L1	5 V.A	
C40 TON	33KW x 6P	110%	1 SEC	1 SEC	58.0 A	62.8 A	CT-2	K-K1, L-L1	5 V.A	
	3.7KW x 4P	110%	1 SEC	1 SEC	7.3 A	8.2 A	CT-2	K-K1, L-L1	5 V.A	
C50 TON	33KW x 6P	110%	1 SEC	1 SEC	58.0 A	62.8 A	CT-2	K-K1, L-L1	5 V.A	
	3.7KW x 4P	110%	1 SEC	1 SEC	7.3 A	8.2 A	CT-2	K-K1, L-L1	5 V.A	
C60 TON	33KW x 6P	110%	1 SEC	1 SEC	58.0 A	62.8 A	CT-2	K-K1, L-L1	5 V.A	
	3.7KW x 4P	110%	1 SEC	1 SEC	7.3 A	8.2 A	CT-2	K-K1, L-L1	5 V.A	
C70 TON	33KW x 6P	110%	1 SEC	1 SEC	58.0 A	62.8 A	CT-2	K-K1, L-L1	5 V.A	
	3.7KW x 4P	110%	1 SEC	1 SEC	7.3 A	8.2 A	CT-2	K-K1, L-L1	5 V.A	

NOTE

1. 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

E.O.C.R 권고 SETTING치

* POWER SOURCE : AC 3Φ 220V 60Hz

극동하이스트(주)

HOIST	MOTOR 용량	MOTOR 정격 전류	DRIVE TYPE	E.O.C.R TYPE	권고 SETTING 치			REMARK
					DELAY TIME	OPERATION TIME	CURRENT	
C15 TON	13KW x 8P	59.0 A	1 DRAVE	SS-60	3 SEC	1 SEC	59.0 A	
	1.8KW x 8P	11.0 A	1 DRAVE	SS-30	3 SEC	1 SEC	11.0 A	
C20 TON	17KW x 8P	76.6 A	1 DRAVE	SS-100	3 SEC	1 SEC	76.6 A	
	1.8KW x 8P	11.0 A	1 DRAVE	SS-30	3 SEC	1 SEC	11.0 A	
C30 TON	17KW x 8P	76.6 A	1 DRAVE	SS-100	3 SEC	1 SEC	76.6 A	
	1.8KW x 8P	11.0 A	1 DRAVE	SS-30	3 SEC	1 SEC	11.0 A	
C35 TON	33KW x 6P	126.6 A	1 DRAVE	SS-130	3 SEC	1 SEC	126.6 A	
	3.7KW x 4P	16.0 A	1 DRAVE	SS-30	3 SEC	1 SEC	16.0 A	
C40 TON	33KW x 6P	126.6 A	1 DRAVE	SS-130	3 SEC	1 SEC	126.6 A	
	3.7KW x 4P	16.0 A	1 DRAVE	SS-30	3 SEC	1 SEC	16.0 A	
C50 TON	33KW x 6P	126.6 A	1 DRAVE	SS-130	3 SEC	1 SEC	126.6 A	
	3.7KW x 4P	16.0 A	1 DRAVE	SS-30	3 SEC	1 SEC	16.0 A	
C60 TON	33KW x 6P	126.6 A	1 DRAVE	SS-130	3 SEC	1 SEC	126.6 A	
	3.7KW x 4P	16.0 A	1 DRAVE	SS-30	3 SEC	1 SEC	16.0 A	
C70 TON	33KW x 6P	126.6 A	1 DRAVE	SS-130	3 SEC	1 SEC	126.6 A	
	3.7KW x 4P	16.0 A	1 DRAVE	SS-30	3 SEC	1 SEC	16.0 A	

NOTE

1. 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

E.O.C.R 권고 SETTING치

* POWER SOURCE : AC 3Φ 380V 60Hz

극동호이스트(주)

HOIST	MOTOR 용량	1 정격 전류	DRIVE TYPE	E.O.C.R TYPE	권고 SETTING 치			REMARK
					DELAY TIME	OPERATION TIME	CURRENT	
C15 TON	13KW x 8P	35.0 A	1 DRAVE	SS-60	3 SEC	1 SEC	35.0 A	
	1.8KW x 8P	6.4 A	1 DRAVE	SS-30	3 SEC	1 SEC	6.4 A	
C20 TON	17KW x 8P	44.3 A	1 DRAVE	SS-60	3 SEC	1 SEC	44.3 A	
	1.8KW x 8P	6.4 A	1 DRAVE	SS-30	3 SEC	1 SEC	6.4 A	
C30 TON	17KW x 8P	44.3 A	1 DRAVE	SS-60	3 SEC	1 SEC	44.3 A	
	1.8KW x 8P	6.4 A	1 DRAVE	SS-30	3 SEC	1 SEC	6.4 A	
C35 TON	33KW x 6P	77.3 A	1 DRAVE	SS-100	3 SEC	1 SEC	77.3 A	
	3.7KW x 4P	9.3 A	1 DRAVE	SS-30	3 SEC	1 SEC	9.3 A	
C40 TON	33KW x 6P	77.3 A	1 DRAVE	SS-100	3 SEC	1 SEC	77.3 A	
	3.7KW x 4P	9.3 A	1 DRAVE	SS-30	3 SEC	1 SEC	9.3 A	
C50 TON	33KW x 6P	77.3 A	1 DRAVE	SS-100	3 SEC	1 SEC	77.3 A	
	3.7KW x 4P	9.3 A	1 DRAVE	SS-30	3 SEC	1 SEC	9.3 A	
C60 TON	33KW x 6P	77.3 A	1 DRAVE	SS-100	3 SEC	1 SEC	77.3 A	
	3.7KW x 4P	9.3 A	1 DRAVE	SS-30	3 SEC	1 SEC	9.3 A	
C70 TON	33KW x 6P	77.3 A	1 DRAVE	SS-100	3 SEC	1 SEC	77.3 A	
	3.7KW x 4P	9.3 A	1 DRAVE	SS-30	3 SEC	1 SEC	9.3 A	

NOTE

1. 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

E.O.C.R 권고 SETTING치

* POWER SOURCE : AC 3Φ 440V 60Hz

극동호이스트(주)

HOIST	MOTOR 용량	MOTOR 정격 전류	DRIVE TYPE	E.O.C.R TYPE	권고 SETTING 치			REMARK
					DELAY TIME	OPERATION TIME	CURRENT	
C15 TON	13KW x 8P	29.5 A	1 DRAVE	SS-30	3 SEC	1 SEC	29.5 A	
	1.8KW x 8P	5.5 A	1 DRAVE	SS-30	3 SEC	1 SEC	5.5 A	
C20 TON	17KW x 8P	38.3 A	1 DRAVE	SS-60	3 SEC	1 SEC	38.3 A	
	1.8KW x 8P	5.5 A	1 DRAVE	SS-30	3 SEC	1 SEC	5.5 A	
C30 TON	17KW x 8P	38.3 A	1 DRAVE	SS-60	3 SEC	1 SEC	38.3 A	
	1.8KW x 8P	5.5 A	1 DRAVE	SS-30	3 SEC	1 SEC	5.5 A	
C35 TON	33KW x 6P	63.3 A	1 DRAVE	SS-100	3 SEC	1 SEC	63.3 A	
	3.7KW x 4P	8.0 A	1 DRAVE	SS-30	3 SEC	1 SEC	8.0 A	
C40 TON	33KW x 6P	63.3 A	1 DRAVE	SS-100	3 SEC	1 SEC	63.3 A	
	3.7KW x 4P	8.0 A	1 DRAVE	SS-30	3 SEC	1 SEC	8.0 A	
C50 TON	33KW x 6P	63.3 A	1 DRAVE	SS-100	3 SEC	1 SEC	63.3 A	
	3.7KW x 4P	8.0 A	1 DRAVE	SS-30	3 SEC	1 SEC	8.0 A	
C60 TON	33KW x 6P	63.3 A	1 DRAVE	SS-100	3 SEC	1 SEC	63.3 A	
	3.7KW x 4P	8.0 A	1 DRAVE	SS-30	3 SEC	1 SEC	8.0 A	
C70 TON	33KW x 6P	63.3 A	1 DRAVE	SS-100	3 SEC	1 SEC	63.3 A	
	3.7KW x 4P	8.0 A	1 DRAVE	SS-30	3 SEC	1 SEC	8.0 A	

NOTE

1. 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

E.O.C.R 권고 SETTING치

* POWER SOURCE : AC 3Φ 460V 60Hz

극동호이스트(주)

HOIST	MOTOR 용량	MOTOR 정격 전류	DRIVE TYPE	E.O.C.R TYPE	권고 SETTING 치			REMARK
					DELAY TIME	OPERATION TIME	CURRENT	
C15 TON	13KW x 8P	29.5 A	1 DRAVE	SS-30	3 SEC	1 SEC	29.5 A	
	1.8KW x 8P	5.5 A	1 DRAVE	SS-30	3 SEC	1 SEC	5.5 A	
C20 TON	17KW x 8P	38.3 A	1 DRAVE	SS-60	3 SEC	1 SEC	38.3 A	
	1.8KW x 8P	5.5 A	1 DRAVE	SS-30	3 SEC	1 SEC	5.5 A	
C30 TON	17KW x 8P	36.7 A	1 DRAVE	SS-60	3 SEC	1 SEC	36.7 A	
	1.8KW x 8P	5.3 A	1 DRAVE	SS-30	3 SEC	1 SEC	5.3 A	
C35 TON	33KW x 6P	60.5 A	1 DRAVE	SS-100	3 SEC	1 SEC	60.5 A	
	3.7KW x 4P	7.7 A	1 DRAVE	SS-30	3 SEC	1 SEC	7.7 A	
C40 TON	33KW x 6P	60.5 A	1 DRAVE	SS-100	3 SEC	1 SEC	60.5 A	
	3.7KW x 4P	7.7 A	1 DRAVE	SS-30	3 SEC	1 SEC	7.7 A	
C50 TON	33KW x 6P	60.5 A	1 DRAVE	SS-100	3 SEC	1 SEC	60.5 A	
	3.7KW x 4P	7.7 A	1 DRAVE	SS-30	3 SEC	1 SEC	7.7 A	
C60 TON	33KW x 6P	60.5 A	1 DRAVE	SS-100	3 SEC	1 SEC	60.5 A	
	3.7KW x 4P	7.7 A	1 DRAVE	SS-30	3 SEC	1 SEC	7.7 A	
C70 TON	33KW x 6P	60.5 A	1 DRAVE	SS-100	3 SEC	1 SEC	60.5 A	
	3.7KW x 4P	7.7 A	1 DRAVE	SS-30	3 SEC	1 SEC	7.7 A	

NOTE

1. 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

E.O.C.R 권고 SETTING치

* POWER SOURCE : AC 3Φ 480V 60Hz

극동호이스트(주)

HOIST	MOTOR 용량	MOTOR 정격 전류	DRIVE TYPE	E.O.C.R TYPE	권고 SETTING 치			REMARK
					DELAY TIME	OPERATION TIME	CURRENT	
C15 TON	13KW x 8P	29.5 A	1 DRAVE	SS-30	3 SEC	1 SEC	29.5 A	
	1.8KW x 8P	5.5 A	1 DRAVE	SS-30	3 SEC	1 SEC	5.5 A	
C20 TON	17KW x 8P	38.3 A	1 DRAVE	SS-60	3 SEC	1 SEC	38.3 A	
	1.8KW x 8P	5.5 A	1 DRAVE	SS-30	3 SEC	1 SEC	5.5 A	
C30 TON	17KW x 8P	35.2 A	1 DRAVE	SS-60	3 SEC	1 SEC	35.2 A	
	1.8KW x 8P	5.1 A	1 DRAVE	SS-30	3 SEC	1 SEC	5.1 A	
C35 TON	33KW x 6P	58.0 A	1 DRAVE	SS-60	3 SEC	1 SEC	58.0 A	
	3.7KW x 4P	7.3 A	1 DRAVE	SS-30	3 SEC	1 SEC	7.3 A	
C40 TON	33KW x 6P	58.0 A	1 DRAVE	SS-60	3 SEC	1 SEC	58.0 A	
	3.7KW x 4P	7.3 A	1 DRAVE	SS-30	3 SEC	1 SEC	7.3 A	
C650 TON	33KW x 6P	58.0 A	1 DRAVE	SS-60	3 SEC	1 SEC	58.0 A	
	3.7KW x 4P	7.3 A	1 DRAVE	SS-30	3 SEC	1 SEC	7.3 A	
C60 TON	33KW x 6P	58.0 A	1 DRAVE	SS-60	3 SEC	1 SEC	58.0 A	
	3.7KW x 4P	7.3 A	1 DRAVE	SS-30	3 SEC	1 SEC	7.3 A	
C70 TON	33KW x 6P	58.0 A	1 DRAVE	SS-60	3 SEC	1 SEC	58.0 A	
	3.7KW x 4P	7.3 A	1 DRAVE	SS-30	3 SEC	1 SEC	7.3 A	

NOTE

1. 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

LOAD LIMITER 권고 SETTING치

* POWER SOURCE : AC 3Φ 220V 60Hz

HOIST	MOTOR 용량	LOAD LIMITER 권고 SETTING치			LOAD CURRENT		C.T MODEL	연결단자 NO	C.T 용량	REMARK
		LOAD CURRENT	ADJ START TIME	SHOCK TIME	100%	110%				
C1 TON	2.4KW x 4P	110%	1 SEC	1 SEC	10 A	11.2 A	CT-2	K-K1, L-L1	5 V.A	
	0.4KW x 4P	110%	1 SEC	1 SEC	2.7 A	3.1 A	CT-1	K-K1, L-L1	5 V.A	
C2 TON	3.7KW x 4P	110%	1 SEC	1 SEC	16.0 A	17.4 A	CT-2	K-K1, L-L1	5 V.A	
	0.4KW x 4P	110%	1 SEC	1 SEC	2.7 A	3.1 A	CT-1	K-K1, L-L1	5 V.A	
C2.8 TON	5.0KW x 4P	110%	1 SEC	1 SEC	22.8 A	24.2 A	CT-2	K-K1, L-L1	5 V.A	
	1.5KW x 4P	110%	1 SEC	1 SEC	7.3 A	8.3 A	CT-1	K-K1, L-L1	5 V.A	
C3 TON	5.5KW x 4P	110%	1 SEC	1 SEC	22.8 A	24.3 A	CT-2	K-K1, L-L1	5 V.A	
	1.5KW x 4P	110%	1 SEC	1 SEC	7.3 A	8.3 A	CT-1	K-K1, L-L1	5 V.A	
C5 TON	5.5KW x 6P	110%	1 SEC	1 SEC	28.2 A	30.1 A	CT-2	K-K1, L-L1	5 V.A	
	1.0KW x 6P	110%	1 SEC	1 SEC	6.7 A	8.1 A	CT-1	K-K1, L-L1	5 V.A	
C7.5 TON	5.5KW x 6P	110%	1 SEC	1 SEC	28.2 A	30.1 A	CT-2	K-K1, L-L1	5 V.A	
	1.0KW x 6P	110%	1 SEC	1 SEC	6.7 A	8.1 A	CT-1	K-K1, L-L1	5 V.A	
C10 TON	9.0KW x 8P	110%	1 SEC	1 SEC	45.0 A	49.1 A	CT-2	K-K1, L-L1	5 V.A	
	1.1KW x 8P	110%	1 SEC	1 SEC	8.0 A	9.6 A	CT-2	K-K1, L-L1	5 V.A	

NOTE

1. 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

LOAD LIMITER 권고 SETTING치

* POWER SOURCE : AC 3Φ 380V 60Hz

HOIST	MOTOR 용량	LOAD LIMITER 권고 SETTING치			LOAD CURRENT		C.T MODEL	연결단자 NO	C.T 용량	REMARK
		LOAD CURRENT	ADJ START TIME	SHOCK TIME	100%	110%				
C1 TON	2.4KW x 4P	110%	1 SEC	1 SEC	5.8 A	6.3 A	CT-2	K-K1, L-L1	5 V.A	
	0.4KW x 4P	110%	1 SEC	1 SEC	1.6 A	2.1 A	CT-1	K-K1, L-L1	5 V.A	
C2 TON	3.7KW x 4P	110%	1 SEC	1 SEC	9.3 A	11.3 A	CT-2	K-K1, L-L1	5 V.A	
	0.4KW x 4P	110%	1 SEC	1 SEC	1.6 A	2.1 A	CT-1	K-K1, L-L1	5 V.A	
C2.8 TON	5.0KW x 4P	110%	1 SEC	1 SEC	12.2 A	13.6 A	CT-2	K-K1, L-L1	5 V.A	
	1.5KW x 4P	110%	1 SEC	1 SEC	4.2 A	5.4 A	CT-1	K-K1, L-L1	5 V.A	
C3 TON	5.5KW x 4P	110%	1 SEC	1 SEC	12.2 A	13.6 A	CT-2	K-K1, L-L1	5 V.A	
	1.5KW x 4P	110%	1 SEC	1 SEC	4.2 A	5.4 A	CT-1	K-K1, L-L1	5 V.A	
C5 TON	5.5KW x 6P	110%	1 SEC	1 SEC	16.3 A	17.8 A	CT-2	K-K1, L-L1	5 V.A	
	1.0KW x 6P	110%	1 SEC	1 SEC	3.9 A	5.3 A	CT-1	K-K1, L-L1	5 V.A	
C7.5 TON	5.5KW x 6P	110%	1 SEC	1 SEC	16.3 A	17.8 A	CT-2	K-K1, L-L1	5 V.A	
	1.0KW x 6P	110%	1 SEC	1 SEC	3.9 A	5.3 A	CT-1	K-K1, L-L1	5 V.A	
C10 TON	9.0KW x 8P	110%	1 SEC	1 SEC	26.0 A	28.6 A	CT-2	K-K1, L-L1	5 V.A	
	1.1KW x 8P	110%	1 SEC	1 SEC	4.6 A	6.1 A	CT-2	K-K1, L-L1	5 V.A	

NOTE

1. 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

LOAD LIMITER 권고 SETTING치

* POWER SOURCE : AC 3Φ 440V 60Hz

HOIST	MOTOR 용량	LOAD LIMITER 권고 SETTING치			LOAD CURRENT		C.T MODEL	연결단자 NO	C.T 용량	REMARK
		LOAD CURRENT	ADJ START TIME	SHOCK TIME	100%	110%				
C1 TON	2.4KW x 4P	110%	1 SEC	1 SEC	5.0 A	7.3 A	CT-2	K-K1, L-L1	5 V.A	
	0.4KW x 4P	110%	1 SEC	1 SEC	1.4 A	1.8 A	CT-1	K-K1, L-L1	5 V.A	
C2 TON	3.7KW x 4P	110%	1 SEC	1 SEC	8.0 A	10.8 A	CT-2	K-K1, L-L1	5 V.A	
	0.4KW x 4P	110%	1 SEC	1 SEC	1.4 A	1.8 A	CT-1	K-K1, L-L1	5 V.A	
C2.8 TON	5.0KW x 4P	110%	1 SEC	1 SEC	10.5 A	13.7 A	CT-2	K-K1, L-L1	5 V.A	
	1.5KW x 4P	110%	1 SEC	1 SEC	3.7 A	4.3 A	CT-1	K-K1, L-L1	5 V.A	
C3 TON	5.5KW x 4P	110%	1 SEC	1 SEC	10.5 A	13.7 A	CT-2	K-K1, L-L1	5 V.A	
	1.5KW x 4P	110%	1 SEC	1 SEC	3.7 A	4.3 A	CT-1	K-K1, L-L1	5 V.A	
C5 TON	5.5KW x 6P	110%	1 SEC	1 SEC	14.1 A	18.5 A	CT-2	K-K1, L-L1	5 V.A	
	1.0KW x 6P	110%	1 SEC	1 SEC	3.3 A	4.7 A	CT-1	K-K1, L-L1	5 V.A	
C7.5 TON	5.5KW x 6P	110%	1 SEC	1 SEC	14.1 A	18.5 A	CT-2	K-K1, L-L1	5 V.A	
	1.0KW x 6P	110%	1 SEC	1 SEC	3.3 A	4.7 A	CT-1	K-K1, L-L1	5 V.A	
C10 TON	9.0KW x 8P	110%	1 SEC	1 SEC	22.5 A	24.8 A	CT-2	K-K1, L-L1	5 V.A	
	1.1KW x 8P	110%	1 SEC	1 SEC	4.0 A	5.4 A	CT-1	K-K1, L-L1	5 V.A	

NOTE

1. 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

LOAD LIMITER 권고 SETTING치

* POWER SOURCE : AC 3Φ 460V 60Hz

HOIST	MOTOR 용량	LOAD LIMITER 권고 SETTING치			LOAD CURRENT		C.T MODEL	연결단자 NO	C.T 용량	REMARK
		LOAD CURRENT	ADJ START TIME	SHOCK TIME	100%	110%				
C1 TON	2.4KW x 4P	110%	1 SEC	1 SEC	4.8 A	5.2 A	CT-2	K-K1, L-L1	5 V.A	
	0.4KW x 4P	110%	1 SEC	1 SEC	1.3 A	1.5 A	CT-1	K-K1, L-L1	5 V.A	
C2 TON	3.7KW x 4P	110%	1 SEC	1 SEC	7.7 A	8.5 A	CT-2	K-K1, L-L1	5 V.A	
	0.4KW x 4P	110%	1 SEC	1 SEC	1.3 A	1.5 A	CT-1	K-K1, L-L1	5 V.A	
C2.8 TON	5.0KW x 4P	110%	1 SEC	1 SEC	10.0 A	11.5 A	CT-2	K-K1, L-L1	5 V.A	
	1.5KW x 4P	110%	1 SEC	1 SEC	3.5 A	4.3 A	CT-1	K-K1, L-L1	5 V.A	
C3 TON	5.5KW x 4P	110%	1 SEC	1 SEC	10.0 A	11.5 A	CT-2	K-K1, L-L1	5 V.A	
	1.5KW x 4P	110%	1 SEC	1 SEC	3.5 A	4.3 A	CT-1	K-K1, L-L1	5 V.A	
C5 TON	5.5KW x 6P	110%	1 SEC	1 SEC	13.5 A	14.7 A	CT-2	K-K1, L-L1	5 V.A	
	1.0KW x 6P	110%	1 SEC	1 SEC	3.2 A	3.6 A	CT-1	K-K1, L-L1	5 V.A	
C7.5 TON	5.5KW x 6P	110%	1 SEC	1 SEC	13.5 A	14.7 A	CT-2	K-K1, L-L1	5 V.A	
	1.0KW x 6P	110%	1 SEC	1 SEC	3.2 A	3.6 A	CT-1	K-K1, L-L1	5 V.A	
C10 TON	9.0KW x 8P	110%	1 SEC	1 SEC	21.5 A	23.7 A	CT-2	K-K1, L-L1	5 V.A	
	1.1KW x 8P	110%	1 SEC	1 SEC	4.0 A	5.4 A	CT-1	K-K1, L-L1	5 V.A	

NOTE

1. 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

LOAD LIMITER 권고 SETTING치

* POWER SOURCE : AC 3Φ 480V 60Hz

HOIST	MOTOR 용량	LOAD LIMITER 권고 SETTING치			LOAD CURRENT		C.T MODEL	연결단자 NO	C.T 용량	REMARK
		LOAD CURRENT	ADJ START TIME	SHOCK TIME	100%	110%				
C1 TON	2.4KW x 4P	110%	1 SEC	1 SEC	4.6 A	5.0 A	CT-2	K-K1, L-L1	5 V.A	
	0.4KW x 4P	110%	1 SEC	1 SEC	1.2 A	1.35 A	CT-1	K-K1, L-L1	5 V.A	
C2 TON	3.7KW x 4P	110%	1 SEC	1 SEC	7.3 A	8.2 A	CT-2	K-K1, L-L1	5 V.A	
	0.4KW x 4P	110%	1 SEC	1 SEC	1.2 A	1.35 A	CT-1	K-K1, L-L1	5 V.A	
C2.8 TON	5.0KW x 4P	110%	1 SEC	1 SEC	9.6 A	11.2 A	CT-2	K-K1, L-L1	5 V.A	
	1.5KW x 4P	110%	1 SEC	1 SEC	3.4 A	4.3 A	CT-1	K-K1, L-L1	5 V.A	
C3 TON	5.5KW x 4P	110%	1 SEC	1 SEC	9.6 A	11.2 A	CT-2	K-K1, L-L1	5 V.A	
	1.5KW x 4P	110%	1 SEC	1 SEC	3.4 A	4.3 A	CT-1	K-K1, L-L1	5 V.A	
C5 TON	5.5KW x 6P	110%	1 SEC	1 SEC	12.9 A	14.2 A	CT-2	K-K1, L-L1	5 V.A	
	1.0KW x 6P	110%	1 SEC	1 SEC	3.1 A	3.5 A	CT-1	K-K1, L-L1	5 V.A	
C7.5 TON	5.5KW x 6P	110%	1 SEC	1 SEC	12.9 A	14.2 A	CT-2	K-K1, L-L1	5 V.A	
	1.0KW x 6P	110%	1 SEC	1 SEC	3.1 A	3.5 A	CT-1	K-K1, L-L1	5 V.A	
C10 TON	9.0KW x 8P	110%	1 SEC	1 SEC	20.6 A	22.7 A	CT-2	K-K1, L-L1	5 V.A	
	1.1KW x 8P	110%	1 SEC	1 SEC	4.0 A	5.4 A	CT-1	K-K1, L-L1	5 V.A	

NOTE

1. 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

E.O.C.R 권고 SETTING치

* POWER SOURCE : AC 3 Ø 220V 60HZ

HOIST	MOTOR 용량	MOTOR 정격 전류	DRIVE TYPE	E.O.C.R TYPE	권고 SETTING 치			REMARK
					DELAY TIME	OPERATION TIME	CURRENT	
C1 TON	2.4KW x 4P	10.0 A	1 DRAVE	SS-30	3 SEC	1 SEC	10.0 A	
	0.4KW x 4P	2.7 A	1 DRAVE	SS-05	3 SEC	1 SEC	2.7 A	
C2 TON	3.7KW x 4P	16.0 A	1 DRAVE	SS-30	3 SEC	1 SEC	16.0 A	
	0.4KW x 4P	2.7 A	1 DRAVE	SS-05	3 SEC	1 SEC	2.7 A	
C2.8 TON	5.0KW x 4P	22.8 A	1 DRAVE	SS-30	3 SEC	1 SEC	22.8 A	
	1.5KW x 4P	7.3 A	1 DRAVE	SS-30	3 SEC	1 SEC	7.3 A	
C3 TON	5.5KW x 4P	22.8 A	1 DRAVE	SS-30	3 SEC	1 SEC	22.8 A	
	1.5KW x 4P	7.3 A	1 DRAVE	SS-30	3 SEC	1 SEC	7.3 A	
C5 TON	5.5KW x 6P	28.2 A	1 DRAVE	SS-30	3 SEC	1 SEC	28.2 A	
	1.0KW x 6P	6.7 A	1 DRAVE	SS-30	3 SEC	1 SEC	6.7 A	
C7.5 TON	5.5KW x 6P	28.2 A	1 DRAVE	SS-30	3 SEC	1 SEC	28.2 A	
	1.0KW x 6P	6.7 A	1 DRAVE	SS-30	3 SEC	1 SEC	6.7 A	
C10 TON	9.0KW x 8P	45.0 A	1 DRAVE	SS-60	3 SEC	1 SEC	45.0 A	
	1.1KW x 8P	8.0 A	1 DRAVE	SS-30	3 SEC	1 SEC	8.0 A	

NOTE

1. 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

E.O.C.R 권고 SETTING치

* POWER SOURCE : AC 3Φ 380V 60HZ

HOIST	MOTOR 용량	정격 전류	DRIVE TYPE	E.O.C.R TYPE	권고 SETTING 치			REMARK
					DELAY TIME	OPERATION TIME	CURRENT	
C1 TON	2.4KW x 4P	5.8 A	1 DRAVE	SS-30	3 SEC	1 SEC	5.8 A	
	0.4KW x 4P	1.6 A	1 DRAVE	SS-05	3 SEC	1 SEC	1.6 A%	
C2 TON	3.7KW x 4P	9.3 A	1 DRAVE	SS-30	3 SEC	1 SEC	9.3 A	
	0.4KW x 4P	1.6 A	1 DRAVE	SS-05	3 SEC	1 SEC	1.6 A	
C2.8 TON	5.0KW x 4P	12.2 A	1 DRAVE	SS-30	3 SEC	1 SEC	12.2 A	
	1.5KW x 4P	4.2 A	1 DRAVE	SS-05	3 SEC	1 SEC	4.2 A	
C3 TON	5.5KW x 4P	12.2 A	1 DRAVE	SS-30	3 SEC	1 SEC	12.2 A	
	1.5KW x 4P	4.2 A	1 DRAVE	SS-05	3 SEC	1 SEC	4.2 A	
C5 TON	5.5KW x 6P	16.3 A	1 DRAVE	SS-30	3 SEC	1 SEC	16.3 A	
	1.0KW x 6P	3.9 A	1 DRAVE	SS-05	3 SEC	1 SEC	3.9 A	
C7.5 TON	5.5KW x 6P	16.3 A	1 DRAVE	SS-30	3 SEC	1 SEC	16.3 A	
	1.0KW x 6P	3.9 A	1 DRAVE	SS-05	3 SEC	1 SEC	3.9 A	
C10 TON	9.0KW x 8P	26.0 A	1 DRAVE	SS-30	3 SEC	1 SEC	26.0 A	
	1.1KW x 8P	4.6 A	1 DRAVE	SS-05	3 SEC	1 SEC	4.6 A	

NOTE

1. 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

E.O.C.R 권고 SETTING치

* POWER SOURCE : AC 3Φ 440V 60Hz

극동호이스트(주)

HOIST	MOTOR 용량	MOTOR 정격 전류	DRIVE TYPE	E.O.C.R TYPE	권고 SETTING 치			REMARK
					DELAY TIME	OPERATION TIME	CURRENT	
C1 TON	2.4KW x 4P	5.0 A	1 DRAVE	SS-30	3 SEC	1 SEC	5.0 A	
	0.4KW x 4P	1.4 A	1 DRAVE	SS-05	3 SEC	1 SEC	1.4 A	
C2 TON	3.7KW x 4P	8.0 A	1 DRAVE	SS-30	3 SEC	1 SEC	8.0 A	
	0.4KW x 4P	1.4 A	1 DRAVE	SS-05	3 SEC	1 SEC	1.4 A	
C2.8 TON	5.0KW x 4P	10.5 A	1 DRAVE	SS-30	3 SEC	1 SEC	10.5 A	
	1.5KW x 4P	3.7 A	1 DRAVE	SS-05	3 SEC	1 SEC	3.7 A	
C3 TON	5.5KW x 4P	10.5 A	1 DRAVE	SS-30	3 SEC	1 SEC	10.5 A	
	1.5KW x 4P	3.7 A	1 DRAVE	SS-05	3 SEC	1 SEC	3.7 A	
C5 TON	5.5KW x 6P	14.1 A	1 DRAVE	SS-30	3 SEC	1 SEC	14.1 A	
	1.0KW x 6P	3.3 A	1 DRAVE	SS-05	3 SEC	1 SEC	3.3 A	
C7.5 TON	5.5KW x 8P	14.1 A	1 DRAVE	SS-30	3 SEC	1 SEC	14.1 A	
	1.0KW x 8P	3.3 A	1 DRAVE	SS-05	3 SEC	1 SEC	3.3 A	
C10 TON	9.0KW x 8P	22.5 A	1 DRAVE	SS-30	3 SEC	1 SEC	22.5 A	
	1.1 KW x 8P	4.0 A	1 DRAVE	SS-05	3 SEC	1 SEC	4.0 A	

NOTE

1. 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

E.O.C.R 권고 SETTING치

* POWER SOURCE : AC 3Φ 460V 60HZ

극동호이스트(주)

HOIST	MOTOR 용량	MOTOR 정격 전류	DRIVE TYPE	E.O.C.R TYPE	권고 SETTING 치			REMARK
					DELAY TIME	OPERATION TIME	CURRENT	
C1 TON	2.4KW x 4P	4.8 A	1 DRAVE	SS-30	3 SEC	1 SEC	4.8 A	
	0.4KW x 4P	1.4 A	1 DRAVE	SS-05	3 SEC	1 SEC	1.4 A	
C2 TON	3.7KW x 4P	7.7 A	1 DRAVE	SS-30	3 SEC	1 SEC	7.7 A	
	0.4KW x 4P	1.4 A	1 DRAVE	SS-05	3 SEC	1 SEC	1.4 A	
C2.8 TON	5.0KW x 4P	10.0 A	1 DRAVE	SS-30	3 SEC	1 SEC	10.0 A	
	1.5KW x 4P	3.5 A	1 DRAVE	SS-05	3 SEC	1 SEC	3.5 A	
C3 TON	5.5KW x 4P	10.0 A	1 DRAVE	SS-30	3 SEC	1 SEC	10.0 A	
	1.5KW x 4P	3.5 A	1 DRAVE	SS-05	3 SEC	1 SEC	3.5 A	
C5 TON	5.5KW x 6P	13.5 A	1 DRAVE	SS-30	3 SEC	1 SEC	13.5 A	
	1.0KW x 6P	3.2 A	1 DRAVE	SS-05	3 SEC	1 SEC	3.2 A	
C7.5 TON	5.5KW x 8P	13.5 A	1 DRAVE	SS-30	3 SEC	1 SEC	13.5 A	
	1.0KW x 8P	3.2 A	1 DRAVE	SS-05	3 SEC	1 SEC	3.2 A	
C10 TON	9.0KW x 8P	21.5 A	1 DRAVE	SS-30	3 SEC	1 SEC	21.5 A	
	1.1KW x 8P	4.0 A	1 DRAVE	SS-05	3 SEC	1 SEC	4.0 A	

NOTE

1. 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

E.O.C.R 권고 SETTING치

* POWER SOURCE : AC 3Φ 480V 60Hz

HOIST	MOTOR 용량	MOTOR 정격 전류	DRIVE TYPE	E.O.C.R TYPE	권고 SETTING 치			REMARK
					DELAY TIME	OPERATION TIME	CURRENT	
C1 TON	2.4KW x 4P	4.6 A	1 DRAVE	SS-30	3 SEC	1 SEC	4.6 A	
	0.4KW x 4P	1.4 A	1 DRAVE	SS-05	3 SEC	1 SEC	1.4 A	
C2 TON	3.7KW x 4P	7.3 A	1 DRAVE	SS-30	3 SEC	1 SEC	7.3 A	
	0.4KW x 4P	1.4 A	1 DRAVE	SS-05	3 SEC	1 SEC	1.4 A	
C2.8 TON	5.0KW x 4P	9.6 A	1 DRAVE	SS-30	3 SEC	1 SEC	9.6 A	
	1.5KW x 4P	3.4 A	1 DRAVE	SS-05	3 SEC	1 SEC	3.4 A	
C3 TON	5.5KW x 4P	9.6 A	1 DRAVE	SS-30	3 SEC	1 SEC	9.6 A	
	1.5KW x 4P	3.4 A	1 DRAVE	SS-05	3 SEC	1 SEC	3.4 A	
C5 TON	5.5KW x 6P	12.9 A	1 DRAVE	SS-30	3 SEC	1 SEC	12.9 A	
	1.0KW x 6P	3.1 A	1 DRAVE	SS-05	3 SEC	1 SEC	3.1 A	
C7.5 TON	5.5KW x 6P	12.9 A	1 DRAVE	SS-30	3 SEC	1 SEC	12.9 A	
	1.0KW x 6P	3.1 A	1 DRAVE	SS-05	3 SEC	1 SEC	3.1 A	
C10 TON	9.0KW x 8P	20.6 A	1 DRAVE	SS-30	3 SEC	1 SEC	20.6 A	
	1.1 KW x 8P	4.0 A	1 DRAVE	SS-05	3 SEC	1 SEC	4.0 A	


NOTE

1. 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	HOISTING
2. MANUFACTURE	극동호이스트 (주)
3. FRAME NUMBER	200 L
4. RATED POWER	17 KW x 8 P
5. RATED VOLTAGE AND FREQUENCY	220 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATTING	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 ℃
10. FULL LOAD SPEED	850 RPM
11. FULL LOAD CURRENT	76.6 A
12. STARTING CURRENT AT RATED VOLTAGE	455.8 A
13. MINIMUM STARTING VOLTAGE	200 V
14. EFFICIENCY AT 100% RATED LOAD	82 %
15. POWER FACTOR AT 100% RATED LOAD	71.5 %
16. STARTING TORQUE	39.72 KG.M
17. SITE ALTTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	TIE FCC
19. TYPE OF BEARING	PL : 6312zz OPL : 6311zz
20. MOUNTING	HORIZONTAL
21. MAXIMUM AMBIENT TEMPURE	40 ℃
22. BEARING LUBRICATION	GREASE
23. STARTING METHOD	FULL VOLTAGE




안전보건공단
KOSHA
KOREA OCCUPATIONAL SAFETY & HEALTH AGENCY

THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	HIOISTING
2. MANUFACTURE	극동호이스트 (주)
3. FRAME NUMBER	200 L
4. RATED POWER	17 KW x 8 P
5. RATED VOLTAGE AND FREQUENCY	380 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATTING	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	850 RPM
11. FULL LOAD CURRENT	44.5 A
12. STARTING CURRENT AT RATED VOLTAGE	263.8 A
13. MINIMUM STARTING VOLTAGE	345 V
14. EFFICIENCY AT 100% RATED LOAD	82 %
15. POWER FACTOR AT 100% RATED LOAD	71.5 %s
16. STARTING TORQUE	39.72 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E F C
19. TYPE OF BEARING	PL : 6312zz OPL : 6311zz
20. MOUNTING	HORIZONTAL
21. MAXIMUM AMBIENT TEMPURE	40 °C
22. BEARING LUBRICATION	GREASE
23. STARTING METHOD	FULL VOLTAGE



사외대행이반


안전보건공단

KOREA OCCUPATIONAL SAFETY & HEALTH AGENCY

THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	HOISTING
2. MANUFACTURE	극동호이스트 (주)
3. FRAME NUMBER	200 L
4. RATED POWER	17 KW x 8 P
5. RATED VOLTAGE AND FREQUENCY	440 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	850 RPM
11. FULL LOAD CURRENT	38.3 A
12. STARTING CURRENT AT RATED VOLTAGE	227.9 A
13. MINIMUM STARTING VOLTAGE	400 V
14. EFFICIENCY AT 100% RATED LOAD	82 %
15. POWER FACTOR AT 100% RATED LOAD	71.5 %
16. STARTING TORQUE	39.72 KG.M
17. SITE ALTTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E F C
19. TYPE OF BEARING	PL : 6312zz OPL : 6311zz
20. MOUNTING	HORIZONTAL
21. MAXIMUM AMBIENT TEMPURE	40 °C
22. BEARING LUBRICATION	GREASE
23. STARTING METHOD	FULL VOLTAGE



사어제해예방



안전보건공단

KOREA OCCUPATIONAL SAFETY & HEALTH AGENCY

THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA


1. SERVICE	HOISTING
2. MANUFACTURE	극동호이스트 (주)
3. FRAME NUMBER	200 L
4. RATED POWER	17 KW x 8 P
5. RATED VOLTAGE AND FREQUENCY	460 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	850 RPM
11. FULL LOAD CURRENT	36.7 A
12. STARTING CURRENT AT RATED VOLTAGE	218.4 A
13. MINIMUM STARTING VOLTAGE	418 V
14. EFFICIENCY AT 100% RATED LOAD	82 %
15. POWER FACTOR AT 100% RATED LOAD	71.5 %
16. STARTING TORQUE	39.72 KG.M
17. SITE ALTTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E F C
19. TYPE OF BEARING	PL : 6312zz OPL : 6311zz
20. MOUNTING	HORIZONTAL
21. MAXIMUM AMBIENT TEMPURE	40 °C
22. BEARING LUBRICATION	GREASE
23. STARTING METHOD	FULL VOLTAGE



THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	HOISTING
2. MANUFACTURE	극동호이스트 (주)
3. FRAME NUMBER	200 L
4. RATED POWER	17 KW x 8 P
5. RATED VOLTAGE AND FREQUENCY	480 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATING	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TEMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	850 RPM
11. FULL LOAD CURRENT	35.2 A
12. STARTING CURRENT AT RATED VOLTAGE	209.3 A
13. MINIMUM STARTING VOLTAGE	436 V
14. EFFICIENCY AT 100% RATED LOAD	82 %
15. POWER FACTOR AT 100% RATED LOAD	71.5 %
16. STARTING TORQUE	39.72 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	TEFC
19. TYPE OF BEARING	PL : 6312zz OPL : 6311zz
20. MOUNTING	HORIZONTAL
21. MAXIMUM AMBIENT TEMPERATURE	40 °C
22. BEARING LUBRICATION	GREASE
23. STARTING METHOD	FULL VOLTAGE



사어재해예방


안전보건공단

KOREA OCCUPATIONAL SAFETY & HEALTH AGENCY

THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA


1. SERVICE	CREEP HOIST
2. MANUFACTURE	극동호이스트 (주)
3. FRAME NUMBER	112 M
4. RATED POWER	1.8 KW x 8 P
5. RATED VOLTAGE AND FREQUENCY	220 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 ℃
10. FULL LOAD SPEED	850 RPM
11. FULL LOAD CURRENT	11 A
12. STARTING CURRENT AT RATED VOLTAGE	55 A
13. MINIMUM STARTING VOLTAGE	200 V
14. EFFICIENCY AT 100% RATED LOAD	71.5 %
15. POWER FACTOR AT 100% RATED LOAD	60 %
16. STARTING TORQUE	6.93 KGM
17. SITE ALTTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	TENV
19. TYPE OF BEARING	PL : 6209zz OPL : 6206zz
20. MOUNTING	HORIZONTAL
21. MAXIMUM AMBIENT TEMPURE	40 ℃
22. BEARING LUBRICATION	GREASE
23. STARTING METHIOD	FULL VOLTAGE



THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	CREEP HOIST
2. MANUFACTURE	극동호이스트 (주)
3. FRAME NUMBER	112 M
4. RATED POWER	1.8 KW x 8 P
5. RATED VOLTAGE AND FREQUENCY	380 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATTING	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 ℃
10. FULL LOAD SPEED	850 RPM
11. FULL LOAD CURRENT	6.4 A
12. STARTING CURRENT AT RATED VOLTAGE	31.9 A
13. MINIMUM STARTING VOLTAGE	345 V
14. EFFICIENCY AT 100% RATED LOAD	71.5 %
15. POWER FACTOR AT 100% RATED LOAD	60 %
16. STARTING TORQUE	6.93 K.G.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	TENV
19. TYPE OF BEARING	PL : 6209zz OPL : 6206zz
20. MOUNTING	HORIZONTAL
21. MAXIMUM AMBIENT TEMPURE	40 ℃
22. BEARING LUBRICATION	GREASE
23. STARTING METHOD	FULL VOLTAGE




산업재해예방
안전보건공단

THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	CREEP HOIST
2. MANUFACTURE	극동호이스트 (주)
3. FRAME NUMBER	112 M
4. RATED POWER	1.8 KW x 8 P
5. RATED VOLTAGE AND FREQUENCY	440 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATTING	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	850 RPM
11. FULL LOAD CURRENT	5.5 A
12. STARTING CURRENT AT RATED VOLTAGE	27.5 A
13. MINIMUM STARTING VOLTAGE	400 V
14. EFFICIENCY AT 100% RATED LOAD	71.5 %
15. POWER FACTOR AT 100% RATED LOAD	60 %
16. STARTING TORQUE	6.93 KGM
17. SITE ALTTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	TENV
19. TYPE OF BEARING	PL : 6209zz OPL : 6206zz
20. MOUNTING	HORIZONTAL
21. MAXIMUM AMBIENT TEMPURE	40 °C
22. BEARING LUBRICATION	GREASE
23. STARTING METHOD	FULL VOLTAGE



산업안전보건공단


안전보건공단

KOREA OCCUPATIONAL SAFETY & HEALTH AGENCY

THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA


1. SERVICE	CREEP HOIST
2. MANUFACTURE	극동호이스트 (주)
3. FRAME NUMBER	112 M
4. RATED POWER	1.8 KW x 8 P
5. RATED VOLTAGE AND FREQUENCY	460 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	850 RPM
11. FULL LOAD CURRENT	5.3 A
12. STARTING CURRENT AT RATED VOLTAGE	26.4 A
13. MINIMUM STARTING VOLTAGE	418 V
14. EFFICIENCY AT 100% RATED LOAD	71.5 %
15. POWER FACTOR AT 100% RATED LOAD	60 %
16. STARTING TORQUE	6.93 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	TENV
19. TYPE OF BEARING	PL : 6209zz OPL : 6206zz
20. MOUNTING	HORIZONTAL
21. MAXIMUM AMBIENT TEMPURE	40 °C
22. BEARING LUBRICATION	GREASE
23. STARTING METHOD	FULL VOLTAGE



THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA


1. SERVICE	CREEP HOIST
2. MANUFACTURE	극동호이스트 (주)
3. FRAME NUMBER	112 M
4. RATED POWER	1.8 KW x 8 P
5. RATED VOLTAGE AND FREQUENCY	480 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 ℃
10. FULL LOAD SPEED	850 RPM
11. FULL LOAD CURRENT	5.1 A
12. STARTING CURRENT AT RATED VOLTAGE	25.3 A
13. MINIMUM STARTING VOLTAGE	436 V
14. EFFICIENCY AT 100% RATED LOAD	71.5 %
15. POWER FACTOR AT 100% RATED LOAD	60 %
16. STARTING TORQUE	6.93 KGM
17. SITE ALTTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	TENV
19. TYPE OF BEARING	PL : 6209zz OPL : 6206zz
20. MOUNTING	HORIZONTAL
21. MAXIMUM AMBIENT TEMPURE	40 ℃
22. BEARING LUBRICATION	GREASE
23. STARTING METHOD	FULL VOLTAGE



THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	TRAVERSING
2. MANUFACTURE	극동호이스트 (주)
3. FRAME NUMBER	90 L
4. RATED POWER	1.5 KW x 4 P
5. RATED VOLTAGE AND FREQUENCY	220 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 ℃
10. FULL LOAD SPEED	1760 RPM
11. FULL LOAD CURRENT	7.3 A
12. STARTING CURRENT AT RATED VOLTAGE	41.8 A
13. MINIMUM STARTING VOLTAGE	200 V
14. EFFICIENCY AT 100% RATED LOAD	73 %
15. POWER FACTOR AT 100% RATED LOAD	75 %
16. STARTING TORQUE	1.95 KGM
17. SITE ALTTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHIOD	TENV
19. TYPE OF BEARING	PL : 6206zz OPL : 6204zz
20. MOUNTING	HORIZONTAL
21. MAXIMUM AMBIENT TEMPURE	40 ℃
22. BEARING LUBRICATION	GREASE
23. STARTING METHOD	FULL VOLTAGE




안전보건공단

THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA


1. SERVICE	TRAVERSING
2. MANUFACTURE	극동호이스트 (주)
3. FRAME NUMBER	90 L
4. RATED POWER	1.5 KW x 4 P
5. RATED VOLTAGE AND FREQUENCY	380 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 ℃
10. FULL LOAD SPEED	1760 RPM
11. FULL LOAD CURRENT	4.2 A
12. STARTING CURRENT AT RATED VOLTAGE	24.2 A
13. MINIMUM STARTING VOLTAGE	343 V
14. EFFICIENCY AT 100% RATED LOAD	73 %
15. POWER FACTOR AT 100% RATED LOAD	75 %
16. STARTING TORQUE	1.93 KGM
17. SITE ALTTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	TENV
19. TYPE OF BEARING	PL : 6206zz OPL : 6204zz
20. MOUNTING	HORIZONTAL
21. MAXIMUM AMBIENT TEMPURE	40 ℃
22. BEARING LUBRICATION	GREASE
23. STARTING METHIOD	FULL VOLTAGE



THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHINICAL DATA


1. SERVICE	TRAVERSING
2. MANUFACTURE	극동호이스트 (주)
3. FRAME NUMBER	90 L
4. RATED POWER	1.5 KW x 4 P
5. RATED VOLTAGE AND FREQUENCY	440 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 ℃
10. FULL LOAD SPEED	1760 RPM
11. FULL LOAD CURRENT	3.7 A
12. STARTING CURRENT AT RATED VOLTAGE	20.9 A
13. MINIMUM STARTING VOLTAGE	400 V
14. EFFICIENCY AT 100% RATED LOAD	73 %
15. POWER FACTOR AT 100% RATED LOAD	75 %
16. STARTING TORQUE	1.95 KGM
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	TENV
19. TYPE OF BEARING	PL : 6206zz OPL : 6204zz
20. MOUNTING	HORIZONTAL
21. MAXIMUM AMBIENT TEMPURE	40 ℃
22. BEARING LUBRICATION	GREASE
23. STARTING METHOD	FULL VOLTAGE



THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA


1. SERVICE	TRAVERSING
2. MANUFACTURE	극동호이스트 (주)
3. FRAME NUMBER	90 L
4. RATED POWER	1.5 KW x 4 P
5. RATED VOLTAGE AND FREQUENCY	460 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATING	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	1760 RPM
11. FULL LOAD CURRENT	3.5 A
12. STARTING CURRENT AT RATED VOLTAGE	20 A
13. MINIMUM STARTING VOLTAGE	418 V
14. EFFICIENCY AT 100% RATED LOAD	73 %
15. POWER FACTOR AT 100% RATED LOAD	75 %
16. STARTING TORQUE	195 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	TENV
19. TYPE OF BEARING	PL : 6206zz OPL : 6204zz
20. MOUNTING	HORIZONTAL
21. MAXIMUM AMBIENT TEMPURE	40 °C
22. BEARING LUBRICATION	GREASE
23. STARTING METHOD	FULL VOLTAGE



THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA


1. SERVICE	TRAVERSING
2. MANUFACTURE	극동호이스트 (주)
3. FRAME NUMBER	90 L
4. RATED POWER	1.5 KW x 4 P
5. RATED VOLTAGE AND FREQUENCY	480 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 ℃
10. FULL LOAD SPEED	1760 RPM
11. FULL LOAD CURRENT	3.4 A
12. STARTING CURRENT AT RATED VOLTAGE	19.2 A
13. MINIMUM STARTING VOLTAGE	436 V
14. EFFICIENCY AT 100% RATED LOAD	73 %
15. POWER FACTOR AT 100% RATED LOAD	75 %
16. STARTING TORQUE	1.95 KGM
17. SITE ALTTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	TENV
19. TYPE OF BEARING	Pl. : 6206zz OPL : 6204zz
20. MOUNTING	HORIZONTAL
21. MAXIMUM AMBIENT TEMPURE	40 ℃
22. BEARING LUBRICATION	GREASE
23. STARTING METHOD	FULL VOLTAGE



THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA


1. SERVICE	TRAVERSING
2. MANUFACTURE	극동호이스트 (주)
3. FRAME NUMBER	90 L
4. RATED POWER	1.0 KW x 6 P
5. RATED VOLTAGE AND FREQUENCY	220 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 ℃
10. FULL LOAD SPEED	1160 RPM
11. FULL LOAD CURRENT	6.7 A
12. STARTING CURRENT AT RATED VOLTAGE	23.8 A
13. MINIMUM STARTING VOLTAGE	200 V
14. EFFICIENCY AT 100% RATED LOAD	63.5 %
15. POWER FACTOR AT 100% RATED LOAD	62 %
16. STARTING TORQUE	1.6 KG.M
17. SITE ALTTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	TENV
19. TYPE OF BEARING	PL : 6206zz OPL : 6204zz
20. MOUNTING	HORIZONTAL
21. MAXIMUM AMBIENT TEMPURE	40 ℃
22. BEARING LUBRICATION	GREASE
23. STARTING METHOD	FULL VOLTAGE



THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA


1. SERVICE	TRAVERSING
2. MANUFACTURE	극동호이스트 (주)
3. FRAME NUMBER	90 L
4. RATED POWER	1.0 KW x 6 P
5. RATED VOLTAGE AND FREQUENCY	380 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 ℃
10. FULL LOAD SPEED	1160 RPM
11. FULL LOAD CURRENT	3.9 A
12. STARTING CURRENT AT RATED VOLTAGE	13.8 A
13. MINIMUM STARTING VOLTAGE	345 V
14. EFFICIENCY AT 100% RATED LOAD	63.5 %
15. POWER FACTOR AT 100% RATED LOAD	62 %
16. STARTING TORQUE	1.6 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	TENV
19. TYPE OF BEARING	PL : 6206zz OPL : 6204zz
20. MOUNTING	HORIZONTAL
21. MAXIMUM AMBIENT TEMPURE	40 ℃
22. BEARING LUBRICATION	GREASE
23. STARTING METHOD	FULL VOLTAGE



THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHINICAL DATA


1. SERVICE	TRAVERSING
2. MANUFACTURE	극동호이스트 (주)
3. FRAME NUMBER	90 L
4. RATED POWER	1.0 KW x 6 P
5. RATED VOLTAGE AND FREQUENCY	440 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATTING	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 ℃
10. FULL LOAD SPEED	1160 RPM
11. FULL LOAD CURRENT	3.3 A
12. STARTING CURRENT AT RATED VOLTAGE	11.9 A
13. MINIMUM STARTING VOLTAGE	400 V
14. EFFICIENCY AT 100% RATED LOAD	63.5 %
15. POWER FACTOR AT 100% RATED LOAD	62 %
16. STARTING TORQUE	1.6 KGM
17. SITE ALTTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	TENV
19. TYPE OF BEARING	PL : 6206zz OPL : 6204zz
20. MOUNTING	HORIZONTAL
21. MAXIMUM AMBIENT TEMPURE	40 ℃
22. BEARING LUBRICATION	GREASE
23. STARTING METHOD	FULL VOLTAGE



THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA


1. SERVICE	TRAVERSING
2. MANUFACTURE	극동호이스트 (주)
3. FRAME NUMBER	90 L
4. RATED POWER	1.0 KW x 6 P
5. RATED VOLTAGE AND FREQUENCY	460 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 ℃
10. FULL LOAD SPEED	1160 RPM
11. FULL LOAD CURRENT	3.2 A
12. STARTING CURRENT AT RATED VOLTAGE	11.9 A
13. MINIMUM STARTING VOLTAGE	418 V
14. EFFICIENCY AT 100% RATED LOAD	63.5 %
15. POWER FACTOR AT 100% RATED LOAD	62 %
16. STARTING TORQUE	1.6 KGM
17. SITE ALTTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	TENV
19. TYPE OF BEARING	PL : 6206zz OPL : 6204zz
20. MOUNTING	HORIZONTAL
21. MAXIMUM AMBIENT TEMPURE	40 ℃
22. BEARING LUBRICATION	GREASE
23. STARTING METHOD	FULL VOLTAGE



THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA


1. SERVICE	TRAVERSING
2. MANUFACTURE	극동호이스트 (주)
3. FRAME NUMBER	90 L
4. RATED POWER	1.0 KW x 6 P
5. RATED VOLTAGE AND FREQUENCY	480 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 ℃
10. FULL LOAD SPEED	1160 RPM
11. FULL LOAD CURRENT	3.1 A
12. STARTING CURRENT AT RATED VOLTAGE	10.9 A
13. MINIMUM STARTING VOLTAGE	436 V
14. EFFICIENCY AT 100% RATED LOAD	63.5 %
15. POWER FACTOR AT 100% RATED LOAD	62 %
16. STARTING TORQUE	1.6 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	TENV
19. TYPE OF BEARING	PL : 6206zz OPL : 6204zz
20. MOUNTING	HORIZONTAL
21. MAXIMUM AMBIENT TEMPURE	40 ℃
22. BEARING LUBRICATION	GREASE
23. STARTING METHOD	FULL VOLTAGE



THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA


1. SERVICE	TRAVERSING
2. MANUFACTURE	국동호이스트(주)
3. FRAME NUMBER	90 L
4. RATED POWER	1.5/0.75 KW x 4/8 P
5. RATED VOLTAGE AND FREQUENCY	220 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	1700/815 RPM
11. FULL LOAD CURRENT	7.2/6.2 A
12. STARTING CURRENT AT RATED VOLTAGE	35.6/21.7 A
13. MINIMUM STARTING VOLTAGE	200 V
14. EFFICIENCY AT 100% RATED LOAD	69.5/63 %
15. POWER FACTOR AT 100% RATED LOAD	74/50 %
16. STARTING TORQUE	1.48/1.22 KG.M
17. SITE ALTTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	TENV
19. TYPE OF BEARING	PL : 6206zz OPL : 6206zz
20. MOUNTING	HORIZONTAL
21. MAXIMUM AMBIENT TEMPURE	40 °C
22. BEARING LUBRICATION	GREASE
23. STARTING METHOD	FULL VOLTAGE



THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA


1. SERVICE	TRAVERSING
2. MANUFACTURE	국동호이스트(주)
3. FRAME NUMBER	90 L
4. RATED POWER	1.5/0.75 KW x 4/8 P
5. RATED VOLTAGE AND FREQUENCY	380 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 ℃
10. FULL LOAD SPEED	1700/815 RPM
11. FULL LOAD CURRENT	4.17/3.59 A
12. STARTING CURRENT AT RATED VOLTAGE	20.6/12.56 A
13. MINIMUM STARTING VOLTAGE	345 V
14. EFFICIENCY AT 100% RATED LOAD	69.5/63 %
15. POWER FACTOR AT 100% RATED LOAD	74/50 %
16. STARTING TORQUE	1.48/1.22 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	TENV
19. TYPE OF BEARING	PL : 6206zz OPI : 6206zz
20. MOUNTING	HORIZONTAL
21. MAXIMUM AMBIENT TEMPURE	40 ℃
22. BEARING LUBRICATION	GREASE
23. STARTING METHOD	FULL VOLTAGE



THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA


1. SERVICE	TRAVERSING
2. MANUFACTURE	극동호이스트(주)
3. FRAME NUMBER	90 L
4. RATED POWER	1.5/0.75 KW x 4/8 P
5. RATED VOLTAGE AND FREQUENCY	440 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	1700/815 RPM
11. FULL LOAD CURRENT	3.6/3.1 A
12. STARTING CURRENT AT RATED VOLTAGE	17.8/10.85 A
13. MINIMUM STARTING VOLTAGE	400 V
14. EFFICIENCY AT 100% RATED LOAD	69.5/63 %
15. POWER FACTOR AT 100% RATED LOAD	74/50 %
16. STARTING TORQUE	1.48/1.22 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	TENV
19. TYPE OF BEARING	PL : 6206zz OPL : 6206zz
20. MOUNTING	HORIZONTAL
21. MAXIMUM AMBIENT TEMPURE	40 °C
22. BEARING LUBRICATION	GREASE
23. STARTING METHOD	FULL VOLTAGE



THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	TRAVERSING
2. MANUFACTURE	극동호이스트(주)
3. FRAME NUMBER	90 L
4. RATED POWER	1.5/0.75 KW x 4/8 P
5. RATED VOLTAGE AND FREQUENCY	460 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 ℃
10. FULL LOAD SPEED	1700/815 RPM
11. FULL LOAD CURRENT	3.44/2.96 A
12. STARTING CURRENT AT RATED VOLTAGE	16.99/10.36 A
13. MINIMUM STARTING VOLTAGE	418 V
14. EFFICIENCY AT 100% RATED LOAD	69.5/63 %
15. POWER FACTOR AT 100% RATED LOAD	74/50 %
16. STARTING TORQUE	1.48/1.22 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	TENV
19. TYPE OF BEARING	PL : 6206zz OPL : 6206zz
20. MOUNTING	HORIZONTAL
21. MAXIMUM AMBIENT TEMPURE	40 ℃
22. BEARING LUBRICATION	GREASE
23. STARTING METHOD	FULL VOLTAGE



산업재해예방


안전보건공단

KOREA OCCUPATIONAL SAFETY & HEALTH AGENCY

THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	TRAVERSING
2. MANUFACTURE	극동호이스트(주)
3. FRAME NUMBER	90 L
4. RATED POWER	15/0.75 KW x 4/8 P
5. RATED VOLTAGE AND FREQUENCY	480 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATTING	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 ℃
10. FULL LOAD SPEED	1700/815 RPM
11. FULL LOAD CURRENT	3.0/2.96 A
12. STARTING CURRENT AT RATED VOLTAGE	14.82/10.36 A
13. MINIMUM STARTING VOLTAGE	436 V
14. EFFICIENCY AT 100% RATED LOAD	69.5/63 %
15. POWER FACTOR AT 100% RATED LOAD	74/50 %
16. STARTING TORQUE	1.48/1.22 KG.M
17. SITE ALTTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	TENV
19. TYPE OF BEARING	PL : 6206zz OPL : 6206zz
20. MOUNTING	HORIZONTAL
21. MAXIMUM AMBIENT TEMPURE	40 ℃
22. BEARING LUBRICATION	GREASE
23. STARTING METHOD	FULL VOLTAGE



THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	TRAVERSING
2. MANUFACTURE	국동호이스트(주)
3. FRAME NUMBER	90 L
4. RATED POWER	1.0/0.5 KW x 6/12 P
5. RATED VOLTAGE AND FREQUENCY	220 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATTING	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	1050/460 RPM
11. FULL LOAD CURRENT	7.1/7.5 A
12. STARTING CURRENT AT RATED VOLTAGE	28.3/22.5 A
13. MINIMUM STARTING VOLTAGE	200 V
14. EFFICIENCY AT 100% RATED LOAD	59.5/35.0 %
15. POWER FACTOR AT 100% RATED LOAD	64.5/54.0 %
16. STARTING TORQUE	1.67/1.48 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	TENV
19. TYPE OF BEARING	PL : 6206zz OPL : 6206zz
20. MOUNTING	HORIZONTAL
21. MAXIMUM AMBIENT TEMPURE	40 °C
22. BEARING LUBRICATION	GREASE
23. STARTING METHIOD	FULL VOLTAGE

THREE PHASE INDUCTION MOTOR DATE SHEET


SCHEDULE OF TECHNICAL DATA

1. SERVICE	TRAVERSING
2. MANUFACTURE	극동호이스트(주)
3. FRAME NUMBER	90 L
4. RATED POWER	1.0/0.5 KW x 6/12 P
5. RATED VOLTAGE AND FREQUENCY	380 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 ℃
10. FULL LOAD SPEED	1050/460 RPM
11. FULL LOAD CURRENT	4.1/4.3 A
12. STARTING CURRENT AT RATED VOLTAGE	16.4/13.0 A
13. MINIMUM STARTING VOLTAGE	345 V
14. EFFICIENCY AT 100% RATED LOAD	59.5/35.0 %
15. POWER FACTOR AT 100% RATED LOAD	64.5/54.0 %
16. STARTING TORQUE	1.67/1.48 K.G.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	TENV
19. TYPE OF BEARING	PL : 6206zz OPL : 6206zz
20. MOUNTING	HORIZONTAL
21. MAXIMUM AMBIENT TEMPURE	40 ℃
22. BEARING LUBRICATION	GREASE
23. STARTING METHOD	FULL VOLTAGE

THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	TRAVERSING
2. MANUFACTURE	극동호이스트(주)
3. FRAME NUMBER	90 L
4. RATED POWER	1.0/0.5 KW x 6/12 P
5. RATED VOLTAGE AND FREQUENCY	440 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 ℃
10. FULL LOAD SPEED	1050/460 RPM
11. FULL LOAD CURRENT	3.5/3.7 A
12. STARTING CURRENT AT RATED VOLTAGE	14.2/12.3 A
13. MINIMUM STARTING VOLTAGE	400 V
14. EFFICIENCY AT 100% RATED LOAD	59.5/35.0 %
15. POWER FACTOR AT 100% RATED LOAD	64.5/54.0 %
16. STARTING TORQUE	1.67/1.48 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	TENV
19. TYPE OF BEARING	PL : 6206zz OPL : 6206zz
20. MOUNTING	HORIZONTAL
21. MAXIMUM AMBIENT TEMPURE	40 ℃
22. BEARING LUBRICATION	GREASE
23. STARTING METHOD	FULL VOLTAGE



THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	TRAVERSING
2. MANUFACTURE	국동호이스트(주)
3. FRAME NUMBER	90 L
4. RATED POWER	1.0/0.5 KW x 6/12 P
5. RATED VOLTAGE AND FREQUENCY	460 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATTING	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 ℃
10. FULL LOAD SPEED	1050/460 RPM
11. FULL LOAD CURRENT	3.4/3.6 A
12. STARTING CURRENT AT RATED VOLTAGE	13.5/10.8 A
13. MINIMUM STARTING VOLTAGE	418 V
14. EFFICIENCY AT 100% RATED LOAD	59.5/35.0 %
15. POWER FACTOR AT 100% RATED LOAD	64.5/51.0 %
16. STARTING TORQUE	1.67/1.48 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	TENV
19. TYPE OF BEARING	PL : 6206zz OPL : 6206zz
20. MOUNTING	HORIZONTAL
21. MAXIMUM AMBIENT TEMPURE	40 ℃
22. BEARING LUBRICATION	GREASE
23. STARTING METHOD	FULL VOLTAGE

THREE PHASE INDUCTION MOTOR DATE SHEET


SCHEDULE OF TECHNICAL DATA

1. SERVICE	TRAVERSING
2. MANUFACTURE	극동호이스트(주)
3. FRAME NUMBER	90 L
4. RATED POWER	1.0/0.5 KW x 6/12 P
5. RATED VOLTAGE AND FREQUENCY	480 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 ℃
10. FULL LOAD SPEED	1050/460 RPM
11. FULL LOAD CURRENT	3.2/3.4 A
12. STARTING CURRENT AT RATED VOLTAGE	13.0/10.3 A
13. MINIMUM STARTING VOLTAGE	436 V
14. EFFICIENCY AT 100% RATED LOAD	59.5/35.0 %
15. POWER FACTOR AT 100% RATED LOAD	64.5/54.0 %
16. STARTING TORQUE	1.67/1.48 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	TENV
19. TYPE OF BEARING	PL : 6206zz OPL : 6206zz
20. MOUNTING	HORIZONTAL
21. MAXIMUM AMBIENT TEMPURE	40 ℃
22. BEARING LUBRICATION	GREASE
23. STARTING METHOD	FULL VOLTAGE

THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	HOISTING
2. MANUFACTURE	극동호이스트 (주)
3. FRAME NUMBER	132 M
4. RATED POWER	5.5 KW x 6 P
5. RATED VOLTAGE AND FREQUENCY	220 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 ℃
10. FULL LOAD SPEED	1164 RPM
11. FULL LOAD CURRENT	28.2 A
12. LOCKED ROTOR CURRENT	155.1 A
13. MINIMUM STARTING VOLTAGE	200 V
14. EFFICIENCY AT 100% RATED LOAD	77 %
15. POWER FACTOR AT 100% RATED LOAD	66.4 %
16. FULL LOAD TORQUE	11.59 KG.M
17. SITE ALTTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	TENV
19. TYPE OF BEARING	PL : 6307zz OPL : 6207zz
20. MOUNTING	HORIZONTAL
21. MAXIMUM AMBIENT TEMPURE	40 ℃
22. BEARING LUBRICATION	GREASE
23. STARTING METHOD	FULL VOLTAGE



사어재해예방


안전보건공단

KOREA OCCUPATIONAL SAFETY & HEALTH AGENCY

THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	HOISTING
2. MANUFACTURE	극동호이스트 (주)
3. FRAME NUMBER	132 M
4. RATED POWER	5.5 KW x 6 P
5. RATED VOLTAGE AND FREQUENCY	380 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 ℃
10. FULL LOAD SPEED	1164 RPM
11. FULL LOAD CURRENT	16.3 A
12. LOCKED ROTOR CURRENT	89.8 A
13. MINIMUM STARTING VOLTAGE	345 V
14. EFFICIENCY AT 100% RATED LOAD	77 %
15. POWER FACTOR AT 100% RATED LOAD	66.4 %
16. FULL LOAD TORQUE	11.59 KG.M
17. SITE ALTTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6307zz OPL : 6207zz
20. MOUNTING	HORIZONTAL
21. MAXIMUM AMBIENT TEMPURE	40 ℃
22. BEARING LUBRICATION	GREASE
23. STARTING METHOD	FULL VOLTAGE



산업재해예방


안전보건공단

KOREA OCCUPATIONAL SAFETY & HEALTH AGENCY

THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	HOISTING
2. MANUFACTURE	극동호이스트 (주)
3. FRAME NUMBER	132 M
4. RATED POWER	5.5 KW x 6 P
5. RATED VOLTAGE AND FREQUENCY	440 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 ℃
10. FULL LOAD SPEED	1164 RPM
11. FULL LOAD CURRENT	14.1 A
12. LOCKED ROTOR CURRENT	77.6 A
13. MINIMUM STARTING VOLTAGE	400 V
14. EFFICIENCY AT 100% RATED LOAD	77 %
15. POWER FACTOR AT 100% RATED LOAD	66.4 %
16. FULL LOAD TORQUE	11.59 KG.M
17. SITE ALTTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6307zz OPL : 6207zz
20. MOUNTING	HORIZONTAL
21. MAXIMUM AMBIENT TEMPURE	40 ℃
22. BEARING LUBRICATION	GREASE
23. STARTING METHOD	FULL VOLTAGE




산업재해예방
안전보건공단
KOSHA

THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	HOISTING
2. MANUFACTURE	극동호이스트 (주)
3. FRAME NUMBER	132 M
4. RATED POWER	5.5 KW x 6 P
5. RATED VOLTAGE AND FREQUENCY	460 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	1164 RPM
11. FULL LOAD CURRENT	13.5 A
12. LOCKED ROTOR CURRENT	74.8 A
13. MINIMUM STARTING VOLTAGE	418 V
14. EFFICIENCY AT 100% RATED LOAD	77 %
15. POWER FACTOR AT 100% RATED LOAD	66.4 %
16. FULL LOAD TORQUE	11.59 KG.M
17. SITE ALTTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	TENV
19. TYPE OF BEARING	PL : 6307zz OPL : 6207zz
20. MOUNTING	HORIZONTAL
21. MAXIMUM AMBIENT TEMPURE	40 °C
22. BEARING LUBRICATION	GREASE
23. STARTING METHOD	FULL VOLTAGE




안전보건공단
KOSHA

THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	HOISTING
2. MANUFACTURE	극동호이스트 (주)
3. FRAME NUMBER	132 M
4. RATED POWER	5.5 KW x 6 P
5. RATED VOLTAGE AND FREQUENCY	480 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATTING	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 ℃
10. FULL LOAD SPEED	1164 RPM
11. FULL LOAD CURRENT	12.9 A
12. LOCKED ROTOR CURRENT	71.2 A
13. MINIMUM STARTING VOLTAGE	436 V
14. EFFICIENCY AT 100% RATED LOAD	77 %
15. POWER FACTOR AT 100% RATED LOAD	66.4 %
16. FULL LOAD TORQUE	11.59 KGM
17. SITE ALTTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	TENV
19. TYPE OF BEARING	PL : 6307zz OPL : 6207zz
20. MOUNTING	HORIZONTAL
21. MAXIMUM AMBIENT TEMPURE	40 ℃
22. BEARING LUBRICATION	GREASE
23. STARTING METHOD	FULL VOLTAGE




안전보건공단
KOSHA

THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	CREEP HOISTING
2. MANUFACTURE	극동호이스트 (주)
3. FRAME NUMBER	90 L
4. RATED POWER	1.0 KW x 6 P
5. RATED VOLTAGE AND FREQUENCY	220 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATTING	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 ℃
10. FULL LOAD SPEED	1164 RPM
11. FULL LOAD CURRENT	6.7 A
12. LOCKED ROTOR CURRENT	23.8 A
13. MINIMUM STARTING VOLTAGE	200 V
14. EFFICIENCY AT 100% RATED LOAD	63.5 %
15. POWER FACTOR AT 100% RATED LOAD	62 %S
16. FULL LOAD TORQUE	1.6 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	TENV
19. TYPE OF BEARING	PL : 6205zz OPL : 6204zz
20. MOUNTING	HORIZONTAL
21. MAXIMUM AMBIENT TEMPURE	40 ℃
22. BEARING LUBRICATION	GREASE
23. STARTING METHOD	FULL VOLTAGE




산업재해예방
안전보건공단

KOREA OCCUPATIONAL SAFETY & HEALTH AGENCY

THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	CREEP HOISTING
2. MANUFACTURE	극동호이스트 (주)
3. FRAME NUMBER	90 L
4. RATED POWER	1.0 KW x 6 P
5. RATED VOLTAGE AND FREQUENCY	380 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATTING	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 ℃
10. FULL LOAD SPEED	1164 RPM
11. FULL LOAD CURRENT	3.9 A
12. LOCKED ROTOR CURRENT	13.8 A
13. MINIMUM STARTING VOLTAGE	345 V
14. EFFICIENCY AT 100% RATED LOAD	63.5 %
15. POWER FACTOR AT 100% RATED LOAD	62 %
16. FULL LOAD TORQUE	1.6 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	TENV
19. TYPE OF BEARING	PL : 6205zz OPL : 6204zz
20. MOUNTING	HORIZONTAL
21. MAXIMUM AMBIENT TEMPURE	40 ℃
22. BEARING LUBRICATION	GREASE
23. STARTING METHOD	FULL VOLTAGE




산업재해예방
안전보건공단

THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	CREEP HOISTING
2. MANUFACTURE	극동호이스트 (주)
3. FRAME NUMBER	90 L
4. RATED POWER	1.0 KW x 6 P
5. RATED VOLTAGE AND FREQUENCY	440 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATTING	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	1164 RPM
11. FULL LOAD CURRENT	3.3 A
12. LOCKED ROTOR CURRENT	11.9 A
13. MINIMUM STARTING VOLTAGE	400 V
14. EFFICIENCY AT 100% RATED LOAD	63.5 %
15. POWER FACTOR AT 100% RATED LOAD	62 %
16. FULL LOAD TORQUE	1.6 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E F C
19. TYPE OF BEARING	PL : 6205zz OPL : 6204zz
20. MOUNTING	HORIZONTAL
21. MAXIMUM AMBIENT TEMPURE	40 °C
22. BEARING LUBRICATION	GREASE
23. STARTING METHOD	FULL VOLTAGE




안전보건공단
KOSHA

THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	CREEP HOISTING
2. MANUFACTURE	극동호이스트 (주)
3. FRAME NUMBER	90 L
4. RATED POWER	1.0 KW x 6 P
5. RATED VOLTAGE AND FREQUENCY	460 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATTING	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 ℃
10. FULL LOAD SPEED	1164 RPM
11. FULL LOAD CURRENT	3.2 A
12. LOCKED ROTOR CURRENT	11.4 A
13. MINIMUM STARTING VOLTAGE	418 V
14. EFFICIENCY AT 100% RATED LOAD	63.5 %
15. POWER FACTOR AT 100% RATED LOAD	62 %S
16. FULL LOAD TORQUE	1.6 KGM
17. SITE ALTTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	TEFC
19. TYPE OF BEARING	PL : 6205zz OPL : 6204zz
20. MOUNTING	HORIZONTAL
21. MAXIMUM AMBIENT TEMPURE	40 ℃
22. BEARING LUBRICATION	GREASE
23. STARTING METHOD	FULL VOLTAGE




안전보건공단
KOSHA

THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	CREEP HOISTING
2. MANUFACTURE	극동호이스트 (주)
3. FRAME NUMBER	90 L
4. RATED POWER	1.0 KW x 6 P
5. RATED VOLTAGE AND FREQUENCY	480 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 ℃
10. FULL LOAD SPEED	1164 RPM
11. FULL LOAD CURRENT	3.1 A
12. LOCKED ROTOR CURRENT	10.9 A
13. MINIMUM STARTING VOLTAGE	436 V
14. EFFICIENCY AT 100% RATED LOAD	63.5 %
15. POWER FACTOR AT 100% RATED LOAD	62 %
16. FULL LOAD TORQUE	1.6 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	TENV
19. TYPE OF BEARING	PL : 6205zz OPL : 6204zz
20. MOUNTING	HORIZONTAL
21. MAXIMUM AMBIENT TEMPURE	40 ℃
22. BEARING LUBRICATION	GREASE
23. STARTING METHOD	FULL VOLTAGE



사업재해예방
안전보건공단
KOSHA

SUB VENDOR LIST

구분	NO	DESCRIPTION	SUB VENDOR	TEL NO.	REMARK
기 계	1	WIRE ROPE	만호 로우프(주)	051-332-3131	
			고려제강 (주)	02-776-4131	
	2	MAGNET CORE	극동호이스트(주)	031-491-5311	
	3	DRUM	극동호이스트(주)	031-491-5311	
	4	GEAR	극동호이스트(주)	031-491-5311	
	5	HOOK ASS'Y	세 일 단 철	032-527-2817	
			대 흥 단 조	032-561-0541	
전 기	6	MIDDLE SHAFT	극동호이스트(주)	031-491-5311	
	7	RAIL CHANNEL ANGLE	인천제철(주)	032-763-5000	
			강원산업(주)	032-756-8881	
	8	MAG CONTACTOR	L.G 전선 (주)	02-273-4140	전 품
			(주) 대 룡	02-242-4141	한국공업협회
			(주) 대성디에스	055-338-3125	
	9	E.O.C.R	삼화기연 (주)	032-62-1331	K.S
			아산 전기	02-2636-8035	
	10	PUSH BUTTON	한영전기 (주)	02-742-0430	전 품
			(주)케이치오토	02-247-8131	전 품
			반도기계 (주)	031-495-8353-4	전 품
	11	LOAD LIMITER	보 창 기 전	032-431-0150	산 안 검
			반도기계 (주)	031-495-8353-4	산 안 검
			정호 엔지니어링	02-681-0553	산 안 검
	12	SILICON	반도기계 (주)	031-495-8353-4	
			아산 전기	02-2636-8035	
			보 창 기 전	032-431-0150	



ORIGINAL

CERT NO. 200704WRS59100

DATE Jun. 08, 2009

MILL TEST CERTIFICATE

THIS IS TO CERTIFY THAT THE MATERIAL DESCRIBED BELOW WAS MANUFACTURED
IN ACCORDANCE WITH KISWIRE LTD SPECIFICATION AND APPLICABLE SECTIONS

OF KSD 3514 - 2002 (B Grade)

TO MESSRS 삼진로프

MATERIAL DESCRIPTION UNGALVANIZED STEEL WIRE ROPE

06 X 37 + FC 1000 M X 5 REEL

EX NO.

ORDER NO. REEL NO. 1 ~ 5 SAMPLING NO. 1

DIAMETER OF ROPE 22.400 mm TYPE OF CORE Fiber Core

SPECIFIED BREAKING LOAD 284.00 kN SAMPLE BROKE AT 294.20 kN

WT. OF ZINC COATING OF OUTER WIRE MIN. g/m'

ROPE LAY RHRL LAY LENGTH 144.1 mm

LUBRICATION A-2

CHEMICAL ANALYSIS OF WIRE ROD

CHARGE NO.	C X 100	Si X 100	Mn X 100	P X 1000	S X 1000
SA61155	71	21	69	11	4.25

DATE OF SAMPLE TEST May. 09, 2007

Approved by Q.C Manager K.H. Bae
KISWIRE LTD., KOREA



KS



JIS



API



ABS



KR




NK



G.Lloyd's



DNV



L.R



BV

KOREA OCCUPATIONAL SAFETY & HEALTH AGENCY

ORIGINAL



No.600 Chuangye Road, Qingdao Development Zone, Shangdong,P.R.China
Tel : 86-532-86821916, Fax :86-532-86821949 www.kiswire.com

ISSUE NO. PW9034

DATE Feb. 19, 2010

MILL TEST CERTIFICATE

THIS IS TO CERTIFY THAT THE MATERIAL DESCRIBED BELOW WAS MANUFACTURED
IN ACCORDANCE WITH KISWIRE LTD SPECIFICATION AND APPLICABLE SECTIONS

OF **KSD 3514** (B Grade)

TO MESSRS **KISWIRE LTD.**

MATERIAL DESCRIPTION **UNGALVANIZED STEEL WIRE ROPE**

06 X 37 + FC **1000M X 3 REEL**

EX NO. **PW9034**

T/T NO.

ORDER NO. REEL NO. **1~3** SAMPLING NO. **1**

DIAMETER OF ROPE **14.0** mm TYPE OF CORE **Fiber Core**

SPECIFIED BREAKING LOAD **111.0** kN SAMPLE BROKE AT **115.6** kN

WT. OF ZINC COATING OF OUTER WIRE MIN. g/m² MAX. g/m²

ROPE LAY **RHRL** LAY LENGTH **91.5** mm

LUBRICATION **A-2**

CHEMICAL ANALYSIS OF WIRE ROD

CHARGE NO.	C×100	Si×100	Mn×100	P×1000	S×1000
049844E	72	24	74	18	9

DATE OF SAMPLE TEST

Feb. 10, 2010

CHIEF INSPECTOR D.S.NA
KISWIRE QINGDAO LTD.

산업재해예방
안전보건공단

KOREA OCCUPATIONAL SAFETY & HEALTH AGENCY