



제2017 - 78663 호

안 전 인 증 서

(사업장명) 극동호이스트(주)

(소 재 지) (154-23)경기도 안산시 단원구 해봉로 119(성곡동)

위 사업장에서 제조하는 아래의 품목이 산업안전보건법 제34조 및 같은 법 시행규칙 제58조의4제4항에 따른 안전인증 심사 결과 안전·보건기준에 적합하므로 안전인증표시의 사용을 인증합니다.

품 목

호이스트

형식,모델(용량,등급)/인증번호

KDC40/5-MA (40/5Ton) / 17-AE2AC-13399

인 증 기 준

고용노동부 고시 제2016 - 29호 (위험기계·기구 안전인증 고시)


인 증 조 건

인증유효기간 : 해당없음

설치장소 : 옥외

2017년 07월 14일

한국산업안전보건공단이사장





심사결과 통지서

신청인	사업장명	극동호이스트(주)	사업장관리번호	134-81-013350
	사업자등록번호	134-81-01335	대표자 성명	최성찬
	소재지	(154 - 23) 경기도 안산시 단원구 해봉로 119(성곡동)		

안전인증대상 기계·기구명		호이스트	
형식(규격)	KDC40/5-MA	용량(등급)	40/5 Ton

산업안전보건법 제 34조 및 같은 법 시행규칙 제58조의4에 따라 실시한

☐ 예비심사

☒ 서면심사

☐ 기술능력 및 생산체계 심사

☐ 개별 제품심사

☐ 개별 제품심사(제작중)

☐ 형식별 제품심사

결과가 ☒ 적 합
☐ 부적합

함을 통지합니다.

2017년 06월 23일

인증심사원

김영태

김영태
(서명 또는 인)

한국산업안전보건공단 중부지역본부장



서 면 심 사 서 류

형식 번호 : KDC40/5 -MA
Double Rail Type Hoist

극 동 호 이 스트 (주)



工場 : 경기도 안산시 단원구 해봉로 119 (성곡동)

電話 : 031) 491 - 5311

FAS : 031) 494 - 5315

동 일 형 식 일 람 표

사업장명	극동호이스트(株)	개정일자 및 번호	인증번호	비 고
형식 및 모델		동일 형식 인정범위 및 내역		모터구동식
형식	모델	권상속도(m/min)	회행속도(m/min)	
KDC40/5-MA	KDC40/5-L12-MA	고속:3.2M/MIN	양정(m)	
	KDC40/5-L18-MA	CREEP:0.32M/MIN	12	
	KDC40/5-L24-MA	5T : SINGLE TYPE	18	
	KDC40/5C-L12-MA	고속:3.2M/MIN	24	
	KDC40/5C-L18-MA	CREEP:0.32M/MIN	12	
	KDC40/5C-L24-MA	5T : CREEP TYPE	18	
			24	

*AUX HOIST TABLE

HOISTING TYPE	*5톤 권상속도
SINGLE TYPE	고속:5.6M/MIN
	저속:4.2M/MIN
	고속:5.6M/MIN
CREEP TYPE	CREEP:0.56M/MIN

형식번호 :	KD5
인증번호 :	15-AQ2AC-00229
적용모델 :	KD5-L12-S, KD5-L18-S, KD5-L24-S
	KDC5-L12-S, KDC5-L18-S, KDC5-L24-S

방호장치의 성능검사 합격증 사본



제 2012-BJ-0009 호



안 전 인 증 서

정호엔지니어링

경기도 광명시 노동사동 440-5

위 사업장에서 제조하는 아래의 품목이 산업안전보건법 제34조 및 같은 법 시행규칙 제58조의4제4항에 따른 안전인증 심사 결과 안전·보건기준에 적합하므로 안전인증표시의 사용을 인증합니다.

품 목

양중기용 과부하방지장치

형식·모델/용량·등급/인증번호

형식·모델	용량·등급	인증번호
JDL-100	J-2	12-AV2BJ-0009

인 증 기 준

방호장치 의무안전인증 고시(고용노동부고시 제2010-36호)

인 증 조 건


아래 주소에서 생산되는 제품에 한함.

정호엔지니어링, 경기도 광명시 노동사동 440-5

2012년 06월 11일

한국산업안전보건공단 이사장





[NOTE]
() 안 치수는 T/S RAIL 73kg/m 용
* 주관, 보관 등시 사용 금지 *

SPECIFICATION					
HOIST		MAIN		AUX	
HOISTING LOAD		40000 KG		5000 KG	
TEST LOAD		50000 KG		6250 KG	
LIFT		12 M		12 M	
HOISTING	SPEED	3.2/0.32 M/MIN	HIGH	5.6 M/MIN	4.2 M/MIN
	MOTOR	33/3.7KW=6/4P		5.5 KW x 6P	4.2 KW x 6P
TRAVERSING	SPEED	15 M/MIN			
	MOTOR	2.2KW x 4P (2UNIT)			
WIRE ROPE	SPEED	10 M/MIN			
	MOTOR	1.5KW x 6P (2UNIT)			
POWER SOURCE	6 x F(2S) #28x6 FALLS (6 x 37) #16 x 2 FALLS				
TRAVERSING RAIL	AC43 220/380/440/480/480V 60Hz				
WEIGHT	30, 37, 50, 73 KG/M				
	8800 KG				


극동호이스트
정격하중
4000KG
VIEW A

극동호이스트
정격하중
500KG
VIEW B

REV	DATE	DESCRIPTION	DRAWN	CHECK	APPROVD
A	29 MAY 2017	FOR CONSTRUCTION	M.H.KIM		
PROJECT					
CLIENT					
MANUFACTURER					
KUKDONG HOIST CO., LTD.					
TITLE					
GENERAL ARRANGEMENT DRAWING					
WIREHOIST_KDC40/5-L12-MA					
SCALE	DWG. NO.	KDC40/5L12MA	SHT. NO.	REV.	A



불법복제 및 배포금지



[NOTE]
() 안 치수는 T/S RAIL 73kg/m 용
* 주관, 보관 등시 사용 금지 *

SPECIFICATION		MAIN	AUX
HOIST			
HOISTING LOAD		40000 KG	5000 KG
TEST LOAD		50000 KG	6250 KG
LIFT		18 M	18 M
HOISTING	SPEED	3.2/0.32 M/MIN	3.6 M/MIN
	MOTOR	33/3.7KW*8/4P	5.5 KW 1 8P
TRAVERSING	SPEED	15 M/MIN	15 M/MIN
	MOTOR	2.2KW x 4P (2UNIT)	10 M/MIN
WIRE ROPE	SPEED	1.5KW x 8P (2UNIT)	1.5KW x 8P (2UNIT)
	MOTOR	6 x F(25) 420d FALLS (8 x 37) #18 x 2 FALLS	ACB3 220/380/440/480/480V 60Hz
POWER SOURCE		30, 37, 50, 73 KG/M	10000 KG
TRAVERSING RAIL			
WEIGHT			


극동호이스트
정격하중
4000KG
VIEW A

극동호이스트
정격하중
5000KG
VIEW B



REVISION	DATE	DESCRIPTION	DRAWN	CHECK	APPROVED
1	29 MAY 2017	FOR CONSTRUCTION	M.H.KIM		
PROJECT					
CLIENT					
MANUFACTURER					
KUKDONG HOIST CO., LTD.					
TITLE					
GENERAL ARRANGEMENT DRAWING					
WIREHOIST_KDC40/5-L18-MA					
SCALE	DWG. NO.	KDC40/5L18MA	SHT. NO.	REV.	A

불법복제 및 배포금지



[NOTE]
() 인 치수는 T/S RAIL 73kg/m 용
* 주된, 보편 등시 사용 금지 *

SPECIFICATION		MAIN	AUX
HOIST			
HOISTING LOAD		40000 KG	5000 KG
TEST LOAD		50000 KG	6250 KG
LIFT		24 M	24 M
HOISTING			
		SPEED 3.2/0.32 M/MIN	HIGH 5.5 M/MIN LOW 4.3 M/MIN
		MOTOR 33/3.7KW/6/4P	5.5 KW x 6P 4.3 KW x 6P
		SPEED 15 M/MIN	
TRAVERSING			
HIGH		2.2KW x 4P (2UNIT)	
LOW		1.5KW x 6P (2UNIT)	
WIRE ROPE		6 x F(25) #28x4 FALLS (6 x 37) #16 x 2 FALLS	
POWER SOURCE		AC#3 220/380/440/480/480V 60Hz	
TRAVERSING RAIL		30, 37, 50, 73 KG/M	
WEIGHT		11600 KG	

극동호이스트
정격하중
4000KG
VIEW A


극동호이스트
정격하중
5000KG
VIEW B




CLIENT	
MANUFACTURER	KUKDONG HOIST CO., LTD.
TITLE	GENERAL ARRANGEMENT DRAWING
SCALE	DWG. NO. KDC40/5L24MA
SHT. NO.	REV. A

--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--

불법복제 및 배포금지





[NOTE]
() 안 치수는 T/S RAIL 73kg/m 용
* 자관, 보관 등시 사용 금지 *


SPECIFICATION		MAIN	AUX
HOIST			
HOISTING LOAD		40000 KG	5000 KG
TEST LOAD		50000 KG	6250 KG
LIFT		18 M	18 M
HOISTING			
MOTOR		3.2/0.32 M/MIN	5.6/0.56 M/MIN
SPEED		33/3.7KW/6/4P	5.5/1.0 KW x 6P
TRAVERSING			
HIGH			
LOW			
WIRE ROPE			
POWER SOURCE			
TRAVERSING RAIL			
WEIGHT			

극동호이스트
정격하중
4000KG
VIEW A

극동호이스트
정격하중
5000KG
VIEW B

REV	DATE	DESCRIPTION	DRAWN	CHECK	APPRVD
Δ	29 MAY 2017	FOR CONSTRUCTION	M.H.KIM		
PROJECT					
CLIENT					
MANUFACTURER					
TITLE					
SCALE					
SHT. NO.					
REV.					





1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
---	---	---	---	---	---	---	---	---	----	----	----	----	----	----	----	----	----	----	----

NO	DESCRIPTION	MT'L	REMARKS
1	PANEL CASE	SPC	1.6t
2	PANEL COVER	SPC	1.6t
3	HINGE	PUR'	
4	CLAMP	PUR'	
5	SPONGE	PUR'	

IN DOOR

OUT DOOR


NOTE

- PROTECTION DEGREE :
 - A. INDOOR TYPE : DUST PROOF
 - B. OUT DOOR TYPE : SPLASH PROOF
- FINAL PAINTING COLOR (MUNSELL NO.)
 - A. IN SIDE : 10B 3/5
 - B. OUT SIDE : 10B 3/5
- PAINTING THICKNESS : ABOVE 40 μ m
- APPLICATION VOLTAGE : AC3 ϕ 220V(380V, 440V, 460V, 480V)
- OPERATION VOLTAGE : AC1 ϕ 110, 120V
- 제어용전선 : 2.5sq KIV, HIV
- 외함 개방 구조는 다음과 같다.
 - 1) 외함 개방시 충전부분이 차단되도록 한다.
 - 2) 외함 개방 후 충전되어있는 부분은 IP2X 이상의 직접 접촉 방호가 되어있을것.

SELECTION	HOIST CAPACITY	DESCRIPTION	IN DOOR			OUT DOOR			REMARK
			A	B	L	A	B	L	
	40 TON	NORMAL	680	220	940	690	220	950	
		CREEP	680	220	940	690	220	950	

CUSTOMER		TITLE	
극동호이스트 주식회사 KUKDONG HOIST CO., LTD.		HOISTING BOX	
		KDC40/5-MA	
05-AUG-2016 REV DATE	REDRAWING K.H.Ian DRAWN	CHECK APPROVD	DESIGN SCALE SHT. NO.
		DWG. NO. KDC40-EC001	
		ORDER NO.	

1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20																																
OUTSIDE										INSIDE										ADR'S NO.																															
355 260 1 2 3 4										M301 M302 EOCR300 RF300 TB																																									
1.6t 1.6t PUR' PUR' 140										<table><thead><tr><th>NO</th><th>SYMBOL</th><th>DESCRIPTION</th><th>SPECIFICATION</th><th>Q'TY</th><th>REMARK</th></tr></thead><tbody><tr><td>1</td><td>M101,102</td><td>MAGNET CONTACT</td><td>DMC40b</td><td>2</td><td>TRAVERSING</td></tr><tr><td>2</td><td>EOCR100</td><td>E.O.C.R</td><td>SS-30</td><td>1</td><td>TRAVERSING</td></tr><tr><td>3</td><td>RF100</td><td>SILICON RECTIFIER</td><td>SR-30</td><td>1</td><td>TRAVERSING</td></tr><tr><td>4</td><td>TB</td><td>TERMINAL BLOCK</td><td>20A,15A</td><td></td><td></td></tr></tbody></table>										NO	SYMBOL	DESCRIPTION	SPECIFICATION	Q'TY	REMARK	1	M101,102	MAGNET CONTACT	DMC40b	2	TRAVERSING	2	EOCR100	E.O.C.R	SS-30	1	TRAVERSING	3	RF100	SILICON RECTIFIER	SR-30	1	TRAVERSING	4	TB	TERMINAL BLOCK	20A,15A				
NO	SYMBOL	DESCRIPTION	SPECIFICATION	Q'TY	REMARK																																														
1	M101,102	MAGNET CONTACT	DMC40b	2	TRAVERSING																																														
2	EOCR100	E.O.C.R	SS-30	1	TRAVERSING																																														
3	RF100	SILICON RECTIFIER	SR-30	1	TRAVERSING																																														
4	TB	TERMINAL BLOCK	20A,15A																																																
DESCRIPTION MT'L REMARKS 1 PANEL CASE SPC 1.6t 2 PANEL COVER SPC 1.6t 3 HINGE PUR' 4 CLAMP PUR'										CUSTOMER TRAVERSING BOX KDC40/5-MA KD 극동호이스트 주식회사 KUKDONG HOIST CO., LTD. DWG. NO. KDC40-EC002										DESIGN SCALE SHT. NO. ORDER NO.																															
DATE 05.AUG.2016 REDRAWING K.H.Han DESCRIPTION DRAWN CHECK APPRVD										REV A DATE 05.AUG.2016 REDRAWING K.H.Han DESCRIPTION DRAWN CHECK APPRVD										⚡																															



NOTE

- 전선의 색상은 다음과 같다.
 - 1) 흑색 : 교류 및 직류 전압회로
 - 2) 적색 : 교류 제어회로
 - 3) 황색 : 직류 제어회로
 - 4) 구황색 : 외부 인증장치 제어회로
- CABLE MATERIAL : KIV OR EQUIVALENT
MIN SIZE : 2.5sq
- 제어용 전선 : 2.5mm KIV/HIV
- 제막시 다소 변경 될수있음.
- 외함 개방구조는 다음과 같을것.
 - 1) 외함 개방시 충전부분이 차단되도록 할것.
 - 2) 외함 개방후 충전되어있는 부분은 IP2X 이상의 직접 접촉 방호가 되어있을것.

1. UPPER LIMIT LS-1의 전압 허용 전류 용량 : AC 600V, 3A
2. UPPER LIMIT LS-2의 전압 허용 전류 용량 : NFB 250AF
3. EARTH TERMINAL RESISTANCE : 0.018
4. POWER SOURCE : AC, 3ø 220V 60HZ

[illegible]


NO	DESCRIPTION	MATERIAL	QTY	SIZE	REMARK
1					
2					
3					
4					
5					
6					
7					
8					
9					
10					


SPECIFICATION SYMBOLS	HOISTING POWER	HOISTING MOTOR	DC MAG. BRAKE	NO FUSE BREAKER	MAGNET CONTACTOR	ELECTRIC OVER CURRENT RELAY	SILICON RECTIFIER	LOAD LIMITER	CABLE
DESCRIPTION	HOIST	IM10	DB10	LS-II & MCCB100	M101, M102	EOR100	RT100	LDL-100	C20-01
SELECTION	40TON AC 3PH 220V 60Hz	33KW x 6P	DC 100V	ABS250AF/175AT	MC-330a	SS-150	SR-60	JDL-30	VCT 70sqx4c
MAKER		KUKDONG			DONG-A	SCHNEIDER/ASAN	ASAN	JUNGHO	DAEDUOK

REV	DATE	DESCRIPTION	DRAWN	CHECK	APPROV
01	JUNE 2017	FIRST ISSUE	H.S.KIM		M.H.KIM
PROJECT					
CLIENT					
MANUFACTURER					
TITLE	40T-CREEP HOISTING POWER CIRCUIT DIAGRAM	KDC40			
SCALE	DWG. NO.	KDC40E22			
SHT. NO.	REV.				

SPECIFICATION	HOSTING POWER	HOSTING MOTOR	CREEP MOTOR	DC MAG ² MOTOR	NO FUSE BREAKER	MAGNET CONTACTOR	ELECTRIC OVER CURRENT RELAY	SILICON RECTIFIER	LOAD LIMITER	CABLE
SYMBOLS DESCRIPTION										
	HOIST	IM10	IM11	DB10, 11	LS-II & MCB31000	M101.M102	EORC100	RF110	LOAD LIMITER	CZ0-01
	40TON AC 3PH 220V 60Hz	3.3KW x 4P	3.7KW x 4P	DC 100V	ABS250AF/75AT	MC-3300	SS-150	SR-60	JDL-100	VCT 70m ² /46
SELECTION	KUKKOONG					LS		SCHNEIDER/ASAN		DAEDUCK
MAKER						DONG-A		ASAN		JUNGHO


1000





ADR'S NO.

REFRIGERATING 구현 시 적용



NO	SYMBOL	DESCRIPTION	SPECIFICATION	Q'TY	REMARK
1	MCCB100	NO FUSE BREAKER	ABS250AF/125AT	1	
2	TR1	TRANS	380/110, 120V 300VA	1	
3	M101,102	MAGNET CONTACT	MC-185a	2	HOISTING
4	EOCR100	E.O.C.R	SS-100	1	HOISTING
5	RF100	SILICON RECTIFIER	SR-60	1	HOISTING
6	M111,112	MAGNET CONTACT	DMC22b	2	CREEP
7	EOCR110	E.O.C.R	SS-30	1	CREEP
8	RF110	SILICON RECTIFIER	SR-30	1	CREEP
9	MCCB10	NO FUSE BREAKER	ABS30AF/5AT	1	REFRIGERATING
10	EOCR10	E.O.C.R	SS-05	1	REFRIGERATING
11	T100	TIMER	AT11DN	1	REFRIGERATING
12	MR10	MAGNET CONTACT	DMC12b	1	REFRIGERATING
13	CR10,20,30,CR,CRMA	RELAY	MINI, 4C	4	SELECT
14	TB	TERMINAL BLOCK	100A,25A,15A		
15	LSIM	UPPER LIMIT	HY-R704A	1	

- NOTE
- 전선의 색상은 다음과 같다.
 - 색 : 교류 및 직류 전원회로
 - 색 : 교류 제어회로
 - 색 : 직류 제어회로
 - 주황색 : 외부 연동장치 제어회로
 - CABLE MATERIAL : KIV OR EQUIVALENT
MIN SIZE : 2.5sq
 - 제어용 전선 : 2.5mm KIV,HIV
 - 제어시 다소 변경 될수있음.
 - 외함 개방구조는 다음과 같을것.
 - 외함 개방시 충전부분이 차단되도록 할것.
 - 외함 개방후 충전되어있는 부분은 IP2X 이상의 직접 접촉 방호가 되어있을것.

- NOTE
- UPPER LIMIT LS-1의 접점 허용 전류 용량 : AC 600V, 3A
 - UPPER LIMIT LS-2의 접점 허용 전류 용량 : NFB 250AF
 - EARTH TERMINAL RESISTANCE : 0.018
 - POWER SOURCE : AC. 3ø 380V 60HZ



CUSTOMER		TITLE	
KUD KUKDONG HOIST CO., LTD.		EARTH DETAILS DRAWING	
KDC40/5-MA		KDC40-BA03	
REV	DATE	DESCRIPTION	APPROV
05.AUG.2016		REDRAWING	K.H.Han
			CHECK
			APPROV


NO	DESCRIPTION	MATERIAL	QTY	SIZE	REMARK
1					
2					
3					
4					
5					
6					
7					
8					
9					
10					


REV	DATE	DESCRIPTION	DRAWN	CHECK	APPROVD
1	01 JUNE 2011	FIRST ISSUE	H.S.KIM		M.H.KIM

PROJECT	CLIENT	MANUFACTURER	TITLE	SCALE	DWG. NO.	SHT. NO.	REV.
		크동호이스트 주식회사 KUDONG HOIST CO., LTD.	40T-CREEP HOISTING POWER CIRCUIT DIAGRAM		KDC40E32	-	-

SPECIFICATION		HOISTING POWER	HOISTING MOTOR	DC MAG ² BREAKER	MAGNET CONTACTOR	ELECTRIC OVER CURRENT RELAY	SILICON RECTIFIER	LOAD LIMITER	CABLE	TITLE	
SYMBOLS	DESCRIPTION									40T-CREEP HOISTING POWER CIRCUIT DIAGRAM	
		HOIST	IM10	DB10, 11	M101,M102	EOCR110	RF100	LOAD LIMITER	C20-01	KDC40	
		40TON AC 3PH 380V 60HZ	33KW x 8P	DC 100V	MC-185G	SS-100	SR-60	JD-100	VCT 35sqm4c	SCALE	DWG. NO.
										SHT. NO.	REV.
	SELECTION MAKER		KUKDOONG		LS	SONNEDER/ASAN	ASAN	JUNGHO	DAEDUCK	KDC40E32	-


불법복제 및 배포금지

[illegible][illegible]



ADR'S NO.

REFRIGERATING 구현 시 적용



NOTE


- 1. UPPER LIMIT LS-1의 접점 허용 전류 용량 : AC 600V, 3A
- 2. UPPER LIMIT LS-2의 접점 허용 전류 용량 : NFB-125AF
- 3. EARTH TERMINAL RESISTANCE : 0.018
- 4. POWER SOURCE : AC, 3ø 440V 60HZ



- NOTE 1. 전선의 색상은 다음과 같다.
- 1) 흑색 : 교류 및 직류 전원회로
 - 2) 적색 : 교류 제어회로
 - 3) 청색 : 직류 제어회로
 - 4) 주황색 : 외부 연동장치 제어회로
2. CABLE MATERIAL : KIV OR EQUIVALENT
3. 제어용 전선 : 2.5mm KIV,HIV
4. 제어시 다소 변경 될수있음.
5. 외함 기방구조는 다음과 같을것.
- 1) 외함 기방시 충전부분이 차단되도록 할것.
 - 2) 외함 기방후 충전되어있는 부분은 IP2X 이상의 직접 접촉 방호가 되어있을것.
- 5) 흑색 또는 녹색과 황색 조합 : 접지
- 6) 청색 : 중성선

NO	SYMBOL	DESCRIPTION	SPECIFICATION	Q'TY	REMARK
1	MCCB100	NO FUSE BREAKER	ABS125AF/100AT	1	
2	TR1	TRANS	440/110,120V 300VA	1	
3	M101,102	MAGNET CONTACT	MC-185a	2	HOISTING
4	EOCR100	E.O.C.R	SS-100	1	HOISTING
5	RF100	SILICON RECTIFIER	SR-60	1	HOISTING
6	M111,112	MAGNET CONTACT	DMC22b	2	CREEP
7	EOCR110	E.O.C.R	SS-30	1	CREEP
8	RF110	SILICON RECTIFIER	SR-30	1	CREEP
9	MCCB10	NO FUSE BREAKER	ABS30AF/SAT	1	REFRIGERATING
10	EOCR10	E.O.C.R	SS-05	1	REFRIGERATING
11	T100	TIMER	AT11DN	1	REFRIGERATING
12	MR10	MAGNET CONTACT	DMC12b	1	REFRIGERATING
13	CR10,20,30,CR,CRMA	RELAY	MINI, 4C	4	SELECT
14	TB	TERMINAL BLOCK	100A,25A,15A		
15	LSIM	UPPER LIMIT	HY-R704A	1	

TITLE		CUSTOMER		DESIGN	SCALE	SHT. NO.	ORDER NO.
EARTH DETAILS DRAWING		극동호이스트 주식회사					
KDC40/5-MA		KUKDONG HOIST CO., LTD.		DWG. NO.			
05 AUG 2016		K.H.Han					
REV	DATE	DESCRIPTION	DRAWN	CHECK	APPRVD	KDC40-BA04	





NO	DESCRIPTION	MATERIAL	QTY	SIZE	REMARK
1	01 JUNE 2011	FIRST ISSUE	H.S. KIM	-	M.H. KIM
REV	DATE	DESCRIPTION	DRAWN	CHECK	APPROV
PROJECT	DATE	DESCRIPTION	DRAWN	CHECK	APPROV
CLIENT	DATE	DESCRIPTION	DRAWN	CHECK	APPROV
MANUFACTURER	DATE	DESCRIPTION	DRAWN	CHECK	APPROV
TITLE	DATE	DESCRIPTION	DRAWN	CHECK	APPROV
SCALE	DATE	DESCRIPTION	DRAWN	CHECK	APPROV
DWG. NO.	DATE	DESCRIPTION	DRAWN	CHECK	APPROV
SHT. NO.	DATE	DESCRIPTION	DRAWN	CHECK	APPROV
REV.	DATE	DESCRIPTION	DRAWN	CHECK	APPROV

SPECIFICATION SYMBOLS	DESCRIPTION	SELECTION	MAKER
40TON AC 3PH 440V 60Hz	HOIST	IM10	3.3KW x 6P
40TON AC 3PH 440V 60Hz	HOISTING MOTOR	IM10	3.3KW x 6P
40TON AC 3PH 440V 60Hz	HOISTING MOTOR	IM10	3.3KW x 6P
40TON AC 3PH 440V 60Hz	HOISTING MOTOR	IM10	3.3KW x 6P
40TON AC 3PH 440V 60Hz	HOISTING MOTOR	IM10	3.3KW x 6P
40TON AC 3PH 440V 60Hz	HOISTING MOTOR	IM10	3.3KW x 6P
40TON AC 3PH 440V 60Hz	HOISTING MOTOR	IM10	3.3KW x 6P
40TON AC 3PH 440V 60Hz	HOISTING MOTOR	IM10	3.3KW x 6P
40TON AC 3PH 440V 60Hz	HOISTING MOTOR	IM10	3.3KW x 6P
40TON AC 3PH 440V 60Hz	HOISTING MOTOR	IM10	3.3KW x 6P

MANUFACTURER	CLIENT	PROJECT	DATE	DESCRIPTION	DRAWN	CHECK	APPROV
KUDONG HOIST CO., LTD.	40T-CREEP HOISTING POWER CIRCUIT DIAGRAM	KDC40	01 JUNE 2011	FIRST ISSUE	H.S. KIM	-	M.H. KIM
SCALE	DWG. NO.	SHT. NO.	REV.				
-	KDC40E42	-	-				

불법복제 및 배포금지





크동호이스트 주식회사
KUKDONG HOIST CO., LTD.

TRaversing POWER CIRCUIT DIAGRAM
KDC40/5-MA


SCALE DWG. NO. KDC405E44
SHT. NO. -
REV. -

MANUFACTURER

CLIENT

PROJECT	01 JUNE 2011	FIRST ISSUE	H.S.KIM	-	M.H.KIM
REV	DATE	DESCRIPTION	DRAWN	CHECK	APPROV

NO	DESCRIPTION	MATERIAL	QTY	SIZE	REMARK
-	-	-	-	-	-
-	-	-	-	-	-



1. 전선의 색상은 다음과 같다.
 - 1) 흑색 : 교류 및 직류 전압회로
 - 2) 적색 : 교류 제어회로
 - 3) 청색 : 직류 제어회로
 - 4) 파랑색 : 외부 전동장치 제어회로
2. CABLE MATERIAL : K1V OR EQUIVALENT
MIN SIZE : 2.5sq
3. 제어용 전선 : 2.5mm K1V,H1V
4. 제직시 다소 변경 될수있음.
5. 외함 개방구조는 다음과 같음.
 - 1) 외함 개방시 운전부분이 차단되도록 함.
 - 2) 외함 개방후 운전되어있는 부분은 IP2X 이상의 차단 접속 방호가 되어있을것.

1) 색상 : 고무 및 지류 전원회로
2) 색상 : 고무 제어회로
3) 색상 : 지류 제어회로
4) 두께 : 외부 전용장치 제어회로

2. CABLE MATERIAL : KIV OR E MIN SIZE KIV,HIV


3. 제어용 전선 : 2.5mm KIV,HIV
4. 제작사 다소 변경 될수있음.
5. 외함 개방구조는 다음과 같을것.

1) 외함 개방시 충전부분이 차단되도
2) 외함 개방후 충전되어있는 부분은


1. UPPER LIMIT LS-1의 전압 허용 전류 용량 : AC 600V, 3A
2. UPPER LIMIT LS-2의 전압 허용 전류 용량 : NFB 125AF
3. EARTH TERMINAL RESISTANCE : 0.018
4. POWER SOURCE : AC. 3φ 460V 60HZ

[illegible]

불법복제 및 배포금지




불법복제 및 배포금지



NO	DESCRIPTION	MATERIAL	QTY	SIZE	REMARK
1	01 JUNE 2011	FIRST ISSUE	H.S.KIM	-	M.H.KIM
2	REV	DATE	DESCRIPTION	DRAWN	CHECK
3	PROJECT				APPROV
4	CLIENT				
5	MANUFACTURER				
6	TITLE				
7	SCALE				
8	DWG. NO.				
9	SHT. NO.				
10	REV				

SPECIFICATION	TRAVERSING POWER	TRAVERSING MOTOR	DC.MAG. BRAKE	MAGNET CONTACTOR	ELECTRIC OVER CURRENT RELAY	SILICON RECTIFIER
SYMBOLS						
DESCRIPTION						
TRAVERSING POWER	AC 3PH 460V 60Hz	IM 30, IM31	DB30, DB31	M301, M302	EOCR300	RF00
TRAVERSING MOTOR	2.2kW x 4P		DC 100V	DMC40b	SS-30	SR-30
DC.MAG. BRAKE	1.5kW x 6P		DC 100V	DMC40b	SS-30	SR-30
MAGNET CONTACTOR				DONG-A	SCHNEIDER/ASAN	ASAN
ELECTRIC OVER CURRENT RELAY						
SILICON RECTIFIER						



극동호이스트 주식회사
KUDONG HOIST CO., LTD.

TRAVERSING POWER CIRCUIT DIAGRAM
KDC40/5-MA

DWG. NO. KDC405E54


SHT. NO. -

REV. -

1 2 3 4 5 6 7 8 9 10 11 12 13 14 15 16 17 18 19 20

ADR'S NO.

REFRIGERATING 구편 시 적용




- NOTE
- 1. 전선의 색상은 다음과 같다.
 - 1) 흑색 : 교류 및 직류 전원회로
 - 2) 적색 : 교류 제어회로
 - 3) 청색 : 직류 제어회로
 - 4) 주황색 : 외부 연동장치 제어회로
 - 2. CABLE MATERIAL : KIV OR EQUIVALENT
 - MIN SIZE : 2.5sq
 - 3. 제어용 전선 : 2.5mm KIV,HIV
 - 4. 제어시 다소 변경 될수있음.
 - 5. 외함 개방구조는 다음과 같을것.
 - 1) 외함 개방시 충전부분이 차단되도록 할것.
 - 2) 외함 개방후 충전되어있는 부분은 IP2X 이상의 직접 접촉 방호가 되어있을것.

- NOTE
- 1. UPPER LIMIT LS-1의 접점 허용 전류 용량. : AC 600V, 3A
 - 2. UPPER LIMIT LS-2의 접점 허용 전류 용량. : NFB-125AF
 - 3. EARTH TERMINAL RESISTANCE : 0.018
 - 4. POWER SOURCE : AC. 3ø 480V 60HZ



--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--

불법복제 및 배포금지



SPECIFICATION	SYMBOLS	HOISTING POWER	HOISTING MOTOR	DC MAG. BRAKE	NO FUSE BREAKER	MAGNET CONTACTOR	ELECTRIC OVER CURRENT RELAY	SILICON RECTIFIER	LOAD LIMITER	CABLE
DESCRIPTION	HOIST	40TON AC 3PH 480V 60Hz	IM10	DB10, 11	LS-II & MCCB100	M101, M102	EOCR100	RF100	LOAD LIMITER	C20-01
SELECTION	MAKER				AB5125AF/100AT	MC-1B5a	SS-100	SR-80	JD-L-100	VCT 25sqx4c
					DC 100V	DONG-A	SCHNEIDER/ASAN	ASAN	JUNCHO	DAEDUCK




극동호이스트 주식회사
KUKDONG HOIST CO., LTD.

TITLE	40T-CREEP HOISTING POWER CIRCUIT DIAGRAM
SCALE	DWG. NO. KDC40E62
REV.	SHT. NO. -
REV.	-

MANUFACTURER	극동호이스트 주식회사 KUKDONG HOIST CO., LTD.
CLIENT	
PROJECT	
REV.	01 JUNE 2017 FIRST ISSUE
DATE	
DESCRIPTION	
DRAWN	H.S.KIM
CHECK	M.H.KIM
APPROVD	

NO	DESCRIPTION	MATERIAL	Q'TY	SIZE	REMARK
-	-	-	-	-	-
-	-	-	-	-	-


[illegible]



NO	DESCRIPTION	MATERIAL	QTY	SIZE	REMARK
1	01 JUNE 2017 FIRST ISSUE	H.S.KIM	-	-	M.H.KIM
REV	DATE	DESCRIPTION	DRAWN	CHECK	APPROVD
PROJECT					
CLIENT					
MANUFACTURER					
TITLE					
SCALE					
DWG. NO.					
SHT. NO.					
REV.					

SPECIFICATION SYMBOLS	TRAVERSING POWER DESCRIPTION	TRAVERSING MOTOR	DC.MAG. BRAKE	MAGNET CONTACTOR	ELECTRIC OVER CURRENT RELAY	SILICON RECTIFIER
DESCRIPTION	AC 3PH 480V 60Hz	IM 30, IM31	DB30, DB31	M301, M302	EOR300	RF00
SELECTION	AC 3PH 480V 60Hz	1.5kW x 8P	DC 100V	DMC40b	SS-30	SR-30
MAKER	KUKDONG			DONG-A	SCHNEIDER/ASAN	ASAN

불법복제 및 배포금지



* KDC40/5(C) 모델에서 AUX의 MAGNET CONTACTOR은 아래 표와 같이 SYMBOL을 변경 적용한다.

NO	DESCRIPTION	KD(C)의 SYMBOL	KDC40/5(C)에서 변경 적용된 SYMBOL
1	MAGNET CONTACT	M101	M201
2	MAGNET CONTACT	M102	M202
3	MAGNET CONTACT	M111	M211
4	MAGNET CONTACT	M112	M212

SPECIFICATION	TIMER	UPPER LIMIT SWITCH	CONTROL RELAY	PENDANT P.B./SW	REMOTE CONTROL	LOAD LIMITER
SYMBOL	T100	LS-IM	CR10, CRMA, CRM	PSB	RCB	LDL-100
MAKER	AT11DN	HY-R704A	MINI 4C	KG-H10EMHCAA	KG AUTO	JEONG HO


NO	DESCRIPTION	MATERIAL	QTY	SIZE	REMARK
1	01 JUNE 2017	FIRST ISSUE			
REV	DATE	DESCRIPTION	DRAWN	CHECK	APPROV
M.H.KIM					
PROJECT					
CLIENT					
MANUFACTURER					
TITLE					
SCALE					
DWG. NO.					
SHT. NO.					
REV.					



크동호이스트 주식회사
KUDONG HOIST CO., LTD.

HOISTING CONTROL CIRCUIT DIAGRAM
KDC40/5-MA (40T-Creep, 5T-Single)
KDC405E105

불법복제 및 배포금지



* KDC40/5(C) 모델에서 AUX의 MAGNET CONTACTOR은 아래 표와 같이 SYMBOL을 변경 적용한다.

NO	DESCRIPTION	KD(C)의 SYMBOL	KDC40/5(C)에서 변경 적용된 SYMBOL
1	MAGNET CONTACT	M101	M201
2	MAGNET CONTACT	M102	M202
3	MAGNET CONTACT	M111	M211
4	MAGNET CONTACT	M112	M212


SPECIFICATION SYMBOL	TIMER	UPPER LIMIT SWITCH	CONTROL RELAY	PENDANT P.B./SW	REMOTE CONTROL	LOAD LIMITER 12
SYMBOL	T100	LS-IM	CR10, CRMA, CRM	PSB	RCB	LOAD LIMITER
MAKER	AT11DN	HY-R704A	MINI 4C	KG-H10EMHCAA	KG AUTO	JDL-100
	AUTONICS	HAN YOUNG	KUK DONG	KG AUTO	KG AUTO	JEONG HO

NO	DESCRIPTION	MATERIAL	QTY	SIZE	REMARK
1	01 JUNE 2017	FIRST ISSUE			
REV	DATE	DESCRIPTION	DRAWN	CHECK	APPROV
PROJECT					
CLIENT					
MANUFACTURER					
TITLE					
SCALE					
DWG. NO.					
SHT. NO.					
REV.					



KUDONG HOIST CO., LTD.
 HOISTING CONTROL CIRCUIT DIAGRAM
 KDC40/5C-MA (40T-Creep, 5T-Creep)
 KDC405E106

불법복제 및 배포금지




NO	DESCRIPTION	MATERIAL	QTY	SIZE	REMARK
1	01 JUNE 2017	FIRST ISSUE			
REV	DATE	DESCRIPTION	DRAWN	CHECK	APPROVD
PROJECT					
CLIENT					
MANUFACTURER					
TITLE					
SCALE					
DWG. NO.					
SHT. NO.					
REV.					

SPECIFICATION	LIMIT SWITCH
SYMBOL	LS301/302
MAKER	KG AUTO

크동호이스트 주식회사
KUDONG HOIST CO., LTD.

TITLE	TRAVERSING & TRAVELLING CONTROL CIRCUIT DIAGRAM
SCALE	KDC40/5-MA
DWG. NO.	KDC405E108
SHT. NO.	-
REV.	-


불법복제 및 배포금지



NO	DESCRIPTION	MATERIAL	QTY	SIZE	REMARK
1	01 JUNE 2017 FIRST ISSUE	H.S.KIM	-	-	M.H.KIM
2	DATE	DESCRIPTION	DRAWN	CHECK	APPROVD
3	PROJECT				
4	CLIENT				
5	MANUFACTURER				
6	TITLE				
7	TRAVERSING & TRAVELLING CONTROL CIRCUIT DIAGRAM				
8	SCALE				
9	DWG. NO.				
10	SHT. NO.				
11	REV.				

SPECIFICATION	TIMER	LIMIT SWITCH
SYMBOL	T100	LS301,302
MAKER	AT11DN	KG-L001
	AUTONICS	KG AUTO

NO	DESCRIPTION	MATERIAL	QTY	SIZE	REMARK
1	01 JUNE 2017 FIRST ISSUE	H.S.KIM	-	-	M.H.KIM
2	DATE	DESCRIPTION	DRAWN	CHECK	APPROVD
3	PROJECT				
4	CLIENT				
5	MANUFACTURER				
6	TITLE				
7	TRAVERSING & TRAVELLING CONTROL CIRCUIT DIAGRAM				
8	SCALE				
9	DWG. NO.				
10	SHT. NO.				
11	REV.				

1	2	3	4	5	6	7	8	9	10																																																											
A	B	C	D	E	F	G	H																																																													
<table><tr><td>NO</td><td>DESCRIPTION</td><td>MATERIAL</td><td>QTY</td><td>SIZE</td><td>REMARK</td></tr><tr><td>-</td><td>-</td><td>-</td><td>-</td><td>-</td><td>-</td></tr><tr><td>-</td><td>-</td><td>-</td><td>-</td><td>-</td><td>-</td></tr><tr><td>-</td><td>-</td><td>-</td><td>-</td><td>-</td><td>-</td></tr></table>										NO	DESCRIPTION	MATERIAL	QTY	SIZE	REMARK	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-																																			
NO	DESCRIPTION	MATERIAL	QTY	SIZE	REMARK																																																															
-	-	-	-	-	-																																																															
-	-	-	-	-	-																																																															
-	-	-	-	-	-																																																															
<table><tr><td>No</td><td>NAME</td><td>DESCRIPTION</td></tr><tr><td>1</td><td>EBS</td><td>EMERGENCY STOP</td></tr><tr><td>2</td><td>REM-PBS</td><td>REMOTE-PENDANT PBS (2STEP)</td></tr><tr><td>3</td><td>MAIN-AUX</td><td>MAIN-AUX (2STEP)</td></tr><tr><td>4</td><td>HO</td><td>HORN</td></tr><tr><td>5</td><td>U</td><td>UP (2STEP)</td></tr><tr><td>6</td><td>D</td><td>DOWN (2STEP)</td></tr><tr><td>7</td><td>E</td><td>EAST (1STEP)</td></tr><tr><td>8</td><td>W</td><td>WEST (1STEP)</td></tr><tr><td>9</td><td>S</td><td>SOUTH (1STEP)</td></tr><tr><td>10</td><td>N</td><td>NORTH (1STEP)</td></tr><tr><td>11</td><td>PUSH BUTTON CASE</td><td></td></tr><tr><td>12</td><td>PUSH BUTTON COVER</td><td></td></tr></table>										No	NAME	DESCRIPTION	1	EBS	EMERGENCY STOP	2	REM-PBS	REMOTE-PENDANT PBS (2STEP)	3	MAIN-AUX	MAIN-AUX (2STEP)	4	HO	HORN	5	U	UP (2STEP)	6	D	DOWN (2STEP)	7	E	EAST (1STEP)	8	W	WEST (1STEP)	9	S	SOUTH (1STEP)	10	N	NORTH (1STEP)	11	PUSH BUTTON CASE		12	PUSH BUTTON COVER																					
No	NAME	DESCRIPTION																																																																		
1	EBS	EMERGENCY STOP																																																																		
2	REM-PBS	REMOTE-PENDANT PBS (2STEP)																																																																		
3	MAIN-AUX	MAIN-AUX (2STEP)																																																																		
4	HO	HORN																																																																		
5	U	UP (2STEP)																																																																		
6	D	DOWN (2STEP)																																																																		
7	E	EAST (1STEP)																																																																		
8	W	WEST (1STEP)																																																																		
9	S	SOUTH (1STEP)																																																																		
10	N	NORTH (1STEP)																																																																		
11	PUSH BUTTON CASE																																																																			
12	PUSH BUTTON COVER																																																																			
 * NOTE 1. MATERIAL : ABS 2. COLOR : YELLOW 3. CONTACTOR : AC 250V 6A 4. CABLE : VCT 1.5sq 5. IP65																																																																				
<table><tr><td>01 JUNE 2017</td><td>FIRST ISSUE</td><td>H.S.KIM</td><td>-</td><td>M.H.KIM</td></tr><tr><td>REV</td><td>DATE</td><td>DESCRIPTION</td><td>DRAWN</td><td>CHECK</td><td>APPROVD</td></tr><tr><td colspan="6">PROJECT</td></tr><tr><td colspan="6">CLIENT</td></tr><tr><td colspan="6">MANUFACTURER</td></tr><tr><td colspan="6">TITLE</td></tr><tr><td colspan="6">SCALE</td></tr><tr><td colspan="6">DWG. NO.</td></tr><tr><td colspan="6">SHT. NO.</td></tr><tr><td colspan="6">REV.</td></tr></table>										01 JUNE 2017	FIRST ISSUE	H.S.KIM	-	M.H.KIM	REV	DATE	DESCRIPTION	DRAWN	CHECK	APPROVD	PROJECT						CLIENT						MANUFACTURER						TITLE						SCALE						DWG. NO.						SHT. NO.						REV.					
01 JUNE 2017	FIRST ISSUE	H.S.KIM	-	M.H.KIM																																																																
REV	DATE	DESCRIPTION	DRAWN	CHECK	APPROVD																																																															
PROJECT																																																																				
CLIENT																																																																				
MANUFACTURER																																																																				
TITLE																																																																				
SCALE																																																																				
DWG. NO.																																																																				
SHT. NO.																																																																				
REV.																																																																				
<table><tr><td colspan="2">KUDONG HOIST CO., LTD.</td></tr><tr><td colspan="2">KUDONG HOIST CO., LTD.</td></tr><tr><td colspan="2">PENDANT PUSH BUTTON SWITCH - LAY OUT</td></tr><tr><td colspan="2">KG-H10EMMHCAA</td></tr><tr><td colspan="2">KDC405E102</td></tr></table>										KUDONG HOIST CO., LTD.		KUDONG HOIST CO., LTD.		PENDANT PUSH BUTTON SWITCH - LAY OUT		KG-H10EMMHCAA		KDC405E102																																																		
KUDONG HOIST CO., LTD.																																																																				
KUDONG HOIST CO., LTD.																																																																				
PENDANT PUSH BUTTON SWITCH - LAY OUT																																																																				
KG-H10EMMHCAA																																																																				
KDC405E102																																																																				
1	2	3	4	5	6	7	8	9	10																																																											
A	B	C	D	E	F	G	H																																																													

IV. 참고자료



불법복제 및 배포금지



5, Sandan 6-ro, Jeonggan-myeon, Gijang-gun, Busan, 46026, Korea
TEL:+82-51-727-0015 FAX:+82-51-727-3247 www.kiswire.com

CERT NO. 201412WRW02000

DATE Jun. 08, 2017

MILL TEST CERTIFICATE

THIS IS TO CERTIFY THAT THE MATERIAL DESCRIBED BELOW WAS MANUFACTURED
IN ACCORDANCE WITH KISWIRE LTD SPECIFICATION AND APPLICABLE SECTIONS

OF KSD 3514 - 2002 (B Grade)

TO MESSRS

MATERIAL DESCRIPTION UNGALVANIZED STEEL WIRE ROPE

06 X 25 (FI) + IWRC 1000 M X 1 REEL

EX NO. 1W6790

ORDER NO. REEL NO. 1 SAMPLING NO. 1

DIAMETER OF ROPE 28.000 mm TYPE OF CORE IWRC

SPECIFIED BREAKING LOAD 519.00 kN SAMPLE BROKE AT 549.09 kN

WT. OF ZINC COATING OF OUTER WIRE MIN. 0.000 g/m²

ROPE LAY RHRL LAY LENGTH 177.18 mm

LUBRICATION B

CHEMICAL ANALYSIS OF WIRE ROD

CHARGE NO.	C X 100	Si X 100	Mn X 100	P X 1000	S X 1000
SF47012	72	21	69	16	7

DATE OF SAMPLE TEST Jan. 06, 2015

S. H. Ham

Approved by Q.C Manager S.H. Ham
KISWIRE LTD., KOREA



KS



JIS



ABS



KR



NK



G.Lloyd's



DNV



L.R



BV

LOAD LIMITER 권고 SETTING치

* POWER SOURCE : AC 3 Ø 220V 60Hz

극동호이스트(주)

HOIST	MOTOR 용량	LOAD LIMITER 권고 SETTING치				C.T 용량	REMARK
		LOAD CURRENT	ADJ	SHOCK TIME	LOAD CURRENT		
40 TON	33KW x 6P	110%	1 SEC	1 SEC	126.6 A	5 V.A	
	3.7KW x 4P	110%	1 SEC	1 SEC	16.0	5 V.A	

* POWER SOURCE : AC 3 Ø 380V 60Hz

극동호이스트(주)

HOIST	MOTOR 용량	LOAD LIMITER 권고 SETTING치				C.T 용량	REMARK
		LOAD CURRENT	ADJ	SHOCK TIME	LOAD CURRENT		
40 TON	33KW x 6P	110%	1 SEC	1 SEC	77.3 A	5 V.A	
	3.7KW x 4P	110%	1 SEC	1 SEC	9.3 A	5 V.A	

* POWER SOURCE : AC 3 Ø 440V 60Hz

극동호이스트(주)

HOIST	MOTOR 용량	LOAD LIMITER 권고 SETTING치				C.T 용량	REMARK
		LOAD CURRENT	ADJ	SHOCK TIME	LOAD CURRENT		
40 TON	33KW x 6P	110%	1 SEC	1 SEC	66.3 A	5 V.A	
	3.7KW x 4P	110%	1 SEC	1 SEC	8.0 A	5 V.A	

NOTE

1. 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

LOAD LIMITER 권고 SETTING치

* POWER SOURCE : AC 3Φ 460V 60Hz							
HOIST	MOTOR 용량	LOAD LIMITER 권고 SETTING치				LOAD CURRENT	
		LOAD CURRENT	ADJ	SHOCK TIME	C.T 용량	REMARK	
		110%	1 SEC	1 SEC			
40 TON	33KW x 6P	110%	1 SEC	1 SEC	56.6 A	62.3 A	5 V.A
	3.7KW x 4P	110%	1 SEC	1 SEC	7.7 A	8.5 A	5 V.A

* POWER SOURCE : AC 3Φ 480V 60Hz							
HOIST	MOTOR 용량	LOAD LIMITER 권고 SETTING치				LOAD CURRENT	
		LOAD CURRENT	ADJ	SHOCK TIME	C.T 용량	REMARK	
		110%	1 SEC	1 SEC			
40 TON	33KW x 6P	110%	1 SEC	1 SEC	54.2 A	59.6 A	5 V.A
	3.7KW x 4P	110%	1 SEC	1 SEC	7.3 A	8.0 A	5 V.A

NOTE

1. 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

E.O.C.R 권고 SETTING치

* POWER SOURCE : AC 3Φ 220V 60Hz

극동호이스트(주)

HOIST	MOTOR 용량	MOTOR 정격 전류	DRIVE TYPE	E.O.C.R TYPE	권고 SETTING 치			REMARK
					DELAY TIME	ERATION TI	CURRENT	
40 TON	33KW x 6P	126.6 A	1 DRAVE	SS-150	3 SEC	1 SEC	126.6 A	
	3.7KW x 4P	16.0 A	1 DRAVE	SS-30	3 SEC	1 SEC	16.0 A	

* POWER SOURCE : AC 3Φ 380V 60Hz

극동호이스트(주)

HOIST	MOTOR 용량	MOTOR 정격 전류	DRIVE TYPE	E.O.C.R TYPE	권고 SETTING 치			REMARK
					DELAY TIME	ERATION TI	CURRENT	
40 TON	33KW x 6P	77.3 A	1 DRAVE	SS-100	3 SEC	1 SEC	77.3 A	
	3.7KW x 4P	9.3 A	1 DRAVE	SS-30	3 SEC	1 SEC	9.3 A	

* POWER SOURCE : AC 3Φ 440V 60Hz

극동호이스트(주)

HOIST	MOTOR 용량	MOTOR 정격 전류	DRIVE TYPE	E.O.C.R TYPE	권고 SETTING 치			REMARK
					DELAY TIME	ERATION TI	CURRENT	
40 TON	33KW x 6P	66.3 A	1 DRAVE	SS-100	3 SEC	1 SEC	66.3 A	
	3.7KW x 4P	8.0 A	1 DRAVE	SS-30	3 SEC	1 SEC	8.0 A	

NOTE

1. 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

* POWER SOURCE : AC 3Φ 460V 60Hz

극동호이스트(주)

HOIST	MOTOR 용량	MOTOR 정격 전류	DRIVE TYPE	E.O.C.R TYPE	권고 SETTING 치			REMARK
					DELAY TIME	ERATION TI	CURRENT	
40 TON	33KW x 6P	56.6 A	1 DRAVE	SS-100	3 SEC	1 SEC	56.6 A	
	3.7KW x 4P	7.7 A	1 DRAVE	SS-30	3 SEC	1 SEC	7.7 A	

* POWER SOURCE : AC 3Φ 480V 60Hz

극동호이스트(주)

HOIST	MOTOR 용량	MOTOR 정격 전류	DRIVE TYPE	E.O.C.R TYPE	권고 SETTING 치			REMARK
					DELAY TIME	ERATION TI	CURRENT	
40 TON	33KW x 6P	54.2 A	1 DRAVE	SS-100	3 SEC	1 SEC	54.2 A	
	3.7KW x 4P	7.3 A	1 DRAVE	SS-30	3 SEC	1 SEC	7.3 A	

NOTE

1. 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.



E.O.C.R 권고 SETTING 치

* POWER SOURCE : AC3Φ 220V 60Hz

극동호이스트 (주)

MOTOR 용량	MOTOR 정격 전류	DRIVE TYPE	E.O.C.R TYPE	권고 SETTING 치			REMARK
				DELAY TIME	OPERATION TIME	CURRENT	
0.2KW x 6P	2.0 A	1 DRIVE	SS - 05	3 SEC	1 SEC	2.0 A	
		2DRIVE	SS - 05	3 SEC	1 SEC	4.0 A	
0.4KW x 4P	2.7 A	1 DRIVE	SS - 05	3 SEC	1 SEC	2.7 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	5.4 A	
0.5KW x 6P	3.4 A	1 DRIVE	SS - 05	3 SEC	1 SEC	3.4 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	6.8 A	
0.75KW x 4P	4.1 A	1 DRIVE	SS - 05	3 SEC	1 SEC	4.1 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	8.2 A	
1.0KW x 6P	6.7 A	1 DRIVE	SS - 30	3 SEC	1 SEC	6.7 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	13.4 A	
1.5KW x 4P	7.3 A	1 DRIVE	SS - 30	3 SEC	1 SEC	7.3 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	14.6 A	
1.5KW x 6P	7.6 A	1 DRIVE	SS - 30	3 SEC	1 SEC	7.6 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	15.2 A	
2.2KW x 4P	10 A	1 DRIVE	SS - 30	3 SEC	1 SEC	10 A	
		2 DRIVE	SS - 30	3 SEC	1 SEC	20 A	
0.8/0.4KW x 4/8P	4.8/4.25 A	1 DRIVE	SS - 05	3 SEC	1 SEC	4.8 A	
		2 DRIVE	SS - 05	3 SEC	1 SEC	4.25 A	
2.2KW x 6P	12 A	1 DRIVE	SS - 30	3 SEC	1 SEC	12 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	24 A	
3.7KW x 4P	16 A	1 DRIVE	SS - 30	3 SEC	1 SEC	16 A	
		2DRIVE	SS - 60	3 SEC	1 SEC	32 A	

NOTE

1, 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

E.O.C.R 권고 SETTING 치

* POWER SOURCE : AC3Φ 380V 60Hz

극동호이스트 (주)

MOTOR 용량	MOTOR 정격 전류	DRIVE TYPE	E.O.C.R TYPE	권고 SETTING 치			REMARK
				DELAY TIME	OPERATION TIME	CURRENT	
0.2KW x 6P	1.2 A	1 DRIVE	SS - 05	3 SEC	1 SEC	1.2 A	
		2DRIVE	SS - 05	3 SEC	1 SEC	2.4 A	
0.4KW x 4P	1.6 A	1 DRIVE	SS - 05	3 SEC	1 SEC	1.6 A	
		2DRIVE	SS - 05	3 SEC	1 SEC	2	
0.5KW x 6P	2.0 A	1 DRIVE	SS - 05	3 SEC	1 SEC	2.0 A	
		2DRIVE	SS - 05	3 SEC	1 SEC	4.0 A	
0.75KW x 4P	2.4 A	1 DRIVE	SS - 05	3 SEC	1 SEC	2.4 A	
		2DRIVE	SS - 05	3 SEC	1 SEC	4.8 A	
1.0KW x 6P	3.9 A	1 DRIVE	SS - 05	3 SEC	1 SEC	3.9 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	7.8 A	
1.5KW x 4P	4.2 A	1 DRIVE	SS - 05	3 SEC	1 SEC	4.2 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	8.4 A	
1.5KW x 6P	4.4 A	1 DRIVE	SS - 05	3 SEC	1 SEC	4.4 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	8.8 A	
2.2KW x 4P	5.8 A	1 DRIVE	SS - 30	3 SEC	1 SEC	5.8 A	
		2 DRIVE	SS - 30	3 SEC	1 SEC	11.6 A	
0.8/0.4KW x 4/8P	2.78/2.63 A	1 DRIVE	SS - 05	3 SEC	1 SEC	2.78 A	
		2 DRIVE	SS - 05	3 SEC	1 SEC	2.63A	
2.2KW x 6P	7.0 A	1 DRIVE	SS - 30	3 SEC	1 SEC	5.48 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	5.26 A	
3.7KW x 4P	9.3 A	1 DRIVE	SS - 30	3 SEC	1 SEC	7.0 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	14 A	
				3 SEC	1 SEC	9.3 A	
				3 SEC	1 SEC	18.6 A	

NOTE

1, 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.



E.O.C.R 권고 SETTING 치

* POWER SOURCE : AC3Φ 440V 60Hz

극동호이스트 (주)

MOTOR 용량	MOTOR 정격 전류	DRIVE TYPE	E.O.C.R TYPE	권고 SETTING 치			REMARK
				DELAY TIME	OPERATION TIME	CURRENT	
0.2KW x 6P	1.0 A	1 DRIVE	SS - 05	3 SEC	1 SEC	1.0 A	
		2DRIVE	SS - 05	3 SEC	1 SEC	2.0 A	
0.4KW x 4P	1.4 A	1 DRIVE	SS - 05	3 SEC	1 SEC	1.4 A	
		2DRIVE	SS - 05	3 SEC	1 SEC	2.8 A	
0.5KW x 6P	1.7 A	1 DRIVE	SS - 05	3 SEC	1 SEC	1.7 A	
		2DRIVE	SS - 05	3 SEC	1 SEC	3.4 A	
0.75KW x 4P	2.0 A	1 DRIVE	SS - 05	3 SEC	1 SEC	2.0 A	
		2DRIVE	SS - 05	3 SEC	1 SEC	4.0 A	
1.0KW x 6P	3.3 A	1 DRIVE	SS - 05	3 SEC	1 SEC	3.3 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	6.6 A	
1.5KW x 4P	3.7 A	1 DRIVE	SS - 05	3 SEC	1 SEC	3.7 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	7.4 A	
1.5KW x 6P	3.8 A	1 DRIVE	SS - 05	3 SEC	1 SEC	3.8 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	7.6 A	
2.2KW x 4P	5.0 A	1 DRIVE	SS - 30	3 SEC	1 SEC	5.0 A	
		2 DRIVE	SS - 30	3 SEC	1 SEC	10 A	
0.8/0.4KW x 4/8P	2.4/2.27 A	1 DRIVE	SS - 05	3 SEC	1 SEC	2.4 A	
		2 DRIVE	SS - 05	3 SEC	1 SEC	2.27 A	
2.2KW x 6P	6.0 A	1 DRIVE	SS - 05	3 SEC	1 SEC	4.8 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	6.0 A	
3.7KW x 4P	8.0 A	1 DRIVE	SS - 30	3 SEC	1 SEC	12.0 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	8.0 A	

NOTE

1, 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

E.O.C.R 권고 SETTING 치

* POWER SOURCE : AC3Φ 460V 60Hz

극동하이스트 (주)

MOTOR 용량	MOTOR 정격 전류	DRIVE TYPE	E.O.C.R TYPE	권고 SETTING 치			REMARK
				DELAY TIME	OPERATION TIME	CURRENT	
0.2KW x 6P	1.0 A	1 DRIVE	SS - 05	3 SEC	1 SEC	1.0 A	
		2DRIVE	SS - 05	3 SEC	1 SEC	2.0 A	
0.4KW x 4P	1.3 A	1 DRIVE	SS - 05	3 SEC	1 SEC	1.3 A	
		2DRIVE	SS - 05	3 SEC	1 SEC	2.6 A	
0.5KW x 6P	1.7 A	1 DRIVE	SS - 05	3 SEC	1 SEC	1.7 A	
		2DRIVE	SS - 05	3 SEC	1 SEC	3.4 A	
0.75KW x 4P	2.0 A	1 DRIVE	SS - 05	3 SEC	1 SEC	2.0 A	
		2DRIVE	SS - 05	3 SEC	1 SEC	4.0 A	
1.0KW x 6P	3.2 A	1 DRIVE	SS - 05	3 SEC	1 SEC	3.2 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	6.4 A	
1.5KW x 4P	3.5 A	1 DRIVE	SS - 05	3 SEC	1 SEC	3.5 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	7.0 A	
1.5KW x 6P	3.6 A	1 DRIVE	SS - 05	3 SEC	1 SEC	3.6 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	7.2 A	
2.2KW x 4P	4.8 A	1 DRIVE	SS - 05	3 SEC	1 SEC	4.8 A	
		2 DRIVE	SS - 30	3 SEC	1 SEC	9.6 A	
0.8/0.4KW x 4/8P	2.3/2.15 A	1 DRIVE	SS - 05	3 SEC	1 SEC	2.3 A	
		2 DRIVE	SS - 05	3 SEC	1 SEC	2.15 A	
2.2KW x 6P	4.8 A	1 DRIVE	SS - 05	3 SEC	1 SEC	4.8 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	9.6 A	
3.7KW x 4P	7.7 A	1 DRIVE	SS - 30	3 SEC	1 SEC	7.7 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	15.4 A	

NOTE

1. 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.



E.O.C.R 권고 SETTING 치

* POWER SOURCE : AC3Φ 480V 60Hz

극동호아스트 (주)

MOTOR 용량	MOTOR 정격 전류	DRIVE TYPE	E.O.C.R TYPE	권고 SETTING 치			REMARK
				DELAY TIME	OPERATION TIME	CURRENT	
0.2KW x 6P	0.9 A	1 DRIVE	SS - 05	3 SEC	1 SEC	0.9 A	
		2DRIVE	SS - 05	3 SEC	1 SEC	1.8 A	
0.4KW x 4P	1.2 A	1 DRIVE	SS - 05	3 SEC	1 SEC	1.2 A	
		2DRIVE	SS - 05	3 SEC	1 SEC	2.4 A	
0.5KW x 6P	1.6 A	1 DRIVE	SS - 05	3 SEC	1 SEC	1.6 A	
		2DRIVE	SS - 05	3 SEC	1 SEC	3.2 A	
0.75KW x 4P	1.9 A	1 DRIVE	SS - 05	3 SEC	1 SEC	1.9 A	
		2DRIVE	SS - 05	3 SEC	1 SEC	3.8 A	
1.0KW x 6P	3.1 A	1 DRIVE	SS - 05	3 SEC	1 SEC	2.1 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	4.2 A	
1.5KW x 4P	3.4 A	1 DRIVE	SS - 05	3 SEC	1 SEC	3.4 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	6.8 A	
1.5KW x 6P	3.5 A	1 DRIVE	SS - 05	3 SEC	1 SEC	3.5 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	7.0 A	
2.2KW x 4P	4.6 A	1 DRIVE	SS - 05	3 SEC	1 SEC	4.6 A	
		2 DRIVE	SS - 30	3 SEC	1 SEC	9.2 A	
0.8/0.4KW x 4/8P	2.22/2.05 A	1 DRIVE	SS - 05	3 SEC	1 SEC	2.22 A	
		2 DRIVE	SS - 05	3 SEC	1 SEC	2.05 A	
2.2KW x 6P	4.6 A	1 DRIVE	SS - 05	3 SEC	1 SEC	4.6 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	9.2 A	
3.7KW x 4P	7.3 A	1 DRIVE	SS - 30	3 SEC	1 SEC	7.3 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	14.6 A	

NOTE

1, 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.



THREE PHASE INDUCTION MOTOR DATA SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	HOISTING
2. MANUFACTURE	극동 호이스트 (주)
3. FRAME NUMBER	225 M
4. RATED POWER	33 KW x 6 P
5. RATED VOLTAGE AND FREQUENCY	220 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1 . 0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TEMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	1160 RPM
11. FULL LOAD CURRENT	126.6 A
12. LOCKED ROTOR CURRENT	760.6 A
13. MINIMUM STARTING VOLTAGE	200 V
14. EFFICIENCY AT 100% RATED LOAD	89.4 %
15. POWER FACTOR AT 100% RATED LOAD	76.5 %
16. FULL LOAD TORQUE	58.2 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E F C
19. TYPE OF BEARING	PL : 6313zz OPL : 6312zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPERATURE	40 °C
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

THREE PHASE INDUCTION MOTOR DATA SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	HOISTING
2. MANUFACTURE	극동 호이스트 (주)
3. FRAME NUMBER	225 M
4. RATED POWER	33 KW x 6 P
5. RATED VOLTAGE AND FREQUENCY	380 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1 . 0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TEMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	1160 RPM
11. FULL LOAD CURRENT	77.3 A
12. LOCKED ROTOR CURRENT	463.8 A
13. MINIMUM STARTING VOLTAGE	345 V
14. EFFICIENCY AT 100% RATED LOAD	89.4 %
15. POWER FACTOR AT 100% RATED LOAD	76.5 %
16. FULL LOAD TORQUE	58.2 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E F C
19. TYPE OF BEARING	PL : 6313zz OPL : 6312zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPERATURE	40 °C
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

THREE PHASE INDUCTION MOTOR DATA SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	HOISTING
2. MANUFACTURE	극동 호이스트 (주)
3. FRAME NUMBER	225 M
4. RATED POWER	33 KW x 6 P
5. RATED VOLTAGE AND FREQUENCY	440 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1 . 0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TEMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	1160 RPM
11. FULL LOAD CURRENT	66.3 A
12. LOCKED ROTOR CURRENT	379.3 A
13. MINIMUM STARTING VOLTAGE	400 V
14. EFFICIENCY AT 100% RATED LOAD	89.4 %
15. POWER FACTOR AT 100% RATED LOAD	76.5 %
16. FULL LOAD TORQUE	58.2 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E F C
19. TYPE OF BEARING	PL : 6313zz OPL : 6312zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPERATURE	40 °C
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

THREE PHASE INDUCTION MOTOR DATA SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	HOISTING
2. MANUFACTURE	극동 호이스트 (주)
3. FRAME NUMBER	225 M
4. RATED POWER	33 KW x 6 P
5. RATED VOLTAGE AND FREQUENCY	460 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1 . 0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TEMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	1160 RPM
11. FULL LOAD CURRENT	56.6 A
12. LOCKED ROTOR CURRENT	339.3 A
13. MINIMUM STARTING VOLTAGE	418 V
14. EFFICIENCY AT 100% RATED LOAD	89.4 %
15. POWER FACTOR AT 100% RATED LOAD	76.5 %
16. FULL LOAD TORQUE	58.2 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E F C
19. TYPE OF BEARING	PL : 6313zz OPL : 6312zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPERATURE	40 °C
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

THREE PHASE INDUCTION MOTOR DATA SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	HOISTING
2. MANUFACTURE	극동 호이스트 (주)
3. FRAME NUMBER	225 M
4. RATED POWER	33 KW x 6 P
5. RATED VOLTAGE AND FREQUENCY	480 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TEMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	1160 RPM
11. FULL LOAD CURRENT	54.2 A
12. LOCKED ROTOR CURRENT	325.14 A
13. MINIMUM STARTING VOLTAGE	436 V
14. EFFICIENCY AT 100% RATED LOAD	89.4 %
15. POWER FACTOR AT 100% RATED LOAD	76.5 %
16. FULL LOAD TORQUE	58.2 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E F C
19. TYPE OF BEARING	PL : 6313zz OPL : 6312zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPERATURE	40 °C
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

THREE PHASE INDUCTION MOTOR DATA SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	CREEP HOISTING
2. MANUFACTURE	극동 호이스트 (주)
3. FRAME NUMBER	112 M
4. RATED POWER	3.7 KW x 4 P
5. RATED VOLTAGE AND FREQUENCY	220 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TEMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	1690 RPM
11. FULL LOAD CURRENT	16.0 A
12. STARTING CURRENT AT RATED VOLTAGE	81.5 A
13. MINIMUM STARTING VOLTAGE	200 V
14. EFFICIENCY AT 100% RATED LOAD	80.0 %
15. POWER FACTOR AT 100% RATED LOAD	76.0 %
16. STARTING TORQUE	4.04 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6206zz OPL : 6206zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPERATURE	40 °C
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

THREE PHASE INDUCTION MOTOR DATA SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	CREEP HOISTING
2. MANUFACTURE	극동 호이스트 (주)
3. FRAME NUMBER	112 M
4. RATED POWER	3.7 KW x 4 P
5. RATED VOLTAGE AND FREQUENCY	380 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TEMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	1690 RPM
11. FULL LOAD CURRENT	9.3 A
12. STARTING CURRENT AT RATED VOLTAGE	56.8 A
13. MINIMUM STARTING VOLTAGE	345 V
14. EFFICIENCY AT 100% RATED LOAD	80.0 %
15. POWER FACTOR AT 100% RATED LOAD	76.0 %
16. STARTING TORQUE	4.04 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6206zz OPL : 6206zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPERATURE	40 °C
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

THREE PHASE INDUCTION MOTOR DATA SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	CREEP HOISTING
2. MANUFACTURE	극동 호이스트 (주)
3. FRAME NUMBER	112 M
4. RATED POWER	3.7 KW x 4 P
5. RATED VOLTAGE AND FREQUENCY	440 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1 . 0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TEMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	1690 RPM
11. FULL LOAD CURRENT	8.0 A
12. STARTING CURRENT AT RATED VOLTAGE	45.7 A
13. MINIMUM STARTING VOLTAGE	400 V
14. EFFICIENCY AT 100% RATED LOAD	80.0 %
15. POWER FACTOR AT 100% RATED LOAD	76.0 %
16. STARTING TORQUE	4.04 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6206zz OPL : 6206zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPERATURE	40 °C
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

THREE PHASE INDUCTION MOTOR DATA SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	CREEP HOISTING
2. MANUFACTURE	극동 호이스트 (주)
3. FRAME NUMBER	112 M
4. RATED POWER	3.7 KW x 4 P
5. RATED VOLTAGE AND FREQUENCY	460 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1 . 0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TEMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	1690 RPM
11. FULL LOAD CURRENT	7.7 A
12. STARTING CURRENT AT RATED VOLTAGE	44.65 A
13. MINIMUM STARTING VOLTAGE	418 V
14. EFFICIENCY AT 100% RATED LOAD	80.0 %
15. POWER FACTOR AT 100% RATED LOAD	76.0 %
16. STARTING TORQUE	4.04 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6206zz OPL : 6206zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPERATURE	40 °C
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

THREE PHASE INDUCTION MOTOR DATA SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	CREEP HOISTING
2. MANUFACTURE	극동 호이스트 (주)
3. FRAME NUMBER	112 M
4. RATED POWER	3.7 KW x 4 P
5. RATED VOLTAGE AND FREQUENCY	480 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1 . 0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TEMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	1690 RPM
11. FULL LOAD CURRENT	7.3 A
12. STARTING CURRENT AT RATED VOLTAGE	43.14 A
13. MINIMUM STARTING VOLTAGE	436 V
14. EFFICIENCY AT 100% RATED LOAD	80.0 %
15. POWER FACTOR AT 100% RATED LOAD	76.0 %
16. STARTING TORQUE	4.04 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6206zz OPL : 6206zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPERATURE	40 °C
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

THREE PHASE INDUCTION MOTOR DATA SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	TRAVERSING
2. MANUFACTURE	극동 호이스트 (주)
3. FRAME NUMBER	112 S
4. RATED POWER	2.2 KW x 4 P
5. RATED VOLTAGE AND FREQUENCY	220 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1 . 0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TEMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	1710 RPM
11. FULL LOAD CURRENT	10.0 A
12. STARTING CURRENT AT RATED VOLTAGE	56.0 A
13. MINIMUM STARTING VOLTAGE	200 V
14. EFFICIENCY AT 100% RATED LOAD	75.0 %
15. POWER FACTOR AT 100% RATED LOAD	77.0 %
16. STARTING TORQUE	2.56 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6206zz OPL : 6206zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPERATURE	40 °C
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

THREE PHASE INDUCTION MOTOR DATA SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	TRAVERSING
2. MANUFACTURE	극동 호이스트 (주)
3. FRAME NUMBER	112 S
4. RATED POWER	2.2 KW x 4 P
5. RATED VOLTAGE AND FREQUENCY	380 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATTING	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TEMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	1710 RPM
11. FULL LOAD CURRENT	5.8 A
12. STARTING CURRENT AT RATED VOLTAGE	43.2 A
13. MINIMUM STARTING VOLTAGE	345 V
14. EFFICIENCY AT 100% RATED LOAD	75.0 %
15. POWER FACTOR AT 100% RATED LOAD	77.0 %
16. STARTING TORQUE	2.56 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6206zz OPL :6206zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPERATURE	40 °C
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

THREE PHASE INDUCTION MOTOR DATA SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	TRAVERSING
2. MANUFACTURE	극동 호이스트 (주)
3. FRAME NUMBER	112 S
4. RATED POWER	2.2 KW x 4 P
5. RATED VOLTAGE AND FREQUENCY	440 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1 . 0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TEMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	1710 RPM
11. FULL LOAD CURRENT	5.0 A
12. STARTING CURRENT AT RATED VOLTAGE	29.7 A
13. MINIMUM STARTING VOLTAGE	400 V
14. EFFICIENCY AT 100% RATED LOAD	75.0 %
15. POWER FACTOR AT 100% RATED LOAD	77.0 %
16. STARTING TORQUE	2.56 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6206zz OPL : 6206zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPERATURE	40 °C
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

THREE PHASE INDUCTION MOTOR DATA SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	TRAVERSING
2. MANUFACTURE	극동 호이스트 (주)
3. FRAME NUMBER	112 S
4. RATED POWER	2.2 KW x 4 P
5. RATED VOLTAGE AND FREQUENCY	460 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1 . 0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TEMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	1710 RPM
11. FULL LOAD CURRENT	4.8 A
12. STARTING CURRENT AT RATED VOLTAGE	28.3 A
13. MINIMUM STARTING VOLTAGE	418 V
14. EFFICIENCY AT 100% RATED LOAD	75.0 %
15. POWER FACTOR AT 100% RATED LOAD	77.0 %
16. STARTING TORQUE	2.56 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6206zz OPL : 6206zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPERATURE	40 °C
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

THREE PHASE INDUCTION MOTOR DATA SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	TRAVERSING
2. MANUFACTURE	극동 호이스트 (주)
3. FRAME NUMBER	112 S
4. RATED POWER	2.2 KW x 4 P
5. RATED VOLTAGE AND FREQUENCY	480 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1 . 0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TEMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	1710 RPM
11. FULL LOAD CURRENT	4.6 A
12. STARTING CURRENT AT RATED VOLTAGE	27.1 A
13. MINIMUM STARTING VOLTAGE	436 V
14. EFFICIENCY AT 100% RATED LOAD	75.0 %
15. POWER FACTOR AT 100% RATED LOAD	77.0 %
16. STARTING TORQUE	2.56 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6206zz OPL : 6206zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPERATURE	40 °C
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

THREE PHASE INDUCTION MOTOR DATA SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	TRAVERSING
2. MANUFACTURE	KUK DONG HOIST CO., LTD.
3. FRAME NUMBER	112 S
4. RATED POWER	1.5 KW x 6 P
5. RATED VOLTAGE AND FREQUENCY	220 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TEMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	1140 RPM
11. FULL LOAD CURRENT	7.6 A
12. STARTING CURRENT AT RATED VOLTAGE	42.5 A
13. MINIMUM STARTING VOLTAGE	200 V
14. EFFICIENCY AT 100% RATED LOAD	74.5 %
15. POWER FACTOR AT 100% RATED LOAD	69.0 %
16. STARTING TORQUE	1.3 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6208zz OPL : 6206zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPERATURE	40 °C
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

THREE PHASE INDUCTION MOTOR DATA SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	TRAVERSING
2. MANUFACTURE	KUK DONG HOIST CO., LTD.
3. FRAME NUMBER	112 S
4. RATED POWER	1.5 KW x 6 P
5. RATED VOLTAGE AND FREQUENCY	380 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1 . 0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TEMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	1140 RPM
11. FULL LOAD CURRENT	4.4 A
12. STARTING CURRENT AT RATED VOLTAGE	36.8 A
13. MINIMUM STARTING VOLTAGE	342 V
14. EFFICIENCY AT 100% RATED LOAD	74.5 %
15. POWER FACTOR AT 100% RATED LOAD	69.0 %
16. STARTING TORQUE	1.3 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6208zz OPL : 6206zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPERATURE	40 °C
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

THREE PHASE INDUCTION MOTOR DATA SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	TRAVERSING
2. MANUFACTURE	KUK DONG HOIST CO., LTD.
3. FRAME NUMBER	112 S
4. RATED POWER	1.5 KW x 6 P
5. RATED VOLTAGE AND FREQUENCY	440 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1 . 0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TEMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	1140 RPM
11. FULL LOAD CURRENT	3.8 A
12. STARTING CURRENT AT RATED VOLTAGE	28.7 A
13. MINIMUM STARTING VOLTAGE	400 V
14. EFFICIENCY AT 100% RATED LOAD	74.5 %
15. POWER FACTOR AT 100% RATED LOAD	69.0 %
16. STARTING TORQUE	1.3 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6208zz OPL : 6206zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPERATURE	40 °C
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

THREE PHASE INDUCTION MOTOR DATA SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	TRAVERSING
2. MANUFACTURE	KUK DONG HOIST CO., LTD.
3. FRAME NUMBER	112 S
4. RATED POWER	1.5 KW x 6 P
5. RATED VOLTAGE AND FREQUENCY	460 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1 . 0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TEMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	1140 RPM
11. FULL LOAD CURRENT	3.6 A
12. STARTING CURRENT AT RATED VOLTAGE	26.8 A
13. MINIMUM STARTING VOLTAGE	400 V
14. EFFICIENCY AT 100% RATED LOAD	74.5 %
15. POWER FACTOR AT 100% RATED LOAD	69.0 %
16. STARTING TORQUE	1.3 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6208zz OPL : 6206zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPERATURE	40 °C
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

THREE PHASE INDUCTION MOTOR DATA SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	TRAVERSING
2. MANUFACTURE	KUK DONG HOIST CO., LTD.
3. FRAME NUMBER	112 S
4. RATED POWER	1.5 KW x 6 P
5. RATED VOLTAGE AND FREQUENCY	480 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1 . 0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TEMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	1140 RPM
11. FULL LOAD CURRENT	3.5 A
12. STARTING CURRENT AT RATED VOLTAGE	25.4 A
13. MINIMUM STARTING VOLTAGE	400 V
14. EFFICIENCY AT 100% RATED LOAD	74.5 %
15. POWER FACTOR AT 100% RATED LOAD	69.0 %
16. STARTING TORQUE	1.3 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6208zz OPL : 6206zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPERATURE	40 °C
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

불법복제 및 배포금지

E56B-2A3B-833B-B079

방송통신기자재등의 적합인증서

Certificate of Broadcasting and Communication Equipments

상호 또는 성명 <i>Trade Name or Applicant</i>	주식회사 케이지오토
기자재 명칭 <i>Equipment Name</i>	특정소출력 무선기기(데이터전송용 무선기기)
기본모델명 <i>Basic Model Number</i>	KG-R12MLHCCC
파생모델명 <i>Series Model Number</i>	KG-R12YLHCCA, KG-R12YLHCCC, KG-R12MLHAAA, KG-R12MLHCCA, KG-R12MLHCAA, KG-R12YLHCAA, KG-R12YLHAAA
인증번호 <i>Certification No.</i>	MSIP-CRM-KGO-KG-R12MLHCCC
제조사/제조국가 <i>Manufacturer/ Country of Origin</i>	주식회사 케이지오토 / 한국
인증연월일 <i>Date of Certification</i>	2015-06-24
기타 <i>Others</i>	

위 기자재는 「전파법」 제58조의2 제2항에 따라 인증되었음을 증명합니다.

It is verified that foregoing equipment has been certificated under the Clause 2, Article 58-2 of Radio Waves Act.


2015년(Year) 06월(Month) 24일(Date)

국립전파연구원장



Director General of National Radio Research Agency



* 인증 받은 방송통신기자재는 반드시 "적합성평가표시"를 부착하여 유통하여야 합니다.
위반시 과태료 처분 및 인증이 취소될 수 있습니다.




불법복제 및 배포금지

수신기


134.0 (브라켓 설치 간격)
115.0 (직접 설치 간격)
103.9
64.0 (직접 설치 간격)



송신기



MATERIAL		FINISH		REMARKS	
SCALE	1/1	DATE	2015.09.03	UNIT	mm
DRAWING BY	DESIGNED BY	CHECKED BY	APPROVED BY	MODEL	무선 리모콘 R12
S. W. HONG				PART NAME	외형도
KG AUTO CO., LTD.				DWG NO.	





제 2015 - 47427 호

안 전 인 증 서

(사업장명)

극동호이스트(주)

(소 재 지) 425-833 경기도 안산시 성곡동 630-2 반월공단 B-607-14

위 사업장에서 제조하는 아래의 품목이 산업안전보건법 제34조 및 같은 법 시행규칙 제58조의4제4항에 따른 안전인증 심사 결과 안전·보건기준에 적합하므로 안전인증표시의 사용을 인증합니다.

_____ 품 목 _____
호이스트

_____ 형식,모델(용량,등급)/인증번호 _____
KD5 (5Ton) /15-AQ2AC-00229

_____ 인 증 기 준 _____
고용노동부 고시 제2012 - 33호 (위험기계,기구 의무안전인증 고시)

_____ 인 증 조 건 _____

2015년 01월 27일



한국산업안전보건공단이사장

서 면 심 사 서 류

형식 번호 : KD5

극 동 호 이 스톱 (주)

工場 : 경기도 안산시 단원구 해봉로 119 (반월공단607-14)

電話 : 031) 491 - 5311

FAX : 031) 494 - 5315



반월공단



불법복제 및 배포금지
불법복제 및 배포금지

동 일 형 식 일 란 표

사업장명	극동호이스트㈜	개정일자 및 번호	2015년 01월 06일	인증번호		
형식 및 모델		동일 형식 인정범위 및 내역				
형식	모델	권상속도 (m/min)	횡행속도 (m/min)	양정(m)	횡행방식	비 고
KD5	KD5-L6-M	8.4	고속:24m/min 저속:16m/min 듀얼고속: 24/12m/min 듀얼저속: 16/8m/min	6	모터구동식	
	KD5-L9-M			9		
	KD5-L12-M			12		
	KD5-L18-M			18		
	KD5-L24-M			24		
	KD5-L30-M			30		
	KD5-L36-M			36		추가
	KD5-L40-M			40		추가
	KD5-L18-M-H			18		
	KD5-L24-M-H			24		
	KD5-L30-M-H			30		
	KD5-L36-M-H			36		추가
	KD5-L40-M-H			40		추가
	KD5-L6-S	4.2		6	정치식	
	KD5-L9-S			9		
	KD5-L12-S			12		
	KD5-L18-S			18		
	KD5-L24-S			24		
	KD5-L30-S			30		
	KD5-L36-S			36		추가
	KD5-L40-S			40		추가
	KD5-L6-P			6	수동구동식	
	KD5-L9-P			9		
	KD5-L12-P			12		
	KDC5-L6-M	5.6/0.56	고속:24m/min 저속:16m/min 듀얼고속: 24/12m/min 듀얼저속: 16/8m/min	6	모터구동식	
	KDC5-L9-M			9		
	KDC5-L12-M			12		
	KDC5-L18-M			18		
	KDC5-L24-M			24		
	KDC5-L30-M			30		
	KDC5-L36-M			36		추가
	KDC5-L40-M			40		추가
	KDC5-L18-M-H			18		
	KDC5-L24-M-H			24		
	KDC5-L30-M-H			30		
	KDC5-L36-M-H			36		추가
	KDC5-L40-M-H			40		추가
	KDC5-L6-S			6	정치식	
	KDC5-L9-S			9		
	KDC5-L12-S			12		
	KDC5-L18-S			18		
	KDC5-L24-S			24		
	KDC5-L30-S			30		
	KDC5-L36-S			36		추가
	KDC5-L40-S			40		추가
	KDC5-L6-P			6	수동구동식	
	KDC5-L9-P			9		
	KDC5-L12-P			12		

불법복제 및 배포금지
불법복제 및 배포금지

제 2012-BJ-0009 호



안 전 인 증 서

정호엔지니어링

경기도 광명시 노동사동 440-5

위 사업장에서 제조하는 아래의 품목이 산업안전보건법 제34조 및 같은 법 시행규칙 제58조의4제4항에 따른 안전인증 심사 결과 안전·보건기준에 적합하므로 안전인증표시의 사용을 인증합니다.

품 목
양중기용 과부하방지장치

형식·모델/용량·등급/인증번호

형식·모델
JDL-100

용량·등급
J-2

인증번호
12-AV2BJ-0009

인 증 기 준

방호장치 의무안전인증 고시(고용노동부고시 제2010-36호)

인 증 조 건

아래 주소에서 생산되는 제품에 한함.
정호엔지니어링, 경기도 광명시 노동사동 440-5

2012년 06월 11일

한국산업안전보건공단 이사장

2. 도 면



한국저작권위원회
안전보건공단

Copyright © 2017 Korea Copyright Commission



불법복제 및 배포금지
불법복제 및 배포금지

1) 기 계



불법복제 및 배포금지

SPECIFICATION			
RATED LOAD	5000	KG	
TESTING LOAD	6250	KG	
LIFT	12	M	
RATING	30	MIN	
HOISTING	H-HIGH	SPEED	8.4 M/MIN
		MOTOR	8.5 KW x 4 P
	HIGH	SPEED	5.6 M/MIN
		MOTOR	5.5 KW x 6 P
	LOW	SPEED	4.2 M/MIN
		MOTOR	4.2 KW x 8 P
WIRE ROPE	(6x37) ø16 x 2 FALLS		
POWER SOURCE	AC3ø 220V(380,440,460,480)V 60HZ		
COLOR	10 B 3/5		
WEIGHT	525 KG		





5											
4											
3	UPPER LIMIT S/W	SS41		1							
2	SAFETY LATCH	SPC		1							
1	EMERGENCY S/W	—		1							
NO.	DESCRIPTIONS	MTL	SET QTY	UNIT	TOTAL WEIGHT KG.	REMARKS					
PROJECT		DATE									
TITLE		20									
DRAWN		SCALE									
ARRANGEMENT DRAWING FOR HOIST		A3/20 /									
DESIGNED		REF DRAWING									
CHECKED											
APPROVED											
SHEET NO.		DRAWING NO.									
KUK DONG HOIST CO., LTD.		KD551200									




불법복제 및 배포금지

SPECIFICATION			
RATED LOAD	5000	KG	
TESTING LOAD	6250	KG	
LIFT	18	M	
RATING	30	MIN	
HOISTING	H-HIGH	SPEED	8.4 M/MIN
		MOTOR	8.5 KW x 4 P
	HIGH	SPEED	5.6 M/MIN
		MOTOR	5.5 KW x 6 P
	LOW	SPEED	4.2 M/MIN
		MOTOR	4.2 KW x 8 P
WIRE ROPE		(6x37) ø16 x 2 FALLS	
POWER SOURCE		AC3ø 220V(380,440,460,480)V 60HZ	
COLOR		10 B 3/5	
WEIGHT		6.30 KG	





4											
3	UPPER LIMIT S/W	SS400	1								
2	SAFETY LATCH	SPC	1								
1	EMERGENCY S/W	—	1								
NO.	DESCRIPTIONS	MTL	SET QTY	SET QTY	UNIT	TOTAL WEIGHT KG.	REMARKS				
PROJECT						DATE					
TITLE		KD5 - L18 - S				SCALE					
DRAWN		ARRANGEMENT DRAWING FOR HOIST				A3/20 /		REF DRAWING			
		DESIGNED CHECKED APPROVED									
 극동호이스트 주식회사 KUK DONG HOIST CO., LTD.		SHEET NO.				DRAWING NO.		KD5S1800			



불법복제 및 배포금지

SPECIFICATION			
RATED LOAD	5000 KG		
TESTING LOAD	6250 KG		
LIFT	24 M		
RATING	30 MIN		
HOISTING	H-HIGH	SPEED	8.4 M/MIN
		MOTOR	8.5 KW x 4 P
	HIGH	SPEED	5.6 M/MIN
		MOTOR	5.5 KW x 6 P
	LOW	SPEED	4.2 M/MIN
		MOTOR	4.2 KW x 8 P
WIRE ROPE	(6x37) ø16 x 2 FALLS		
POWER SOURCE	AC3ø 220V(380,440,460,480)V 60HZ		
COLOR	10 B 3/5		
WEIGHT	686 KG		





4												
3	UPPER LIMIT S/W	SS400	1									
2	SAFETY LATCH	SPC	1									
1	EMERGENCY S/W	—	1									
NO.	DESCRIPTIONS	MTL	SET QTY	UNIT	TOTAL WEIGHT KG.	REMARKS						
PROJECT		DATE										
TITLE		20 . . .										
DRAWN		SCALE										
		A3/20 /										
		REF DRAWING										
 극동호이스트 주식회사 KUK DONG HOIST CO., LTD.		SHEET NO.		DRAWING NO.								



불법복제 및 배포금지



SPECIFICATION			
RATED LOAD		5000	KG
TESTING LOAD		6250	KG
LIFT		12	M
RATING		30	MIN
HOISTING	SPEED	5.6 / 0.56	M/MIN
	MOTOR	5.5 / 1.0 KW x 6 P	
WIRE ROPE	(6x37) Ø16 x 2 FALLS		
POWER SOURCE	AC 3Ø 220V(380,440,480)V 60HZ		
COLOR	10 B 3/5		
WEIGHT	585 KG		



5											
4											
3	UPPER LIMIT S/W	SS41		1							
2	SAFETY LATCH	SPC		1							
1	EMERGENCY S/W	—		1							
NO.	DESCRIPTIONS	MTL	SET QTY	SET QTY	UNIT	TOTAL WEIGHT KG.	REMARKS				
PROJECT						DATE					
TITLE		KDC - L12 - S				20		SCALE			
DRAWN		ARRANGEMENT DRAWING FOR HOIST				A3/20 /		REF DRAWING			
		DESIGNED		CHECKED		APPROVED					
 KUK DONG HOIST CO., LTD.		KUK DONG HOIST CO., LTD.				SHEET NO.		DRAWING NO.			
								KDC5S1200			



불법복제 및 배포금지





SPECIFICATION		
RATED LOAD	5000	KG
TESTING LOAD	6250	KG
LIFT	18	M
RATING	30	MIN
HOISTING	SPEED	5.6 / 0.56 M/MIN
	MOTOR	5.5 / 1.0 KW x 6 P
WIRE ROPE		(6x37) Ø16 x 2 FALLS
POWER SOURCE	AC3Ø 220V(380,440,460,480)V 60Hz	
COLOR	10 B 3/5	
WEIGHT	890 KG	

[illegible]

불법복제 및 배포금지

SPECIFICATION			
RATED LOAD	5000	KG	
TESTING LOAD	6250	KG	
LIFT	24	M	
RATING	30	MIN	
	5.6 / 0.56	M/MIN	
HOISTING	5.5 / 1.0	KW x 6 P	
WIRE ROPE	(6x37) ϕ 16 x 2 FALLS		
POWER SOURCE	AC3 ϕ 220V(380,440,460,480)V	60HZ	
COLOR	10 B 3/5		
WEIGHT	750	KG	

[illegible]

국동호이스트 주식회사
KUK DONG HOIST CO., LTD.

2) 전 기



☐ 보호본딩회로의 연속성 확인

시험전선의 최소유효 단면적(mm²)	최고 전압 강하(V)
1.0	3.3
1.5	2.6
2.5	1.9
4.0	1.4
>6.0	1.0

① 보호본딩회로의 연속성의 검증은 PELV전원(50/60Hz)에서 최소 10A 이상의 전류를 10초 이상의 인가에 의한다.

시험은 PE단자와 보호본딩회로의 여러지점 사이에서 이루어진다.

② PE단자와 시험 지점 사이에서 측정된 전압은(표 참조) 값을 초과해서는 아니된다.

☐ 절연저항 시험

전원선과 보호본딩선 사이를 직류 500V로 측정된 절연저항 값은 1MΩ 이상이어야 한다.


☐ 내전압 시험

① PELV 전압에서 작동되도록 설계된 전기장치의 회로를 제외한 모든 회로와 보호본딩회로의 전선 사이에 1초 이상 지속되는 다음의 시험 전압에 견딜수 있어야 한다.

- 장치의 정격전압의 두배 또는 1,000V 중 큰값의 전압

② 이 시험을 견딜수 없도록 설계된 부품은 시험이 진행되기 전에 차단하여야 한다.

* MAIN POWER : AC 3PH 220V,380V,440V,460V,480 60Hz (LIFT 6, 9, 12, 18, 24, 30, 36, 40M)



 3 PHASE INDUCTION MOTOR			
	KW	P TYPE	TENV
VOLTS		V RATING	min
AMP.S		A AMP.TEMP	40°C
HEARTS		INS.CLASS	F
R.P.M		BEARING	
ROTOR	C	BEARING	
SERIAL.		DATE	
KUKDONG HOIST CO.,LTD			

MK	DATE						
REVISIONS							
	CHK.	APP.					
DRAWING TITLE			WIRE HOIST NAME PLATE				
CUSTOMER							
DRAWING	DESIGN	CHECKED	APPROVED	SCALE	DATE	ORDER NO.	
				NONE			
국동호이스트 주식회사 KUK DONG HOIST CO., LTD.				DWG. NO	KD5E0601		

1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20	
															NO		DESCRIPTION		CABLE SIZE	
															1		MAIN EARTH LINE		USER SCOPE	
															2		HOST POWER SOURCE WITH EARTH		VCT 10(8.0)SQ x 1C	
															3		HOISTING MOTOR WITH EARTH		VCT 10(8.0)SQ x 1C	

* CY CABLE 4C중 1C는 EARTH로 사용함.

- NOTE -

1. 권동기 외함, 제어반의 프레임 등은 접지하여 그 접지 저항은

400V 미만 : 100옴 이하임것.(3종 접지)

400V 이상 : 10옴 이하임것.(특 3종접지)

2. MAIN S/W BOX는 3종 접지 요.

등전위접지

1. 전기장비와 기계의 노출된 모든 도선부는 보호분리회로에 연결되어야 하여 허용한 접지저항성 기능이 유지되어야함.

2. 보호분리회로에는 개폐기, 과전류보호장치가 부착되지 않아야 함다.

시험대상 전선의 최소 유효단면적	최고전압강하(V)
1.0	3.3
1.5	2.6
2.5	1.6
4.0	1.4
>6.0	1.0

1. MAIN S/W BOX

2. HOISTING BOX


3. HOISTING MOTOR

USER SCOPE

KUKDONG SCOPE

DRAWING	DESIGN	CHECKED	APPROVED	SCALE	DATE	ORDER NO.
EARTH DETAILS DRAWING						
KUDONGHOIST CO., LTD.						2003.07.01
KUKDONG HOIST CO., LTD.						KD5S-EC000

1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
POWER CIRCUIT																			
TRAVELLING POWER SUPPLY SYSTEM																			
ADR'S NO.																			A1






1. EARTH : 제 3종접지 공시(400V 미만전압 : 100 OHM 이하)
즉 3종접지 공시(400V 이상전압 : 10 OHM 이하)

1. 전선의 색상은 다음과 같다.
- 1) 흑 색 : 교류 및 직류전원선
 - 2) 적 색 : 교류제어선
 - 3) 청 색 : 직류제어선
 - 4) 녹색 또는 녹색과 황색 혼용 : 접지
2. 표시등의 색상은 다음과 같다.
- 1) 적 색 : 비상
 - 2) 황 색 : 비정상
 - 3) 녹색 : 정상
 - 4) 청색 : 의무
 - 5) 흰색 : 중립
3. 조차 배선의 색상은 다음과 같다.
- 1) 적 색 : 비상
 - 2) 황 색 : 비정상
 - 3) 청 색 : 의무
 - 4) 흰색, 회색 또는 황색 : 지정된 의미없음

SELECTION	VOLTAGE	F11 F12	F13	MCCB100	TR10
	220V	2A	3A	53AF/50AT	220/110,120V 100VA
	380V	1A	3A	53AF/40AT	220/110,120V 100VA
	440V	1A	3A	33AF/30AT	220/110,120V 100VA
	460V	1A	3A	33AF/30AT	220/110,120V 100VA
	480V	1A	3A	33AF/30AT	220/110,120V 100VA

DRAWING	DESIGN	CHECKED	APPROVED	SCALE	DATE	ORDER NO.
				NONE		
KUK DONG HOIST CO., LTD.						KD5E001
주식회사						DWG. NO
KUK DONG HOIST CO., LTD.						
DIAGRAM						
MAIN POWER CIRCUIT 1						
DRAWING TITLE						
REVISIONS						
DATE	CHK.	APP.				




1. PROTECTION DEGREE ;
 - A. INDOOR TYPE : DUST PROOF
 - B. OUT DOOR TYPE : SPLASH PROOF
2. FINAL PAINTING COLOR (MUNSELL NO.)
 - A. IN SIDE : 10B 3/5
 - B. OUT SIDE : 10B 3/5
3. PAINTING THICKNESS : ABOVE 40 μ m
4. APPLICATION VOLTAGE : 220V, 380V, 440V, 460V, 480V
5. 제어용 전선 : 2.5sq KIV, H1V
6. 외함 기밀 구조는 다음과 같다.
 - 1) 외함 개방시 충전 부분이 차단되도록 한다.
 - 2) 외함 개방 후 충전되어있는 부분은 IP2X 이상의 직접 접촉 방호가 되어있을것.

SELECTION	HOIST CAPACITY	DESCRIPTION	IN DOOR			OUT DOOR			REMARK
			A	B	L	A	B	L	
	5 TON	NORMAL	360	170	790	360	170	810	
		CREEP	360	170	790	360	170	810	

[illegible]

1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
ADR'S NO.																			

NO	DESCRIPTION	SPECIFICATION	Q'TY	REMARK
1	CHASSIS PLATE		1	아 연 도 금
2	CABLE DUCT		1	
3	N.F.B	53AF/50AT	1	HOISTING
4	MAGNET CONTACTOR	DMC48C	1	MAIN MAG.
5	MAGNET CONTACTOR	DMC85C	2	HOISTING
6	SILICON RECTIFIER	SR-60	1	HOISTING
7	E.O.C.R	SS-30	1	HOISTING
8	FUSE	2 A	2	
9	FUSE	3 A	1	
10	TRANSFORMER	220V/110V,120V, 100VA	1	
11	UPPER LIMIT	AC 600V/75A	1	
12	TERMINAL BLOCK	60A,15A		
13	EARTH TERMINAL	3tx20x50	1	



NOTE 1. 전선의 색상은 다음과 같다.
1) 흑색 : 교류 및 직류 전원선
2) 적색 : 교류제어선
3) 청색 : 직류제어선
4) 녹색 또는 노색과 노랑 혼용 : 접지선
2. CABLE MATERIAL : KIV OR EQUIVALENT
MIN SIZE : 2.5sq
3. 제어용 전선 : 2.5mm KIV,HIV
4. 제자리 다스 변경 필요있음.
5. 외함 개방시 중전부본이 차단되도록 함.
1) 외함 개방후 중전부본이 차단되도록 함.
2) 외함 개방후 중전부본이 차단되도록 함.


NOTE
1. UPPER LIMIT LS-1,LS-2의 접점 허용 전류 용량 : AC 600V, 75A
2. POWER SOURCE : AC. 3φ 220V 60HZ
3. EARTH TERMINAL RESISTANCE : 0.018 Ω



DRAWING	DESIGN	CHECKED	APPROVED	SCALE	DATE	ORDER NO.
HOIST CONTROL BOX (소고속)						
ARRANGEMENT DRAWING						
KUK DONG HOIST CO., LTD.						
DWG. NO. KD5BA20S						
CUSTOMER						
DRAWING TITLE						
REVISIONS						
DATE						

1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
																			ADR'S NO.

NO	DESCRIPTION	SPECIFICATION	Q'TY	REMARK
1	CHASSIS PLATE		1	아 연 도 금
2	CABLE DUCT	—	1	
3	N.F.B	53AF/40AT	1	HOISTING
4	MAGNET CONTACTOR	DMC48C	1	MAIN MAG.
5	MAGNET CONTACTOR	DMC65C	2	HOISTING
6	SILICON RECTIFIER	SR-60	1	HOISTING
7	E.O.C.R	SS-30	1	HOISTING
8	FUSE	2 A	2	
9	FUSE	3 A	1	
10	TRANSFORMER	220V/110V,120V, 100VA	1	
11	UPPER LIMIT	AC 600V/75A	1	
12	TERMINAL BLOCK	60A,15A		
13	EARTH TERMINAL	3tx20x50	1	



NOTE

- UPPER LIMIT LS-1,LS-2의 전압 허용 전류 용량 : AC 600V, 75A
- POWER SOURCE : AC. 3Ø 220V 60HZ
- EARTH TERMINAL RESISTANCE : 0.018 Ω

NOTE 1. 전선의 색상은 다음과 같다.


- 색상 : 교류 및 직류 전원선
 - 색상 : 교류 제어선
 - 색상 : 직류 제어선
 - 녹색 또는 녹색과 노랑 혼합 : 접지선
2. CABLE MATERIAL : KIV OR EQUIVALENT
MIN SIZE : 2.5sq
- 제어용 전선 : 2.5mm KIV,HIV
 - 제어시 다소 변경 될수있음.
 - 외함 개방구조는 다음과 같음것.
 - 외함 개방시 충전부분이 차단되도록 함것.
- 2) 외함 개방후 충전되어있는 부분은 IP2X 이상의 직접 접촉 방호가 되어있음것.



CUSTOMER	DRAWING		DESIGN	CHECKED	APPROVED	SCALE	DATE	ORDER NO.
	HOIST CONTROL BOX (고구)					NONE		
DRAWING TITLE	ARRANGEMENT DRAWING		KUK DONG HOIST CO., LTD.		DWG. NO	KD5BA21S		
DATE	REVISIONS	CHK. APP.						

1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
																			ADR'S NO.

NO	DESCRIPTION	SPECIFICATION	Q'TY	REMARK
1	CHASSIS PLATE		1	이전 도금
2	CABLE DUCT	-	1	
3	N.F.B	53AF/40AT	1	HOISTING
4	MAGNET CONTACTOR	DMC4BC	1	MAIN MAG.
5	MAGNET CONTACTOR	DMC65C	2	HOISTING
6	SILICON RECTIFIER	SR-60	1	HOISTING
7	E.O.C.R	SS-30	1	HOISTING
8	FUSE	2 A	2	
9	FUSE	3 A	1	
10	TRANSFORMER	220V/110V,120V, 100VA	1	
11	UPPER LIMIT	AC 600V/75A	1	
12	TERMINAL BLOCK	60A,15A		
13	EARTH TERMINAL	3t×20×50	1	




NOTE 1. 전선의 색상은 다음과 같다.
1) 흑색 : 교류 및 직류전원선
2) 적색 : 교류제어선
3) 청색 : 직류제어선
4) 녹색 또는 녹색과 노랑 혼용 : 접지선
2. CABLE MATERIAL : KIV OR EQUIVALENT
3. 제어용 전선 : 2.5mm KIV,HIV
4. 제직시 다소 변경 될수있음.
5. 외함 개방후 충전부분이 차단되도록 할것.
1) 외함 개방후 충전부분이 차단되도록 할것.
2) 외함 개방후 충전부분이 차단되도록 할것.

NOTE
1. UPPER LIMIT LS-1,LS-2의 접점 허용 전류 용량 : AC 600V, 75A
2. POWER SOURCE : AC. 3φ 220V 60HZ
3. EARTH TERMINAL RESISTANCE : 0.018 Ω



DRAWING		DESIGN	CHECKED	APPROVED	SCALE	DATE	ORDER NO.
HOIST CONTROL BOX (제어)					NONE		
ARRANGEMENT DRAWING		KUK DONG HOIST CO., LTD.			DWG. NO	KDSBA22S	
CUSTOMER	DRAWING TITLE	CHK.	APP.				
REVISIONS							
MK	DATE						


1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
POWER CIRCUIT																			
HOISTING MOTION																			
ADR'S NO.																			B1



SPECIFICATION SYMBOLS	HOISTING POWER	HOISTING MOTOR	DC MAG. BRAKE	NO. FUSE BREAKER	TRANSFORMER	FUSE	MAIN MAGNET	MAGNET CONTACTOR	UPPER LIMIT	ELECTRIC OVER CURRENT RELAY	SILICON RECTIFIER	LOAD LIMITER	CABLE
DESCRIPTION	HOIST	IM 10	DB10	MCCB100	TR 1	F11, F12	M1	M101, M102	LS-I, LS-II	EOCR100	RF100	LOAD LIMITER	C20-01
	5TON AC 3PH 220V 60Hz	8.5KW x 4P	DC 100V	ABS-53AF/50AT	220/110, 120V/100VA	2A	DMC48C	DMC85C	AC 800V 75A	SS-30	SR-60	JDL-100	VFC1 10sqx4c
	5TON AC 3PH 220V 60Hz	5.5KW x 6P	DC 100V	ABS-53AF/40AT	220/110, 120V/100VA	2A	DMC48C	DMC85C	AC 800V 75A	SS-30	SR-60	JDL-100	VFC1 10sqx4c
	5TON AC 3PH 220V 60Hz	4.2KW x 8P	DC 100V	ABS-53AF/40AT	220/110, 120V/100VA	2A	DMC48C	DMC48C	AC 800V 75A	SS-30	SR-60	JDL-100	VFC1 10sqx4c
SELECTION MAKER				LS	SHINHAN	-		DONG-A	KUKDONG	APPROVED	SCALE	DATE	ORDER NO.
		CUSTOMER											
		DRAWING TITLE	HOISTING POWER & CONTROL CIRCUIT										
		CHK.	DIAGRAM										
REVISIONS			 KUDONGHOIST CO., LTD.										
DATE			DWG. NO										
NO.			KD5E2ZS										


1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
																			ADR'S NO.

NO	DESCRIPTION	SPECIFICATION	Q'TY	REMARK
1	CHASSIS PLATE		1	이 현 도 급
2	CABLE DUCT	-	1	
3	N.F.B	53AF/40AT	1	HOISTING
4	MAGNET CONTACTOR	DMC40C	1	MAIN MAG.
5	MAGNET CONTACTOR	DMC48C	2	HOISTING
6	SILICON RECTIFIER	SR-60	1	HOISTING
7	E.O.C.R	SS-30	1	HOISTING
8	FUSE	1 A	2	
9	FUSE	3 A	1	
10	TRANSFORMER	380V/110V,120V, 100VA	1	
11	UPPER LIMIT	AC 600V/75A	1	
12	TERMINAL BLOCK	60A,15A		
13	EARTH TERMINAL	3tx20x50	1	



NOTE 1. 전선의 색상은 다음과 같다.
 1) 흑색 : 교류 및 직류전원선
 2) 적색 : 교류제어선
 3) 청색 : 직류제어선
 4) 녹색 또는 노색과 노랑 혼용 : 접지선
 2. CABLE MATERIAL : KIV OR EQUIVALENT
 MIN SIZE : 2.5sq
 3. 제어용 전선 : 2.5mm KIV,HIV
 4. 제지시 다소 변경 될수있음.
 5. 외함 개방구조는 다음과 같음.
 1) 외함 개방시 충전부분이 차단되도록 함.
 2) 외함 개방후 충전되어있는 부분은 IP2X 이상의 직접 접촉 방호가 되어있음.


NOTE
 1. UPPER LIMIT LS-1,LS-2의 접점 허용 전류, 용량. : AC 600V, 75A
 2. POWER SOURCE : AC. 3ø 380V 60HZ
 3. EARTH TERMINAL RESISTANCE : 0.018 Ω



MK	DATE	REVISIONS	CHK.	APP.	CUSTOMER	DRAWING TITLE	ORDER NO.
						HOIST CONTROL BOX (소고속) ARRANGEMENT DRAWING	
						 국동호이스트 주식회사 KUK DONG HOIST CO., LTD.	DWG. NO KD5BA30S

1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
ADR'S NO.																			

NO	DESCRIPTION	SPECIFICATION	Q'TY	REMARK
1	CHASSIS PLATE		1	아 연 도 금
2	CABLE DUCT	-	1	
3	N.F.B	33AF/30AT	1	HOISTING
4	MAGNET CONTACTOR	DMC40C	1	MAIN MAG.
5	MAGNET CONTACTOR	DMC48C	2	HOISTING
6	SILICON RECTIFIER	SR-60	1	HOISTING
7	E.O.C.R	SS-30	1	HOISTING
8	FUSE	1 A	2	
9	FUSE	3 A	1	
10	TRANSFORMER	380V/110V,120V, 100VA	1	
11	UPPER LIMIT	AC 600V/75A	1	
12	TERMINAL BLOCK	60A,15A		
13	EARTH TERMINAL	3tx20x50	1	



NOTE 1. 전선의 색상은 다음과 같다.
 1) 흑색 : 그라운드 전선
 2) 적색 : 그라운드 전선
 3) 청색 : 그라운드 전선
 4) 녹색 또는 노란색 : 노란색 : 접지선
 2. CABLE MATERIAL : KIV OR EQUIVALENT
 MIN SIZE : 2.5sq
 3. 제어용 전선 : 2.5mm KIV,HIV
 4. 제작성 다소 변경 될수있음.
 5. 외함 개방시 충전부분이 차단되도록 함.
 1) 외함 개방시 충전부분이 차단되도록 함.
 2) 외함 개방후 충전되어있는 부분은 IP2X 이상의 직접 접촉 방호가 되어있음.


NOTE
 1. UPPER LIMIT LS-1,LS-2의 접점 허용 전류 용량 : AC 600V, 75A
 2. POWER SOURCE : AC. 3φ 380V 60HZ
 3. EARTH TERMINAL RESISTANCE : 0.018 Ω



DRAWING	DESIGN	CHECKED	APPROVED	SCALE	DATE	ORDER NO.
HOIST CONTROL BOX (고속) ARRANGEMENT DRAWING						
KUK DONG HOIST CO., LTD.						KD58A31S
CUSTOMER						
DRAWING TITLE						
DATE	REVISIONS	CHK.	APP.			

1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20.
ADR'S NO.																			

NO	DESCRIPTION	SPECIFICATION	Q'TY	REMARK
1	CHASSIS PLATE		1	아 연 도 금
2	CABLE DUCT	-	1	
3	N.F.B	33AF/20AT	1	HOISTING
4	MAGNET CONTACTOR	DMC40C	1	MAIN MAG.
5	MAGNET CONTACTOR	DMC48C	2	HOISTING
6	SILICON RECTIFIER	SR-60	1	HOISTING
7	E.O.C.R	SS-30	1	HOISTING
8	FUSE	1 A	2	
9	FUSE	3 A	1	
10	TRANSFORMER	380V/110V,120V, 100VA	1	
11	UPPER LIMIT	AC 600V/75A	1	
12	TERMINAL BLOCK	60A,15A		
13	EARTH TERMINAL	3tx20x50	1	



NOTE

- UPPER LIMIT LS-1,LS-2의 직접 허용 전류 용량 : AC 600V, 75A
- POWER SOURCE : AC. 3ø 380V 60HZ
- EARTH TERMINAL RESISTANCE : 0.018 Ω


- NOTE 1. 전선의 색상은 다음과 같다.
- 색상 : 교류 및 직류전원선
 - 색상 : 교류제어선
 - 색상 : 직류제어선
 - 색상 또는 번호와 노랑 혼용 : 접지선
2. CABLE MATERIAL : KIV OR EQUIVALENT
MIN SIZE : 2.5sq
- 제어용 전선 : 2.5mm KIV,HIV
 - 제어시 다스 변경 필수있음.
 - 외함 개방시 중전부분이 차단되도록 함것.
 - 외함 개방시 중전부분이 차단되도록 함것.
- 2) 외함 개방후 중전부분이 차단되도록 함것.



DRAWING	DESIGN	CHECKED	APPROVED	SCALE	DATE	ORDER NO.
				NONE		
HOIST CONTROL BOX (저속)						
ARRANGEMENT DRAWING						
CUSTOMER						
DRAWING TITLE						
REVISIONS						
DATE						
CHK APP.						
KUK DONG HOIST CO., LTD.						K05BA32S

불법복제 및 배포금지
불법복제 및 배포금지

1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	19	20
POWER CIRCUIT HOISTING MOTION																		
ADR'S NO. B1																		



SPECIFICATION SYMBOLS	HOISTING POWER	HOISTING MOTOR	DC MAG. BREAKER	NO FUSE BREAKER	TRANSFORMER	FUSE	MAIN MAGNET	MAGNET CONTACTOR	UPPER LIMIT	ELECTRIC OVER CURRENT RELAY	SILICON RECTIFIER	LOAD LIMITER	CABLE
DESCRIPTION	HOIST	IM 10	DB10	MCCB100	TR 1	F1, F12	M1	M101, M102	LS-1, LS-11	EOCR100	RF100	LDL-100	C20-01
	5TON AC 3PH 380V 60Hz	8.5KW x 4P	DC 100V	ABS-53AF/40AT	380/110, 120V, 100VA	1A	DMC40C	DMC48C	AC 600V 75A	SS-30	SR-60	JD-100	VFCT 6.0sqx4c
	5TON AC 3PH 380V 60Hz	5.5KW x 6P	DC 100V	ABE-33AF/30AT	380/110, 120V, 100VA	1A	DMC40C	DMC48C	AC 600V 75A	SS-30	SR-60	JD-100	VFCT 6.0sqx4c
	5TON AC 3PH 380V 60Hz	4.2KW x 8P	DC 100V	ABE-33AF/20AT	380/110, 120V, 100VA	1A	DMC48C	DMC48C	AC 600V 75A	SS-30	SR-60	JD-100	VFCT 6.0sqx4c
SELECTION MAKER			KUKDONG	LS	SHINHAN	-		DONG-A	KUKDONG	ASECO		JUNGHO	DONGIL
CUSTOMER													
DRAWING TITLE													
REVISIONS													
DATE													
CHK.													
APP.													
DWG. NO.													KD5E32S

KD
KUK DONG HOIST CO., LTD.



- 1) ସମ୍ପଦ : ଗୁଣାଯାଇଥିବାର
- 2) ସମ୍ପଦ : ଗୁଣାଯାଇ
- 3) ସମ୍ପଦ : ଗୁଣାଯାଇ
- 4) ସମ୍ପଦ : ଗୁଣାଯାଇ

2. CABLE MATERIAL : -KIV OR EQUIVALENT

3. 제어용 전선 : 2.5mm KIV.HIV
MIN SIZE : 2.5sq

4. 제각시 다스릴수있음.

이항구장사주공공

1) 외함 개방시 용전부분이 차단되도록 함.

2) 외함 개형후 충전되어있는 부분은 IP2X 이상의 직접 전격 방호가 되어있을 것.


NO	DESCRIPTION	SPECIFICATION	Q'TY	REMARK
1	CHASSIS PLATE		1	아 연 도 금
2	CABLE DUCT	-	1	
3	N.F.B	33AF/30AT	1	HOISTING
4	MAGNET CONTACTOR	DMC32C	1	MAIN MAG.
5	MAGNET CONTACTOR	DMC48C	2	HOISTING
6	SILICON RECTIFIER	SR-60	1	HOISTING
7	E.O.C.R	SS-30	1	HOISTING
8	FUSE	1 A	2	
9	FUSE	3 A	1	
10	TRANSFORMER	440V/110V,120V, 100VA	1	
11	UPPER LIMIT	AC 600V/75A	1	
12	TERMINAL BLOCK	60A,15A		
13	EARTH TERMINAL	3tx20x50	1	

NOTE

1. UPPER LIMIT LS-1, LS-2의 접점 허용 전류 용량 : AC 600V, 75A
2. POWER SOURCE : AC, 3 ϕ 440V 60HZ
3. EARTH TERMINAL RESISTANCE : 0.018 Ω

[illegible]

NO	DESCRIPTION	SPECIFICATION	Q'TY	REMARK
1	CHASSIS PLATE		1	아 연 도 금
2	CABLE DUCT	-	1	
3	N.F.B	33AF/30AT	1	HOISTING
4	MAGNET CONTACTOR	DMC32C	1	MAIN MAG.
5	MAGNET CONTACTOR	DMC48C	2	HOISTING
6	SILICON RECTIFIER	SR-60	1	HOISTING
7	E.O.C.R	SS-30	1	HOISTING
8	FUSE	1 A	2	
9	FUSE	3 A	1	
10	TRANSFORMER	440V/110V,120V, 100VA	1	
11	UPPER LIMIT	AC 600V/75A	1	
12	TERMINAL BLOCK	60A,15A		
13	EARTH TERMINAL	3tx20x50	1	



NOTE 1. 전선의 색상은 다음과 같다.

- 1) 흑색 : 교류 및 직류전원선
- 2) 적색 : 교류제어선
- 3) 청색 : 직류제어선
- 4) 녹색 또는 녹색과 노랑 혼용 : 접지선

2. CABLE MATERIAL : KIV OR EQUIVALENT

MIN SIZE : 2.5sq

3. 제어용 전선 : 2.5mm KIV,HIV

4. 제하시 디스 변경 필수있음.

5. 외함 개방구조는 다음과 같을것.

1) 외함 개방시 충전부분이 차단되도록 할것.

2) 외함 개방후 충전되어있는 부분은 IP2X 이상의 직접 접촉 방호가 되어있을것.

NOTE


1. UPPER LIMIT LS-1,LS-2의 감전 허용 전류 용량 : AC 600V, 75A
2. POWER SOURCE : AC. 3Φ 440V 60HZ
3. EARTH TERMINAL RESISTANCE : 0.018 Ω



DRAWING		DESIGN	CHECKED	APPROVED	SCALE	DATE	ORDER NO.
HOIST CONTROL BOX (고속)					NONE		
ARRANGEMENT DRAWING		국동호이스트 주식회사 KUK DONG HOIST CO., LTD.			DWG. NO	K058A41S	
CUSTOMER	DRAWING TITLE	CHK.	APP.	REVISIONS	DATE		

1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
																			ADR'S NO.

NO	DESCRIPTION	SPECIFICATION	Q'TY	REMARK
1	CHASSIS PLATE		1	아 현 도 급
2	CABLE DUCT	-	1	
3	N.F.B	33AF/20AT	1	HOISTING
4	MAGNET CONTACTOR	DMC22C	1	MAIN MAG.
5	MAGNET CONTACTOR	DMC48C	2	HOISTING
6	SILICON RECTIFIER	SR-60	1	HOISTING
7	E.O.C.R	SS-30	1	HOISTING
8	FUSE	1 A	2	
9	FUSE	3 A	1	
10	TRANSFORMER	440V/110V,120V, 100VA	1	
11	UPPER LIMIT	AC 600V/75A	1	
12	TERMINAL BLOCK	60A,15A		
13	EARTH TERMINAL	3tx20x50	1	




NOTE 1. 전선의 색상은 다음과 같다.
1) 흑색 : 교류 및 직류전원선
2) 적색 : 교류제어선
3) 청색 : 직류제어선
4) 녹색 또는 노란색 : 노랑 콘용 ; 접지선
2. CABLE MATERIAL : KIV OR EQUIVALENT
MIN SIZE : 2.5sq
3. 제어용 전선 : 2.5mm KIV,HIV
4. 제라시 디스 변경 필수있음.
5. 외함 개방구조는 다음과 같음것.
1) 외함 개방시 승전부분이 차단되도록 함것.
2) 외함 개방후 용전되어있는 부분은 IP2X 이상의 차폐 접속 필요가 되어있음것.

NOTE
1. UPPER LIMIT LS-1,LS-2의 접점 허용 전류 용량 : AC 600V, 75A
2. POWER SOURCE : AC. 3φ 440V 60HZ
3. EARTH TERMINAL RESISTANCE : 0.018 Ω




Δ	Δ	Δ	Δ	Δ	Δ	Δ	Δ	Δ	Δ	Δ	Δ	Δ	Δ	Δ	Δ	Δ	Δ	Δ	Δ
CUSTOMER										DRAWING TITLE									
HOIST CONTROL BOX (저속)										ARRANGEMENT DRAWING									
REVISIONS										CHK. APP.									
DATE										MKT									
KUK DONG HOIST CO., LTD.										KDSBA42S									
DWG. NO										ORDER NO.									



1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
																			ADR'S NO.

NO	DESCRIPTION	SPECIFICATION	Q'TY	REMARK
1	CHASSIS PLATE		1	아 연 도 금
2	CABLE DUCT	-	1	
3	N.F.B	33AF/30AT	1	HOISTING
4	MAGNET CONTACTOR	DMC32C	1	MAIN MAG.
5	MAGNET CONTACTOR	DMC48C	2	HOISTING
6	SILICON RECTIFIER	SR-60	1	HOISTING
7	E.O.C.R	SS-30	1	HOISTING
8	FUSE	1 A	2	
9	FUSE	3 A	1	
10	TRANSFORMER	460V/110V,120V, 100VA	1	
11	UPPER LIMIT	AC 600V/75A	1	
12	TERMINAL BLOCK	60A,15A		
13	EARTH TERMINAL	3tx20x50	1	



NOTE 1. 전선의 색상은 다음과 같다.
 1) 흑색 : 고압용 직류전원선
 2) 적색 : 교류제어선
 3) 청색 : 교류제어선
 4) 녹색 또는 노색과 노랑 혼합 : 접지선

2. CABLE MATERIAL : KIV OR EQUIVALENT
 MIN SIZE : 2.5sq

3. 제어용 전선 : 2.5mm KIV,HIV

4. 제지시 다소 변경 될수있음.

5. 외함 개방시 중전부분이 차단되도록 함것.

1) 외함 개방시 중전부분이 차단되도록 함것.
 2) 외함 개방후 중전되어있는 부분은 IP2X 이상의 직접 접촉 방호가 되어있을것.


NOTE
 1. UPPER LIMIT LS-1,LS-2의 직접 허용 전류 용량 : AC 600V, 75A
 2. POWER SOURCE : AC 3φ 460V 60HZ
 3. EARTH TERMINAL RESISTANCE : 0.018 Ω



MK DATE REVISIONS CHK. APP.	CUSTOMER		DRAWING	DESIGN	CHECKED	APPROVED	SCALE	DATE	ORDER NO.
			HOIST CONTROL BOX (호이스)				NONE		
			ARRANGEMENT DRAWING						
			KUK DONG HOIST CO., LTD. 국동호이스트 주식회사		DWG. NO		KD5BA50S		

1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20.
ADR'S NO.																			

NO	DESCRIPTION	SPECIFICATION	Q'TY	REMARK
1	CHASSIS PLATE		1	아 연 도 금
2	CABLE DUCT	-	1	
3	N.F.B	33AF/30AT	1	HOISTING
4	MAGNET CONTACTOR	DMC32C	1	MAIN MAG.
5	MAGNET CONTACTOR	DMC48C	2	HOISTING
6	SILICON RECTIFIER	SR-60	1	HOISTING
7	E.O.C.R	SS-30	1	HOISTING
8	FUSE	1 A	2	
9	FUSE	3 A	1	
10	TRANSFORMER	460V/110V,120V, 100VA	1	
11	UPPER LIMIT	AC 600V/75A	1	
12	TERMINAL BLOCK	60A,15A		
13	EARTH TERMINAL	3tx20x50	1	



NOTE 1. 전선의 색상은 다음과 같다.

- 1) 흑색 : 교류 및 직류전선
- 2) 적색 : 교류제어선
- 3) 청색 : 직류제어선
- 4) 녹색 또는 노색과 노랑 혼합 : 접지선

2. CABLE MATERIAL : KIV OR EQUIVALENT

3. 제어용 전선 : 2.5mm KIV,HIV

4. 제지시 다소 변경 될수있음.

5. 외함 개방구조는 다음과 같음.

1) 외함 개방시 중전부분이 차단되도록 함.

2) 외함 개방후 중전부분이 차단되는 부분은 IP2X 이상의 직접 접촉 방호가 되어있음.

NOTE

1. UPPER LIMIT LS-1,LS-2의 변형 허용 전류 용량 : AC 600V, 75A

2. POWER SOURCE : AC, 3 ϕ 460V 60HZ

3. EARTH TERMINAL RESISTANCE : 0.018 Ω




DRAWING	DESIGN	CHECKED	APPROVED	SCALE	DATE	ORDER NO.
HOIST CONTROL BOX (고크)						
ARRANGEMENT DRAWING						
CUSTOMER						
DRAWING TITLE						
DATE	REVISIONS	CHK.	APP.	DWG. NO		KD5BA51S



극동호이스트 주식회사
KUK DONG HOIST CO., LTD.

1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20.
																			ADR'S NO.

NO	DESCRIPTION	SPECIFICATION	Q'TY	REMARK
1	CHASSIS PLATE		1	아 연 도 금
2	CABLE DUCT	-	1	
3	N.F.B	33AF/20AT	1	HOISTING
4	MAGNET CONTACTOR	DMC22C	1	MAIN MAG.
5	MAGNET CONTACTOR	DMC48C	2	HOISTING
6	SILICON RECTIFIER	SR-60	1	HOISTING
7	E.O.C.R	SS-30	1	HOISTING
8	FUSE	1 A	2	
9	FUSE	3 A	1	
10	TRANSFORMER	460V/110V,120V, 100VA	1	
11	UPPER LIMIT	AC 600V/75A	1	
12	TERMINAL BLOCK	60A,15A		
13	EARTH TERMINAL	3t×20×50	1	




NOTE 1. 전선의 색상은 다음과 같다.
 1) 흑색 : 교류 및 직류전원선
 2) 적색 : 교류제어선
 3) 청색 : 직류제어선
 4) 녹색 또는 녹색과 노랑 혼용 : 접지선
 2. CABLE MATERIAL : KIV OR EQUIVALENT
 MIN SIZE : 2.5sq
 3. 제어용 전선 : 2.5mm KIV,HIV
 4. 제라시 다소 변경 될수있음.
 5. 외함 개량구조는 다음과 같을것.
 1) 외함 개량시 충전부분이 차단되도록 할것.
 2) 외함 개량후 충전되어있는 부분은 IP2X 이상의 직접 접촉 방호가 되어있을것.

NOTE
 1. UPPER LIMIT LS-1,LS-2의 한점 허용 전류 용량 : AC 600V, 75A
 2. POWER SOURCE : AC. 3ø 460V 60HZ
 3. EARTH TERMINAL RESISTANCE : 0.018 Ω




DRAWING		DESIGN	CHECKED	APPROVED	SCALE	DATE	ORDER NO.
HOIST CONTROL BOX (저속)					NONE		
ARRANGEMENT DRAWING		국동호이스트 주식회사 KUK DONG HOIST CO., LTD.			DWG. NO	KDSBA52S	
CUSTOMER	DRAWING TITLE	CHK.	APP.				
	REVISIONS						
DATE							



1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
ADR'S NO.																			

NO	DESCRIPTION	SPECIFICATION	Q'TY	REMARK
1	CHASSIS PLATE		1	아 연 도 판
2	CABLE DUCT	-	1	
3	N.F.B	33AF/30AT	1	HOISTING
4	MAGNET CONTACTOR	DMC32C	1	MAIN MAG.
5	MAGNET CONTACTOR	DMC48C	2	HOISTING
6	SILICON RECTIFIER	SR-60	1	HOISTING
7	E.O.C.R	SS-30	1	HOISTING
8	FUSE	1 A	2	
9	FUSE	3 A	1	
10	TRANSFORMER	480V/110V,120V, 100VA	1	
11	UPPER LIMIT	AC 600V/75A	1	
12	TERMINAL BLOCK	60A,15A		
13	EARTH TERMINAL	3tX20X50	1	



NOTE 1. 전선의 색상은 다음과 같다.

- 1) 녹색 : 교류 및 직류전선
- 2) 적색 : 교류제어선
- 3) 청색 : 직류제어선
- 4) 녹색 또는 녹색과 노랑 혼용 : 접지선

2. CABLE MATERIAL : KIV OR EQUIVALENT

3. 제어용 전선 : 2.5mm KIV,HIV

4. 제라시 다스 변경 필수있음.

5. 외함 개방구조는 다음과 같을것.

- 1) 외함 개방시 충전부분이 차단되도록 할것.
- 2) 외함 개방후 충전되어있는 부분은 IP2X 이상의 직접 접촉 방호가 되어있을것.

NOTE


- 1. UPPER LIMIT LS-1,LS-2의 직접 허용 전류 용량 : AC 600V, 75A
- 2. POWER SOURCE : AC. 3φ 480V 60HZ
- 3. EARTH TERMINAL RESISTANCE : 0.018 Ω



DRAWING		DESIGN	CHECKED	APPROVED	SCALE	DATE	ORDER NO.
HOIST CONTROL BOX (호이스)					NONE		
ARRANGEMENT DRAWING							
KUK DONG HOIST CO., LTD.					DWG. NO		KD5BA60S
DATE	REVISIONS	CHK	APP.				

1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
																			ADR'S NO.

NO	DESCRIPTION	SPECIFICATION	Q'TY	REMARK
1	CHASSIS PLATE		1	아 연 도 금
2	CABLE DUCT	-	1	
3	N.F.B	33AF/30AT	1	HOISTING
4	MAGNET CONTACTOR	DMC32C	1	MAIN MAG.
5	MAGNET CONTACTOR	DMC48C	2	HOISTING
6	SILICON RECTIFIER	SR-60	1	HOISTING
7	E.O.C.R	SS-30	1	HOISTING
8	FUSE	1 A	2	
9	FUSE	3 A	1	
10	TRANSFORMER	480V/110V,120V, 100VA	1	
11	UPPER LIMIT	AC 600V/75A	1	
12	TERMINAL BLOCK	60A,15A		
13	EARTH TERMINAL	3tx20x50	1	




NOTE 1. 전선의 역상은 다음과 같다.
1) 흑색 : 교류 및 직류전원선
2) 적색 : 교류제어선
3) 청색 : 직류제어선
4) 녹색 또는 녹색과 노랑 혼용 : 접지선
2. CABLE MATERIAL : KIV OR EQUIVALENT
MIN SIZE : 2.5sq
3. 제어용 전선 : 2.5mm KIV,HIV
4. 제라시 디스 변경 필수있음.
5. 외함 개방구조는 다음과 같음.
1) 외함 개방시 중진부분이 차단되도록 함.
2) 외함 개방후 충전되어있는 부분은 IP2X 이상의 직접 접촉 방호가 되어있음.

NOTE
1. UPPER LIMIT LS-1,LS-2의 전평 허용 전류 용량 : AC 600V, 75A
2. POWER SOURCE : AC 3ø 480V 60HZ
3. EARTH TERMINAL RESISTANCE : 0.018 Ω



DRAWING	DESIGN	CHECKED	APPROVED	SCALE	DATE	ORDER NO.
HOIST CONTROL BOX (고속)						
ARRANGEMENT DRAWING						
CUSTOMER						
DRAWING TITLE						
REVISIONS	CHK	APP				
DATE						
KUDONGHOIST KUK DONG HOIST CO., LTD.						KD58A61S

1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20.
---	---	---	---	---	---	---	---	---	----	----	----	----	----	----	----	----	----	----	-----



NOTE 1. 전선의 예상은 다를수 있다.

- 1) 實名 : 古事類聚 卷之四
- 2) 實名 : 古事類聚 卷之四
- 3) 實名 : 古事類聚 卷之四

2. CABLE MATERIAL : KIV OR EQUIVALENT

3. 제어용 전선 : 2.5mm KIV.HIV


4. 제작시 다소 변경 될수있음.

5. 외환 개방구조는 디플레이션과 감축시킨다.


1) 외항 기항시 응진부분이 차단되도록 함것.

2) 외환 개방후 증권거래소는 부록된 IPX 이상의 외환 잔액 확보가 되어있을지.

[illegible]




1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
EM, STOP										CONTROL CIRCUIT									
OVER LOAD BUZZER										UP									
DOWN										ADR'S NO.									
										A5									



SPECIFICATION SYMBOLS		UPPER LIMIT		PENDANT P.B. S/W		LOAD LIMITER		LIMIT SWITCH	
DESCRIPTION		LS-1		E.S.B		LOAD LIMITER		LS-301,302	
		AC 600V 3A		250V 3A		JDL-100		HY - W904	
		AC 600V 3A		250V 3A		JDL-100		HY - W904	
MAKER		KUNHUNG		KG-AUTO		JUNGHO		HANYOUNG	
CHECKED		APPROVED		SCALE		DATE		ORDER NO.	
				NONE					
DRAWING		DESIGN		DWG. NO		KD5E002S			
CUSTOMER		DRAWING TITLE		REVISIONS		CHK		APP.	
		MAIN POWER 2 & CONTROL CIRCUIT							
		DIAGRAM							
KUK DONG HOIST CO., LTD.									

KD



* IP : 55 이상 *

개상	구분	조각버튼	표시등
좌측		비상	비상
중앙		비정상	비정상
우측		정상	정상
정중		무	무
좌측, 하측, 좌측		지정된의미없음	기타


No	Description	MATERIAL	QTY	SIZE	UNIT WEIGHT(kg)	TOTAL REMARK
Scales Pro- jection	W8 SANGLES	DWG. K.M.S90	CHK.	APP.		PUSH BUTTON SWITCH & EMERGENCY BUTTON SWITCH
Mass	Kg			Title		KG-H02EA
(KD) KUK DONG HOIST CO., LTD.			DWG No,			

KDC5-L6(9, 12, 18, 24, 30, 36, 40)-S
KDC5-L6(9, 12) - P



안전보건공단

* MAIN POWER : AC 3PH 220V,380V,440V,460V,480 60Hz (LIFT 5, 9, 12, 18, 24, 30, 36, 40M)



ELECTRIC WIRE ROPE HOIST			
MODEL		RATING	
CAPACITY	Kg	LIFT	m
HOIST SPEED	m/min	POWER SOURCE	V Hz
HOIST MOTOR	Kw P	AMP. S R&T HOIST	A
TRAV. SPEED	m/min	AMP. S R&T TRAV.	A
TRAV. MOTOR	Kw P	WIRE ROPE	Ø
WIDTH OF RAIL	mm	WEIGHT	Kg
DATE		SERIAL	
KUKDONG HOIST CO.,LTD			

		3 PHASE INDUCTION MOTOR	
KW	P TYPE	TENV	
VOLTS	V RATING	min	
AMP.S	A AMP. TEMP	40°C	
HEARTS	INS.CLASS	F	
R.P.M	BEARING		
ROTOR	C		
SERIAL	DATE		
KUKDONG HOIST CO.,LTD			

3 PHASE INDUCTION MOTOR	
KW	TYPE TENV
VOLTS	VIRATING min
AMP S	A AMP. TEMP 40C
HEARTS	INS.CLASS F
R.P.M	BEARING
ROTOR	C BEARING
SERIAL	DATE

KUKDONG HOIST CO.,LTD

☐								
☐								
☐								
☐								
☐								
DATE								
REVISIONS								
CHECK								
DRAWING TITLE	WIRE HOIST NAME PLATE							
CUSTOMER								
DRAWING								
DESIGN								
CHECKED								
APPROVED								
SCALE	NONE							
DWG. NO.	KD5E0601							
DATE								
ORDER NO.								

[illegible]

NO	DESCRIPTION	CABLE SIZE
1	MAIN EARTH LINE	USER SCOPE
2	MOIST POWER SOURCE WITH EARTH	VCTF 10(&O)50 x 1C
3	HASTING MOTOR WITH EARTH	VCT 10(&O)50 x 1C
4	CRIMP MOTOR WITH EARTH	VCT 4,050 x 1C

* CV CABLE 4C중 1C는 EARTH도 사용함.

- NOTE -

1. 전동기 외함, 제어반의 프레임 등은 접지하여 그 접지 저항은
400V 미만 : 100옴을 이하일것.(3점 점)
400V 이상 : 10옴을 이하일것.(각 3점점지)
- 2.MAIN S/W BOX는 3점 접지 요.


ಇದೇ ಸಂಚಿಕೆಯಲ್ಲಿ

1. 전기장벽화 기체의 노출된 모든 도전부는 보호분말층으로 인장되어야 하며 적절한 접지연속성 기능이 유지되어야함.
2. 보호분말층에서는 기체기, 차단류도오정치가 부족되지 않아야 한다.


시원口상 전신의 최소 유포단면적	최고전압강하(V)
1.0	3.3
1.5	2.6
2.5	1.6
4.0	1.4
>6.0	1.0

— — — — — USER SCOPE

KUKDONG SCOPE

[illegible]

1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
POWER CIRCUIT																			
TRAVELLING POWER SUPPLY SYSTEM																			
ADR'S NO.																			A1



SELECTION	VOLTAGE	F11 F12	F13	MCCB100	TR10
	220V	2A	3A	53AF/40AT	220/110,120V 100VA
	380V	1A	3A	33AF/30AT	380/110,120V 100VA
	440V	1A	3A	33AF/30AT	440/110,120V 100VA
	460V	1A	3A	33AF/30AT	460/110,120V 100VA
	480V	1A	3A	33AF/30AT	480/110,120V 100VA

POWER SOURCE
AC 3ø 60Hz

1. EARTH : 제 3종접지 공사(400V 미만전압 : 100 OHM 이하)
즉 3종접지 공사(400V 이상전압 : 10 OHM 이하)

1. 전선의 색상은 다음과 같다.
- 1) 흑색 : 교류 및 직류 전원선
 - 2) 적색 : 교류 제어선
 - 3) 청색 : 교류 제어선
 - 4) 녹색 또는 녹색과 황색 혼용 : 접지
2. 표시등의 색상은 다음과 같다.
- 1) 적색 : 비상
 - 2) 황색 : 비정상
 - 3) 녹색 : 정상
 - 4) 청색 : 의무
 - 5) 흰색 : 광립
3. 조차 버튼의 색상은 다음과 같다.
- 1) 적색 : 비상
 - 2) 황색 : 비정상
 - 3) 청색 : 의무
 - 4) 흰색, 회색 또는 흑색 : 지정된 의미없음

DRAWING	DESIGN	CHECKED	APPROVED	SCALE	DATE	ORDER NO.
				NONE		
KUK DONG HOIST CO., LTD.						KDC5E001
DRAWING TITLE						
MAIN POWER CIRCUIT 1						
DIAGRAM						
DATE	REVISIONS	CHK.	APP.			

1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
---	---	---	---	---	---	---	---	---	----	----	----	----	----	----	----	----	----	----	----

극동 호이스트
제한하중
5000K

사용전압 : 000V
조작전압 : 000V

NO	DESCRIPTION	MT'L	REMARKS
1	PANEL CASE	SPC	1.6t
2	PANEL COVER	SPC	1.6t
3	HINGE	PUR'	
4	CLAMP	PUR'	
5	SPONGE	PUR'	

IN DOOR

OUT DOOR

N O T E

1.PROTECTION DEGREE ;
A. INDOOR TYPE : DUST PROOF
B. OUT DOOR TYPE : SPLASH PROOF

2.FINAL PAINTING COLOR (MUNSELL NO.)
A. IN SIDE : 10B 3/5
B. OUT SIDE : 10B 3/5

3.PAINTING THICKNESS : ABOVE 40 um


4.APPLICATION VOLTAGE : 220V,380V,440V,460V,480V

5.제어용 전선 : 2.5sq KIV,HIV

6.외함 거방 구조는 다음과 같다.
1) 외함 거방시 충전부분이 차단되도록 한다.
2) 외함 거방 후 충전되어있는 부분은 IP2X 이상의
직접 접촉 방호가 되어있을것.

SELECTION	HOIST CAPACITY	DESCRIPTION	IN DOOR			OUT DOOR			REMARK
			A	B	L	A	B	L	
	5 TON	NORMAL	360	170	790	360	170	810	
		CREEP	360	170	790	360	170	810	

DRAWING	DESIGN	CHECKED	APPROVED	SCALE	DATE	ORDER NO.
극동호이스트 주식회사 KUK DONG HOIST CO., LTD. DWG. NO KDC5EB00						

1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
																			ADR'S NO.
NO	DESCRIPTION	SPECIFICATION														Q'TY	REMARK		
1	CHASSIS PLATE															1	아 연 토 금		
2	CABLE DUCT	-														1			
3	N.F.B	53AF/40AT														1	HOISTING		
4	MAGNET CONTACTOR	DMC48C														1	MAIN MAG.		
5	MAGNET CONTACTOR	DMC65C														2	HOISTING		
6	MAGNET CONTACTOR	DMC22C														2	CREEP HOIST		
7	SILICON RECTIFIER	SR-60														1	HOISTING		
8	SILICON RECTIFIER	SR-30														1	CREEP HOIST		
9	E.O.C.R	SS-30														1	HOISTING		
10	E.O.C.R	SS-30														1	CREEP HOIST		
11	FUSE	2 A														2			
12	FUSE	3 A														1			
13	TRANSFORMER	220V/110V(120V), 100VA														1			
14	UPPER LIMITER	AC 600V, 75A														1	LS-1,2		
15	TERMINAL BLOCK	60A,15A																	
16	EARTH TERMINAL	3t×20×50														1			


NOTE 1. 전선의 색상은 다음과 같다.
 1) 흑색 : 교류 및 직류 전원선으로 5) 정색 : 직류 제어선으로
 2) 적색 : 교류 제어선
 3) 파랑색 : 외부 전원선에서 공급되는 연동장치 제어피로
 4) 녹색 또는 노색과 황색 혼용 : 접지선
 2. CABLE MATERIAL : KIV OR EQUIVALENT
 3. 제어용 전선 : 2.5mm KIV,HIV
 4. 제지시 다소 변경 될수있음.
 5. 외함 개방시 중전부분이 차단되도록 함것.
 1) 외함 개방시 중전부분이 차단되도록 함것.
 2) 외함 개방 후 중전되어있는 부분은 IP2X 이상의 차단 접합 부분이 되어있을것.

NOTE
 1. UPPER LIMIT LS-1,LS-2의 전원 허용 전류 용량 : AC 600V, 75A
 2. POWER SOURCE : AC. 3φ 220V 60HZ
 3. EARTH TERMINAL RESISTANCE : 0.018Ω



DRAWING	DESIGN	CHECKED	APPROVED	SCALE	DATE	ORDER NO.
 KUK DONG HOIST CO., LTD.						KDC5BA21
CREEP HOIST CONTROL BOX						
ARRANGEMENT DRAWING						
CUSTOMER						
DRAWING TITLE						
REVISIONS	CHK.	APP.				
DATE						

[illegible]



1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
---	---	---	---	---	---	---	---	---	----	----	----	----	----	----	----	----	----	----	----

NOTE

- UPPER LIMIT LS-1,LS-2의 접점 허용 전류 용량 : AC 600V, 75A
- POWER SOURCE : AC. 3φ 380V 60HZ
- EARTH TERMINAL RESISTANCE : 0.018Ω

NOTE 1. 전선의 색상은 다음과 같다.

- 1) 녹색 : 교류 및 직류 전원선
- 2) 적색 : 교류제어선
- 3) 주황색 : 외부 전원에서 공급되는 컨트롤러 제어회로
- 4) 녹색 또는 노색과 황색 혼용 : 접지선

2. CABLE MATERIAL : KIV OR EQUIVALENT

3. 제어용 전선 : 2.5mm KIV,HIV
MIN SIZE : 2.5sq

4. 제작시 다소 변경 될수있음.

5. 외함 개방구조는 다음과 같음.

1) 외함 개방시 충전부분이 차단되도록 함.

2) 외함 개방후 충전되어있는 부분은 IP2X 이상의 직접 접촉 방호가 되어있음.

NO	DESCRIPTION	SPECIFICATION	Q'TY	REMARK
1	CHASSIS PLATE		1	아 연 도 금
2	CABLE DUCT	-	1	
3	N.F.B	33AF/30AT	1	HOISTING
4	MAGNET CONTACTOR	DMC32C	1	MAIN MAG.
5	MAGNET CONTACTOR	DMC48C	2	HOISTING
6	MAGNET CONTACTOR	DMC22C	2	CREEP HOIST
7	SILICON RECTIFIER	SR-60	1	HOISTING
8	SILICON RECTIFIER	SR-30	1	CREEP HOIST
9	E.O.C.R	SS-30	1	HOISTING
10	E.O.C.R	SS-05	1	CREEP HOIST
11	FUSE	1 A	2	
12	FUSE	3 A	1	
13	TRANSFORMER	380V/110V(120V), 100VA	1	
14	UPPER LIMITER	AC 600V, 75A	1	LS-1,2
15	TERMINAL BLOCK	60A,15A		
16	EARTH TERMINAL	3tx20x50	1	

NOTE

- UPPER LIMIT LS-1,LS-2의 접점 허용 전류 용량 : AC 600V, 75A
- POWER SOURCE : AC. 3φ 380V 60HZ
- EARTH TERMINAL RESISTANCE : 0.018Ω

NOTE 1. 전선의 색상은 다음과 같다.

- 1) 녹색 : 교류 및 직류 전원선
- 2) 적색 : 교류제어선
- 3) 주황색 : 외부 전원에서 공급되는 컨트롤러 제어회로
- 4) 녹색 또는 노색과 황색 혼용 : 접지선

2. CABLE MATERIAL : KIV OR EQUIVALENT

3. 제어용 전선 : 2.5mm KIV,HIV
MIN SIZE : 2.5sq

4. 제작시 다소 변경 될수있음.

5. 외함 개방구조는 다음과 같음.

1) 외함 개방시 충전부분이 차단되도록 함.

2) 외함 개방후 충전되어있는 부분은 IP2X 이상의 직접 접촉 방호가 되어있음.

DRAWING	DESIGN	CHECKED	APPROVED	SCALE	DATE	ORDER NO.
				NONE		

CREEP HOIST CONTROL BOX


ARRANGEMENT DRAWING

국동호이스트 주식회사
KUK DONG HOIST CO., LTD.

DWG. NO KDC5BA31

[illegible]

1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
POWER CIRCUITS																			
HOISTING MOTION										CREEP HOIST MOTION									
ADR'S NO.										B1									



SPECIFICATION SYMBOLS	HOISTING POWER	HOISTING MOTOR	CREEP MOTOR	DC MAG. BRAKE	NO FUSE BREAKER	TRANSFORMER	FUSE	MAGNET CONTACTOR	UPPER LIMIT	ELECTRIC OVER CURRENT RELAY	SILICON RECTIFIER	LOAD LIMITER	CABLE			
	DESCRIPTION	HOIST	IM 10	IM 11	DB10, 11	MCCB100	TR 1 280V/110V/240V, 100VA	F11, F12 F13	M101, M102 M111, M112	LS-I, LS-II	EOCR100	EOCR110	RF100	RF110	LOAD LIMITER	C20-01
SELECTION	STON AC 3PH 380V 60Hz	5.5KW x 6P	1.0KNx6P	DC 100V	DBE-33AF/30A		1A 3A	DOC-48P	DOC-22P	SS-30	SS-05	SR-80	SR-30	JUL-100	VFCT 6.0sq4c	
	MAKER	KUKDONG			DAERYUK	SHINHAN	-	DAERYUK	KUKDONG	ASECO			JUNGH0	DONGIL		
MK	DATE	REVISIONS	CHK.	APP.	DRAWING TITLE	CUSTOMER	CREEP HOISTING POWER CONTROL CIRCUIT									
							DWG. NO	KDC5E32								

1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19
---	---	---	---	---	---	---	---	---	----	----	----	----	----	----	----	----	----	----

NOTE


1. 전선의 역성은 다음과 같다.
- 1) 흑색 : 교류 및 직류 전원선로
- 2) 적색 : 교류제어선
- 3) 주황색 : 외부 전원선에서 공급되는 연동장치 제어회로
- 4) 녹색 또는 녹색과 황색 혼합 : 접지선

2. CABLE MATERIAL : KIV OR EQUIVALENT

MIN SIZE : 2.5sq


3. 제어용 전선 : 2.5mm KIV,HIV
4. 제작성시 다스 변경 될수있음.
5. 외함 개발구조는 다음과 같을것.

- 1) 외함 개발시 중전부분이 차단되도록 할것.
- 2) 외함 개발후 통전되어있는 부분은 IPXX 이상의 차단 전류 보호가 되어있을것

[illegible]

[illegible]

1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
POWER CIRC...																			
HOISTING MOTION										CREEP HOIST MOTION									
										ADR'S NO.									
										B1									



SPECIFICATION SYMBOLS	HOISTING POWER	HOISTING MOTOR	CREEP MOTOR	DC MAG. BRAKE	NO FUSE BREAKER	TRANSFORMER	FUSE	MAGNET CONTACTOR	UPPER LIMIT	ELECTRIC OVER CURRENT RELAY	SILICON RECTIFIER	LOAD LIMITER	CABLE	
	HOIST	IM 10	IM 11	DB10, 11	MCCB100	TR 1	F11,F12	M101,M102	LS-I, LS-II	EOCR100	RF100	LOAD LIMITER	C20-01	
SELECTION	5TON AC 3PH 440V 60Hz	5.5KW x 6P	1.0KWAx6P	DC 100V	ABE-33AF/30A	440/110V120V100VA	1A 3A	DMC48C	AC 600V 75A	SS-30	SR-60	JDL-100	VFCT 6.0sqx4c	
	MAKER	KUKDONG			LS	SHINHAN	-	DONG-A		ASECO		JUNGHO	DONGIL	
DATE	REVISIONS	CHK.	APP.	CUSTOMER		CREEP HOISTING POWER CONTROL CIRCUIT								
				DRAWING		TITLE								
				TITLE		DWG. NO								
WK				KUKDONG HOIST CO., LTD.		KUK DONG HOIST CO., LTD.								KDC5E42

1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
---	---	---	---	---	---	---	---	---	----	----	----	----	----	----	----	----	----	----	----

NO	DESCRIPTION	SPECIFICATION	Q'TY	REMARK
1	CHASSIS PLATE		1	아 연 도 판
2	CABLE DUCT		1	
3	N.F.B	33AF/30AT	1	HOISTING
4	MAGNET CONTACTOR	DMC32C	1	MAIN MAG.
5	MAGNET CONTACTOR	DMC48C	2	HOISTING
6	MAGNET CONTACTOR	DMC22C	2	CREEP HOIST
7	SILICON RECTIFIER	SR-60	1	HOISTING
8	SILICON RECTIFIER	SR-30	1	CREEP HOIST
9	E.O.C.R	SS-30	1	HOISTING
10	E.O.C.R	SS-05	1	CREEP HOIST
11	FUSE	1 A	2	
12	FUSE	3 A	1	
13	TRANSFORMER	460V/110V(120V), 100VA	1	
14	UPPER LIMITER	AC 600V, 75A	1	LS-1,2
15	TERMINAL BLOCK	60A,15A		
16	EARTH TERMINAL	3tx20x50	1	

NOTE 1. 전선의 색상은 다음과 같다.
 1) 흑색 : 교류 및 직류 전원선으로
 2) 적색 : 교류제어선
 3) 주황색 : 외부 전원에서 공급되는 연동장치 제어회로
 4) 녹색 또는 녹색과 황색 혼용 : 접지선
 2. CABLE MATERIAL : KIV OR EQUIVALENT
 3. 제어용 전선 : 2.5mm KIV,HIV
 4. 제작성 디스 변경 필수있음.
 5. 외함 개방시 충전부분이 차단되도록 함것.
 1) 외함 개방시 충전부분이 차단되도록 함것.
 2) 외함 개방후 충전되어있는 부분은 IP2X 이상의 직접 접촉 방호가 되어있음것.

NOTE

1. UPPER LIMIT LS-1,LS-2의 접점 허용 전류 용량 : AC 600V, 75A

2. POWER SOURCE : AC 3ø 460V 60HZ

3. EARTH TERMINAL RESISTANCE : 0.018Ω

REVISIONS

NO	DATE	REVISIONS	CHK.	APP.

CREEP HOIST CONTROL BOX

ARRANGEMENT DRAWING

CUSTOMER

국동호이스트 주식회사

KUK DONG HOIST CO., LTD.

ORDER NO.

KDC58A51


The diagram illustrates a complex power control system for a creep hoist. It features two primary motor circuits: one for the main hoisting motion (IM10) and another for the creep motion (IM11). Each motor circuit is equipped with a dedicated fuse, a transformer, and a contactor. Safety and protection elements are integrated throughout, including upper and lower limit switches, a load limiter, and DC magnetic brakes. The system also includes various interlocking mechanisms and sensors to ensure safe and controlled operation. The diagram is a detailed technical drawing showing the electrical connections and components for the creep hoist motion.

ADR'S NO.

NO	DESCRIPTION	SPECIFICATION	Q'TY	REMARK
1	CHASSIS PLATE		1	아 연 도 금
2	CABLE DUCT	-	1	
3	N.F.B	33AF/30AT	1	HOISTING
4	MAGNET CONTACTOR	DMC32C	1	MAIN MAG.
5	MAGNET CONTACTOR	DMC48C	2	HOISTING
6	MAGNET CONTACTOR	DMC22C	2	CREEP HOIST
7	SILICON RECTIFIER	SR-60	1	HOISTING
8	SILICON RECTIFIER	SR-30	1	CREEP HOIST
9	E.O.C.R	SS-30	1	HOISTING
10	E.O.C.R	SS-05	1	CREEP HOIST
11	FUSE	1 A	2	
12	FUSE	3 A	1	
13	TRANSFORMER	480V/110V(120V), 100VA	1	
14	UPPER LIMITER	AC 600V, 75A	1	LS-1,2
15	TERMINAL BLOCK	60A,15A		
16	EARTH TERMINAL	3tx20x50	1	

NOTE 1. 전선의 색상과 같다.

- 1) 폭역 : 교류 및 직류 전원선으로
 - 2) 폭역 : 교류 제어선
 - 3) 주광선 : 외부 전원에서 공급되는 연동장치 제어회로
 - 4) 폭역 또는 폭역과 광역 혼용 : 접지선
2. CABLE MATERIAL : KIV OR EQUIVALENT
MIN SIZE : 2.5sq
3. 제어용 전선 : 2.5mm KIV,HIV
 4. 제작시 다스 변경 필수있음.
 5. 외함 개방구조는 다용과 같음것.
 - 1) 외함 개방시 충전부분이 차단되도록 함것.
 - 2) 외함 개방후 충전되어있는 부분은 IP2X 이상의 적접 접촉 방호가 되어있음것.




- NOTE
1. UPPER LIMIT LS-1,LS-2의 접점 허용 전류 용량 : AC 600V, 75A
 2. POWER SOURCE : AC. 3φ 480V 60HZ
 3. EARTH TERMINAL RESISTANCE : 0.018Ω





DRAWING	DESIGN	CHECKED	APPROVED	SCALE	DATE	ORDER NO.
CREEP HOIST CONTROL BOX						
ARRANGEMENT DRAWING						
KUD KUK DONG HOIST CO., LTD.						KDC58A61
DATE	REVISIONS	CHK.	APP.			

[illegible]

1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
										POWER CIR.									
HOISTING MOTION										CREEP HOIST MOTION									
(A1/A06)(A1/A05)(A1/A07)(A1/A02)																			
∇ ∇ ∇ ∇ ∇																			
										ADR'S NO. BT									

[illegible]





* IP : 55 이상

구분	조사대상	조사비트	표시등
화상	적색	비상	비상
	황색	비정상	비정상
	녹색	정상	정상
	청색	의무	의무
화상, 화상-촉각		지정된의미없음	기타

NO	DESCRIPTION	MATERIAL	QTY	SIZE	UNIT WEIGHT(Kg)		REMARK
Scale	NG						PUSH BUTTON SWITCH & EMERGENCY BUTTON SWITCH KG-H02EA
Pro- tection	3 ANGLES						
Mass	Kg						
 KUK DONG HOIST CO., LTD.				DWG No.			

불법복제 및 배포금지
불법복제 및 배포금지

THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	HOISTING
2. MANUFACTURE	극동호이스트 (주)
3. FRAME NUMBER	132 M
4. RATED POWER	5.5 KW x 6 P
5. RATED VOLTAGE AND FREQUENCY	220 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATTING	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 ℃
10. FULL LOAD SPEED	1160 RPM
11. FULL LOAD CURRENT	28.2 A
12. LOCKED ROTOR CURRENT	155.1 A
13. MINIMUM STARTING VOLTAGE	200 V
14. EFFICIENCY AT 100% RATED LOAD	77 %
15. POWER FACTOR AT 100% RATED LOAD	66.4 %
16. FULL LOAD TORQUE	11.59 KGM
17. SITE ALTTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6307zz OPL : 6207zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPURE	40 ℃
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	HOISTING
2. MANUFACTURE	극동호이스트 (주)
3. FRAME NUMBER	132 M
4. RATED POWER	5.5 KW x 6 P
5. RATED VOLTAGE AND FREQUENCY	380 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATTING	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 ℃
10. FULL LOAD SPEED	1160 RPM
11. FULL LOAD CURRENT	16.3 A
12. LOCKER ROTOR CURRENT	89.8 A
13. MINIMUM STARTING VOLTAGE	342 V
14. EFFICIENCY AT 100% RATED LOAD	77 %
15. POWER FACTOR AT 100% RATED LOAD	66.4 %
16. FULL LOAD TORQUE	11.59 KG.M
17. SITE ALTTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6307zz OPL : 6207zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPURE	40 ℃
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	HOISTING
2. MANUFACTURE	극동호이스트 (주)
3. FRAME NUMBER	132 M
4. RATED POWER	5.5 KW x 6 P
5. RATED VOLTAGE AND FREQUENCY	440 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATTING	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 ℃
10. FULL LOAD SPEED	1160 RPM
11. FULL LOAD CURRENT	14.1 A
12. LOCKED ROTOR CURRENT	77.6 A
13. MINIMUM STARTING VOLTAGE	400 V
14. EFFICIENCY AT 100% RATED LOAD	77 %
15. POWER FACTOR AT 100% RATED LOAD	66.4 %
16. FULL LOAD TORQUE	11.59 KG.M
17. SITE ALTTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6307zz OPL : 6207zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPURE	40 ℃
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	HOISTING
2. MANUFACTURE	극동호이스트 (주)
3. FRAME NUMBER	132 L
4. RATED POWER	5.5 KW x 6 P
5. RATED VOLTAGE AND FREQUENCY	460 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 ℃
10. FULL LOAD SPEED	1160 RPM
11. FULL LOAD CURRENT	13.5 A
12. LOCKED ROTOR CURRENT	74.3 A
13. MINIMUM STARTING VOLTAGE	418 V
14. EFFICIENCY AT 100% RATED LOAD	77 %
15. POWER FACTOR AT 100% RATED LOAD	66.4 %
16. FULL LOAD TORQUE	11.59 KG.M
17. SITE ALTTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6307zz OPL : 6207zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPURE	40 ℃
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

불법복제 및 배포금지
불법복제 및 배포금지

THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	HOISTING
2. MANUFACTURE	극동호이스트 (주)
3. FRAME NUMBER	132 M
4. RATED POWER	5.5 KW x 6 P
5. RATED VOLTAGE AND FREQUENCY	480 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATTING	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 ℃
10. FULL LOAD SPEED	1160 RPM
11. FULL LOAD CURRENT	12.9 A
12. LOCKED ROTOR CURRENT	71.2 A
13. MINIMUM STARTING VOLTAGE	436 V
14. EFFICIENCY AT 100% RATED LOAD	77 %
15. POWER FACTOR AT 100% RATED LOAD	66.4 %
16. FULL LOAD TORQUE	11.59 KG.M
17. SITE ALTTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6307zz OPL : 6207zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPURE	40 ℃
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

불법복제 및 배포금지
불법복제 및 배포금지

THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	HOISTING
2. MANUFACTURE	극동호이스트 (주)
3. FRAME NUMBER	132 M
4. RATED POWER	4.2 KW x 8 P
5. RATED VOLTAGE AND FREQUENCY	220 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATTING	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 ℃
10. FULL LOAD SPEED	860 RPM
11. FULL LOAD CURRENT	23.0 A
12. LOCKED ROTOR CURRENT	136.2 A
13. MINIMUM STARTING VOLTAGE	200 V
14. EFFICIENCY AT 100% RATED LOAD	77.5 %
15. POWER FACTOR AT 100% RATED LOAD	60 %
16. FULL LOAD TORQUE	14.93 KGM
17. SITE ALTTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6307zz OPL : 6207zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPURE	40 ℃
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

불법복제 및 배포금지
불법복제 및 배포금지

THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	HOISTING
2. MANUFACTURE	극동호이스트 (주)
3. FRAME NUMBER	132 M
4. RATED POWER	4.2 KW x 8 P
5. RATED VOLTAGE AND FREQUENCY	380 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 ℃
10. FULL LOAD SPEED	860 RPM
11. FULL LOAD CURRENT	13.3 A
12. LOCKED ROTOR CURRENT	78.8 A
13. MINIMUM STARTING VOLTAGE	342 V
14. EFFICIENCY AT 100% RATED LOAD	77.5 %
15. POWER FACTOR AT 100% RATED LOAD	60 %
16. FULL ROTOR TORQUE	14.93 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6307zz OPL : 6207zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPURE	40 ℃
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	HOISTING
2. MANUFACTURE	극동호이스트 (주)
3. FRAME NUMBER	132 M
4. RATED POWER	4.2 KW x 8 P
5. RATED VOLTAGE AND FREQUENCY	440 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 ℃
10. FULL LOAD SPEED	860 RPM
11. FULL LOAD CURRENT	11.5 A
12. LOCKED ROTOR CURRENT	68.1 A
13. MINIMUM STARTING VOLTAGE	400 V
14. EFFICIENCY AT 100% RATED LOAD	77.5 %
15. POWER FACTOR AT 100% RATED LOAD	60 %
16. FULL LOAD TORQUE	14.93 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6307zz OPL : 6207zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPURE	40 ℃
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	HOISTING
2. MANUFACTURE	극동호이스트 (주)
3. FRAME NUMBER	132 M
4. RATED POWER	4.2 KW x 8 P
5. RATED VOLTAGE AND FREQUENCY	460 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 ℃
10. FULL LOAD SPEED	860 RPM
11. FULL LOAD CURRENT	11.0 A
12. LOCKED ROTOR CURRENT	65.1 A
13. MINIMUM STARTING VOLTAGE	418 V
14. EFFICIENCY AT 100% RATED LOAD	77.5 %
15. POWER FACTOR AT 100% RATED LOAD	60 %
16. FULL LOAD TORQUE	14.93 KG.M
17. SITE ALTTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6307zz OPL : 6207zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPURE	40 ℃
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

불법복제 및 배포금지
불법복제 및 배포금지

THREE PHASE INDUCTION MOTOR DATE SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	HOISTING
2. MANUFACTURE	극동호이스트 (주)
3. FRAME NUMBER	132 M
4. RATED POWER	4.2 KW x 8 P
5. RATED VOLTAGE AND FREQUENCY	480 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATTING	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 ℃
10. FULL LOAD SPEED	860 RPM
11. FULL LOAD CURRENT	10.5 A
12. LOCKED ROTOR CURRENT	62.4 A
13. MINIMUM STARTING VOLTAGE	436 V
14. EFFICIENCY AT 100% RATED LOAD	77.5 %
15. POWER FACTOR AT 100% RATED LOAD	60 %
16. FULL LOAD TORQUE	14.93 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6307zz OPL : 6207zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPURE	40 ℃
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

LOAD LIMITER 권고 SETTING치

* POWER SOURCE : AC 3Φ 220V 60Hz

극동하이스트(주)

HOIST	MOTOR 용량	LOAD LIMITER 권고 SETTING치			LOAD CURRENT		C.T MODEL	연결단자 NO	C.T 용량	REMARK
		LOAD CURRENT	ADJ START TIME	SHOCK TIME	100%	110%				
0.5 TON	1.2KW x 8P	110%	1 SEC	1 SEC	8.0 A	9.0 A	CT-1	K, L	5 V.A	
	1.5KW x 6P	110%	1 SEC	1 SEC	7.6 A	8.4 A	CT-1	K, L	5 V.A	
	2.4KW x 4P	110%	1 SEC	1 SEC	10 A	11.2 A	CT-1	K, L	5 V.A	
1 TON	1.2KW x 8P	110%	1 SEC	1 SEC	8.0 A	9.0 A	CT-1	K, L	5 V.A	
	1.5KW x 6P	110%	1 SEC	1 SEC	7.6 A	8.4 A	CT-1	K, L	5 V.A	
	2.4KW x 4P	110%	1 SEC	1 SEC	10 A	11.2 A	CT-1	K, L	5 V.A	
2 TON	1.8KW x 8P	110%	1 SEC	1 SEC	11.0 A	12.2 A	CT-1	K, L	5 V.A	
	2.5KW x 6P	110%	1 SEC	1 SEC	12.0 A	13.2 A	CT-1	K, L	5 V.A	
	3.7KW x 4P	110%	1 SEC	1 SEC	16.0 A	17.6 A	CT-1	K, L	5 V.A	
2.8 TON	2.5KW x 8P	110%	1 SEC	1 SEC	17.7 A	19.5 A	CT-1	K, L	5 V.A	
	5.0KW x 4P	110%	1 SEC	1 SEC	22.8 A	25.0 A	CT-1	K, L	5 V.A	
	2.8KW x 8P	110%	1 SEC	1 SEC	17.7 A	19.5 A	CT-1	K, L	5 V.A	
3 TON	5.5KW x 4P	110%	1 SEC	1 SEC	22.8 A	25.0 A	CT-1	K, L	5 V.A	
	4.2KW x 8P	110%	1 SEC	1 SEC	23.0 A	25.3 A	CT-1	K, L	5 V.A	
	5.5KW x 6P	110%	1 SEC	1 SEC	28.2 A	31.0 A	CT-1	K, L	5 V.A	
5 TON	8.5KW x 4P	110%	1 SEC	1 SEC	34.4 A	38.4 A	CT-1	K, L	5 V.A	
	4.2KW x 8P	110%	1 SEC	1 SEC	23.0 A	25.3 A	CT-1	K, L	5 V.A	
	5.5KW x 6P	110%	1 SEC	1 SEC	28.2 A	31.0 A	CT-1	K, L	5 V.A	
7.5 TON	8.5KW x 4P	110%	1 SEC	1 SEC	34.4 A	38.4 A	CT-1	K, L	5 V.A	

NOTE

1. 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.



LOAD LIMITER 권고 SETTING치

* POWER SOURCE : AC 3Φ 380V 60Hz

극동하이스트(주)

HOIST	MOTOR 용량	LOAD LIMITER 권고 SETTING치			LOAD CURRENT		C.T MODEL	연결단자 NO	C.T 용량	REMARK
		LOAD CURRENT	ADJ START TIME	SHOCK TIME	100%	110%				
0.5 TON	1.2KW x 8P	110%	1 SEC	1 SEC	4.6 A	5.2 A	CT-1	K ₁ L	5 V.A	
	1.5KW x 6P	110%	1 SEC	1 SEC	5.4 A	4.9 A	CT-1	K ₁ L	5 V.A	
	2.4KW x 4P	110%	1 SEC	1 SEC	5.6 A	6.4 A	CT-1	K ₁ L	5 V.A	
1 TON	1.2KW x 8P	110%	1 SEC	1 SEC	4.6 A	5.2 A	CT-1	K ₁ L	5 V.A	
	1.5KW x 6P	110%	1 SEC	1 SEC	5.4 A	4.9 A	CT-1	K ₁ L	5 V.A	
	2.4KW x 4P	110%	1 SEC	1 SEC	5.6 A	6.4 A	CT-1	K ₁ L	5 V.A	
2 TON	1.8KW x 8P	110%	1 SEC	1 SEC	6.4 A	7.1 A	CT-1	K ₁ L	5 V.A	
	2.5KW x 6P	110%	1 SEC	1 SEC	7.0 A	7.7 A	CT-1	K ₁ L	5 V.A	
	3.7KW x 4P	110%	1 SEC	1 SEC	9.3 A	10.3 A	CT-1	K ₁ L	5 V.A	
2.8 TON	2.5KW x 8P	110%	1 SEC	1 SEC	10.3 A	11.4 A	CT-1	K ₁ L	5 V.A	
	5.0KW x 4P	110%	1 SEC	1 SEC	12.2 A	13.5 A	CT-1	K ₁ L	5 V.A	
	2.8KW x 8P	110%	1 SEC	1 SEC	10.3 A	11.4 A	CT-1	K ₁ L	5 V.A	
3 TON	5.5KW x 4P	110%	1 SEC	1 SEC	12.2 A	13.5 A	CT-1	K ₁ L	5 V.A	
	4.2KW x 8P	110%	1 SEC	1 SEC	13.3 A	14.6 A	CT-1	K ₁ L	5 V.A	
	5.5KW x 6P	110%	1 SEC	1 SEC	19.9 A	23.1 A	CT-1	K ₁ L	5 V.A	
5 TON	8.5KW x 4P	110%	1 SEC	1 SEC	16.3 A	18.0 A	CT-1	K ₁ L	5 V.A	
	4.2KW x 8P	110%	1 SEC	1 SEC	13.3 A	14.6 A	CT-1	K ₁ L	5 V.A	
	5.5KW x 6P	110%	1 SEC	1 SEC	19.9 A	23.1 A	CT-1	K ₁ L	5 V.A	
7.5 TON	8.5KW x 4P	110%	1 SEC	1 SEC	16.3 A	18.0 A	CT-1	K ₁ L	5 V.A	
	4.2KW x 8P	110%	1 SEC	1 SEC	13.3 A	14.6 A	CT-1	K ₁ L	5 V.A	
	5.5KW x 6P	110%	1 SEC	1 SEC	19.9 A	23.1 A	CT-1	K ₁ L	5 V.A	

NOTE

1. 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.



LOAD LIMITER 권고 SETTING치

* POWER SOURCE : AC 3Φ 440V 60Hz

극동호이스트(株)

HOIST	MOTOR 용량	LOAD LIMITER 권고 SETTING치			LOAD CURRENT		C.T MODEL	연결단자 NO	C.T 용량	REMARK
		LOAD CURRENT	ADJ START TIME	SHOCK TIME	100%	110%				
0.5 TON	1.2KW x 8P	110%	1 SEC	1 SEC	4.0 A	4.6 A	CT-1	K, L	5 V.A	
	1.5KW x 6P	110%	1 SEC	1 SEC	3.8 A	4.5 A	CT-1	K, L	5 V.A	
	2.4KW x 4P	110%	1 SEC	1 SEC	5.0 A	5.9 A	CT-1	K, L	5 V.A	
1 TON	1.2KW x 8P	110%	1 SEC	1 SEC	4.0 A	4.6 A	CT-1	K, L	5 V.A	
	1.5KW x 6P	110%	1 SEC	1 SEC	3.8 A	4.5 A	CT-1	K, L	5 V.A	
	2.4KW x 4P	110%	1 SEC	1 SEC	5.0 A	5.9 A	CT-1	K, L	5 V.A	
2 TON	1.8KW x 8P	110%	1 SEC	1 SEC	5.5 A	6.1 A	CT-1	K, L	5 V.A	
	2.5KW x 6P	110%	1 SEC	1 SEC	5.8 A	6.4 A	CT-1	K, L	5 V.A	
	3.7KW x 4P	110%	1 SEC	1 SEC	8.0 A	10.8 A	CT-1	K, L	5 V.A	
2.8 TON	2.5KW x 8P	110%	1 SEC	1 SEC	8.9 A	9.8 A	CT-1	K, L	5 V.A	
	5.0KW x 4P	110%	1 SEC	1 SEC	10.5 A	11.6 A	CT-1	K, L	5 V.A	
	2.8KW x 8P	110%	1 SEC	1 SEC	8.9 A	9.8 A	CT-1	K, L	5 V.A	
3 TON	5.5KW x 4P	110%	1 SEC	1 SEC	10.5 A	11.6 A	CT-1	K, L	5 V.A	
	4.2KW x 8P	110%	1 SEC	1 SEC	11.5 A	12.7 A	CT-1	K, L	5 V.A	
	5.5KW x 6P	110%	1 SEC	1 SEC	14.1 A	15.5 A	CT-1	K, L	5 V.A	
5 TON	8.5KW x 4P	110%	1 SEC	1 SEC	18.1 A	21.7 A	CT-1	K, L	5 V.A	
	4.2KW x 8P	110%	1 SEC	1 SEC	11.5 A	12.7 A	CT-1	K, L	5 V.A	
	5.5KW x 6P	110%	1 SEC	1 SEC	14.1 A	15.5 A	CT-1	K, L	5 V.A	
7.5 TON	8.5KW x 4P	110%	1 SEC	1 SEC	16.5 A	20.5 A	CT-1	K, L	5 V.A	

NOTE

1. 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.



LOAD LIMITER 권고 SETTING치

* POWER SOURCE : AC 3Φ 460V 60Hz

국동호이스트(주)

HOIST	MOTOR 용량	LOAD LIMITER 권고 SETTING치			LOAD CURRENT		C.T MODEL	연결단자 NO	C.T 용량	REMARK
		LOAD CURRENT	ADJ START TIME	SHOCK TIME	100%	110%				
0.5 TON	1.2KW x 8P	110%	1 SEC	1 SEC	3.8 A	4.4 A	CT-1	K, L	5 V.A	
	1.5KW x 6P	110%	1 SEC	1 SEC	3.6 A	4.1 A	CT-1	K, L	5 V.A	
	2.4KW x 4P	110%	1 SEC	1 SEC	4.8 A	5.2 A	CT-1	K, L	5 V.A	
1 TON	1.2KW x 8P	110%	1 SEC	1 SEC	3.8 A	4.4 A	CT-1	K, L	5 V.A	
	1.5KW x 6P	110%	1 SEC	1 SEC	3.6 A	4.1 A	CT-1	K, L	5 V.A	
	2.4KW x 4P	110%	1 SEC	1 SEC	4.8 A	5.2 A	CT-1	K, L	5 V.A	
2 TON	1.8KW x 8P	110%	1 SEC	1 SEC	5.3 A	5.9 A	CT-1	K, L	5 V.A	
	2.5KW x 6P	110%	1 SEC	1 SEC	5.5 A	6.1 A	CT-1	K, L	5 V.A	
	3.7KW x 4P	110%	1 SEC	1 SEC	7.7 A	8.5 A	CT-1	K, L	5 V.A	
2.8T	2.5KW x 8P	110%	1 SEC	1 SEC	7.7 A	8.5 A	CT-1	K, L	5 V.A	
	5.0KW x 4P	110%	1 SEC	1 SEC	10.0 A	11.5 A	CT-1	K, L	5 V.A	
3TON	2.8KW x 8P	110%	1 SEC	1 SEC	7.7 A	8.5 A	CT-1	K, L	5 V.A	
	5.5KW x 4P	110%	1 SEC	1 SEC	10.0 A	11.5 A	CT-1	K, L	5 V.A	
5 TON	4.2KW x 8P	110%	1 SEC	1 SEC	11.0 A	12.2 A	CT-1	K, L	5 V.A	
	5.5KW x 6P	110%	1 SEC	1 SEC	13.5 A	14.7 A	CT-1	K, L	5 V.A	
	8.5KW x 4P	110%	1 SEC	1 SEC	16.5 A	20.5 A	CT-1	K, L	5 V.A	
7.5 TON	4.2KW x 8P	110%	1 SEC	1 SEC	11.0 A	12.2 A	CT-1	K, L	5 V.A	
	5.5KW x 6P	110%	1 SEC	1 SEC	13.5 A	14.7 A	CT-1	K, L	5 V.A	
	8.5KW x 4P	110%	1 SEC	1 SEC	16.5 A	20.5 A	CT-1	K, L	5 V.A	

NOTE

1. 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.



LOAD LIMITER 권고 SETTING

* POWER SOURCE : AC 3Φ 480V 60Hz

극동호이스트(주)

HOIST	MOTOR 용량	LOAD LIMITER 권고 SETTING			LOAD CURRENT		C.T MODEL	연결단자 NO	C.T 용량	REMARK
		LOAD CURRENT	ADJ START TIME	SHOCK TIME	100%	110%				
0.5 TON	1.2KW x 8P	110%	1 SEC	1 SEC	3.6 A	4.2 A	CT-1	K, L	5 V.A	
	1.5KW x 6P	110%	1 SEC	1 SEC	3.5 A	3.9 A	CT-1	K, L	5 V.A	
	2.4KW x 4P	110%	1 SEC	1 SEC	4.6 A	5.1 A	CT-1	K, L	5 V.A	
1 TON	1.2KW x 8P	110%	1 SEC	1 SEC	3.6 A	4.2 A	CT-1	K, L	5 V.A	
	1.5KW x 6P	110%	1 SEC	1 SEC	3.5 A	3.9 A	CT-1	K, L	5 V.A	
	2.4KW x 4P	110%	1 SEC	1 SEC	4.6 A	5.1 A	CT-1	K, L	5 V.A	
2 TON	1.8KW x 8P	110%	1 SEC	1 SEC	5.1 A	5.8 A	CT-1	K, L	5 V.A	
	2.5KW x 6P	110%	1 SEC	1 SEC	5.3 A	6.0 A	CT-1	K, L	5 V.A	
	3.7KW x 4P	110%	1 SEC	1 SEC	7.3 A	8.2 A	CT-1	K, L	5 V.A	
2.8 TON	2.5KW x 8P	110%	1 SEC	1 SEC	7.3 A	8.2 A	CT-1	K, L	5 V.A	
	5.0KW x 4P	110%	1 SEC	1 SEC	9.6 A	11.2 A	CT-1	K, L	5 V.A	
	2.8KW x 8P	110%	1 SEC	1 SEC	7.3 A	8.2 A	CT-1	K, L	5 V.A	
3 TON	5.5KW x 4P	110%	1 SEC	1 SEC	9.6 A	11.2 A	CT-1	K, L	5 V.A	
	4.2KW x 8P	110%	1 SEC	1 SEC	10.5 A	12.0 A	CT-1	K, L	5 V.A	
	5.5KW x 6P	110%	1 SEC	1 SEC	12.9 A	14.2 A	CT-1	K, L	5 V.A	
5 TON	8.5KW x 4P	110%	1 SEC	1 SEC	15.8 A	19.9 A	CT-1	K, L	5 V.A	
	4.2KW x 8P	110%	1 SEC	1 SEC	10.5 A	12.0 A	CT-1	K, L	5 V.A	
	5.5KW x 6P	110%	1 SEC	1 SEC	12.9 A	14.2 A	CT-1	K, L	5 V.A	
7.5 TON	8.5KW x 4P	110%	1 SEC	1 SEC	15.8 A	19.9 A	CT-1	K, L	5 V.A	
	4.2KW x 8P	110%	1 SEC	1 SEC	10.5 A	12.0 A	CT-1	K, L	5 V.A	
	5.5KW x 6P	110%	1 SEC	1 SEC	12.9 A	14.2 A	CT-1	K, L	5 V.A	

NOTE

1. 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.



E.O.C.R 권고 SETTING치

* POWER SOURCE : AC 3Φ 220V 60Hz

극동하이스트(주)

HOIST	MOTOR 용량	MOTOR 정격 전류	DRIVE TYPE	E.O.C.R TYPE	권고 SETTING 치			REMARK
					DELAY TIME	OPERATION TIME	CURRENT	
0.5 TON	1.2KW x 8P	8.0 A	1 DRIVE	SS-30	3 SEC	1 SEC	8.0 A	
	1.5KW x 6P	7.6 A	1 DRIVE	SS-30	3 SEC	1 SEC	7.6 A	
	2.4KW x 4P	10.0 A	1 DRAVE	SS-30	3 SEC	1 SEC	10.0 A	
1 TON	1.2KW x 8P	8.0 A	1 DRIVE	SS-30	3 SEC	1 SEC	8.0 A	
	1.5KW x 6P	7.6 A	1 DRIVE	SS-30	3 SEC	1 SEC	7.6 A	
	2.4KW x 4P	10.0 A	1 DRAVE	SS-30	3 SEC	1 SEC	10.0 A	
2 TON	1.8KW x 8P	11.0 A	1 DRAVE	SS-30	3 SEC	1 SEC	11.0 A	
	2.5KW x 6P	12.0 A	1 DRAVE	SS-30	3 SEC	1 SEC	12.0 A	
	3.7KW x 4P	16.0 A	1 DRAVE	SS-30	3 SEC	1 SEC	16.0 A	
2.8 TON	2.5KW x 8P	17.7 A	1 DRAVE	SS-30	3 SEC	1 SEC	17.7 A	
	5.0KW x 4P	22.8 A	1 DRAVE	SS-30	3 SEC	1 SEC	22.8 A	
	2.8KW x 8P	17.7 A	1 DRAVE	SS-30	3 SEC	1 SEC	17.7 A	
3 TON	5.5KW x 4P	22.8 A	1 DRAVE	SS-30	3 SEC	1 SEC	22.8 A	
	4.2KW x 8P	23.0 A	1 DRAVE	SS-30	3 SEC	1 SEC	23.0 A	
	5.5KW x 6P	28.2 A	1 DRAVE	SS-30	3 SEC	1 SEC	28.2 A	
5 TON	8.5KW x 4P	34.4 A	1 DRAVE	SS-30	3 SEC	1 SEC	34.4 A	
	4.2KW x 8P	23.0 A	1 DRAVE	SS-30	3 SEC	1 SEC	23.0 A	
	5.5KW x 6P	28.2 A	1 DRAVE	SS-30	3 SEC	1 SEC	28.2 A	
7.5 TON	8.5KW x 4P	34.4 A	1 DRAVE	SS-30	3 SEC	1 SEC	34.4 A	
	4.2KW x 8P	23.0 A	1 DRAVE	SS-30	3 SEC	1 SEC	23.0 A	
	5.5KW x 6P	28.2 A	1 DRAVE	SS-30	3 SEC	1 SEC	28.2 A	

NOTE

1. 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.



E.O.C.R 권고 SETTING치

* POWER SOURCE : AC 3Φ 380V 60HZ

국동호이스트(주)

HOIST	MOTOR 용량	1 정격 전류	DRIVE TYPE	E.O.C.R TYPE	권고 SETTING 치			REMARK
					DELAY TIME	OPERATION TIME	CURRENT	
0.5 TON	1.2KW x 8P	4.6 A	1 DRIVE	SS-30	3 SEC	1 SEC	4.6 A	
	1.5KW x 6P	5.4 A	1 DRIVE	SS-30	3 SEC	1 SEC	5.4 A	
	2.4KW x 4P	5.6 A	1 DRAVE	SS-30	3 SEC	1 SEC	5.6 A	
1 TON	1.2KW x 8P	4.6 A	1 DRIVE	SS-30	3 SEC	1 SEC	4.6 A	
	1.5KW x 6P	5.4 A	1 DRIVE	SS-30	3 SEC	1 SEC	5.4 A	
	2.4KW x 4P	5.6 A	1 DRAVE	SS-30	3 SEC	1 SEC	5.6 A	
2 TON	1.8KW x 8P	6.4 A	1 DRAVE	SS-30	3 SEC	1 SEC	6.4 A	
	2.5KW x 6P	7.0 A	1 DRAVE	SS-30	3 SEC	1 SEC	7.0 A	
	3.7KW x 4P	9.3 A	1 DRAVE	SS-30	3 SEC	1 SEC	9.3 A	
2.8 TON	2.5KW x 8P	10.3 A	1 DRAVE	SS-30	3 SEC	1 SEC	10.3 A	
	5.0KW x 4P	12.2 A	1 DRAVE	SS-30	3 SEC	1 SEC	12.2 A	
	2.8KW x 8P	10.3 A	1 DRAVE	SS-30	3 SEC	1 SEC	10.3 A	
3 TON	5.5KW x 4P	12.2 A	1 DRAVE	SS-30	3 SEC	1 SEC	12.2 A	
	4.2KW x 8P	13.3 A	1 DRAVE	SS-30	3 SEC	1 SEC	13.3 A	
	5.5KW x 6P	16.3 A	1 DRAVE	SS-30	3 SEC	1 SEC	16.3 A	
5 TON	8.5KW x 4P	19.9 A	1 DRAVE	SS-30	3 SEC	1 SEC	19.9 A	
	4.2KW x 8P	13.3 A	1 DRAVE	SS-30	3 SEC	1 SEC	13.3 A	
	5.5KW x 6P	16.3 A	1 DRAVE	SS-30	3 SEC	1 SEC	16.3 A	
7.5 TON	8.5KW x 4P	19.9 A	1 DRAVE	SS-30	3 SEC	1 SEC	19.9 A	
	4.2KW x 8P	13.3 A	1 DRAVE	SS-30	3 SEC	1 SEC	13.3 A	
	5.5KW x 6P	16.3 A	1 DRAVE	SS-30	3 SEC	1 SEC	16.3 A	

NOTE

1. 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.



E.O.C.R 권고 SETTING치

* POWER SOURCE : AC 3Φ 440V 60HZ

극동호이스트(주)

HOIST	MOTOR 용량	MOTOR 정격 전류	DRIVE TYPE	E.O.C.R TYPE	권고 SETTING 치			REMARK
					DELAY TIME	OPERATION TIME	CURRENT	
0.5 TON	1.2KW x 8P	4.0 A	1 DRIVE	SS-06	3 SEC	1 SEC	4.0 A	
	1.5KW x 6P	3.8 A	1 DRIVE	SS-06	3 SEC	1 SEC	3.8 A	
	2.4KW x 4P	5.0 A	1 DRAVE	SS-30	3 SEC	1 SEC	5.0 A	
1 TON	1.2KW x 8P	4.0 A	1 DRIVE	SS-06	3 SEC	1 SEC	4.0 A	
	1.5KW x 6P	3.8 A	1 DRIVE	SS-06	3 SEC	1 SEC	3.8 A	
	2.4KW x 4P	5.0 A	1 DRAVE	SS-30	3 SEC	1 SEC	5.0 A	
2 TON	1.8KW x 8P	5.5 A	1 DRAVE	SS-30	3 SEC	1 SEC	5.5 A	
	2.5KW x 6P	5.8 A	1 DRAVE	SS-30	3 SEC	1 SEC	5.8 A	
	3.7KW x 4P	8.0 A	1 DRAVE	SS-30	3 SEC	1 SEC	8.0 A	
2.8 TON	2.5KW x 8P	8.9 A	1 DRAVE	SS-30	3 SEC	1 SEC	8.9 A	
	5.0KW x 4P	10.5 A	1 DRAVE	SS-30	3 SEC	1 SEC	10.5 A	
	2.8KW x 6P	8.9 A	1 DRAVE	SS-30	3 SEC	1 SEC	8.9 A	
3 TON	5.5KW x 4P	10.5 A	1 DRAVE	SS-30	3 SEC	1 SEC	10.5 A	
	4.2KW x 8P	11.5 A	1 DRAVE	SS-30	3 SEC	1 SEC	11.5 A	
	5.5KW x 6P	14.1 A	1 DRAVE	SS-30	3 SEC	1 SEC	14.1 A	
5 TON	8.5KW x 4P	18.1 A	1 DRAVE	SS-30	3 SEC	1 SEC	16.5 A	
	4.2KW x 8P	11.5 A	1 DRAVE	SS-30	3 SEC	1 SEC	11.5 A	
	5.5KW x 6P	14.1 A	1 DRAVE	SS-30	3 SEC	1 SEC	14.1 A	
7.5 TON	8.5KW x 4P	16.5 A	1 DRAVE	SS-30	3 SEC	1 SEC	16.5 A	

NOTE

1. 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.



E.O.C.R 권고 SETTING치

* POWER SOURCE : AC 3Φ 460V 60Hz

극동호이스트(주)

HOIST	MOTOR 용량	MOTOR 정격 전류	DRIVE TYPE	E.O.C.R TYPE	권고 SETTING 치			REMARK
					DELAY TIME	OPERATION TIME	CURRENT	
0.5 TON	1.2KW x 8P	3.8 A	1 DRIVE	SS-06	3 SEC	1 SEC	3.8 A	
	1.5KW x 6P	3.6 A	1 DRIVE	SS-06	3 SEC	1 SEC	3.6 A	
	2.4KW x 4P	4.8 A	1 DRAVE	SS-06	3 SEC	1 SEC	4.8 A	
1 TON	1.8KW x 8P	5.3 A	1 DRAVE	SS-30	3 SEC	1 SEC	5.3 A	
	2.5KW x 6P	5.5 A	1 DRAVE	SS-30	3 SEC	1 SEC	5.8 A	
	3.7KW x 4P	7.7 A	1 DRAVE	SS-30	3 SEC	1 SEC	7.7 A	
2 TON	1.8KW x 8P	5.3 A	1 DRAVE	SS-30	3 SEC	1 SEC	5.3 A	
	2.5KW x 6P	5.5 A	1 DRAVE	SS-30	3 SEC	1 SEC	5.8 A	
	3.7KW x 4P	7.7 A	1 DRAVE	SS-30	3 SEC	1 SEC	7.7 A	
2.8 TON	2.5KW x 8P	7.7 A	1 DRAVE	SS-30	3 SEC	1 SEC	7.7 A	
	5.0KW x 4P	10.0 A	1 DRAVE	SS-30	3 SEC	1 SEC	10.0 A	
	2.8KW x 8P	7.7 A	1 DRAVE	SS-30	3 SEC	1 SEC	7.7 A	
3 TON	5.5KW x 4P	10.0 A	1 DRAVE	SS-30	3 SEC	1 SEC	10.0 A	
	4.2KW x 8P	11.0 A	1 DRAVE	SS-30	3 SEC	1 SEC	11.0 A	
	5.5KW x 6P	13.5 A	1 DRAVE	SS-30	3 SEC	1 SEC	13.5 A	
5 TON	8.5KW x 4P	16.5 A	1 DRAVE	SS-30	3 SEC	1 SEC	16.5 A	
	4.2KW x 8P	11.0 A	1 DRAVE	SS-30	3 SEC	1 SEC	11.0 A	
	5.5KW x 6P	13.5 A	1 DRAVE	SS-30	3 SEC	1 SEC	13.5 A	
7.5 TON	8.5KW x 4P	16.5 A	1 DRAVE	SS-30	3 SEC	1 SEC	16.5 A	
	4.2KW x 8P	11.0 A	1 DRAVE	SS-30	3 SEC	1 SEC	11.0 A	
	5.5KW x 6P	13.5 A	1 DRAVE	SS-30	3 SEC	1 SEC	13.5 A	

NOTE

1. 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.



E.O.C.R 권고 SETTING치

* POWER SOURCE : AC 3Φ 480V 60Hz

극동호이스트(주)

HOIST	MOTOR 용량	MOTOR 정격 전류	DRIVE TYPE	E.O.C.R TYPE	권고 SETTING 치			REMARK
					DELAY TIME	OPERATION TIME	CURRENT	
0.5 TON	1.2KW x 8P	3.6 A	1 DRIVE	SS-06	3 SEC	1 SEC	3.6 A	
	1.5KW x 6P	3.5 A	1 DRIVE	SS-06	3 SEC	1 SEC	3.5 A	
	2.4KW x 4P	4.6 A	1 DRAVE	SS-06	3 SEC	1 SEC	4.6 A	
1 TON	1.2KW x 8P	3.6 A	1 DRIVE	SS-06	3 SEC	1 SEC	3.6 A	
	1.5KW x 6P	3.5 A	1 DRIVE	SS-06	3 SEC	1 SEC	3.5 A	
	2.4KW x 4P	4.6 A	1 DRAVE	SS-06	3 SEC	1 SEC	4.6 A	
2 TON	1.8KW x 8P	5.1 A	1 DRAVE	SS-30	3 SEC	1 SEC	5.1 A	
	2.5KW x 6P	5.3 A	1 DRAVE	SS-30	3 SEC	1 SEC	5.3 A	
	3.7KW x 4P	7.3 A	1 DRAVE	SS-30	3 SEC	1 SEC	7.3 A	
2.8 TON	2.5KW x 8P	7.3 A	1 DRAVE	SS-30	3 SEC	1 SEC	7.3 A	
	5.0KW x 4P	9.6 A	1 DRAVE	SS-30	3 SEC	1 SEC	9.6 A	
	2.8KW x 8P	7.3 A	1 DRAVE	SS-30	3 SEC	1 SEC	7.3 A	
3 TON	5.5KW x 4P	9.6 A	1 DRAVE	SS-30	3 SEC	1 SEC	9.6 A	
	4.2KW x 8P	10.5 A	1 DRAVE	SS-30	3 SEC	1 SEC	10.5 A	
	5.5KW x 6P	12.9 A	1 DRAVE	SS-30	3 SEC	1 SEC	12.9 A	
5 TON	8.5KW x 4P	15.8 A	1 DRAVE	SS-30	3 SEC	1 SEC	15.8 A	
	4.2KW x 8P	10.5 A	1 DRAVE	SS-30	3 SEC	1 SEC	10.5 A	
	5.5KW x 6P	12.9 A	1 DRAVE	SS-30	3 SEC	1 SEC	12.9 A	
7.5 TON	8.5KW x 4P	15.8 A	1 DRAVE	SS-30	3 SEC	1 SEC	15.8 A	

NOTE

1. 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.



SUB VENDOR LIST

구분	NO	DESCRIPTION	SUB VENDOR	TEL NO.	REMARK
기 계	1	WIRE ROPE	만호 로우프(주)	051-332-3131	
			고려제강 (주)	02-776-4131	
	2	MAGNET CORE	극동호이스트(주)	031-491-5311	
	3	DRUM	극동호이스트(주)	031-491-5311	
	4	GEAR	극동호이스트(주)	031-491-5311	
	5	HOOK ASS'Y	제 일 단 철	032-527-2817	
			대 흥 단 조	032-561-0541	
	6	MIDDLE SHAFT	극동호이스트(주)	031-491-5311	
전 기	8	MAG CONTACTOR	인천제철(주)	032-763-5000	
			강원산업(주)	032-756-8881	
	9	E.O.C.R	L.G 전선 (주)	02-273-4140	전 품
			(주) 대 륙	02-242-4141	한국공업협회
	10	PUSH BUTTON	(주) 대성디에스	055-338-3125	
			삼화기연 (주)	032-62-1331	K.S
			아산 전기	02-2636-8035	
	11	LOAD LIMITER	한영전기 (주)	02-742-0430	전 품
			(주)케이치오토	02-247-3131	전 품
			반도기계 (주)	031-495-8353-4	전 품
	12	SILICON	보 창 기 전	032-431-0150	산 안 검
			반도기계 (주)	031-495-8353-4	산 안 검
			정호 엔지니어링	02-681-0553	산 안 검
			반도기계 (주)	031-495-8353-4	
			아산 전기	02-2636-8035	
			보 창 기 전	032-431-0150	



ISSUE NO. PW1416

DATE 2014-01-29

MILL TEST CERTIFICATE

THIS IS TO CERTIFY THAT THE MATERIAL DESCRIBED BELOW WAS MANUFACTURED
IN ACCORDANCE WITH KISWIRE LTD SPECIFICATION AND APPLICABLE SECTIONS

OF **KSD 3514 - 2002** (**B** Grade)

TO MESSRS KISWIRE LTD.
MATERIAL DESCRIPTION UNGALVANIZED STEEL WIRE ROPE
06X37 + FC 2000M X 3 REEL

EX NO. PW1416 T/T NO.
ORDER NO. REEL NO. 2 ~ 4 SAMPLING NO. 2
DIAMETER OF ROPE 16.0 mm TYPE OF CORE Fiber Core
SPECIFIED BREAKING LOAD 145.0 kN SAMPLE BROKE AT 157.575 kN
WT. OF ZINC COATING OF OUTER WIRE MIN. g/m² MAX. g/m²
ROPE LAY RHRL (OZ) LAY LENGTH 106.4 mm
LUBRICATION A-2

CHEMICAL ANALYSIS OF WIRE ROD

CHARGE NO.	C X 100	Si X 100	Mn X 100	P X 1000	S X 1000
SD51275791	61	20	55	7	13



KS



JIS

DATE OF SAMPLE TEST 2014-01-29

KISWIRE

불법복제 및 배포금지
불법복제 및 배포금지



www.tuv.com

Page 5 of 8

Report No. 13601062 002

EN 60947-5-1			
Clause	Requirement - Test	Result - Remark	Verdict

Annex C of IEC 60947-1			P
------------------------	--	--	---

Annex C	Degree of protection of enclosed control circuit-devices		P
C.1	Scope		
	This annex applies to degrees of protection of enclosed switchgear and control gear at rated voltages not exceeding 1000 V a.c. or 1500 V d.c. hereafter referred as "equipment"		
C.2	Object		
	Clause 2 of IEC 60529 applies with additional requirements of this annex		
C.3	Definitions		
	Clause 3 of IEC 60529 applies except that "Enclosure" is replaced by the following:		
	"A part providing a specified degree of protection of equipment against certain external influences and a specified degree of protection against approach to or contact with live parts and moving parts"		
C.4	Designation		
	Clause 4 of IEC 60529 applies except for letters H, M and S		N/A
C.5	Degrees of protection against access to hazardous parts and against ingress of solid foreign objects indicated by the first characteristic numeral		
	Clause 5 of IEC 60529 applies	6	P
C.6	Degrees of protection against ingress of water indicated by the second characteristic numeral		
	Clause 6 of IEC 60529 applies	5	P
C.7	Degrees of protection against access to hazardous parts indicated by the additional letter		
	Clause 7 of IEC 60529 applies		N/A
C.8	Supplementary letters		
	Clause 8 of IEC 60529 applies		N/A
C.9	Examples of designations with IP Code		
	Clause 9 of IEC 60529 applies		P
C.10	Marking		
			P

TRF-No.: IEC60947_5_1A

C.5, C.6항이 IP65 PASS를 뜻함.



ISSUE NO. PW1416

DATE 2014-01-29

MILL TEST CERTIFICATE

THIS IS TO CERTIFY THAT THE MATERIAL DESCRIBED BELOW WAS MANUFACTURED
IN ACCORDANCE WITH KISWIRE LTD SPECIFICATION AND APPLICABLE SECTIONS

OF **KSD 3514 - 2002** (**B** Grade)

TO MESSRS KISWIRE LTD.

MATERIAL DESCRIPTION UNGALVANIZED STEEL WIRE ROPE

06X37 + FC 2000M X 3 REEL

EX NO. PW1416

T/T NO.

ORDER NO. REEL NO. 2 ~ 4 SAMPLING NO. 2

DIAMETER OF ROPE 16.0 mm TYPE OF CORE Fiber Core

SPECIFIED BREAKING LOAD 145.0 kN SAMPLE BROKE AT 157.575 kN

WT. OF ZINC COATING OF OUTER WIRE MIN. g/m² MAX. g/m²

ROPE LAY RHRL (OZ) LAY LENGTH 106.4 mm

LUBRICATION A-2

CHEMICAL ANALYSIS OF WIRE ROD

CHARGE NO.	C X 100	Si X 100	Mn X 100	P X 1000	S X 1000
SD51275791	61	20	55	7	13



KS



JIS

DATE OF SAMPLE TEST 2014-01-29

KISWIRE

EN 60947-5-1			
Clause	Requirement - Test	Result - Remark	Verdict

Annex C of IEC 60947-1			P
------------------------	--	--	---

Annex C	Degree of protection of enclosed control circuit-devices		P
C.1	Scope		
	This annex applies to degrees of protection of enclosed switchgear and control gear at rated voltages not exceeding 1000 V a.c. or 1500 V d.c. hereafter referred as "equipment"		
C.2	Object		
	Clause 2 of IEC 60529 applies with additional requirements of this annex		
C.3	Definitions		
	Clause 3 of IEC 60529 applies except that "Enclosure" is replaced by the following:		
	"A part providing a specified degree of protection of equipment against certain external influences and a specified degree of protection against approach to or contact with live parts and moving parts"		
C.4	Designation		
	Clause 4 of IEC 60529 applies except for letters H, M and S		N/A
C.5	Degrees of protection against access to hazardous parts and against ingress of solid foreign objects indicated by the first characteristic numeral		
	Clause 5 of IEC 60529 applies	6	P
C.6	Degrees of protection against ingress of water indicated by the second characteristic numeral		
	Clause 6 of IEC 60529 applies	6	P
C.7	Degrees of protection against access to hazardous parts indicated by the additional letter		N/A
	Clause 7 of IEC 60529 applies		N/A
C.8	Supplementary letters		N/A
	Clause 8 of IEC 60529 applies		N/A
C.9	Examples of designations with IP Code		P
	Clause 9 of IEC 60529 applies		P
C.10	Marking		P

TRF-No.: IEC60947_5_1A

C.5, C.6항이 IP65 PASS를 뜻함.