



심사결과 통지서

신청인	사업장명	극동호이스트(주)	사업장관리번호	134-81-013350
	사업자등록번호	134-81-01335	대표자 성명	최성찬
	소재지	(154 - 23) 경기도 안산시 단원구 해봉로 119(성곡동)		

안전인증대상 기계·기구명

호이스트 [동일형식인정 - "별첨" 참조]

형 식 (규 격)	KD15T-D	용 량 (등 급)	15 Ton
-----------	---------	-----------	--------

산업안전보건법 제 34조 및 같은 법 시행규칙 제58조의4에 따라 실시한

[] 예비심사

[√] 서면심사

[] 기술능력 및 생산체계 심사

[] 개별 제품심사

[] 개별 제품심사(제작중)

[] 형식별 제품심사

결과가 [√] 적 합
[] 부적합

함을 통지합니다.

2019년 05월 16일

인증심사원

이승태

이 승태 (서명 또는 인)

한국산업안전보건공단 이사장





제2022 - 2226284 호

안 전 인 증 서

(사업장명) 극동호이스트(주)

(소 재 지) (15423)경기도 안산시 단원구 성곡동 630-2

위 사업장에서 제조하는 아래의 품목이 산업안전보건법 제84조 및 시행규칙 제110조제1항에 따른 안전인증 심사 결과 안전·보건기준에 적합하므로 안전인증표시의 사용을 인증합니다.

_____ 품 목 _____

호이스트 (국내품)

_____ 형식,모델(용량,등급)/인증번호 _____

KD15T-D (15Ton) / 22-AH2AC-00042

_____ 인 증 기 준 _____

고용노동부 고시 제2020 - 41호 (위험기계·기구 안전인증 고시)

_____ 인 증 조 건 _____

(15423)경기도 안산시 단원구 성곡동 630-2에서 생산된 동일 형식 제품에 한함

설치장소 : 옥외

2022년 09월 22일

한국산업안전보건공단 이사장



서 면 심 사 서 류

형식 번호 : KD15T-D

극 동 호 이 스톱 (주)



주소 : 경기도 안산시 단원구 해봉로 119 (성곡동)

TEL : 031) 491 - 5311

FAX : 031) 494 - 5315

산업재해예방
안전보건공단
KOSHA OCCUPATIONAL SAFETY & HEALTH CENTER



동일 형식 일람표

사업장명		구동호이스트(주)	개정일자 및 번호		인증번호	비고
형식 및 모델			동일 형식 인정범위 및 내역			
형식	모델		권상속도(m/min)	회행속도(m/min)	양정(m)	
KD15T-D	KD15-L12-D		고속 : 4.5 m/min 저속 : 3.0 m/min	고속 : 15 m/min 저속 : 10 m/min 듀얼 고속 : 15/7.5 m/min 듀얼 저속 : 10/5 m/min	12	모터 구동식
	KD15-L18-D				18	
	KD15-L24-D				24	
	KD15-L30-D				30	
회행 인버터 포함						



제 2012-BJ-0009 호



안 전 인 증 서

정호엔지니어링

경기도 광명시 노동사동 440-5

위 사업장에서 제조하는 아래의 품목이 산업안전보건법 제34조 및 같은 법 시행규칙 제58조의4제4항에 따른 안전인증 심사 결과 안전·보건기준에 적합하므로 안전인증표시의 사용을 인증합니다.

품 목

양중기용 과부하방지장치

형식·모델/용량·등급/인증번호

형식·모델	용량·등급	인증번호
JDL-100	J-2	12-AV2BJ-0009

인 증 기 준

방호장치 의무안전인증 고시(고용노동부고시 제2010-36호)

인 증 조 건

아래 주소에서 생산되는 제품에 한함.

정호엔지니어링, 경기도 광명시 노동사동 440-5

2012년 06월 11일

한국산업안전보건공단 이사장



제 2012-BJ-0008 호



안 전 인 증 서

정호엔지니어링

경기도 광명시 노동사동 440-5

위 사업장에서 제조하는 아래의 품목이 산업안전보건법 제34조 및 같은 법 시행규칙 제58조의4제4항에 따른 안전인증 심사 결과 안전·보건기준에 적합하므로 안전인증표시의 사용을 인증합니다.

품 목

양중기용 과부하방지장치

형식·모델/용량·등급/인증번호

형식·모델	용량·등급	인증번호
JDLS-70	J-2	12-AV2BJ-0008

인 증 기 준

방호장치 의무안전인증 고시(고용노동부고시 제2010-36호)

인 증 조 건

아래 주소에서 생산되는 제품에 한함.

정호엔지니어링, 경기도 광명시 노동사동 440-5

2012년 06월 11일



한국산업안전보건공단 이사장



Ⅱ. 도 면

1. 기 계







SPECIFICATION			
HOISTING LOAD		15 TON	
TESTING LOAD		18.75 TON	
HOISTING	LIFT	12 M	
	SPEED	4.5 M/MIN	
HOISTING	MOTOR	13 KW x 8P	
	SPEED	3 M/MIN	
HOISTING	MOTOR	8.5 KW x 12P	
	SPEED	15 M/MIN	
HOISTING	MOTOR	1.5 KW x 4 P	
	SPEED	10 M/MIN	
HOISTING	MOTOR	1.0 KW x 6 P	
	SPEED	15/7.5 M/MIN	
HOISTING	MOTOR	1.5/0.75 KW x 4/8 P	
	SPEED	10/5 M/MIN	
HOISTING	MOTOR	1.0/0.5 KW x 6/12 P	
	SPEED	(6x29 WRC) Ø18 x 4 FALLS	
WIRE ROPE		AC3Ø 220/380/440/460/480V 60Hz	
POWER SOURCE		22 KG/M	
TRAVERSING RAIL		1970 KG	
GROSS WEIGHT			

5	T/S RAIL	—			—			22KG/M
4	UPPER LIMIT S/W	SS400			1			
3	SAFETY LATCH	SPC			1			
2	EMERGENCY S/W	—			1			
1	LOAD LIMITER	—			1			
NO.	DESCRIPTION	MT'L	SUB QTY	TOTAL	SUB WEIGHT(Kg)	REMARKS.		
						DATE	DIM	PROJECTION
PROJECT							mm	
TITLE		KD15 — L12 — D				SCALE	A3/20	3rd
DRAWN		ARRANGEMENT DRAWING FOR HOIST						
		DESIGNED	CHECKED	APPROVED			REF. DRAWING	
		극동호이스트 주식회사 KUK DONG HOIST CO., LTD.				SHEET No. DWG No. KD15D1200		

극동호이스트
제한하중
15000 K

VIEW A







SPECIFICATION		
HOISTING LOAD	15 TON	
TESTING LOAD	18.75 TON	
LIFT		
HOISTING	HIGH	SPEED 4.5 M/MIN
	MOTOR	13 KW x 8P
	LOW	SPEED 3 M/MIN
		MOTOR 8.5 KW x 12P
	HIGH	SPEED 15 M/MIN
		MOTOR 1.5 KW x 4 P
TRAVERSING -ING	LOW	SPEED 10 M/MIN
	MOTOR	1.0 KW x 6 P
	DUAL	SPEED 15/7.5 M/MIN
	HIGH	MOTOR 1.5/0.75 KW x 4/8 P
	DUAL	SPEED 10/5 M/MIN
	LOW	MOTOR 1.0/0.5 KW x 6/12 P
WIRE ROPE		(6x29 IWRC) Ø18 x 4 FALLS
POWER SOURCE		AC3Ø 220/380/ 440/460/480V 60Hz
TRAVERSING RAIL		22 KG/M
GROSS WEIGHT		1970 KG

5	T/S RAIL	—			—				22KG/M	
4	UPPER LIMIT S/W	SS400			1					
3	SAFETY LATCH	SPC			1					
2	EMERGENCY S/W	—			1					
1	LOAD LIMITER	—			1					
NO.	DESCRIPTION	MT'L	SUB QTY	TOTAL	SUB WEIGHT(Kg)	TOTAL	REMARKS.			
PROJECT	KD15 — L18 — D ARRANGEMENT DRAWING FOR HOIST						DATE	DIM		
								mm		
TITLE	KD15 — L18 — D ARRANGEMENT DRAWING FOR HOIST						SCALE	PROJECTION		
							A3/20	3rd		
DRAWN	DESIGNED	CHECKED	APPROVED	REF. DRAWING						
 KUK DONG HOIST CO., LTD.				SHEET No.		DWG No.				
						KD15D1800				

제한하중
15000 K

VIEW A







SPECIFICATION		
HOISTING LOAD	15 TON	
TESTING LOAD	18.75 TON	
LIFT	24 M	
HOISTING	HIGH	SPEED MOTOR
	LOW	SPEED MOTOR
		SPEED MOTOR
	HIGH	SPEED MOTOR
TRAVERSING RAIL	LOW	SPEED MOTOR
	DUAL	SPEED MOTOR
		SPEED MOTOR
	LOW	SPEED MOTOR
WIRE ROPE	(6x29 IWRC) $\phi 18 \times 4$ FALLS	
POWER SOURCE	AC3 ϕ 220/380/ 440/460/480V 60Hz	
TRAVERSING RAIL	22 KG/M	
GROSS WEIGHT	2100 KG	

5	T/S RAIL	—			—			22KG/M	
4	UPPER LIMIT S/W	SS400			1				
3	SAFETY LATCH	SPC			1				
2	EMERGENCY S/W	—			1				
1	LOAD LIMITER	—			1				
NO.	DESCRIPTION	MT'L	SUB QTY	TOTAL	SUB	TOTAL WEIGHT(Kg)	REMARKS.		
PROJECT			DATE		DIM				
TITLE	KD15 — L24 — D		SCALE		PROJECTION				
	ARRANGEMENT DRAWING FOR HOIST		A3/20		3rd				
DRAWN	SIGNED	CHECKED	APPROVED	REF.		DRAWING			
 극동호이스트 주식회사 KUK DONG HOIST CO., LTD.		SHEET No.		DWG No.		KD15D2400			

내일 < 화요일 > 15000 K
제한하중

VIEW A





SPECIFICATION			
HOISTING LOAD	15 TON		
TESTING LOAD	18.75 TON		
LIFT	30 M		
HOISTING	SPEED	4.5 M/MIN	
	MOTOR	13 KW x 8P	
LOW	SPEED	3 M/MIN	
	MOTOR	8.5 KW x 12P	
HIGH	SPEED	15 M/MIN	
	MOTOR	1.5 KW x 4 P (2UNIT)	
LOW	SPEED	10 M/MIN	
	MOTOR	1.0 KW x 6 P (2UNIT)	
DUAL	SPEED	15/7.5 M/MIN	
	MOTOR	1.5/0.75KWx4/8P (2UNIT)	
DUAL	SPEED	10/5 M/MIN	
	MOTOR	1.0/0.5KWx6/12P (2UNIT)	
WIRE ROPE (6x29 IWRC) ϕ 18 x 4 FALLS			
POWER SOURCE AC3 ϕ 220/380/440/460/480V 60Hz			
TRAVERSING RAIL			
GROSS WEIGHT 2250 KG			

극동호이스트
제한하중
15000 K

VIEW A



5	T/S RAIL	-	-	-	-	22KG/M	
4	UPPER LIMIT S/W	SS400	1				
3	SAFETY LATCH	SPC	1				
2	EMERGENCY S/W	-	1				
1	LOAD LIMITER	-	1				
NO.	DESCRIPTION	MT'L	SUB QTY	TOTAL	SUB WEIGHT(kg)	DATE	REMARKS.
PROJECT							
TITLE							
KD15 - L30 - D							
ARRANGEMENT DRAWING FOR HOIST							
DRAWN	DESIGNED	CHECKED	APPROVED	SCALE	PROJECTION	REF. DRAWING	
				A3/20	3rd		
SHEET No. DWG No. KD15D3000							
극동호이스트 주식회사 KUK DONG HOIST CO., LTD.							

ELECTRICAL SPECIFICATION

POWER SOURCE : AC 3Φ 220V, 380V, 440V, 460V, 480V 60Hz

CONTROL SOURCE : AC 1Φ 110V, 120V 60Hz

OBJECT	MOTOR OUTPUT	220V		380V		440V	460V	480V	440,460,480V	BRAKE	REMARK
		STATOR CURRENT	1st CABLE SIZE	STATOR CURRENT	1st CABLE SIZE	STATOR CURRENT	STATOR CURRENT	STATOR CURRENT	1st CABLE SIZE		
MAIN HOIST	HIGH	59.00 A	25.0 sq	34.20 A	16.0 sq	29.5 A	28.4 A	27.2 A	10.0 sq	DC MAG. BRAKE	
	LOW	58.60 A	25.0 sq	33.90 A	16.0 sq	29.3 A	28.1 A	26.9 A	10.0 sq	DC MAG. BRAKE	
TRAVERSING	HIGH	7.30 A	4.0 sq	4.20 A	4.0 sq	3.70 A	3.50 A	3.40 A	4.0 sq	DC MAG. BRAKE	1 DRIVE
	LOW	6.70 A	4.0 sq	3.90 A	4.0 sq	3.30 A	3.20 A	3.10 A	4.0 sq	DC MAG. BRAKE	1 DRIVE
CONTROL CIRCUIT		2 A	2.5 sq	2 A	2.5 sq	2 A	2 A	2 A	2.5 sq		
LIGHTING & ACC'Y CIRCUIT											
SUB TOTAL (PEAK LOAD)		HIGH	68.30 A	40.40 A	16.0 sq	35.20 A	33.90 A	32.60 A	10.0 sq	I(A)=M/H + T/S + ASS'Y	
SUB TOTAL (NORMAL LOAD)		LOW	67.30 A	39.80 A	16.0 sq	34.60 A	33.30 A	32.00 A	10.0 sq	I(A)=M/H + T/S + ASS'Y	

* 위 계산은 HIGH(MAX.)일때와 LOW(MIN.)일때만 계산한것임.

* 위 계산은 LIFT 12(18,24)M에 적용.

ELECTRICAL SPECIFICATION

. POWER SOURCE : AC 3Φ 220V, 380V, 440V,460V,480V 60Hz

. CONTROL SOURCE : AC 1Φ 110V, 120V 60Hz

OBJECT	MOTOR OUTPUT	220V		380V		440V	460V	480V	440,460,480V	BRAKE	REMARK
		STATOR CURRENT	1st CABLE SIZE	STATOR CURRENT	1st CABLE SIZE	STATOR CURRENT	STATOR CURRENT	STATOR CURRENT	1st CABLE SIZE		
MAIN HOIST	HIGH	59.00 A	25.0 sq	34.20 A	16.0 sq	29.5 A	28.4 A	27.2 A	10.0 sq	DC MAG. BRAKE	
	LOW	58.60 A	25.0 sq	33.90 A	16.0 sq	29.3 A	28.1 A	26.9 A	10.0 sq	DC MAG. BRAKE	
TRAVERSING	HIGH	(7.3)*2	4.0 sq	(4.2)*2	4.0 sq	(3.7)*2	(3.5)*2	(3.4)*2	4.0 sq	DC MAG. BRAKE	2 DRIVE
	LOW	(6.7)*2	4.0 sq	(3.9)*2	4.0 sq	(3.3)*2	(3.2)*2	(3.1)*2	4.0 sq	DC MAG. BRAKE	2 DRIVE
CONTROL CIRCUIT		2 A	2.5 sq	2 A	2.5 sq	2 A	2 A	2 A	2.5 sq		
LIGHTING & ACC'Y CIRCUIT											
SUB TOTAL (PEAK LOAD)		HIGH	75.60 A	44.60 A	16.0 sq	38.90 A	37.40 A	36.00 A	10.0 sq	I(A)=M/H + T/S + ASS'Y	
SUB TOTAL (NORMAL LOAD)		LOW	74.00 A	43.70 A	16.0 sq	37.90 A	36.50 A	35.10 A	10.0 sq	I(A)=M/H + T/S + ASS'Y	

*. 위 계산은 HIGH(MAX.)일때와 LOW(MIN.)일때만 계산한것임.

*. 위 계산은 LIFT 30M에 적용.


~~192.168.11.51 / 2019-05-21 13:51:47~~



NO	TYPE		
		220V	
1	VCT	25sqx4c	1
2	VCT	40sqx4c	1

A																
A																
A																
A																
MK	DATE															
REVISIONS										CHK.	APP.					
										GROUND WIRE SYSTEM						
										-----  극동호이스트 주식회사 KUK DONG HOIST CO., LTD.						
										DRAWING	DESIGN	CHECKED	APPROVED	SCALE	DATE	ORDER NO.
										NONE						
										DWG. NO						
										KD15D-E001						

A				CUSTOMER	DRAWING TITLE	DRAWING DESIGN CHECKED APPROVED SCALE DATE ORDER NO.
A						NONE
A					GROUND WIRE SYSTEM	KD KUK DONG HOIST CO., LTD.
A						
DATE				CHK.	APP.	DWG. NO KD15D-E001
REVISIONS						



본 도면은 EARTH를 명기하기 위한 도면으로서
실제 배치와 다를 수 있으며 HOIST 본체와의
EARTH용 CABLE은 REFERENCE임

NO	CABLE					REMARK
	TYPE	SIZE				
		220V	380V	TYPE		
		220V	380V	TYPE	440V,460V,480V	
1	VCT	25sqx4c	16sqx5c	VCT	10sqx5c	HOISTING MOTOR WITH EARTH
2	VCT	4.0sqx4c+2.5sqx3c		VCT	4.0sqx4c+2.5sqx3c	T/S MOTOR WITH EARTH
3	VCT	25sqx4c	16sqx4c	VCT	10sqx4c	MAIN POWER WITH EARTH


[illegible]

1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
															NO	DESCRIPTION			CABLE SIZE
															1	MAIN EARTH LINE			USER SCOPE
															2	POWER SOURCE			USER SCOPE
															3	TROLLEY BAR			USER SCOPE
															4	POWER SOURCE WITH EARTH			USER SCOPE
															5	HOIST POWER SOURCE WITH EARTH			220V : VCT 25.0SQ x 1C 380V : VCT 16.0SQ x 1C 440, 460, 480V : VCT 10.0SQ x 1C
															6	HOISTING MOTOR WITH EARTH			220V : VCT 25.0SQ x 1C 380V : VCT 16.0SQ x 1C 440, 460, 480V : VCT 10.0SQ x 1C
															7	TRAVERSING MOTOR WITH EARTH			VCT 4.0SQ x 1C

등전위점지

1. 전기검사와 기계의 노출된 모든 도전부는 보호분리막에 인접되어야 하며 적절한 접지연속성 기능이 유지되어야 함.
2. 보호분리막에는 때때, 과전류보호장치가 부착되지 않아야 한다.

시험대상 전선의 최소 유효단면적	최고전압강하(V)
1.0	3.3
1.5	2.6
2.5	1.6
4.0	1.4
>6.0	1.0



USER SCOPE

KUKDONG SCOPE


A				CUSTOMER	DRAWING	DRAWING	DESIGN	CHECKED	APPROVED	SCALE	DATE	ORDER NO.
A					TITLE	EARTH DETAILS DRAWING				NONE	2003.07.01	
A												
A												
MK	DATE	REVISIONS	CHK.	APP.				Kukdonghoist 주식회사 KUK DONG HOIST CO., LTD. 	DWG. NO		KD15-EC000	

[illegible]

동전위잡지

1. 전기장비와 기계의 노출된 모든 도전부는 보호봉합선에 연결되어야 하며 적절한 접지연속성 기능이 유지되어야 함.
2. 보호봉합선에는 개폐기, 과전류보호장치가 부착되지 않아야 한다.

시험대상 전선의 최소 유효단면적	최고전압강하(V)
1.0	3.3
1.5	2.6
2.5	1.6
4.0	1.4
>6.0	1.0



USER SCOPE

KUKDONG SCOPE

[illegible]

1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
																			ADR'S NO.

NO	DESCRIPTION	MT'L	REMARKS
1	PANEL CASE	SPC	1.6t
2	PANEL COVER	SPC	1.6t
3	HINGE	PUR'	
4	CLAMP	PUR'	
5	SPONGE	PUR'	
6	MIRCO S/W	PUR'	도어커버 개폐시 ON/OFF

NOTE

1.PROTECTION DEGREE ;
A, INDOOR TYPE : DUST PROOF
B, OUT DOOR TYPE : SPLASH PROOF

2.FINAL PAINTING COLOR (MUNSELL NO.)
A. IN SIDE : 10B 3/5
B. OUT SIDE : 10B 3/5

3.PAINTING THICKNESS :ABOVE 40 um


4.APPLICATION VOLTAGE : 220V,380V,440V,460V,480V

5.제어용 전선 : 1.5sq KIV,HIV


6.외함 개방구조는 다음과 같다.
1) 외함 개방시 충전부분이 차단되도록 한다.
2) 외함 개방 후 충전되어있는 부분은 IP2X 이상의 직접접촉 방호가 되어있을것.

SELECTION	HOIST CAPACITY	DESCRIPTION	IN DOOR			OUT DOOR			REMARK
			A	B	L	A	B	L	
	15 TON	NORMAL	650	220	850	650	220	850	
	15 TON	CREEP	650	220	850	650	220	850	

 KDK	DRAWING	DESIGN	CHECKED	APPROVED	SCALE	DATE	ORDER NO.
	HOISTING CONTROL BOX LAY-OUT						 KDK
CUSTOMER		DRAWING TITLE		DWG. NO		KD15EB00	



1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20.
ADR'S NO.																			



NOTE

1. UPPER LIMIT LS-1의 전점 허용 전류 용량 : AC 600V, 3A
2. UPPER LIMIT LS-2의 전점 허용 전류 용량 : NFB 103AF
3. EARTH TERMINAL RESISTANCE : 0.018 Ω
4. POWER SOURCE : AC. 3Ø 220V 60HZ





- NOTE 1. 전선의 색상은 다음과 같다.
- 1) 흑색 : 교류 및 직류 전원선으로
 - 2) 적색 : 교류제어회로
 - 3) 주황색 : 외부 전원선에서 공급되는 전동장치 제어회로
 - 4) 녹색 또는 녹색과 황색 혼용 : 접지선
2. CABLE MATERIAL : KIV OR EQUIVALENT
3. 제어용 전선 : 1.5mm KIV,HIV
4. 제작시 다소 변경 될수있음.
5. 외함 개방시 증전부본이 차단되도록 함것.
- 1) 외함 개방후 증전부본이 차단되도록 함것.
- 2) 외함 개방후 증전부본이 차단되도록 함것.

— 주형 포함 시 3. MAIN MAG. 삭제 —

NO	DESCRIPTION	SPECIFICATION	Q'TY	REMARK
1	CHASSIS PLATE		1	아 연 도 금
2	CABLE DUCT	—	1	
3	MAGNET CONTACT	DMC85	1	M1, MAIN MAG.
4	MAGNET CONTACT	MC-185a	2	HOISTING
5	MAGNET CONTACT	DMC22b	2	TRAVERSING
7	SILICON RECTIFIER	SR-60	1	HOISTING
8	SILICON RECTIFIER	SR-30	1	TRAVERSING
9	E.O.C.R	SS-100	1	HOISTING
10	E.O.C.R	SS-30	1	TRAVERSING
11	MCCB100	103AF/100AT	1	LS-2
12	UPPER LIMIT	AC 600V/3A	1	LS-1
13	LIMIT LEVER	SS400	1	
14	FUSE (F11,F12)	3 A	2	
15	FUSE (F13)	5 A	1	
16	TRANSFORMER	220V/110,120V, 200VA	1	
17	TERMINAL BLOCK	100A,25A		
18	TERMINAL BLOCK	15A		
19	EARTH TERMINAL	5tx25x50	1	


DRAWING	DESIGN	CHECKED	APPROVED	SCALE	DATE	ORDER NO.
				NONE		
HOISTING CONTROL BOX						
ARRANGEMENT DRAWING						
극동호이스트 주식회사 KUK DONG HOIST CO., LTD.						KD15BA21
DATE	REVISIONS	CHK.	APP.	DWG. NO		






SPECIFICATION SYMBOLS	HOISTING POWER	HOISTING MOTOR	TRAVERSING MOTOR	DC MAG. BRAKE	NO FUSE BREAKER	TRANSFORMER	FUSE	MAIN MAGNET	MAGNET CONTACTOR	UPPER LIMIT	ELECTRIC OVER CURRENT RELAY	SILICON RECTIFIER	LOAD LIMITER	CABLE						
DESCRIPTION	HOIST	IM 10	IM 31,32	DB10,31,32	LS - II & MCCB100	TR 1	F11,F12	M1	M101,M102,M301,M302	LS-I	EOCR100	EOCR300	RF100	RF300	C20-01					
							15TON AC3PH 220V 60Hz	13KW x 8P	1.5KW x 4P	DC 100V	ABS-103AF/100AT	220/110,120V,200VA	3A	5A	DMC85	MC-185a	DMC22b	AC 600V 3A	SS-100	SS-30
	15TON AC3PH 220V 60Hz	8.5KWx12P	1.0KW x 6P	DC 100V	ABS-103AF/100AT	220/110,120V,200VA	3A	5A	DMC85	MC-185a	DMC22b	AC 600V 3A	SS-100	SS-30	SR-60	SR-30	JDL-100	VCT 25sq x 4C		
SELECTION MAKER	KUKDONG																			
					CUSTOMER				DRAWING	DESIGN	CHECKED	APPROVED	SCALE	DATE	ORDER NO.					
	HOISTING & T/S POWER CONTROL CIRCUIT																			
	DRAWING TITLE																			
	REVISIONS																			
	CHK. APP.																			
DATE	KUKDONG HOIST CO., LTD.														DWG. NO			KD15E23		

1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
POWER CIRCUIT										TRaversing Motion									
HOISTING MOTION										B1									
ADR'S NO.										B1									





SPECIFICATION SYMBOLS	HOISTING POWER	HOISTING MOTOR	TRAVERSING MOTOR	DC MAG. BRAKE	NO FUSE BREAKER	TRANSFORMER	FUSE	MAGNET CONTACTOR	UPPER LIMIT	ELECTRIC OVER CURRENT RELAY	SILICON RECTIFIER	LOAD LIMITER	CABLE	
DESCRIPTION	HOIST	IM 10	IM 31,32	DB10,31,32	LS - II & MCCB100	TR 1	F11,F12	M101,M102,M301,M302	LS-I	EOCR100	RF100	RF300	C20-01	
	15TON AC3PH 220V 60Hz	13KW x 8P	1.5KW x 4P	DC 100V	ABS-103AF/100AT	220/110,120V,200VA	3A	5A MC-185a	AC 600V 3A	SS-100	SR-60	JDL-100	VCT 25sq x 4C	
	15TON AC3PH 220V 60Hz	8.5KWx12P	1.0KW x 6P	DC 100V	ABS-103AF/100AT	220/110,120V,200VA	3A	5A MC-185a	AC 600V 3A	SS-100	SR-60	JDL-100	VCT 25sq x 4C	
SELECTION MAKER	KUKDONG			LS		SHINHAN	LS		KUKDONG	ASECO		JUNGHO	DONGIL	
				CUSTOMER										ORDER NO.
				DRAWING TITLE		HOISTING & T/S POWER CONTROL CIRCUIT								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
						KUKDONG HOIST CO., LTD.								
				</										


1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
POWER CIRCUIT										TRaversing Motion									
HOISTING MOTION										B1									
C20-01										ADR'S NO.									




SPECIFICATION SYMBOLS	HOISTING POWER	HOISTING MOTOR	TRaversing MOTOR	DC MAG. BRAKE	NO FUSE BREAKER	TRANSFORMER	FUSE	MAIN MAGNET	MAGNET CONTACTOR	UPPER LIMIT	ELECTRIC OVER CURRENT RELAY	SILICON RECTIFIER	LOAD LIMITER	CABLE
DESCRIPTION	HOIST	IM 10	IM 31, 32	DB10, 31, 32	LS-II & MCCB100	TR 1	F11, F12	M1	M101, M102	LS-I	EOCR100	RF100	LOAD LIMITER	C20-01
	15TON AC3PH 380V 60Hz	13KW x 8P	1.5KW x 4P	DC 100V	ABS-53AF/50AT	380/110, 120V, 200VA	2A	DMC50	MC-100a	AC 600V 3A	SS-60	SR-60	JDL-100	VCT 16sqx4c
	15TON AC3PH 380V 60Hz	8.5KW x 12P	1.0KW x 6P	DC 100V	ABS-53AF/50AT	380/110, 120V, 200VA	2A	DMC50	MC-100a	AC 600V 3A	SS-60	SR-60	JDL-100	VCT 16sqx4c
SELECTION MAKER	KUKDONG													
	KUKDONG				LS	SHINHAN	-	DONG-A	LS	DONG-A	KUKDONG	ASECO	JUNGHO	DONGIL
	CUSTOMER				DRAWING				DESIGN	CHECKED	APPROVED	SCALE	DATE	ORDER NO.
	DRAWING TITLE				HOISTING & T/S POWER CONTROL CIRCUIT									
	REVISIONS				DIAGRAM									
DATE					CHK.				DWG. NO				KD15E33	
MK									KUKDONG HOIST CO., LTD.					










192.168.11.51 / 2019-05-21 13:51:47



NOTE

1. UPPER LIMIT LS-1의 접점 허용 전류 용량 : AC 600V, 3A
2. UPPER LIMIT LS-2의 접점 허용 전류 용량 : NFB 53AF
3. EARTH TERMINAL RESISTANCE : 0.018 Ω
4. POWER SOURCE : AC. 3φ 460V 60HZ




NOTE 1. 전선의 색상은 다음과 같다.

- 1) 흑색 : 교류 및 직류 전원선으로 5) 정색 : 직류 제어선으로
 - 2) 적색 : 교류제어회로
 - 3) 파랑색 : 외부 전원에서 공급되는 연동장치 제어회로
 - 4) 녹색 또는 녹색과 황색 혼용 : 접지선
2. CABLE MATERIAL : KIV OR EQUIVALENT
MIN SIZE : 1.5sq
3. 제어용 전선 : 1.5mm KIV, H1V
 4. 제어시 다소 변경 될수있음.
 5. 외함 개방구조는 다음과 같을것.
- 1) 외함 개방시 승전부분이 차단되도록 할것.
 - 2) 외함 개방후 승전되어있는 부분은 IP2X 이상의 직접 접촉 방호가 되어있을것.

— 주행 포함 시 3. MAIN MAG. 삭제 —


NO	DESCRIPTION	SPECIFICATION	Q'TY	REMARK
1	CHASSIS PLATE		1	아 연 도 플
2	CABLE DUCT	-	1	
3	MAGNET CONTACT	DMC50	1	M1, MAIN MAG.
4	MAGNET CONTACT	DMC85	2	HOISTING
5	MAGNET CONTACT	DMC22b	2	TRAVERSING
7	SILICON RECTIFIER	SR-60	1	HOISTING
8	SILICON RECTIFIER	SR-30	1	TRAVERSING
9	E.O.C.R	SS-60	1	HOISTING
10	E.O.C.R	SS-05 (30M : SS-30)	1	TRAVERSING
11	MCCB100	53AF/40AT	1	LS-2
12	UPPER LIMIT	AC 600V/3A	1	LS-1
13	LIMIT LEVER	SS-400	1	
14	FUSE (F11,F12)	2 A	2	
15	FUSE (F13)	5 A	1	
16	TRANSFORMER	460V/110,120V, 200VA	1	
17	TERMINAL BLOCK	60A,25A		
18	TERMINAL BLOCK	15A		
19	EARTH TERMINAL	5t25x50	1	

DRAWING	DESIGN	CHECKED	APPROVED	SCALE	DATE	ORDER NO.
				NONE		
 극동호이스트 주식회사 KUK DONG HOIST CO., LTD.						KD15BA51
KD-WM-20T-L12 HOISTING CONTROL BOX ARRANGEMENT DRAWING						
CUSTOMER						
DRAWING TITLE						
REVISIONS						
DATE	CHK.	APP.				






1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20											
POWER CIRCUIT										TRaversing Motion										B1		ADR'S NO.								
																				C20-01										
SPECIFICATION SYMBOLS		HOISTING POWER	HOIST	HOISTING MOTOR	IM 10	TRaversing MOTOR	IM 31, 32	DC MAG. BRAKE	DB10, 31, 32	NO FUSE BREAKER	LS-II & MCCB100	TRANSFORMER	TR 1	FUSE	F11, F12	F13	MAIN MAGNET	M1	MAGNET CONTACTOR	M101, M102	UPPER LIMIT	LS-I	ELECTRIC OVER CURRENT RELAY	EOCR300	SILICON RECTIFIER	RF100	LOAD LIMITER	RF300	CABLE	C20-01
DESCRIPTION		15TON AC3PH 460V 60Hz	1.3KW x 8P	1.5KW x 4P	1.5KW x 4P	1.5KW x 4P	1.5KW x 4P	DC 100V	DC 100V	ABS-53AF/40AT	ABS-53AF/40AT	460/110, 120V, 200VA	2A	2A	2A	5A	DMC50	DMC85	DMC22b	DMC22b	AC 600V 3A	SS-60	SS-60	SS-60	SR-60	SR-30	JDL-100	VCT 10sqx4c		
SELECTION MAKER		15TON AC3PH 460V 60Hz	8.5KW x 12P	1.0KW x 6P	1.0KW x 6P	1.0KW x 6P	1.0KW x 6P	DC 100V	DC 100V	ABS-53AF/40AT	ABS-53AF/40AT	460/110, 120V, 200VA	2A	2A	2A	5A	DMC50	DMC85	DMC22b	DMC22b	AC 600V 3A	SS-60	SS-60	SS-60	SR-60	SR-30	JDL-100	VCT 10sqx4c		
KUKDONG																				ASECO		JUNGHO		DONGIL						
CUSTOMER																				APPROVED		SCALE		DATE		ORDER NO.				
DRAWING TITLE		HOISTING & T/S POWER CONTROL CIRCUIT																		DESIGN		CHECKED		NONE						
REVISIONS		DIAGRAM																		DWG. NO		KUKDONG HOIST CO., LTD.		KD15E53						
DATE																				KUKDONG HOIST CO., LTD.		KUKDONG		JUNGHO		DONGIL				
CHK.																				KUKDONG HOIST CO., LTD.		KUKDONG		JUNGHO		DONGIL				
APP.																				KUKDONG HOIST CO., LTD.		KUKDONG		JUNGHO		DONGIL				
MK																				KUKDONG HOIST CO., LTD.		KUKDONG		JUNGHO		DONGIL				




1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
POWER CIRCUIT																			
TRAVERSING MOTION																			
ADR'S NO.																			C2



--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--

1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
POWER CIRCUIT																			
TRAVERSING MOTION																			
C2																			ADR'S NO.





SPECIFICATION	SYMBOLS	DESCRIPTION	DC MAG' BRAKE	MAGNET CONTACTOR	SILICON RECTIFIER	ELECTRIC OVER CURRENT RELAY	TRANSFORMER
		TRAVERSING MOTOR	DB30, 31	M301, M302, M303, M304, M305	RF 300	EOCR 301,302	TR300
		IM 30, 31					
		460V 1.5/0.75KWx4/8P AC3PH 460V 60Hz	DC 100V	DMC22b	SR-30	SS-30	AC460/220V, 500VA
		460V 1.0/0.5KWx6/12P AC3PH 460V 60Hz	DC 100V	DMC22b	SR-30	SS-30	AC460/220V, 500VA
SELECTION	MAKER	DONG-A					
		KUKDONG					
		ASECO					
		SHINHAN					
DRAWING		DESIGN	CHECKED	APPROVED	SCALE	DATE	ORDER NO.
TRAVERSING POWER CONTROL CIRCUIT					NONE		
DRAWING TITLE		KUK DONG HOIST CO., LTD.					
CHK. APP.		DWG. NO					
REVISIONS		KD15E56					
MK	DATE						


[illegible]


192.168.11.51 / 2019-05-21 13:51:47


192.168.11.51 / 2019-05-21 13:51:47












SPECIFICATION		EMERGENCY		TIME RELAY		LOAD LIMITER		LIMIT SWITCH	
SYMBOLS	DESCRIPTION	UPPER LIMIT	S/W	T301,302	LOAD LIMITER	LS-301,302	LS-301,302	LS-301,302	LS-301,302
		LS-1	E.S.B	T301,302	LOAD LIMITER	JDL-100	KG-L001	KG-AUTO	KG-AUTO
		AC 600V 3A	250V 3A	LA2DT2	JUNCHO	LS	KG-AUTO	KG-AUTO	KG-AUTO
		KUKDONG	KG-AUTO	LS	DATE	SCALE	ORDER NO.		
		CHECKED	APPROVED	NONE					
		DESIGN							
		DRAWING							
		MAIN POWER 2 & CONTROL CIRCUIT							
		DIAGRAM							
		CUSTOMER							
		DRAWING TITLE							
		REVISIONS							
		DATE	CHK.	APP.					
		KUK DONG HOIST CO., LTD.							
		DWG. NO							
		KD15E005							





R1	S1	T1		U30	V30	W30	P30	N30	C2	P	ED1	R30A	WD1	R30A	HS1
----	----	----	--	-----	-----	-----	-----	-----	----	---	-----	------	-----	------	-----



P	ED1	MD1	MD2A	HS1	
---	-----	-----	------	-----	--


11	EARTH BUS BAR	PUR	1		
10	DUCT	PUR	1		
9	TERMINAL BLOCK	PUR	1		
8	INVERTER	PUR	1		
7	TR	PUR	1		
6	RELAY & SCKET	PUR	1		
5	RF	PUR	1		
4	MC	PUR	1		
3	MCCB	PUR	1		

2	속판	SS400		1									
1	T/S BOX	PUR		1									
NO.	DESCRIPTION	MTL	SUB	TOTAL	SUB	TOTAL	WEIGHT(kg)	REMARKS.					
			QTY										
PROJECT						DATE		DIM					
TITLE						SCALE		PROJECTION					
		T/S CONTROL PANEL(INVERTER)				A3/3		3/d					
DRAWN	DESIGNED	CHECKED	APPROVED		REF. DRAWING								
 극동호이스트 주식회사 KUK DONG HOIST CO., LTD.		SHEET No.		DWG No.		KD15EI001							

[illegible]

1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
POWER CIRCUIT DIAGRAM										CONTROL CIRCUIT DIAGRAM									
TRAVERSING MOTION										HIGH SPEED									
E R101 S101 T101										ADR'S NO.									
																			
SPECIFICATION SYMBOLS										SILICON RECTIFIER									
DESCRIPTION										INVERTER									
SELECTION MAKER										CONTROL RELAY									
TRAVERSING POWER										BRAKE MAGNET									
IM 30,31										M301									
1.0KW x 6P										DMC22b									
AC 3PH 220V 60Hz										380(440,460,480)/220V,500VA									
AC 3PH 380(440,460,480)V 60Hz										LS									
KUK DONG HOIST										DRAWING									
CUSTOMER										DESIGN									
INVERTER CONTROL										CHECKED									
DRAWING TITLE										APPROVED									
TRAVERSING POWER & CONTROL CIRCUIT										SCALE									
DIAGRAM										DATE									
KUK DONG HOIST CO., LTD.										ORDR NO.									
REVISIONS										DWG. NO									
CHK. APP.										KD15E1003									
DATE																			

1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
POWER CIRCUIT DIAGRAM										CONTROL CIRCUIT DIAGRAM									
TRAVERSING MOTION										BRAKE EAST WEST HIGH SPEED									
E R101 STATION 101										PSB									
																			
SPECIFICATION SYMBOLS DESCRIPTION										TRANSFORMER									
AC 3PH 220V 60Hz										TR 300									
AC 3PH 380(440,460,480)V 60Hz										380(440,460,480)/220V,500VA									
SELECTION MAKER										LS									
TRAVERSING POWER										NO FUSE BREAKER									
IM 30,31										MCCB300									
1.5KW x 4P										ABE-33AF/20AT									
1.5KW x 4P										ABE-33AF/15AT									
KUK DONG HOIST										LS									
CUSTOMER										INVERTER CONTROL									
DRAWING TITLE										TRAVERSING POWER & CONTROL CIRCUIT									
REVISIONS										DIAGRAM									
DATE										KUK DONG HOIST CO., LTD.									
CHK. APP.										KUK DONG HOIST CO., LTD.									
DRAWING NO										DWG. NO									
ORDER NO.										KD15E1005									



색상	구분	조각번호	포시등
적색		비상	비상
황색		비정상	비정상
녹색		정상	정상
청색		의무	의무
흰색, 회색, 흑색		지정된의미없음	기타


* MATERIAL : POLYCARBONATE(PLASTIC)

* BODY COLOR : YELLOW, BLACK

* IP : 55 이상

NO	SYMBOL	TYPE	SPEC.	COLOR
1	E.B.S	PUSH LOCK TURN RESET TYPE	250VAC x 6A	RED
2	SPARE			
3	상	1PUSH BUTTON 1STEP (2STEP)		BLACK
4	하	1PUSH BUTTON 1STEP (2STEP)		
5	동(전)	1PUSH BUTTON 1STEP (2STEP)		
6	서(후)	1PUSH BUTTON 1STEP (2STEP)		
7	보조 와이어	ø 2.0		

REV	DATE	DESCRIPTION	DRAWN	CHECK	APPROV	TITLE	CUSTOMER	DESIGN	SCALE	SHT. NO.	ORDER NO.
05.AUG.2016		REDRAWING	K.H.Han			PENDANT PUSH BUTTON SWITCH LAY OUT	크동호이스트 주식회사 KUKDONG HOIST CO., LTD.				



색상	구분	조작버튼	표시등
좌측	비상	비상	비상
우측	비상	비상	비상
중심	정상	정상	정상
상단	의무	의무	의무
하단	지정된의미없음	지정된의미없음	기타

* MATERIAL : POLYCARBONATE(PLASTIC)

* BODY COLOR : YELLOW, BLACK

* IP : 55 이상

NO	SYMBOL	TYPE	SPEC.	COLOR
1	E.B.S	PUSH LOCK TURN RESET TYPE	250VAC x 6A	RED
2	SPARE			
3	상	1PUSH BUTTON 1STEP (2STEP)		BLACK
4	하	1PUSH BUTTON 1STEP (2STEP)		
5	동 (좌)	1PUSH BUTTON 1STEP (2STEP)		
6	서 (우)	1PUSH BUTTON 1STEP (2STEP)		
7	남 (전)	1PUSH BUTTON 1STEP		
8	북 (후)	1PUSH BUTTON 1STEP		
9	보조 WIRE	ø 2.0		

REV	DATE	REDRAWING	DESCRIPTION	DRAWN	CHECK	APPROVD	TITLE	CUSTOMER	DESIGN	SCALE	SHT. NO.	ORDER NO.
05.AUG.2016				K.H.Han			PENDANT PUSH BUTTON SWITCH LAY OUT	극동호이스트 주식회사 KUDDONG HOIST CO., LTD.				

LOAD LIMITER 권고 SETTING치

극동하이스트(주)

* POWER SOURCE : AC 3Φ 220V 60Hz

HOIST	MOTOR 용량	LOAD LIMITER 권고 SETTING치			LOAD CURRENT		C.T MODEL	연결단자 NO	C.T 용량	REMARK
		LOAD CURRENT	ADJ START TIME	SHOCK TIME	100%	110%				
10 TON	9.0KW x 8P	110%	1 SEC	1 SEC	45.0 A	49.5 A	CT-2	K-K1, L-L1	5 V.A	
	13KW x 6P	110%	1 SEC	1 SEC	53.0 A	58.3 A	CT-2	K-K1, L-L1	5 V.A	
15 TON	8.5KW x 12P	110%	1 SEC	1 SEC	58.6 A	64.4 A	CT-2	K-K1, L-L1	5 V.A	
	13KW x 8P	110%	1 SEC	1 SEC	59.0 A	64.9 A	CT-2	K-K1, L-L1	5 V.A	
20 TON	11.5KW x 12P	110%	1 SEC	1 SEC	70.8 A	77.9 A	CT-2	K-K1, L-L1	5 V.A	
	17KW x 8P	110%	1 SEC	1 SEC	76.6 A	84.3 A	CT-2	K-K1, L-L1	5 V.A	
	23KW x 6P	110%	1 SEC	1 SEC	93.2 A	100.4 A	CT-2	K-K1, L-L1	5 V.A	
30 TON	11.5KW x 12P	110%	1 SEC	1 SEC	70.8 A	77.9 A	CT-2	K-K1, L-L1	5 V.A	
	17KW x 8P	110%	1 SEC	1 SEC	76.6 A	84.3 A	CT-2	K-K1, L-L1	5 V.A	
	23KW x 6P	110%	1 SEC	1 SEC	93.2 A	100.4 A	CT-2	K-K1, L-L1	5 V.A	
35 TON	33KW x 6P	110%	1 SEC	1 SEC	126.6 A	134.2 A	CT-2	K-K1, L-L1	5 V.A	
40 TON	33KW x 6P	110%	1 SEC	1 SEC	126.6 A	134.2 A	CT-2	K-K1, L-L1	5 V.A	
50 TON	33KW x 6P	110%	1 SEC	1 SEC	126.6 A	134.2 A	CT-2	K-K1, L-L1	5 V.A	
60 TON	33KW x 6P	110%	1 SEC	1 SEC	126.6 A	134.2 A	CT-2	K-K1, L-L1	5 V.A	
70 TON	33KW x 6P	110%	1 SEC	1 SEC	126.6 A	134.2 A	CT-2	K-K1, L-L1	5 V.A	

NOTE

1. 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

LOAD LIMITER 권고 SETTING치

극동호이스트(주)

* POWER SOURCE : AC 3ϕ 380V 60Hz

HOIST	MOTOR 용량	LOAD LIMITER 권고 SETTING치			LOAD CURRENT		C.T MODEL	연결단자 NO	C.T 용량	REMARK
		LOAD CURRENT	ADJ START TIME	SHOCK TIME	100%	110%				
10 TON	9.0KW x 8P	110%	1 SEC	1 SEC	26.0 A	28.6 A	CT-2	K-K1, L-L1	5 V.A	
	13KW x 6P	110%	1 SEC	1 SEC	30.7 A	33.8 A	CT-2	K-K1, L-L1	5 V.A	
15 TON	8.5KW x 12P	110%	1 SEC	1 SEC	33.9 A	38.3 A	CT-2	K-K1, L-L1	5 V.A	
	13KW x 8P	110%	1 SEC	1 SEC	34.2 A	38.8 A	CT-2	K-K1, L-L1	5 V.A	
20 TON	11.5KW x 12P	110%	1 SEC	1 SEC	41.0 A	46.8 A	CT-2	K-K1, L-L1	5 V.A	
	17KW x 8P	110%	1 SEC	1 SEC	44.3 A	50.1 A	CT-2	K-K1, L-L1	5 V.A	
	23KW x 6P	110%	1 SEC	1 SEC	54.0 A	60.2 A	CT-2	K-K1, L-L1	5 V.A	
30 TON	11.5KW x 12P	110%	1 SEC	1 SEC	41.0 A	46.8 A	CT-2	K-K1, L-L1	5 V.A	
	17KW x 8P	110%	1 SEC	1 SEC	44.3 A	50.1 A	CT-2	K-K1, L-L1	5 V.A	
	23KW x 6P	110%	1 SEC	1 SEC	54.0 A	60.2 A	CT-2	K-K1, L-L1	5 V.A	
35 TON	33KW x 6P	110%	1 SEC	1 SEC	77.3 A	82.8 A	CT-2	K-K1, L-L1	5 V.A	
40 TON	33KW x 6P	110%	1 SEC	1 SEC	77.3 A	82.8 A	CT-2	K-K1, L-L1	5 V.A	
50 TON	33KW x 6P	110%	1 SEC	1 SEC	77.3 A	82.8 A	CT-2	K-K1, L-L1	5 V.A	
60 TON	33KW x 6P	110%	1 SEC	1 SEC	77.3 A	82.8 A	CT-2	K-K1, L-L1	5 V.A	
70 TON	33KW x 6P	110%	1 SEC	1 SEC	77.3 A	82.8 A	CT-2	K-K1, L-L1	5 V.A	

NOTE

1. 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

LOAD LIMITER 권고 SETTING치

극동호이스트(주)

* POWER SOURCE : AC 3Φ 440V 60Hz

HOIST	MOTOR 용량	LOAD LIMITER 권고 SETTING치			LOAD CURRENT		C.T MODEL	연결단자 NO	C.T 용량	REMARK
		LOAD CURRENT	ADJ START TIME	SHOCK TIME	100%	110%				
10 TON	9.0KW x 8P	110%	1 SEC	1 SEC	22.5 A	24.8 A	CT-2	K-K1, L-L1	5 V.A	
	13KW x 6P	110%	1 SEC	1 SEC	26.5 A	29.2 A	CT-2	K-K1, L-L1	5 V.A	
15 TON	8.5KW x 12P	110%	1 SEC	1 SEC	29.3 A	33.4 A	CT-2	K-K1, L-L1	5 V.A	
	13KW x 8P	110%	1 SEC	1 SEC	29.5 A	33.6 A	CT-2	K-K1, L-L1	5 V.A	
20 TON	11.5KW x 12P	110%	1 SEC	1 SEC	35.4 A	39.7 A	CT-2	K-K1, L-L1	5 V.A	
	17KW x 8P	110%	1 SEC	1 SEC	38.3 A	42.1 A	CT-2	K-K1, L-L1	5 V.A	
30 TON	23KW x 6P	110%	1 SEC	1 SEC	46.6 A	50.3 A	CT-2	K-K1, L-L1	5 V.A	
	11.5KW x 12P	110%	1 SEC	1 SEC	35.4 A	39.7 A	CT-2	K-K1, L-L1	5 V.A	
35 TON	17KW x 8P	110%	1 SEC	1 SEC	38.3 A	42.1 A	CT-2	K-K1, L-L1	5 V.A	
	23KW x 6P	110%	1 SEC	1 SEC	46.6 A	50.3 A	CT-2	K-K1, L-L1	5 V.A	
40 TON	33KW x 6P	110%	1 SEC	1 SEC	63.6 A	68.6 A	CT-2	K-K1, L-L1	5 V.A	
	33KW x 6P	110%	1 SEC	1 SEC	63.6 A	68.6 A	CT-2	K-K1, L-L1	5 V.A	
50 TON	33KW x 6P	110%	1 SEC	1 SEC	63.6 A	68.6 A	CT-2	K-K1, L-L1	5 V.A	
	33KW x 6P	110%	1 SEC	1 SEC	63.6 A	68.6 A	CT-2	K-K1, L-L1	5 V.A	
60 TON	33KW x 6P	110%	1 SEC	1 SEC	63.6 A	68.6 A	CT-2	K-K1, L-L1	5 V.A	
	33KW x 6P	110%	1 SEC	1 SEC	63.6 A	68.6 A	CT-2	K-K1, L-L1	5 V.A	
70 TON	33KW x 6P	110%	1 SEC	1 SEC	63.6 A	68.6 A	CT-2	K-K1, L-L1	5 V.A	
	33KW x 6P	110%	1 SEC	1 SEC	63.6 A	68.6 A	CT-2	K-K1, L-L1	5 V.A	

NOTE

1. 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

LOAD LIMITER 권고 SETTING치

* POWER SOURCE : AC 3ϕ 460V 60Hz 극동호이스트(주)

HOIST	MOTOR 용량	LOAD LIMITER 권고 SETTING치			LOAD CURRENT		C.T MODEL	연결단자 NO	C.T 용량	REMARK
		LOAD CURRENT	ADJ START TIME	SHOCK TIME	100%	110%				
10 TON	9.0KW x 8P	110%	1 SEC	1 SEC	21.5 A	23.7 A	CT-2	K-K1, L-L1	5 V.A	
	13KW x 6P	110%	1 SEC	1 SEC	25.4 A	28.0 A	CT-2	K-K1, L-L1	5 V.A	
15 TON	8.5KW x 12P	110%	1 SEC	1 SEC	28.1 A	32.0 A	CT-2	K-K1, L-L1	5 V.A	
	13KW x 8P	110%	1 SEC	1 SEC	28.4 A	32.1 A	CT-2	K-K1, L-L1	5 V.A	
20 TON	11.5KW x 12P	110%	1 SEC	1 SEC	33.9 A	37.7 A	CT-2	K-K1, L-L1	5 V.A	
	17KW x 8P	110%	1 SEC	1 SEC	36.7 A	40.5 A	CT-2	K-K1, L-L1	5 V.A	
	23KW x 6P	110%	1 SEC	1 SEC	44.5 A	48.3 A	CT-2	K-K1, L-L1	5 V.A	
30 TON	11.5KW x 12P	110%	1 SEC	1 SEC	33.9 A	37.7 A	CT-2	K-K1, L-L1	5 V.A	
	17KW x 8P	110%	1 SEC	1 SEC	36.7 A	40.5 A	CT-2	K-K1, L-L1	5 V.A	
	23KW x 6P	110%	1 SEC	1 SEC	44.5 A	48.3 A	CT-2	K-K1, L-L1	5 V.A	
35 TON	33KW x 6P	110%	1 SEC	1 SEC	60.5 A	65.5 A	CT-2	K-K1, L-L1	5 V.A	
40 TON	33KW x 6P	110%	1 SEC	1 SEC	60.5 A	65.5 A	CT-2	K-K1, L-L1	5 V.A	
50 TON	33KW x 6P	110%	1 SEC	1 SEC	60.5 A	65.5 A	CT-2	K-K1, L-L1	5 V.A	
60 TON	33KW x 6P	110%	1 SEC	1 SEC	60.5 A	65.5 A	CT-2	K-K1, L-L1	5 V.A	
70 TON	33KW x 6P	110%	1 SEC	1 SEC	60.5 A	65.5 A	CT-2	K-K1, L-L1	5 V.A	

NOTE

1. 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

LOAD LIMITER 권고 SETTING치

* POWER SOURCE : AC 3Φ 480V 60Hz

극동하이스트(주)

HOIST	MOTOR 용량	LOAD LIMITER 권고 SETTING치			LOAD CURRENT		C.T MODEL	연결단자 NO	C.T 용량	REMARK
		LOAD CURRENT	ADJ START TIME	SHOCK TIME	100%	110%				
10 TON	9.0KW x 8P	110%	1 SEC	1 SEC	20.6 A	22.7 A	CT-2	K-K1, L-L1	5 V.A	
	13KW x 6P	110%	1 SEC	1 SEC	25.4 A	28.0 A	CT-2	K-K1, L-L1	5 V.A	
15 TON	8.5KW x 12P	110%	1 SEC	1 SEC	26.9 A	31.1 A	CT-2	K-K1, L-L1	5 V.A	
	13KW x 8P	110%	1 SEC	1 SEC	27.2 A	31.4 A	CT-2	K-K1, L-L1	5 V.A	
20 TON	11.5KW x 12P	110%	1 SEC	1 SEC	32.5 A	36.9 A	CT-2	K-K1, L-L1	5 V.A	
	17KW x 8P	110%	1 SEC	1 SEC	35.2 A	39.6 A	CT-2	K-K1, L-L1	5 V.A	
	23KW x 6P	110%	1 SEC	1 SEC	42.6 A	46.9 A	CT-2	K-K1, L-L1	5 V.A	
30 TON	11.5KW x 12P	110%	1 SEC	1 SEC	32.5 A	36.9 A	CT-2	K-K1, L-L1	5 V.A	
	17KW x 8P	110%	1 SEC	1 SEC	35.2 A	39.6 A	CT-2	K-K1, L-L1	5 V.A	
	23KW x 6P	110%	1 SEC	1 SEC	42.6 A	46.9 A	CT-2	K-K1, L-L1	5 V.A	
35 TON	33KW x 6P	110%	1 SEC	1 SEC	58.0 A	62.8 A	CT-2	K-K1, L-L1	5 V.A	
40 TON	33KW x 6P	110%	1 SEC	1 SEC	58.0 A	62.8 A	CT-2	K-K1, L-L1	5 V.A	
50 TON	33KW x 6P	110%	1 SEC	1 SEC	58.0 A	62.8 A	CT-2	K-K1, L-L1	5 V.A	
60 TON	33KW x 6P	110%	1 SEC	1 SEC	58.0 A	62.8 A	CT-2	K-K1, L-L1	5 V.A	
70 TON	33KW x 6P	110%	1 SEC	1 SEC	58.0 A	62.8 A	CT-2	K-K1, L-L1	5 V.A	

NOTE

1. 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

E.O.C.R 권고 SETTING치

* POWER SOURCE : AC 3Φ 220V 60Hz

극동호이스트(주)

HOIST	MOTOR 용량	MOTOR 정격 전류	DRIVE TYPE	E.O.C.R TYPE	권고 SETTING 치			REMARK
					DELAY TIME	ERATION TI	CURRENT	
10 TON	9.0KW x 8P	45.0 A	1 DRAVE	SS-60	3 SEC	1 SEC	45.0 A	
	13KW x 6P	53.0 A	1 DRAVE	SS-60	3 SEC	1 SEC	53.0 A	
15 TON	8.5KW x 12P	58.6 A	1 DRAVE	SS-100	3 SEC	1 SEC	58.6 A	
	13KW x 8P	59.0 A	1 DRAVE	SS-100	3 SEC	1 SEC	59.0 A	
20 TON	11.5KW x 12P	70.8 A	1 DRAVE	SS-100	3 SEC	1 SEC	70.8 A	
	17KW x 8P	76.6 A	1 DRAVE	SS-100	3 SEC	1 SEC	76.6 A	
	23KW x 6P	93.2 A	1 DRAVE	SS-100	3 SEC	1 SEC	93.2 A	
30 TON	11.5KW x 12P	70.8 A	1 DRAVE	SS-100	3 SEC	1 SEC	70.8 A	
	17KW x 8P	76.6 A	1 DRAVE	SS-100	3 SEC	1 SEC	76.6 A	
	23KW x 6P	93.2 A	1 DRAVE	SS-100	3 SEC	1 SEC	93.2 A	
35 TON	33KW x 6P	126.6 A	1 DRAVE	SS-130	3 SEC	1 SEC	126.6 A	
40 TON	33KW x 6P	126.6 A	1 DRAVE	SS-130	3 SEC	1 SEC	126.6 A	
50 TON	33KW x 6P	126.6 A	1 DRAVE	SS-130	3 SEC	1 SEC	126.6 A	
60 TON	33KW x 6P	126.6 A	1 DRAVE	SS-130	3 SEC	1 SEC	126.6 A	
70 TON	33KW x 6P	126.6 A	1 DRAVE	SS-130	3 SEC	1 SEC	126.6 A	

NOTE

1. 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

E.O.C.R 권고 SETTING치

* POWER SOURCE : AC 3Φ 380V 60Hz

극동호이스트(주)

HOIST	MOTOR 용량	MOTOR 정격 전류	DRIVE TYPE	E.O.C.R TYPE	권고 SETTING 치			REMARK
					DELAY TIME	ERATION TI	CURRENT	
10 TON	9.0KW x 8P	26.0 A	1 DRAVE	SS-30	3 SEC	1 SEC	26.0 A	
	13KW x 6P	30.7 A	1 DRAVE	SS-60	3 SEC	1 SEC	30.7 A	
15 TON	8.5KW x 12P	33.9 A	1 DRAVE	SS-60	3 SEC	1 SEC	33.9 A	
	13KW x 8P	34.2 A	1 DRAVE	SS-60	3 SEC	1 SEC	34.2 A	
20 TON	11.5KW x 12P	41.0 A	1 DRAVE	SS-60	3 SEC	1 SEC	41.0 A	
	17KW x 8P	44.3 A	1 DRAVE	SS-60	3 SEC	1 SEC	44.3 A	
	23KW x 6P	54.0 A	1 DRAVE	SS-60	3 SEC	1 SEC	54.0 A	
30 TON	11.5KW x 12P	41.0 A	1 DRAVE	SS-60	3 SEC	1 SEC	41.0 A	
	17KW x 8P	43.3 A	1 DRAVE	SS-60	3 SEC	1 SEC	43.3 A	
	23KW x 6P	54.0 A	1 DRAVE	SS-60	3 SEC	1 SEC	54.0 A	
35 TON	33KW x 6P	77.3 A	1 DRAVE	SS-100	3 SEC	1 SEC	77.3 A	
40 TON	33KW x 6P	77.3 A	1 DRAVE	SS-100	3 SEC	1 SEC	77.3 A	
50 TON	33KW x 6P	77.3 A	1 DRAVE	SS-100	3 SEC	1 SEC	77.3 A	
60 TON	33KW x 6P	77.3 A	1 DRAVE	SS-100	3 SEC	1 SEC	77.3 A	
70 TON	33KW x 6P	77.3 A	1 DRAVE	SS-100	3 SEC	1 SEC	77.3 A	

NOTE

1. 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

E.O.C.R 권고 SETTING치

* POWER SOURCE : AC 3Φ 440V 60Hz

극동호이스트(주)

HOIST	MOTOR 용량	MOTOR 정격 전류	DRIVE TYPE	E.O.C.R TYPE	권고 SETTING 치			REMARK
					DELAY TIME	ERATION TI	CURRENT	
10 TON	9.0KW x 8P	22.5 A	1 DRAVE	SS-30	3 SEC	1 SEC	22.5 A	
	13KW x 6P	26.5 A	1 DRAVE	SS-30	3 SEC	1 SEC	26.5 A	
15 TON	8.5KW x 12P	29.3 A	1 DRAVE	SS-60	3 SEC	1 SEC	29.3 A	
	13KW x 8P	29.5 A	1 DRAVE	SS-60	3 SEC	1 SEC	29.5 A	
20 TON	11.5KW x 12P	35.4 A	1 DRAVE	SS-60	3 SEC	1 SEC	35.4 A	
	17KW x 8P	38.3 A	1 DRAVE	SS-60	3 SEC	1 SEC	38.3 A	
	23KW x 6P	44.6 A	1 DRAVE	SS-60	3 SEC	1 SEC	44.6 A	
30 TON	11.5KW x 12P	35.4 A	1 DRAVE	SS-60	3 SEC	1 SEC	35.4 A	
	17KW x 8P	38.3 A	1 DRAVE	SS-60	3 SEC	1 SEC	38.3 A	
	23KW x 6P	44.6 A	1 DRAVE	SS-60	3 SEC	1 SEC	44.6 A	
35 TON	33KW x 6P	63.3 A	1 DRAVE	SS-100	3 SEC	1 SEC	63.3 A	
40 TON	33KW x 6P	63.3 A	1 DRAVE	SS-100	3 SEC	1 SEC	63.3 A	
50 TON	33KW x 6P	63.3 A	1 DRAVE	SS-100	3 SEC	1 SEC	63.3 A	
60 TON	33KW x 6P	63.3 A	1 DRAVE	SS-100	3 SEC	1 SEC	63.3 A	
70 TON	33KW x 6P	63.3 A	1 DRAVE	SS-100	3 SEC	1 SEC	63.3 A	

NOTE

1. 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

E.O.C.R 권고 SETTING치

* POWER SOURCE : AC 3Φ 460V 60Hz

극동호이스트(주)

HOIST	MOTOR 용량	MOTOR 정격 전류	DRIVE TYPE	E.O.C.R TYPE	권고 SETTING 치			REMARK
					DELAY TIME	ERATION TI	CURRENT	
10 TON	9.0KW x 8P	21.5 A	1 DRAVE	SS-30	3 SEC	1 SEC	21.5 A	
	13KW x 6P	25.4 A	1 DRAVE	SS-30	3 SEC	1 SEC	25.4 A	
15 TON	8.5KW x 12P	28.1 A	1 DRAVE	SS-60	3 SEC	1 SEC	28.1 A	
	13KW x 8P	28.4 A	1 DRAVE	SS-60	3 SEC	1 SEC	28.4 A	
20 TON	11.5KW x 12P	33.9 A	1 DRAVE	SS-60	3 SEC	1 SEC	33.9 A	
	17KW x 8P	36.7 A	1 DRAVE	SS-60	3 SEC	1 SEC	36.7 A	
	23KW x 6P	44.5 A	1 DRAVE	SS-60	3 SEC	1 SEC	44.5 A	
30 TON	11.5KW x 12P	33.9 A	1 DRAVE	SS-60	3 SEC	1 SEC	33.9 A	
	17KW x 8P	36.7 A	1 DRAVE	SS-60	3 SEC	1 SEC	36.7 A	
	23KW x 6P	44.5 A	1 DRAVE	SS-60	3 SEC	1 SEC	44.5 A	
35 TON	33KW x 6P	60.5 A	1 DRAVE	SS-100	3 SEC	1 SEC	60.5 A	
40 TON	33KW x 6P	60.5 A	1 DRAVE	SS-100	3 SEC	1 SEC	60.5 A	
50 TON	33KW x 6P	60.5 A	1 DRAVE	SS-100	3 SEC	1 SEC	60.5 A	
60 TON	33KW x 6P	60.5 A	1 DRAVE	SS-100	3 SEC	1 SEC	60.5 A	
70 TON	33KW x 6P	60.5 A	1 DRAVE	SS-100	3 SEC	1 SEC	60.5 A	

NOTE

1. 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

E.O.C.R 권고 SETTING치

* POWER SOURCE : AC 3Φ 480V 60Hz

극동호이스트(주)

HOIST	MOTOR 용량	MOTOR 정격 전류	DRIVE TYPE	E.O.C.R TYPE	권고 SETTING 치			REMARK
					DELAY TIME	ERATION TI	CURRENT	
10 TON	9.0KW x 8P	20.6 A	1 DRAVE	SS-30	3 SEC	1 SEC	20.6 A	
	13KW x 6P	25.4 A	1 DRAVE	SS-30	3 SEC	1 SEC	25.4 A	
15 TON	8.5KW x 12P	26.9 A	1 DRAVE	SS-60	3 SEC	1 SEC	26.9 A	
	13KW x 8P	27.2 A	1 DRAVE	SS-60	3 SEC	1 SEC	27.2 A	
20 TON	11.5KW x 12P	32.5 A	1 DRAVE	SS-60	3 SEC	1 SEC	32.5 A	
	17KW x 8P	35.2 A	1 DRAVE	SS-60	3 SEC	1 SEC	35.2 A	
	23KW x 6P	42.6 A	1 DRAVE	SS-60	3 SEC	1 SEC	42.6 A	
30 TON	11.5KW x 12P	32.5 A	1 DRAVE	SS-60	3 SEC	1 SEC	32.5 A	
	17KW x 8P	35.2 A	1 DRAVE	SS-60	3 SEC	1 SEC	35.2 A	
	23KW x 6P	42.6 A	1 DRAVE	SS-60	3 SEC	1 SEC	42.6 A	
35 TON	33KW x 6P	58.0 A	1 DRAVE	SS-60	3 SEC	1 SEC	58.0 A	
40 TON	33KW x 6P	58.0 A	1 DRAVE	SS-60	3 SEC	1 SEC	58.0 A	
50 TON	33KW x 6P	58.0 A	1 DRAVE	SS-60	3 SEC	1 SEC	58.0 A	
60 TON	33KW x 6P	58.0 A	1 DRAVE	SS-60	3 SEC	1 SEC	58.0 A	
70 TON	33KW x 6P	58.0 A	1 DRAVE	SS-60	3 SEC	1 SEC	58.0 A	

NOTE

1. 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

E.O.C.R 권고 SETTING 치

극동하이스트 (주)

* POWER SOURCE : AC3Ø 220V 60Hz

MOTOR 용량	MOTOR 정격 전류	DRIVE TYPE	E.O.C.R TYPE	권고 SETTING 치			REMARK
				DELAY TIME	OPERATION TIME	CURRENT	
0.2KW x 6P	2.0 A	1 DRIVE	SS - 05	3 SEC	1 SEC	2.0 A	
		2DRIVE	SS - 05	3 SEC	1 SEC	4.0 A	
0.4KW x 4P	2.7 A	1 DRIVE	SS - 05	3 SEC	1 SEC	2.7 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	5.4 A	
0.5KW x 6P	3.4 A	1 DRIVE	SS - 05	3 SEC	1 SEC	3.4 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	6.8 A	
0.75KW x 4P	4.1 A	1 DRIVE	SS - 05	3 SEC	1 SEC	4.1 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	8.2 A	
1.0KW x 6P	6.7 A	1 DRIVE	SS - 30	3 SEC	1 SEC	6.7 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	13.4 A	
1.5KW x 4P	7.3 A	1 DRIVE	SS - 30	3 SEC	1 SEC	7.3 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	14.6 A	
1.5KW x 6P	7.6 A	1 DRIVE	SS - 30	3 SEC	1 SEC	7.6 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	15.2 A	
2.2KW x 4P	10 A	1 DRIVE	SS - 30	3 SEC	1 SEC	10 A	
		2 DRIVE	SS - 30	3 SEC	1 SEC	20 A	
0.8/0.4KW x 4/8P	4.8/4.25 A	1 DRIVE	SS - 05	3 SEC	1 SEC	4.8 A	
			SS - 05	3 SEC	1 SEC	4.25 A	
		2 DRIVE	SS - 30	3 SEC	1 SEC	9.6 A	
			SS - 30	3 SEC	1 SEC	8.5 A	
2.2KW x 6P	12 A	1 DRIVE	SS - 30	3 SEC	1 SEC	12 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	24 A	
3.7KW x 4P	16 A	1 DRIVE	SS - 30	3 SEC	1 SEC	16 A	
		2DRIVE	SS - 60	3 SEC	1 SEC	32 A	

NOTE

1, 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

E.O.C.R 권고 SETTING 치

극동하이스트 (주)

* POWER SOURCE : AC3Ø 380V 60Hz

MOTOR 용량	MOTOR 정격 전류	DRIVE TYPE	E.O.C.R TYPE	권고 SETTING 치			REMARK
				DELAY TIME	OPERATION TIME	CURRENT	
0.2KW x 6P	1.2 A	1 DRIVE	SS - 05	3 SEC	1 SEC	1.2 A	
		2DRIVE	SS - 05	3 SEC	1 SEC	2.4 A	
0.4KW x 4P	1.6 A	1 DRIVE	SS - 05	3 SEC	1 SEC	1.6 A	
		2DRIVE	SS - 05	3 SEC	1 SEC	2	
0.5KW x 6P	2.0 A	1 DRIVE	SS - 05	3 SEC	1 SEC	2.0 A	
		2DRIVE	SS - 05	3 SEC	1 SEC	4.0 A	
0.75KW x 4P	2.4 A	1 DRIVE	SS - 05	3 SEC	1 SEC	2.4 A	
		2DRIVE	SS - 05	3 SEC	1 SEC	4.8 A	
1.0KW x 6P	3.9 A	1 DRIVE	SS - 05	3 SEC	1 SEC	3.9 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	7.8 A	
1.5KW x 4P	4.2 A	1 DRIVE	SS - 05	3 SEC	1 SEC	4.2 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	8.4 A	
1.5KW x 6P	4.4 A	1 DRIVE	SS - 05	3 SEC	1 SEC	4.4 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	8.8 A	
2.2KW x 4P	5.8 A	1 DRIVE	SS - 30	3 SEC	1 SEC	5.8 A	
		2 DRIVE	SS - 30	3 SEC	1 SEC	11.6 A	
0.8/0.4KW x 4/8P	2.78/2.63 A	1 DRIVE	SS - 05	3 SEC	1 SEC	2.78 A	
			SS - 05	3 SEC	1 SEC	2.63A	
		2 DRIVE	SS - 30	3 SEC	1 SEC	5.48 A	
			SS - 30	3 SEC	1 SEC	5.26 A	
2.2KW x 6P	7.0 A	1 DRIVE	SS - 30	3 SEC	1 SEC	7.0 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	14 A	
3.7KW x 4P	9.3 A	1 DRIVE	SS - 30	3 SEC	1 SEC	9.3 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	18.6 A	

NOTE

1, 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

E.O.C.R 권고 SETTING 치

극동호이스트 (주)

* POWER SOURCE : AC3Φ 440V 60Hz

MOTOR 용량	MOTOR 정격 전류	DRIVE TYPE	E.O.C.R TYPE	권고 SETTING 치			REMARK
				DELAY TIME	OPERATION TIME	CURRENT	
0.2KW x 6P	1.0 A	1 DRIVE	SS - 05	3 SEC	1 SEC	1.0 A	
		2DRIVE	SS - 05	3 SEC	1 SEC	2.0 A	
0.4KW x 4P	1.4 A	1 DRIVE	SS - 05	3 SEC	1 SEC	1.4 A	
		2DRIVE	SS - 05	3 SEC	1 SEC	2.8 A	
0.5KW x 6P	1.7 A	1 DRIVE	SS - 05	3 SEC	1 SEC	1.7 A	
		2DRIVE	SS - 05	3 SEC	1 SEC	3.4 A	
0.75KW x 4P	2.0 A	1 DRIVE	SS - 05	3 SEC	1 SEC	2.0 A	
		2DRIVE	SS - 05	3 SEC	1 SEC	4.0 A	
1.0KW x 6P	3.3 A	1 DRIVE	SS - 05	3 SEC	1 SEC	3.3 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	6.6 A	
1.5KW x 4P	3.7 A	1 DRIVE	SS - 05	3 SEC	1 SEC	3.7 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	7.4 A	
1.5KW x 6P	3.8 A	1 DRIVE	SS - 05	3 SEC	1 SEC	3.8 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	7.6 A	
2.2KW x 4P	5.0 A	1 DRIVE	SS - 30	3 SEC	1 SEC	5.0 A	
		2 DRIVE	SS - 30	3 SEC	1 SEC	10 A	
0.8/0.4KW x 4/8P	2.4/2.27 A	1 DRIVE	SS - 05	3 SEC	1 SEC	2.4 A	
			SS - 05	3 SEC	1 SEC	2.27 A	
		2 DRIVE	SS - 05	3 SEC	1 SEC	4.8 A	
			SS - 05	3 SEC	1 SEC	4.54 A	
2.2KW x 6P	6.0 A	1 DRIVE	SS - 30	3 SEC	1 SEC	6.0 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	12.0 A	
3.7KW x 4P	8.0 A	1 DRIVE	SS - 30	3 SEC	1 SEC	8.0 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	16 A	

NOTE

1, 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

E.O.C.R 권고 SETTING 치

극동호이스트 (주)

* POWER SOURCE : AC3Φ 460V 60Hz

MOTOR 용량	MOTOR 정격 전류	DRIVE TYPE	E.O.C.R TYPE	권고 SETTING 치			REMARK
				DELAY TIME	OPERATION TIME	CURRENT	
0.2KW x 6P	1.0 A	1 DRIVE	SS - 05	3 SEC	1 SEC	1.0 A	
		2DRIVE	SS - 05	3 SEC	1 SEC	2.0 A	
0.4KW x 4P	1.3 A	1 DRIVE	SS - 05	3 SEC	1 SEC	1.3 A	
		2DRIVE	SS - 05	3 SEC	1 SEC	2.6 A	
0.5KW x 6P	1.7 A	1 DRIVE	SS - 05	3 SEC	1 SEC	1.7 A	
		2DRIVE	SS - 05	3 SEC	1 SEC	3.4 A	
0.75KW x 4P	2.0 A	1 DRIVE	SS - 05	3 SEC	1 SEC	2.0 A	
		2DRIVE	SS - 05	3 SEC	1 SEC	4.0 A	
1.0KW x 6P	3.2 A	1 DRIVE	SS - 05	3 SEC	1 SEC	3.2 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	6.4 A	
1.5KW x 4P	3.5 A	1 DRIVE	SS - 05	3 SEC	1 SEC	3.5 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	7.0 A	
1.5KW x 6P	3.6 A	1 DRIVE	SS - 05	3 SEC	1 SEC	3.6 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	7.2 A	
2.2KW x 4P	4.8 A	1 DRIVE	SS - 05	3 SEC	1 SEC	4.8 A	
		2 DRIVE	SS - 30	3 SEC	1 SEC	9.6 A	
0.8/0.4KW x 4/8P	2.3/2.15 A	1 DRIVE	SS - 05	3 SEC	1 SEC	2.3 A	
		2 DRIVE	SS - 05	3 SEC	1 SEC	2.15 A	
			SS - 05	3 SEC	1 SEC	4.6 A	
			SS - 05	3 SEC	1 SEC	4.3 A	
2.2KW x 6P	4.8 A	1 DRIVE	SS - 05	3 SEC	1 SEC	4.8 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	9.6 A	
3.7KW x 4P	7.7 A	1 DRIVE	SS - 30	3 SEC	1 SEC	7.7 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	15.4 A	

NOTE

1, 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

E.O.C.R 권고 SETTING 치

극동호아스트 (주)

* POWER SOURCE : AC3Φ 480V 60Hz

MOTOR 용량	MOTOR 정격 전류	DRIVE TYPE	E.O.C.R TYPE	권고 SETTING 치			REMARK
				DELAY TIME	OPERATION TIME	CURRENT	
0.2KW x 6P	0.9 A	1 DRIVE	SS - 05	3 SEC	1 SEC	0.9 A	
		2DRIVE	SS - 05	3 SEC	1 SEC	1.8 A	
0.4KW x 4P	1.2 A	1 DRIVE	SS - 05	3 SEC	1 SEC	1.2 A	
		2DRIVE	SS - 05	3 SEC	1 SEC	2.4 A	
0.5KW x 6P	1.6 A	1 DRIVE	SS - 05	3 SEC	1 SEC	1.6 A	
		2DRIVE	SS - 05	3 SEC	1 SEC	3.2 A	
0.75KW x 4P	1.9 A	1 DRIVE	SS - 05	3 SEC	1 SEC	1.9 A	
		2DRIVE	SS - 05	3 SEC	1 SEC	3.8 A	
1.0KW x 6P	3.1 A	1 DRIVE	SS - 05	3 SEC	1 SEC	2.1 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	4.2 A	
1.5KW x 4P	3.4 A	1 DRIVE	SS - 05	3 SEC	1 SEC	3.4 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	6.8 A	
1.5KW x 6P	3.5 A	1 DRIVE	SS - 05	3 SEC	1 SEC	3.5 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	7.0 A	
2.2KW x 4P	4.6 A	1 DRIVE	SS - 05	3 SEC	1 SEC	4.6 A	
		2 DRIVE	SS - 30	3 SEC	1 SEC	9.2 A	
0.8/0.4KW x 4/8P	2.22/2.05 A	1 DRIVE	SS - 05	3 SEC	1 SEC	2.22 A	
		2 DRIVE	SS - 05	3 SEC	1 SEC	2.05 A	
			SS - 05	3 SEC	1 SEC	4.44 A	
		1 DRIVE	SS - 05	3 SEC	1 SEC	4.1 A	
2.2KW x 6P	4.6 A	1 DRIVE	SS - 05	3 SEC	1 SEC	4.6 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	9.2 A	
3.7KW x 4P	7.3 A	1 DRIVE	SS - 30	3 SEC	1 SEC	7.3 A	
		2DRIVE	SS - 30	3 SEC	1 SEC	14.6 A	

NOTE

1, 상기 TABLE의 수치는 권고 SETTING 수치이며 MOTOR의 특성 및 현장 조건에 따라 변경 가능함.

THREE PHASE INDUCTION MOTOR DATA SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	HOISTING
2. MANUFACTURE	극동 호이스트 (주)
3. FRAME NUMBER	200 M
4. RATED POWER	13 KW x 8 P
5. RATED VOLTAGE AND FREQUENCY	220 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1 . 0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TEMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	870 RPM
11. FULL LOAD CURRENT	59.0 A
12. STARTING CURRENT AT RATED VOLTAGE	344.5 A
13. MINIMUM STARTING VOLTAGE	198 V
14. EFFICIENCY AT 100% RATED LOAD	82.0 %
15. POWER FACTOR AT 100% RATED LOAD	70.5 %
16. STARTING TORQUE	31.2 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6311zz OPL : 6311zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPERATURE	40 °C
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

THREE PHASE INDUCTION MOTOR DATA SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	HOISTING
2. MANUFACTURE	극동 호이스트 (주)
3. FRAME NUMBER	200 M
4. RATED POWER	13 KW x 8 P
5. RATED VOLTAGE AND FREQUENCY	380 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1 . 0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TEMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	870 RPM
11. FULL LOAD CURRENT	34.2 A
12. STARTING CURRENT AT RATED VOLTAGE	199 A
13. MINIMUM STARTING VOLTAGE	342 V
14. EFFICIENCY AT 100% RATED LOAD	82.0 %
15. POWER FACTOR AT 100% RATED LOAD	70.5 %
16. STARTING TORQUE	31.2 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6311zz OPL : 6311zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPERATURE	40 °C
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

THREE PHASE INDUCTION MOTOR DATA SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	HOISTING
2. MANUFACTURE	극동 호이스트 (주)
3. FRAME NUMBER	200 M
4. RATED POWER	13 KW x 8 P
5. RATED VOLTAGE AND FREQUENCY	440 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TEMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	870 RPM
11. FULL LOAD CURRENT	29.5 A
12. STARTING CURRENT AT RATED VOLTAGE	173 A
13. MINIMUM STARTING VOLTAGE	396 V
14. EFFICIENCY AT 100% RATED LOAD	82.0 %
15. POWER FACTOR AT 100% RATED LOAD	70.5 %
16. STARTING TORQUE	31.2 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6311zz OPL : 6311zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPERATURE	40 °C
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

THREE PHASE INDUCTION MOTOR DATA SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	HOISTING
2. MANUFACTURE	극동 호이스트 (주)
3. FRAME NUMBER	200 M
4. RATED POWER	13 KW x 8 P
5. RATED VOLTAGE AND FREQUENCY	460 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TEMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	870 RPM
11. FULL LOAD CURRENT	28.4 A
12. STARTING CURRENT AT RATED VOLTAGE	164.8 A
13. MINIMUM STARTING VOLTAGE	414 V
14. EFFICIENCY AT 100% RATED LOAD	82.0 %
15. POWER FACTOR AT 100% RATED LOAD	70.5 %
16. STARTING TORQUE	31.2 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6311zz OPL : 6311zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPERATURE	40 °C
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

THREE PHASE INDUCTION MOTOR DATA SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	HOISTING
2. MANUFACTURE	극동 호이스트 (주)
3. FRAME NUMBER	200 M
4. RATED POWER	13 KW x 8 P
5. RATED VOLTAGE AND FREQUENCY	480 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TEMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	870 RPM
11. FULL LOAD CURRENT	27.2 A
12. STARTING CURRENT AT RATED VOLTAGE	158.0 A
13. MINIMUM STARTING VOLTAGE	432 V
14. EFFICIENCY AT 100% RATED LOAD	82.0 %
15. POWER FACTOR AT 100% RATED LOAD	70.5 %
16. STARTING TORQUE	31.2 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6311zz OPL : 6311zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPERATURE	40 °C
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

THREE PHASE INDUCTION MOTOR DATA SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	HOISTING
2. MANUFACTURE	극동 호이스트 (주)
3. FRAME NUMBER	200 M
4. RATED POWER	8.5 KW x 12 P
5. RATED VOLTAGE AND FREQUENCY	220 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TEMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	576 RPM
11. FULL LOAD CURRENT	58.6 A
12. STARTING CURRENT AT RATED VOLTAGE	263.7 A
13. MINIMUM STARTING VOLTAGE	198 V
14. EFFICIENCY AT 100% RATED LOAD	77.5 %
15. POWER FACTOR AT 100% RATED LOAD	49.0 %
16. STARTING TORQUE	28.11 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6311zz OPL : 6311zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPERATURE	40 °C
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

THREE PHASE INDUCTION MOTOR DATA SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	HOISTING
2. MANUFACTURE	극동 호이스트 (주)
3. FRAME NUMBER	200 M
4. RATED POWER	8.5 KW x 12 P
5. RATED VOLTAGE AND FREQUENCY	380 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1 . 0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TEMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	576 RPM
11. FULL LOAD CURRENT	33.9 A
12. STARTING CURRENT AT RATED VOLTAGE	152.6 A
13. MINIMUM STARTING VOLTAGE	342 V
14. EFFICIENCY AT 100% RATED LOAD	77.5 %
15. POWER FACTOR AT 100% RATED LOAD	49.0 %
16. STARTING TORQUE	28.11 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6311zz OPL : 6311zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPERATURE	40 °C
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

THREE PHASE INDUCTION MOTOR DATA SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	HOISTING
2. MANUFACTURE	극동 호이스트 (주)
3. FRAME NUMBER	200 M
4. RATED POWER	8.5 KW x 12 P
5. RATED VOLTAGE AND FREQUENCY	440 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TEMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	576 RPM
11. FULL LOAD CURRENT	29.3 A
12. STARTING CURRENT AT RATED VOLTAGE	131.9 A
13. MINIMUM STARTING VOLTAGE	396 V
14. EFFICIENCY AT 100% RATED LOAD	77.5 %
15. POWER FACTOR AT 100% RATED LOAD	49.0 %
16. STARTING TORQUE	28.11 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6311zz OPL : 6311zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPERATURE	40 °C
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

THREE PHASE INDUCTION MOTOR DATA SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	HOISTING
2. MANUFACTURE	극동 호이스트 (주)
3. FRAME NUMBER	200 M
4. RATED POWER	8.5 KW x 12 P
5. RATED VOLTAGE AND FREQUENCY	460 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1 . 0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TEMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	576 RPM
11. FULL LOAD CURRENT	28.1 A
12. STARTING CURRENT AT RATED VOLTAGE	126.5 A
13. MINIMUM STARTING VOLTAGE	414 V
14. EFFICIENCY AT 100% RATED LOAD	77.5 %
15. POWER FACTOR AT 100% RATED LOAD	49.0 %
16. STARTING TORQUE	28.11 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6311zz OPL : 6311zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPERATURE	40 °C
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

THREE PHASE INDUCTION MOTOR DATA SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	HOISTING
2. MANUFACTURE	극동 호이스트 (주)
3. FRAME NUMBER	200 M
4. RATED POWER	8.5 KW x 12 P
5. RATED VOLTAGE AND FREQUENCY	480 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1 . 0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TEMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	576 RPM
11. FULL LOAD CURRENT	26.9 A
12. STARTING CURRENT AT RATED VOLTAGE	121.2 A
13. MINIMUM STARTING VOLTAGE	432 V
14. EFFICIENCY AT 100% RATED LOAD	77.5 %
15. POWER FACTOR AT 100% RATED LOAD	49.0 %
16. STARTING TORQUE	28.11 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6311zz OPL : 6311zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPERATURE	40 °C
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

THREE PHASE INDUCTION MOTOR DATA SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	TRAVERSING
2. MANUFACTURE	극동호이스트 (주)
3. FRAME NUMBER	90 L
4. RATED POWER	1.5 KW x 4 P
5. RATED VOLTAGE AND FREQUENCY	220 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TEMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	1710 RPM
11. FULL LOAD CURRENT	7.3 A
12. STARTING CURRENT AT RATED VOLTAGE	42.0 A
13. MINIMUM STARTING VOLTAGE	198 V
14. EFFICIENCY AT 100% RATED LOAD	73.0 %
15. POWER FACTOR AT 100% RATED LOAD	75.0 %
16. STARTING TORQUE	1.72 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6205zz OPL : 6204zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPERATURE	40 °C
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

THREE PHASE INDUCTION MOTOR DATA SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	TRAVERSING
2. MANUFACTURE	극동호이스트 (주)
3. FRAME NUMBER	90 L
4. RATED POWER	1.5 KW x 4 P
5. RATED VOLTAGE AND FREQUENCY	380 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TEMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	1710 RPM
11. FULL LOAD CURRENT	4.2 A
12. STARTING CURRENT AT RATED VOLTAGE	24.2 A
13. MINIMUM STARTING VOLTAGE	342 V
14. EFFICIENCY AT 100% RATED LOAD	73.0 %
15. POWER FACTOR AT 100% RATED LOAD	75.0 %
16. STARTING TORQUE	1.72 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6205zz OPL : 6204zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPERATURE	40 °C
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

THREE PHASE INDUCTION MOTOR DATA SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	TRAVERSING
2. MANUFACTURE	극동호이스트 (주)
3. FRAME NUMBER	90 L
4. RATED POWER	1.5 KW x 4 P
5. RATED VOLTAGE AND FREQUENCY	440 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1 . 0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TEMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	1710 RPM
11. FULL LOAD CURRENT	3.7A
12. STARTING CURRENT AT RATED VOLTAGE	21.0 A
13. MINIMUM STARTING VOLTAGE	396 V
14. EFFICIENCY AT 100% RATED LOAD	73.0 %
15. POWER FACTOR AT 100% RATED LOAD	75.0 %
16. STARTING TORQUE	1.72 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6205zz OPL : 6204zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPERATURE	40 °C
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

THREE PHASE INDUCTION MOTOR DATA SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	TRAVERSING
2. MANUFACTURE	극동호이스트 (주)
3. FRAME NUMBER	90 L
4. RATED POWER	1.5 KW x 4 P
5. RATED VOLTAGE AND FREQUENCY	460 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TEMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	1710 RPM
11. FULL LOAD CURRENT	3.5A
12. STARTING CURRENT AT RATED VOLTAGE	20.8 A
13. MINIMUM STARTING VOLTAGE	414 V
14. EFFICIENCY AT 100% RATED LOAD	73.0 %
15. POWER FACTOR AT 100% RATED LOAD	75.0 %
16. STARTING TORQUE	1.72 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6205zz OPL : 6204zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPERATURE	40 °C
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

THREE PHASE INDUCTION MOTOR DATA SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	TRAVERSING
2. MANUFACTURE	극동호이스트 (주)
3. FRAME NUMBER	90 L
4. RATED POWER	1.5 KW x 4 P
5. RATED VOLTAGE AND FREQUENCY	480 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TEMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	1710 RPM
11. FULL LOAD CURRENT	3.4A
12. STARTING CURRENT AT RATED VOLTAGE	20.0 A
13. MINIMUM STARTING VOLTAGE	432 V
14. EFFICIENCY AT 100% RATED LOAD	73.0 %
15. POWER FACTOR AT 100% RATED LOAD	75.0 %
16. STARTING TORQUE	1.72 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6205zz OPL : 6204zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPERATURE	40 °C
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

THREE PHASE INDUCTION MOTOR DATA SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	TRAVERSING
2. MANUFACTURE	극동 호이스트 (주)
3. FRAME NUMBER	80 S
4. RATED POWER	1.0 KW x 6 P
5. RATED VOLTAGE AND FREQUENCY	220 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TEMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	1140 RPM
11. FULL LOAD CURRENT	6.7 A
12. LOCKED ROTOR CURRENT	23.8 A
13. MINIMUM STARTING VOLTAGE	198 V
14. EFFICIENCY AT 100% RATED LOAD	63.5 %
15. POWER FACTOR AT 100% RATED LOAD	62.0 %
16. STARTING TORQUE	1.1 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6207zz OPL : 6204zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPERATURE	40 °C
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

THREE PHASE INDUCTION MOTOR DATA SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	TRAVERSING
2. MANUFACTURE	극동 호이스트 (주)
3. FRAME NUMBER	80 S
4. RATED POWER	1.0 KW x 6 P
5. RATED VOLTAGE AND FREQUENCY	380 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TEMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	1140 RPM
11. FULL LOAD CURRENT	3.85 A
12. LOCKED ROTOR CURRENT	13.78 A
13. MINIMUM STARTING VOLTAGE	342 V
14. EFFICIENCY AT 100% RATED LOAD	63.5 %
15. POWER FACTOR AT 100% RATED LOAD	62.0 %
16. STARTING TORQUE	1.1 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6207zz OPL : 6204zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPERATURE	40 °C
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

THREE PHASE INDUCTION MOTOR DATA SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	TRAVERSING
2. MANUFACTURE	극동 호이스트 (주)
3. FRAME NUMBER	80 S
4. RATED POWER	1.0 KW x 6 P
5. RATED VOLTAGE AND FREQUENCY	440 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TEMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	1140 RPM
11. FULL LOAD CURRENT	3.33 A
12. LOCKED ROTOR CURRENT	11.9 A
13. MINIMUM STARTING VOLTAGE	396 V
14. EFFICIENCY AT 100% RATED LOAD	63.5 %
15. POWER FACTOR AT 100% RATED LOAD	62.0 %
16. STARTING TORQUE	1.1 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6207zz OPL : 6204zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPERATURE	40 °C
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

THREE PHASE INDUCTION MOTOR DATA SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	TRAVERSING
2. MANUFACTURE	극동 호이스트 (주)
3. FRAME NUMBER	80 S
4. RATED POWER	1.0 KW x 6 P
5. RATED VOLTAGE AND FREQUENCY	460 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TEMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	1140 RPM
11. FULL LOAD CURRENT	3.2 A
12. LOCKED ROTOR CURRENT	11.37 A
13. MINIMUM STARTING VOLTAGE	414 V
14. EFFICIENCY AT 100% RATED LOAD	63.5 %
15. POWER FACTOR AT 100% RATED LOAD	62.0 %
16. STARTING TORQUE	1.1 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6207zz OPL : 6204zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPERATURE	40 °C
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

THREE PHASE INDUCTION MOTOR DATA SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	TRAVERSING
2. MANUFACTURE	극동 호이스트 (주)
3. FRAME NUMBER	80 S
4. RATED POWER	1.0 KW x 6 P
5. RATED VOLTAGE AND FREQUENCY	480 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TEMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	1140 RPM
11. FULL LOAD CURRENT	3.05 A
12. LOCKED ROTOR CURRENT	10.9 A
13. MINIMUM STARTING VOLTAGE	432 V
14. EFFICIENCY AT 100% RATED LOAD	63.5 %
15. POWER FACTOR AT 100% RATED LOAD	62.0 %
16. STARTING TORQUE	1.1 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6207zz OPL : 6204zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPERATURE	40 °C
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

THREE PHASE INDUCTION MOTOR DATA SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	TRAVERSING
2. MANUFACTURE	극동호이스트(주)
3. FRAME NUMBER	112 S
4. RATED POWER	1.5/0.75 KW x 4/8 P
5. RATED VOLTAGE AND FREQUENCY	220 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TEMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	1670/815 RPM
11. FULL LOAD CURRENT	7.2/6.2 A
12. STARTING CURRENT AT RATED VOLTAGE	35.6/21.7 A
13. MINIMUM STARTING VOLTAGE	198 V
14. EFFICIENCY AT 100% RATED LOAD	69.5/63 %
15. POWER FACTOR AT 100% RATED LOAD	74/50 %
16. STARTING TORQUE	1.48/1.22 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6206zz OPL : 6206zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPERATURE	40 °C
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

THREE PHASE INDUCTION MOTOR DATA SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	TRAVERSING
2. MANUFACTURE	극동호이스트(주)
3. FRAME NUMBER	112 S
4. RATED POWER	1.5/0.75 KW x 4/8 P
5. RATED VOLTAGE AND FREQUENCY	380 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TEMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	1670/815 RPM
11. FULL LOAD CURRENT	4.17/3.59 A
12. STARTING CURRENT AT RATED VOLTAGE	20.6/12.56 A
13. MINIMUM STARTING VOLTAGE	342 V
14. EFFICIENCY AT 100% RATED LOAD	69.5/63 %
15. POWER FACTOR AT 100% RATED LOAD	74/50 %
16. STARTING TORQUE	1.48/1.22 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6206zz OPL : 6206zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPERATURE	40 °C
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

THREE PHASE INDUCTION MOTOR DATA SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	TRAVERSING
2. MANUFACTURE	극동호이스트(주)
3. FRAME NUMBER	112 S
4. RATED POWER	1.5/0.75 KW x 4/8 P
5. RATED VOLTAGE AND FREQUENCY	440 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TEMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	1670/815 RPM
11. FULL LOAD CURRENT	3.6/3.1 A
12. STARTING CURRENT AT RATED VOLTAGE	17.8/10.85 A
13. MINIMUM STARTING VOLTAGE	396 V
14. EFFICIENCY AT 100% RATED LOAD	69.5/63 %
15. POWER FACTOR AT 100% RATED LOAD	74/50 %
16. STARTING TORQUE	1.48/1.22 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6206zz OPL : 6206zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPERATURE	40 °C
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

THREE PHASE INDUCTION MOTOR DATA SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	TRAVERSING
2. MANUFACTURE	극동호이스트(주)
3. FRAME NUMBER	112 S
4. RATED POWER	1.5/0.75 KW x 4/8 P
5. RATED VOLTAGE AND FREQUENCY	460 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1 . 0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TEMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	1700/815 RPM
11. FULL LOAD CURRENT	3.44/2.96 A
12. STARTING CURRENT AT RATED VOLTAGE	1670/815 RPM
13. MINIMUM STARTING VOLTAGE	414 V
14. EFFICIENCY AT 100% RATED LOAD	69.5/63 %
15. POWER FACTOR AT 100% RATED LOAD	74/50 %
16. STARTING TORQUE	1.48/1.22 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6206zz OPL : 6206zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPERATURE	40 °C
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

THREE PHASE INDUCTION MOTOR DATA SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	TRAVERSING
2. MANUFACTURE	극동호이스트(주)
3. FRAME NUMBER	112 S
4. RATED POWER	1.5/0.75 KW x 4/8 P
5. RATED VOLTAGE AND FREQUENCY	480 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1 . 0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TRMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	1670/815 RPM
11. FULL LOAD CURRENT	3.5/3.0 A
12. STARTING CURRENT AT RATED VOLTAGE	17.5/10.76 A
13. MINIMUM STARTING VOLTAGE	432 V
14. EFFICIENCY AT 100% RATED LOAD	69.5/63 %
15. POWER FACTOR AT 100% RATED LOAD	74/50 %
16. STARTING TORQUE	1.48/1.22 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6206zz OPL : 6206zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPERATURE	40 °C
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

THREE PHASE INDUCTION MOTOR DATA SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	TRAVERSING
2. MANUFACTURE	극동호이스트(주)
3. FRAME NUMBER	112 S
4. RATED POWER	1.0/0.5 KW x 6/12 P
5. RATED VOLTAGE AND FREQUENCY	220 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1 . 0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TEMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	1050/460 RPM
11. FULL LOAD CURRENT	7.1/7.5 A
12. STARTING CURRENT AT RATED VOLTAGE	28.3/22.5 A
13. MINIMUM STARTING VOLTAGE	198 V
14. EFFICIENCY AT 100% RATED LOAD	59.5/35.0 %
15. POWER FACTOR AT 100% RATED LOAD	64.5/54.0 %
16. STARTING TORQUE	1.67/1.48 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6206zz OPL : 6206zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPERATURE	40 °C
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

THREE PHASE INDUCTION MOTOR DATA SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	TRAVERSING
2. MANUFACTURE	극동호이스트(주)
3. FRAME NUMBER	112 S
4. RATED POWER	1.0/0.5 KW x 6/12 P
5. RATED VOLTAGE AND FREQUENCY	380 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1 . 0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TEMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	1050/460 RPM
11. FULL LOAD CURRENT	4.1/4.3 A
12. STARTING CURRENT AT RATED VOLTAGE	16.4/13.0 A
13. MINIMUM STARTING VOLTAGE	342 V
14. EFFICIENCY AT 100% RATED LOAD	59.5/35.0 %
15. POWER FACTOR AT 100% RATED LOAD	64.5/54.0 %
16. STARTING TORQUE	1.67/1.48 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6206zz OPL : 6206zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPERATURE	40 °C
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

THREE PHASE INDUCTION MOTOR DATA SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	TRAVERSING
2. MANUFACTURE	극동호이스트(주)
3. FRAME NUMBER	112 S
4. RATED POWER	1.0/0.5 KW x 6/12 P
5. RATED VOLTAGE AND FREQUENCY	440 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TEMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	1050/460 RPM
11. FULL LOAD CURRENT	3.5/3.7 A
12. STARTING CURRENT AT RATED VOLTAGE	14.2/12.3 A
13. MINIMUM STARTING VOLTAGE	396 V
14. EFFICIENCY AT 100% RATED LOAD	59.5/35.0 %
15. POWER FACTOR AT 100% RATED LOAD	64.5/54.0 %
16. STARTING TORQUE	1.67/1.48 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6206zz OPL : 6206zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPERATURE	40 °C
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

THREE PHASE INDUCTION MOTOR DATA SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	TRAVERSING
2. MANUFACTURE	극동호이스트(주)
3. FRAME NUMBER	112 S
4. RATED POWER	1.0/0.5 KW x 6/12 P
5. RATED VOLTAGE AND FREQUENCY	460 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TEMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	1050/460 RPM
11. FULL LOAD CURRENT	3.4/3.6 A
12. STARTING CURRENT AT RATED VOLTAGE	13.5/10.8 A
13. MINIMUM STARTING VOLTAGE	414 V
14. EFFICIENCY AT 100% RATED LOAD	59.5/35.0 %
15. POWER FACTOR AT 100% RATED LOAD	64.5/54.0 %
16. STARTING TORQUE	1.67/1.48 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6206zz OPL : 6206zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPERATURE	40 °C
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E

THREE PHASE INDUCTION MOTOR DATA SHEET

SCHEDULE OF TECHNICAL DATA

1. SERVICE	TRAVERSING
2. MANUFACTURE	극동호이스트(주)
3. FRAME NUMBER	112 S
4. RATED POWER	1.0/0.5 KW x 6/12 P
5. RATED VOLTAGE AND FREQUENCY	480 V 60 Hz
6. MOTOR TYPE	SQUIRREL CAGE ROTOR TYPE
7. SERVICE FACTOR AND RATting	1.0 , 30 MIN
8. LOCATION AND INSULATION CLASS	INDOOR, OUTDOOR, B CLASS
9. DESIGN TEMPERATURE RISE(BY RESISTANCE)	80 °C
10. FULL LOAD SPEED	1050/460 RPM
11. FULL LOAD CURRENT	3.2/3.4 A
12. STARTING CURRENT AT RATED VOLTAGE	13.0/10.3 A
13. MINIMUM STARTING VOLTAGE	432 V
14. EFFICIENCY AT 100% RATED LOAD	59.5/35.0 %
15. POWER FACTOR AT 100% RATED LOAD	64.5/54.0 %
16. STARTING TORQUE	1.67/1.48 KG.M
17. SITE ALTITUDE(UNDER)	1000 M
18. ENCLOSURE & COOLING METHOD	T E N V
19. TYPE OF BEARING	PL : 6206zz OPL : 6206zz
20. MOUNTING	H O R I Z O N T A L
21. MAXIMUM AMBIENT TEMPERATURE	40 °C
22. BEARING LUBRICATION	G R E A S E
23. STARTING METHOD	F U L L V O L T A G E



5, Sandan 6-ro, Jeonggan-myeon, Gijang-gun, Busan, 46026, Korea
TEL:+82-51-727-0015 FAX:+82-51-727-3247 www.kiswire.com

CERT NO. 201304WRW45800

DATE Feb. 20, 2015

MILL TEST CERTIFICATE

THIS IS TO CERTIFY THAT THE MATERIAL DESCRIBED BELOW WAS MANUFACTURED
IN ACCORDANCE WITH KISWIRE LTD SPECIFICATION AND APPLICABLE SECTIONS

OF KSD 3514 - 2002 (B Grade)

TO MESSRS

MATERIAL DESCRIPTION UNGALVANIZED STEEL WIRE ROPE

06 X 29 (FI) + IWRC 2000 M X 5 REEL

EX NO. 1W6288

ORDER NO. _____ REEL NO. 1 ~ 5 SAMPLING NO. 1

DIAMETER OF ROPE 18.000 mm TYPE OF CORE IWRC

SPECIFIED BREAKING LOAD 219.00 kN SAMPLE BROKE AT 231.69 kN

WT. OF ZINC COATING OF OUTER WIRE MIN. 0.000 g/m²

ROPE LAY RHRL LAY LENGTH 113.72 mm

LUBRICATION A-2

CHEMICAL ANALYSIS OF WIRE ROD

CHARGE NO.	C X 100	Si X 100	Mn X 100	P X 1000	S X 1000
M29703	75	16	76	15	10

DATE OF SAMPLE TEST Apr. 23, 2013

S. H. Ham

Approved by Q.C Manager S.H. Ham
KISWIRE LTD., KOREA



KS



JIS



ABS



KR



NK



G.Lloyd's



DNV



LR



BV